

# 3. Electrical Parts List

\*S.N.A. : Service Not Available

Location no. Code no. Description & Specification Remarks

## \*\*\*\* MM-L7/ZL7 Parts List \*\*\*\*

AH26-00129A	TRANS POWER	-,W2000,--,115/230V,60/50Hz,-
AH38-10001A	FM-WIRE	1007#22,1500MM
AH39-00257G	POWER CORD	MAX980,;,CP2,250V,2.5A,1650mm/
AH40-00008A	TUNER-PACK	KST-MB14L51-50,FM/MW/LW,--,
AH42-20001P	LOOP-ANT	TT,1000MM,18.5UH
AH59-00105A	REMOCON-ASSY	MM-L7,--,22KEY,--,BA
AH59-00106A	DECK	DA23L,MCD-MP65,BALL,--,DECK
AH59-00122A	DECK-CASSETTE	ADR248BTR,MM-L7,--,DC12V,--,
AH68-00770B	MANUAL-BOOK	MM-N7,RDS,ENG,;,80G PAPER,;,26
AH68-00770C	MANUAL-BOOK	MM-N7,RDS,GER,;,80G PAPER,;,26
AH68-00770D	MANUAL-BOOK	MM-N7,RDS,FRN,;,80G PAPER,;,26
AH68-00770G	MANUAL-BOOK	MM-L7,RDS,NL,;,80G PAPER,;,260
AH68-40042B	CARD WARRANTY	ALL,EU,ART,;,L210,;,W145,;,;

## AH92-00942A ASSY MAIN PCB MM-L7/ZL7

PWA2	AH39-00068A	LEAD CONNECTOR-ASSY	150MM,--,5264/5395-05,1007#22
PWA1	AH39-00305A	WIRE HARNESS	MM-L7,--,5P,--,5264,51088,
PWA3	AH39-20008N	LEAD-CONNECTOR ASSY	5264,5395,2P,200MM,1007#26
AD14	0402-000157	DIODE-RECTIFIER	1N5402,200V,3A,DO-2
AD15	0402-000157	DIODE-RECTIFIER	1N5402,200V,3A,DO-2
AD16	0402-000157	DIODE-RECTIFIER	1N5402,200V,3A,DO-2
AD17	0402-000157	DIODE-RECTIFIER	1N5402,200V,3A,DO-2
AQ7	0502-000424	TR-POWER	2S81566-F,PNP,-60V,-50V,3
AI1	1201-001026	IC-POWER AMP	TD47265
AI2	1203-000242	IC-POS.FIXED REG.	7812,TO-220,EP,;,PLASTIC,11.5/
UI2	1203-000276	IC-POS.FIXED REG.	KA7805-AB,TO-220,3P,;,PLASTIC,
FI1	1204-001776	IC-SOUND PROCESSOR	TDA7442D,SOP,28P,295MIL,PLASTI
PC3	2401-001067	C-AL	300UF,20%,42V,GP,18*35,5,7.5m
AC15	2401-001883	C-AL	1000UF,20%,25V,GP,13x21mm,5mm,
AC16	2401-001883	C-AL	1000UF,20%,25V,GP,13x21mm,5mm,
AC7	2401-001883	C-AL	1000UF,20%,25V,GP,13x21mm,5mm,
AC20	2401-002258	C-AL	4700UF,20%,50V,GP,22X40MM,5MM
MWF1	3710-001684	CONNECTOR-SOCKET	30P,1R,1,25mmANGLE,TKC-V30X-A1
CWA1	3711-001137	CONNECTOR-HEADER	BOX,8P,1R,20MM,STRAIGHT,SN
SPK	3716-000209	TERMINAL-BLOCK	--,60V,7A
AUX	3722-000377	JACK-PCA	4P/2C,3.5mm,16~22,SN
AD151	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD152	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD153	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD21	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD25	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD26	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD27	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD29	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD30	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD31	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD6	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD7	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD8	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
QD1	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
QD3	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
QD4	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
QD5	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
QD6	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
TD20	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
UD2	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
AD1	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
AD10	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
AD11	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
AD12	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
AD13	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
AD18	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
AD2	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
AD24	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
AD35	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
QD2	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
QD3	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
AD36	0402-000151	DIODE-RECTIFIER	1N5392,100V,1.5A,DO-15
AD37	0402-000151	DIODE-RECTIFIER	1N5392,100V,1.5A,DO-15
AD38	0402-000151	DIODE-RECTIFIER	1N5392,100V,1.5A,DO-15
AZD3	0403-000393	DIODE-ZENER	UZP5,1B,5.1V,4.8-5.4V,1W,DO
AZD2	0403-000396	DIODE-ZENER	UZP6,8B,6.8V,6.4-7.2V,1W,DO-41
AZD1	0403-001009	DIODE-ZENER	UZP27B,27V,25.5-30V,1W,DO-4
AQ16	0501-000010	TR-SMALL SIGNAL	KSC1008-YTA,NPN,80V,60V,700mA,
AQ6	0501-000010	TR-SMALL SIGNAL	KSC1008-YTA,NPN,80V,60V,700mA,
AQ13	0501-000331	TR-SMALL SIGNAL	KSC1008-YTA,160V,140V,700mA
AQ18	0501-000407	TR-SMALL SIGNAL	KSD471-YTA,40V,30V,1A,800m TP
AQ8	0501-000407	TR-SMALL SIGNAL	KSD471-YTA,40V,30V,1A,800m TP
AQ11	0501-000610	TR-SMALL SIGNAL	KSAG28A,PNP,-30V,-30V,-2A,1W
AQ3	0501-000610	TR-SMALL SIGNAL	KSAG28A,PNP,-30V,-30V,-2A,1W
AQ12	0504-000121	TR-DIGITAL	KSR1007TA/108M,300MW,22K-47K
AQ14	0504-000121	TR-DIGITAL	KSR1007TA/108M,300MW,22K-47K
AQ15	0504-000121	TR-DIGITAL	KSR1007TA/108M,300MW,22K-47K
AQ17	0504-000121	TR-DIGITAL	KSR1007TA/108M,300MW,22K-47K
AQ4	0504-000121	TR-DIGITAL	KSR1007TA/108M,300MW,22K-47K

Location no. Code no. Description & Specification Remarks

AQ5	0504-000121	TR-DIGITAL	KSR1007TA/108M,300MW,22K-47K
QJ7	0504-000121	TR-DIGITAL	KSR1007TA/108M,300MW,22K-47K
CQ1	0504-000122	TR-DIGITAL	KSR1009TA, 300MW,4.7KOHM,TO-9
CQ2	0504-000122	TR-DIGITAL	KSR1009TA, 300MW,4.7KOHM,TO-9
AQ9	0504-001003	TR-DIGITAL	KSR2003TA,300mW,22K-22Kohm
CQ3	0504-001003	TR-DIGITAL	KSR2003TA,300mW,22K-22Kohm
QR32	2001-000008	R-CARBON	15Kohm,5%,1/8W,AA,TP,1.8x3.2mm
QR33	2001-000008	R-CARBON	15Kohm,5%,1/8W,AA,TP,1.8x3.2mm
OR1	2001-000028	R-CARBON(S)	100ohm,5%,1/2W,AA,TP,2.4x6.4mm
OR2	2001-000028	R-CARBON(S)	100ohm,5%,1/2W,AA,TP,2.4x6.4mm
AR38	2001-000052	R-CARBON(S)	3.3Kohm,5%,1/2W,AA,TP,2.4x6.4mm
AR43	2001-000052	R-CARBON(S)	3.3Kohm,5%,1/2W,AA,TP,2.4x6.4mm
AR60	2001-000066	R-CARBON(S)	10Kohm,5%,1/2W,AA,TP,2.4x6.4mm
JW81	2001-000331	R-CARBON	12Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR81	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR82	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
AR49	2001-000449	R-CARBON	2.2Kohm,5%,1/8W,AA,TP,1.8x3.2mm
AR65	2001-000449	R-CARBON	2.2Kohm,5%,1/8W,AA,TP,1.8x3.2mm
QR26	2001-000515	R-CARBON	220ohm,5%,1/8W,AA,TP,1.8x3.2mm
QR27	2001-000515	R-CARBON	220ohm,5%,1/8W,AA,TP,1.8x3.2mm
AR151	2001-000522	R-CARBON	22Kohm,5%,1/8W,AA,TP,1.8x3.2mm
AR39	2001-000522	R-CARBON	22Kohm,5%,1/8W,AA,TP,1.8x3.2mm
AR56	2001-000522	R-CARBON	22Kohm,5%,1/8W,AA,TP,1.8x3.2mm
AR64	2001-000522	R-CARBON	22Kohm,5%,1/8W,AA,TP,1.8x3.2mm
AR14	2001-000554	R-CARBON	270ohm,5%,1/8W,AA,TP,1.8x3.2mm
AR15	2001-000554	R-CARBON	270ohm,5%,1/8W,AA,TP,1.8x3.2mm
AR16	2001-000563	R-CARBON	27Kohm,5%,1/8W,AA,TP,1.8x3.2mm
AR17	2001-000563	R-CARBON	27Kohm,5%,1/8W,AA,TP,1.8x3.2mm
QR34	2001-000591	R-CARBON	3.3Kohm,5%,1/8W,AA,TP,1.8x3.2mm
QR35	2001-000591	R-CARBON	3.3Kohm,5%,1/8W,AA,TP,1.8x3.2mm
TR56	2001-000977	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8x3.2mm
TR57	2001-000977	R-CARBON	8.2KOHM,5%,1/8W,AA,TP,1.8x3.2mm
AR42	2001-001093	R-CARBON(S)	2.2Kohm,5%,1/2W,AA,TP,2.4x6.4mm
AR1	2001-001096	R-CARBON(S)	2.2ohm,5%,1/2W,AA,TP,2.4x6.4mm
OR4	2001-001107	R-CARBON(S)	220ohm,5%,1/2W,AA,TP,2.4x6.4mm
AR30	2001-001138	R-CARBON(S)	390ohm,5%,1/2W,AA,TP,2.4x6.4mm
AR41	2001-001144	R-CARBON(S)	4.7Kohm,5%,1/2W,AA,TP,2.4x6.4mm
AR20	2001-001146	R-CARBON(S)	4.7ohm,5%,1/2W,AA,TP,2.4x6.4mm
AR21	2001-001146	R-CARBON(S)	4.7ohm,5%,1/2W,AA,TP,2.4x6.4mm
OR3	2001-001153	R-CARBON(S)	47ohm,5%,1/2W,AA,TP,2.4x6.4mm
AR45	2001-001163	R-CARBON(S)	560ohm,5%,1/2W,AA,TP,2.4x6.4mm
AR46	2001-001163	R-CARBON(S)	560ohm,5%,1/2W,AA,TP,2.4x6.4mm
AR4	2001-001178	R-CARBON	680ohm,5%,1/2W,AA,TP,2.4x6.4mm
AC51	2201-000163	C-CERAMIC,DISC	10nF,+80-20%,50V,VS16,5,5.5MM
OC1	2201-000361	C-CERAMIC,DISC	22nF,+80%,20% 50V VS5 0.4 0.4
AC13	2301-000375	C-FILM,PEF	100nF,10%,50V,11x12.5x6.5,TP
AC14	2301-000375	C-FILM,PEF	100nF,10%,50V,11x12.5x6.5,TP
CC10	2401-000240	C-AL	100uF,20%,10V,GP,5*11mm,5mm,TP
UC7	2401-000240	C-AL	100uF,20%,10V,GP,5*11mm,5mm,TP
OC2	2401-000357	C-AL	100uF,0.250V,GP,8*12.5MM,SSL
AC40	2401-000419	C-AL	10uF,20%,16V,GP,5*11.5MM,TP
AC8	2401-000419	C-AL	10uF,20%,16V,GP,5*11.5MM,TP
AC27	2401-000438	C-AL	10uF,20%,25V,GP,5*11.5mm,TP
AC22	2401-000475	C-AL	10uF,20%,50V,GP,5*11.5mm,TP
AC41	2401-000795	C-AL	220uF,20%,16V,GP,8*12.5MM,TP
OC3	2401-000907	C-AL	22uF,20%,16V,GP,5*11.5MM,TP
CC1	2401-001355	C-AL	470uF,20%,10V,GP,8x11.5,5MM,TP
AC11	2401-001645	C-AL	680nF,20%,50V,GP,5*11.5mm,TP
AC30	2401-001645	C-AL	680nF,20%,50V,GP,5*11.5mm,TP
QC16	2401-001895	C-AL	100uF,20%,16V,GP,6.3*11.5MM,TP
AC10	2401-001912	C-AL	1uF,20%,50V,GP,5*11.5mm,TP
AC28	2401-001912	C-AL	1uF,20%,50V,GP,5*11.5mm,TP
AC29	2401-001938	C-AL	22uF,20%,25V,GP,5*11.5mm,TP
QC24	2401-001954	C-AL	4.7uF,20%,50V,GP,5*11.5MM,TP
AC6	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC1L	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC1R	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC10	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC2L	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC2R	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC23	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC25	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC3L	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC3R	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC4L	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC4R	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC5L	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
QC5R	2401-002180	C-AL	2.2uF,20%,50V,GP,5*11.5mm,TP
JW36	2007-000029	R-CHIP	0ohm,5%,1/10W,DA,TP,2012
JW1	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
JW2	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
JW1	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
JW14	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
JW2	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
JW3	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
JW4	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
JW5	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
AR8	2007-000078	R-CHIP	1KOHM,5%,1/16W,TP,1608
CR7	2007-000078	R-CHIP	1KOHM,5%,1/16W,TP,1608

Location no.	Code no.	Description & Specification	Remarks
CR5	2007-000082	R-CHIP	3.3KOHM,5%,1/16W,DA,TP,1608
CR6	2007-000082	R-CHIP	3.3KOHM,5%,1/16W,DA,TP,1608
CR3	2007-000084	R-CHIP	4.7KOHM,5%,1/16W,DA,TP,1608
CR4	2007-000084	R-CHIP	4.7KOHM,5%,1/16W,DA,TP,1608
TR52	2007-000084	R-CHIP	4.7KOHM,5%,1/16W,DA,TP,1608
QR1L	2007-000086	R-CHIP	5.6KOHM,5%,1/16W,DA,TP
QR1R	2007-000086	R-CHIP	5.6KOHM,5%,1/16W,DA,TP
AR61	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
AR62	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
AR63	2007-000091	R-CHIP	12KOHM,5%,1/16W,DA,TP,1608
JW15	2007-000091	R-CHIP	12KOHM,5%,1/16W,DA,TP,1608
QR23	2007-000091	R-CHIP	12KOHM,5%,1/16W,DA,TP,1608
QR31	2007-000091	R-CHIP	12KOHM,5%,1/16W,DA,TP,1608
TR54	2007-000091	R-CHIP	12KOHM,5%,1/16W,DA,TP,1608
TR55	2007-000091	R-CHIP	12KOHM,5%,1/16W,DA,TP,1608
AR48	2007-000094	R-CHIP	22KOHM,5%,1/16W,DA,TP
AR5	2007-000094	R-CHIP	22KOHM,5%,1/16W,DA,TP
AR52	2007-000094	R-CHIP	22KOHM,5%,1/16W,DA,TP
AR54	2007-000094	R-CHIP	22KOHM,5%,1/16W,DA,TP
AR11	2007-000097	R-CHIP	47KOHM,5%,1/16W,TP,1608
AR58	2007-000097	R-CHIP	47KOHM,5%,1/16W,TP,1608
AR6	2007-000097	R-CHIP	47KOHM,5%,1/16W,TP,1608
AR11L	2007-000098	R-CHIP	56Kohm,5%,1/16W,DA,TP,1608
AR29	2007-000098	R-CHIP	56Kohm,5%,1/16W,DA,TP,1608
AR9	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
OR10	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
OR11	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
OR4	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
OR5	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
OR6	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
OR7	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
OR8	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
OR9	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR8	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
AR31	2007-000124	R-CHIP	2.2KOHM,5%,1/16W,DA,TP,1608
AR32	2007-000124	R-CHIP	2.2KOHM,5%,1/16W,DA,TP,1608
AR47	2007-000124	R-CHIP	2.2KOHM,5%,1/16W,DA,TP,1608
AR55	2007-000819	R-CHIP	390Kohm,5%,1/16W,DA,TP,1608
CC2	2203-000062	C-CERAMIC,CHIP	47nF,+80-20%,50V,YSV,TP,1608,-
QC121	2203-000062	C-CERAMIC,CHIP	47nF,+80-20%,50V,YSV,TP,1608,-
TC1	2203-000062	C-CERAMIC,CHIP	47nF,+80-20%,50V,YSV,TP,1608,-
TC2	2203-000062	C-CERAMIC,CHIP	47nF,+80-20%,50V,YSV,TP,1608,-
UC16	2203-000062	C-CERAMIC,CHIP	47nF,+80-20%,50V,YSV,TP,1608,-
CC70	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
OC4	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
OC41	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
OC5	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
NC1	2203-000440	C-CERAMIC,CHIP	1nF,10%,50V,X7R,TP,1608,-
QC11	2203-000592	C-CERAMIC,CHIP	0.22nF,5%,50V,NPO,TP,1608
QC12	2203-000592	C-CERAMIC,CHIP	0.22nF,5%,50V,NPO,TP,1608
TC59	2203-000592	C-CERAMIC,CHIP	0.22nF,5%,50V,NPO,TP,1608
TC61	2203-000592	C-CERAMIC,CHIP	0.22nF,5%,50V,NPO,TP,1608
JC111	2203-000681	C-CERAMIC,CHIP	27pF,5%,50V,X7R,TP,1608,-
QC8L	2203-001034	C-CERAMIC,CHIP	5.6nF,10%,50V,X7R,TP,1608,-
QC8R	2203-001034	C-CERAMIC,CHIP	5.6nF,10%,50V,X7R,TP,1608,-
AC12	2203-001223	C-CERAMIC,CHIP	820pF,10%,50V,X7R,TP,2012,2.0mm,T
AC9	2203-001223	C-CERAMIC,CHIP	820pF,10%,50V,X7R,TP,2012,2.0mm,T
AC26	2203-002398	C-CERAMIC,CHIP	22nF,10%,50V,X7R,TP,1608
QC8L	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
QC8R	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
QC7L	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
QC7R	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608

#### AH92-00947A ASSY H/P PCB MM-L7/ZL7

HCW3	3711-000826	CONNECTOR-HEADER	BOX,2P,1R,2MM,ANGLE,SN
HCW1	3711-001009	CONNECTOR-HEADER	BOX,5P,1R,2.5MM,AN
HJ1	3722-001588	JACK-PHONE	7P,3.6PI,AG,BLK,-
HR1	2001-000107	R-CARBON(S)	220ohm,5%,1/2W,AA,TP,2.4x6.4mm
HR2	2001-000107	R-CARBON(S)	220ohm,5%,1/2W,AA,TP,2.4x6.4mm
HL1	2701-000111	INDUCTOR-AXIAL	100uH,10%,2.5x3.4,LAL02TB101K
HL2	2701-000111	INDUCTOR-AXIAL	100uH,10%,2.5x3.4,LAL02TB101K
HL3	2701-000111	INDUCTOR-AXIAL	100uH,10%,2.5x3.4,LAL02TB101K
US11	3404-000165	SWITCH-TACT	12V,50mA,160gf,SKHV10910A
MR9	2007-000124	R-CHIP	2.2KOHM,5%,1/16W,DA,TP,1608
UR21	2007-000134	R-CHIP	33KOHM,5%,1/16W,DA,TP,1608
HC1	2203-000062	C-CERAMIC,CHIP	47nF,+80-20%,50V,YSV,TP,1608,-
HC2	2203-000062	C-CERAMIC,CHIP	47nF,+80-20%,50V,YSV,TP,1608,-

#### AH92-00948A ASSY MAIN PCB OPTION MM-L7/ZL7

OSC1	AH26-10003C	COIL-TRAP	PCHNS-537IEQJ,BIAS-TRAP,-,85
DWA2	AH39-00062A	LEAD CONNECTOR-ASSY	5295,PHR,-,6P,150MM,1C
MWF9	AH39-00159A	LEAD CONNECTOR-ASSY	-N6-13P,100T#28,250MM,BLK/RED
JC1	1201-000358	IC-PREAMP	S1A0291*01-A0B0,24SDIP
MWF8	3711-000307	CONNECTOR-HEADER	BOX,3P,1R,2.5MM,-,BRASS
JD10	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
JD3	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
JD4	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
JD5	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
JD6	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
JD7	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
JD8	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
UD18	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
UD19	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41

JD2	0403-000339	DIODE-ZENER	UZ3.0B,3V,2.8-3.2V,500mW,DO
JQ1	0501-000010	TR-SMALL SIGNAL	KSC1008-YTA,NPN,80V,60V,700mA
JQ10	0501-000010	TR-SMALL SIGNAL	KSC1008-YTA,NPN,80V,60V,700mA
JQ4	0501-000303	TR-SMALL SIGNAL	KSA733YTA,PNP,-60V,-50V,-150mA
JQ5	0501-000369	TR-SMALL SIGNAL	KSC2331-YTA,80V,60V,700mA
JQ6	0501-000369	TR-SMALL SIGNAL	KSC2331-YTA,80V,60V,700mA
JQ3L	0501-000407	TR-SMALL SIGNAL	KSD471-YTA,40V,30V,1A,800m TP
JQ3R	0501-000407	TR-SMALL SIGNAL	KSD471-YTA,40V,30V,1A,800m TP
JQ9	0501-000407	TR-SMALL SIGNAL	KSD471-YTA,40V,30V,1A,800m TP
UQ3	0501-000610	TR-SMALL SIGNAL	KSA928A,PNP,-30V,-30V,-2A,1W
UQ4	0501-000610	TR-SMALL SIGNAL	KSA928A,PNP,-30V,-30V,-2A,1W
UQ1	0504-000118	TR-DIGITAL	KSR1003TA,NPN,300MW,22K-22KOHM
UQ2	0504-000118	TR-DIGITAL	KSR1003TA,NPN,300MW,22K-22KOHM
JQ11	0504-001003	TR-DIGITAL	KSR2003TA,300mW,22K-22Kohm
JR23	2001-000028	R-CARBON(S)	10ohm,5%,1/2W,AA,TP,2.4x6.4mm
JR37	2001-000117	R-CARBON(S)	68ohm,5%,1/2W,AA,TP,2.4x6.4mm
JR67	2001-000290	R-CARBON	10Kohm,5%,1/8W,AA,TP,1.8x3.2mm
JR13R	2001-000397	R-CARBON	RN 1/8T 180K-J
JR2L	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
JR2R	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
JR6R	2001-000527	R-CARBON	22ohm,5%,1/8W,AA,TP,1.8x3.2mm
JR11R	2001-000734	R-CARBON	4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m
JR66	2001-000773	R-CARBON	470Kohm,5%,1/8W,AA,TP,1.8x3.2m
JR32	2001-000802	R-CARBON	5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m
JR31	2001-000894	R-CARBON	6.8ohm,5%,1/8W,AA,TP,1.8x3.2mm
JR29	2001-001077	R-CARBON(S)	150ohm,5%,1/2W,AA,TP,2.4x6.4mm
UR70	2001-001163	R-CARBON(S)	560ohm,5%,1/2W,AA,TP,2.4x6.4mm
UR71	2001-001163	R-CARBON(S)	560ohm,5%,1/2W,AA,TP,2.4x6.4mm
SVR1	2103-000341	VR-SEMI	2Kohm,30%,1/10W,TOP
JCSL	2202-000779	C-CERAMIC,MLC-AXIAL	1.5NF,20%,16V,Y5R,TP,3.5X
JCSR	2202-000779	C-CERAMIC,MLC-AXIAL	1.5NF,20%,16V,Y5R,TP,3.5X
JC27	2301-000404	C-FILM,PEF	2.2nF,10%,50V,5.5x12x3,TP
JC34	2301-000422	C-FILM,PEF	3.3nF,10%,50V,5.5x7x3,TP
JC18	2401-000907	C-AL	22uF,20%,16V,GP,5*11,5MM,TP
JC19	2401-000907	C-AL	22uF,20%,16V,GP,5*11,5MM,TP
JC10L	2401-001022	C-AL	3.3uF,20%,50V,SME,5*11,5MM,TP
JC10R	2401-001022	C-AL	3.3uF,20%,50V,SME,5*11,5MM,TP
JC12L	2401-001022	C-AL	3.3uF,20%,50V,SME,5*11,5MM,TP
JC12R	2401-001022	C-AL	3.3uF,20%,50V,SME,5*11,5MM,TP
JC31	2401-001538	C-AL	47uF,20%,25V,GP,5*11,5mm,TP
UC83	2401-001895	C-AL	100uF,20%,16V,GP,6.3*11,5MM,TP
JC22	2401-001912	C-AL	1uF,20%,50V,GP,5*11,5mm,TP
JC23	2401-001912	C-AL	1uF,20%,50V,GP,5*11,5mm,TP
JC7L	2401-001912	C-AL	1uF,20%,50V,GP,5*11,5mm,TP
JC7R	2401-001912	C-AL	1uF,20%,50V,GP,5*11,5mm,TP
JC11L	2401-001975	C-AL	47uF,20%,16V,GP,5*11,5mm,TP
JC11R	2401-001975	C-AL	47uF,20%,16V,GP,5*11,5mm,TP
JC21	2401-001975	C-AL	47uF,20%,16V,GP,5*11,5mm,TP
JC27	2401-001975	C-AL	47uF,20%,16V,GP,5*11,5mm,TP
JC3L	2401-001975	C-AL	47uF,20%,16V,GP,5*11,5mm,TP
JC3R	2401-001975	C-AL	47uF,20%,16V,GP,5*11,5mm,TP
JW10	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
JR6L	2007-000071	R-CHIP	22OHM,5%,1/16W,DA,TP,1608
JR6R	2007-000071	R-CHIP	22OHM,5%,1/16W,DA,TP,1608
JR63	2007-000074	R-CHIP	100OHM,5%,1/16W,DA,TP,1608
UR63	2007-000074	R-CHIP	100OHM,5%,1/16W,DA,TP,1608
UR64	2007-000074	R-CHIP	100OHM,5%,1/16W,DA,TP,1608
UR75	2007-000074	R-CHIP	100OHM,5%,1/16W,DA,TP,1608
JR1L	2007-000078	R-CHIP	1KOHM,5%,1/16W,TP,1608
JR1R	2007-000078	R-CHIP	1KOHM,5%,1/16W,TP,1608
JR12L	2007-000078	R-CHIP	1KOHM,5%,1/16W,TP,1608
JR12R	2007-000078	R-CHIP	1KOHM,5%,1/16W,TP,1608
JR11L	2007-000084	R-CHIP	4.7KOHM,5%,1/16W,DA,TP,1608
JR32	2007-000086	R-CHIP	5.6KOHM,5%,1/16W,DA,TP
JR9L	2007-000086	R-CHIP	5.6KOHM,5%,1/16W,DA,TP
JR9R	2007-000086	R-CHIP	5.6KOHM,5%,1/16W,DA,TP
JR4L	2007-000087	R-CHIP	6.8KOHM,5%,1/16W,DA,TP,1608
JR4R	2007-000087	R-CHIP	6.8KOHM,5%,1/16W,DA,TP,1608
JR21	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
JR30	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
JR61	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
JR17	2007-000092	R-CHIP	15KOHM,5%,1/16W,DA,TP
JR17R	2007-000092	R-CHIP	15KOHM,5%,1/16W,DA,TP
JR26	2007-000094	R-CHIP	22KOHM,5%,1/16W,DA,TP
JR64	2007-000094	R-CHIP	22KOHM,5%,1/16W,DA,TP
TR65	2007-000094	R-CHIP	22KOHM,5%,1/16W,DA,TP
JR19	2007-000098	R-CHIP	56Kohm,5%,1/16W,DA,TP,1608
JR8L	2007-000118	R-CHIP	390ohm,5%,1/16W,DA,TP,1608
JR8R	2007-000118	R-CHIP	390ohm,5%,1/16W,DA,TP,1608
JR28	2007-000123	R-CHIP	1.5KOHM,5%,1/16W,DA,TP,1608
JR1	2007-000124	R-CHIP	2.2KOHM,5%,1/16W,DA,TP,1608
JR15	2007-000124	R-CHIP	2.2KOHM,5%,1/16W,DA,TP,1608
JR25	2007-000124	R-CHIP	2.2KOHM,5%,1/16W,DA,TP,1608
JR60	2007-000124	R-CHIP	2.2KOHM,5%,1/16W,DA,TP,1608
JR13L	2007-000132	R-CHIP	180Kohm,5%,1/16W,DA,TP,1608
JR3L	2007-000132	R-CHIP	180Kohm,5%,1/16W,DA,TP,1608
JR3R	2007-000132	R-CHIP	180Kohm,5%,1/16W,DA,TP,1608
JC13L	2203-000236	C-CERAMIC,CHIP	100PF,5%,50V,NPO,1608
JC13R	2203-000236	C-CERAMIC,CHIP	100PF,5%,50V,NPO,1608
JC2L	2203-000236	C-CERAMIC,CHIP	100PF,5%,50V,NPO,1608
JC2R	2203-000236	C-CERAMIC,CHIP	100PF,5%,50V,NPO,1608
JC72	2203-000236	C-CERAMIC,CHIP	100PF,5%,50V,NPO,1608
JC8	2203-000236	C-CERAMIC,CHIP	100PF,5%,50V,NPO,1608
JC30	2203-000257	C-CERAMIC,CHIP	10NF,10%,50V,X7R,TP,1608

Location no.	Code no.	Description & Specification	Remarks
UC65	2203-000405	C-CERAMIC,CHIP	180pF,5%,50V,NPO,TP,1608,-
UC66	2203-000405	C-CERAMIC,CHIP	180pF,5%,50V,NPO,TP,1608,-
JC70	2203-000440	C-CERAMIC,CHIP	1nF,10%,50V,X7R,TP,1608,-
JC111	2203-000681	C-CERAMIC,CHIP	270F,5%,50V,NPO,TP,1608,-
JC4L	2203-000802	C-CERAMIC,CHIP	33nF,10%,50V,X7R,TP,2012,TP
JC4R	2203-000802	C-CERAMIC,CHIP	33nF,10%,50V,X7R,TP,2012,TP
JC14L	2203-001554	C-CERAMIC,CHIP	1.8nF,10%,50V,X7R,TP,1608
JC14R	2203-001554	C-CERAMIC,CHIP	1.8nF,10%,50V,X7R,TP,1608
JC15L	2203-001554	C-CERAMIC,CHIP	1.8nF,10%,50V,X7R,TP,1608
JC15R	2203-001554	C-CERAMIC,CHIP	1.8nF,10%,50V,X7R,TP,1608
JC50	2203-002398	C-CERAMIC,CHIP	22nF,10%,50V,X7R,TP,1608
JC26	2203-005221	C-CERAMIC,CHIP	15nF,10%,50V,X7R,TP,1608,-

#### AH92-00949A ASSY FRONT PCB MM-L7/LZL7

RMC1	AC59-60060A	MODULE-REMOCON	GP1U281R,SHARP,38KHZ,-
VFD	AH07-00044A	VF DISPLAY	HNA-09MS17T,W2000,29°66.9°22.8
UIC1	AH09-00055A	IC MICOM	LC866548V-5V75 S3500/S3600,-
UCW3	AH39-00085A	LEAD CONNECTOR-ASSY	-,5100u,5295,3P,150MM,1007#28
UCW4	AH39-00109A	LEAD CONNECTOR-ASSY	-,5295,5100u,2P,160MM,1007#
UCW2	AH39-00264A	WIRE HARNESS	W2000,1007,-,02P,-,-,5295,5
	AH61-00639A	HOLDER-VFD	MM-L7,ABS 94HB,-,-,-
UCW1	3708-000181	CONNECTOR-FPC/FC/PIC	16P,1.25MM,STRAIGHT,S
FWC1	3711-004757	CONNECTOR-HEADER	TKC-V30P-A1,1.25MM,ANGLE
UD1	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
UD10	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
UD2	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
UD9	0401-000101	DIODE-SWITCHING	1N4148,100V,200mA,500mW,4nS
UD11	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
UD12	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
UD13	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
UD14	0402-000127	DIODE-RECTIFIER	1N4002,100V,1A,DO-41
UQ1	0501-000398	TR-SMALL SIGNAL	KSC945-YTA,NPN,60V,50V,150MA,
UR25	2001-000290	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR44	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR54	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR55	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR56	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR57	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR59	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR70	2001-000429	R-CARBON	1Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR17	2001-000449	R-CARBON	2.2Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR22	2001-000449	R-CARBON	2.2Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR30	2001-000449	R-CARBON	2.2Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR14	2001-000591	R-CARBON	3.3Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR18	2001-000591	R-CARBON	3.3Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR23	2001-000591	R-CARBON	3.3Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR15	2001-000802	R-CARBON	5.6Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR19	2001-000802	R-CARBON	5.6Kohm,5%,1/8W,AA,TP,1.8x3.2mm
UR50	2001-001107	R-CARBON(S)	220ohm,5%,1/2W,AA,TP,2.4x6.4mm
UC15	2202-000854	C-CERAMIC,MLC-AXIAL	47nF,+80-20%,50V,Y5V,3.5x19mm,-
UC3	2401-000243	C-AL	100uF,20%,10V,GP,6*5,2.5MM,TP
UC4	2401-000244	C-AL	100uF,20%,10V,GP,6*3*7,5MM,TP
UC5	2401-001238	C-AL	4.7uF,20%,25V,GP,3*5,2.5MM,TP
UC1	2401-001355	C-AL	470uF,20%,10V,GP,8x11,5.5MM,TP
UC2	2401-001931	C-AL	220nF,20%,50V,GP,4*7,5MM,TP
UC6	2401-001952	C-AL	4.7uF,20%,50V,GP,5*7,5mm,TP
UC7	2401-001952	C-AL	4.7uF,20%,50V,GP,5*7,5mm,TP
UX2	2801-001394	CRYSTAL-UNIT	32.768KHz,20ppm,28-AA,Y,12.5pF,
UX1	2802-000181	RESONATOR-CERAMIC	6MHz,0.3%,BK,9.0X4.0X7.5M
US1-10	3404-000165	SWITCH-TACT	12V,50mA,160gf,SKHV10910A
US12-17	3404-000165	SWITCH-TACT	12V,50mA,160gf,SKHV10910A
UJW16	2007-000029	R-CHIP	0ohm,5%,1/10W,DA,TP,2012
JW36	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW1	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW10	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW11	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW13	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW14	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW15	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW4	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW5	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW6	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW8	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
UJW9	2007-000033	R-CHIP	0ohm,5%,1/8W,DA,TP,3216
JWJ3	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
UJW17	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
UJW2	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
UR37	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
UR38	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608
UR27	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608
UR33-36	2007-000078	R-CHIP	1KOHM,5%,1/16W,TP,1608
UR39-43	2007-000078	R-CHIP	1KOHM,5%,1/16W,TP,1608
UR45-49	2007-000078	R-CHIP	1KOHM,5%,1/16W,TP,1608
UR60-62	2007-000078	R-CHIP	1KOHM,5%,1/16W,TP,1608
UR29	2007-000084	R-CHIP	4.7KOHM,5%,1/16W,DA,TP,1608
UR24	2007-000086	R-CHIP	5.6KOHM,5%,1/16W,DA,TP,
UR10	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
UR11	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
UR12	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
UR16	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
UR20	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
UR51	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608
UR52	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608

Location no.	Code no.	Description & Specification	Remarks
UR70	2007-000097	R-CHIP	47KOHM,5%,1/16W,TP,1608
UR1	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR2	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR3	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR4	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR5	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR6	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR7	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR71	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR72	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR9	2007-000102	R-CHIP	100KOHM,5%,1/16W,DA,TP
UR28	2007-000106	R-CHIP	220K D.R/TP(1608)
UR13	2007-000124	R-CHIP	2.2KOHM,5%,1/16W,DA,TP,1608
UR21	2007-000134	R-CHIP	33KOHM,5%,1/16W,DA,TP,1608
UR26	2007-000134	R-CHIP	33KOHM,5%,1/16W,DA,TP,1608
UR31	2007-000305	R-CHIP	10Mohm,5%,1/16W,DA,TP,1608
UR32	2007-001026	R-CHIP	560Kohm,5%,1/16W,DA,TP,1608
UC14	2203-000062	C-CERAMIC,CHIP	47nF,+80-20%,50V,Y5V,TP,1608,-
UC13	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
UC8	2203-000384	C-CERAMIC,CHIP	.015nF,5%,50V,NPO,TP,1608
UC9	2203-000384	C-CERAMIC,CHIP	.015nF,5%,50V,NPO,TP,1608
UC10	2203-000681	C-CERAMIC,CHIP	27pF,5%,50V,NPO,TP,1608,-
UC11	2203-000681	C-CERAMIC,CHIP	27pF,5%,50V,NPO,TP,1608,-
UC12	2203-000979	C-CERAMIC,CHIP	47nF,10%,50V,X7R,TP,2012,-,TP
UC15	2203-000979	C-CERAMIC,CHIP	47nF,10%,50V,X7R,TP,2012,-,TP

#### AH92-00950A ASSY PCB POWER MM-L7/LZL7

PL1	AH27-10001F	COIL-CHOKE	27uH,K,Q30,-,-,DR(6.5°7.5),-,-
PL2	AH27-10001F	COIL-CHOKE	27uH,K,Q30,-,-,DR(6.5°7.5),-,-
PC1	2201-000795	C-CERAMIC,DISC	10nF,10%,400V,Y5P,TP
PC2	2201-000795	C-CERAMIC,DISC	10nF,10%,400V,Y5P,TP
PF3	3601-000282	FUSE-CARTRIDGE	250V,4A,TIME-LAG,GLASS,5.2°20M
PF2	3601-000304	FUSE-CARTRIDGE	250V,630mA,TIME-LAG,GLASS,5x20
PJ1	3711-000190	CONNECTOR-HEADER	1WALL,2P,1R,7.92mm,STRAIGHT,SN
PWA2	3711-000820	CONNECTOR-HEADER	5267-02A 2P ST
PWA4	3711-001011	CONNECTOR-HEADER	BOX,5P,1R,2.5mm,STRAIGHT,SN
PD1	0402-000151	DIODE-RECTIFIER	1N5392,100V,1.5A,DO-15
PD2	0402-000151	DIODE-RECTIFIER	1N5392,100V,1.5A,DO-15
PD3	0402-000151	DIODE-RECTIFIER	1N5392,100V,1.5A,DO-15
PD4	0402-000151	DIODE-RECTIFIER	1N5392,100V,1.5A,DO-15
PF2*2	3602-000147	FUSE-CLIP	250V,7.5A,30mohm
PF3*2	3602-000147	FUSE-CLIP	250V,7.5A,30mohm
PJW2	3811-000389	WIRE-NO SHEATH CU	SPCW,300V,52.4mm,1/0.5mm,-,-
PJW3	3811-000389	WIRE-NO SHEATH CU	SPCW,300V,52.4mm,1/0.5mm,-,-

#### AH92-00952A ASSY PCB SUB MM-L7/LZL7

MOT	AH31-10021A	MOTOR-DC	RF-500TB,9VDC/130mA,
OCW6-OCW7	AH39-00307A	WIRE HARNESS	MM-L7,-,-,2P,-,-,5295,5295,-
OCW3-OCW4	AH39-00308A	WIRE HARNESS	MM-L7,-,-,2P,-,-,5295,5295,-
ULED1	0601-001436	LED	SEL,U1E10CXM BLUESMM,470NM
ULED2	0601-001436	LED	SEL,U1E10CXM BLUESMM,470NM
MXC1	2202-000797	C-CERAMIC,MLC-AXIAL	10nF,30%,16V,Y5R,3.5x19mm,-,TP
OS1	3405-000101	SWITCH-MICRO	MLS-24
OS2	3405-000101	SWITCH-MICRO	MLS-24
OS3	3405-000101	SWITCH-MICRO	MLS-24
OCW5	3711-000826	CONNECTOR-HEADER	BOX,2P,1R,2MM,ANGLE,SN
OCW5	3711-000827	CONNECTOR-HEADER	BOX,2P,1R,2mm,STRAIGHT,SN
OCW2	3711-000906	CONNECTOR-HEADER	BOX,3P,1R,2mm,ANGLE,SN

#### AH92-00952C ASSY PCB MM-L7/LZL7

DIC1	AH14-10004R	IC	M74HC04,SOP,TAPE,14P
DWF1	AH39-00096B	LEAD CONNECTOR ASSY	#1007,28,AWG28,3P,300m
	0603-001069	OPTIC TRANSMITTER	5V,8Mb/s,-,17dBm,660nm,4mA
DC1	2201-000361	C-CERAMIC,DISC	22nF,+80%,-20% 50V Y5V 8.0°4.0
DC3	2201-000487	C-CERAMIC,DISC	33pF,5%,50V,SL,4x3.5mm,5mm,TP
DC2	2401-000240	C-AL	100uF,20%,10V,GP,5*11mm,5mm,TP
DFT1	2901-001139	FILTER-EMI ON BOARD	50V,-5A,-,390PF,7°2
MWF4	3708-001094	CONNECTOR-FPC/FC/PIC	13P,1.25mm,STRAIGHT,SN
	3809-001234	CABLE-FLAT	30V,80C,150mm,13P,1.25mm,UL289

#### AH92-00952E ASSY PCB MM-L7/LZL7 CE OPTION

PL1	AH27-10001F	COIL-CHOKE	27uH,K,Q30,-,-,DR(6.5°7.5),-,-
PL2	AH27-10001F	COIL-CHOKE	27uH,K,Q30,-,-,DR(6.5°7.5),-,-
AL1	AH27-90001A	COIL-SPRING	2.2uH,-,-,SPRING
AL2	AH27-90001A	COIL-SPRING	2.2uH,-,-,SPRING
AL3	AH27-90001A	COIL-SPRING	2.2uH,-,-,SPRING
AL4	AH27-90001A	COIL-SPRING	2.2uH,-,-,SPRING
AC3	2201-000565	C-CERAMIC,DISC	47nF,+80%,-20% 50V Y5V 12.5°4
AC5	2201-000565	C-CERAMIC,DISC	47nF,+80%,-20% 50V Y5V 12.5°4
FTZ1	2201-000565	C-CERAMIC,DISC	47nF,+80%,-20% 50V Y5V 12.5°4
FTZ4	2201-000565	C-CERAMIC,DISC	47nF,+80%,-20% 50V Y5V 12.5°4
PC1	2201-000795	C-CERAMIC,DISC	10nF,10%,400V,Y5P,TP
PC2	2201-000795	C-CERAMIC,DISC	10nF,10%,400V,Y5P,TP
GC111	2202-000797	C-CERAMIC,MLC-AXIAL	10nF,30%,16V,Y5R,3.5x19mm,-,TP
HL1	2701-000111	INDUCTOR-AXIAL	100uH,10%,2.5x3.4,LA,02TB101K
HL2	2701-000111	INDUCTOR-AXIAL	100uH,10%,2.5x3.4,LA,02TB101K
HL3	2701-000111	INDUCTOR-AXIAL	100uH,10%,2.5x3.4,LA,02TB101K

# Location no. Code no. Description & Specification Remarks

G3HI-SLIM SLIM CD PACK		MM-L7
AH92-00923A ASSY PCB-CD		G3HI-SLIM,3.5S
CW106	AH39-00060A	LEAD CONNECTOR-ASSY
CW103	AH39-00300A	LEAD CONNECTOR ASSY
WIC401	1003-001162	IC-MOTOR DRIVER
X201	2802-000211	RESONATOR-CERAMIC
CW105	3708-000451	CONNECTOR-FPC/FC/PIC
CW101	3708-001388	CONNECTOR-FPC/FC/PIC
CW107	3711-000906	CONNECTOR-HEADER
CW102	3711-004381	CONNECTOR-HEADER
D301	0402-000151	DIODE-RECTIFIER
ZD301	0403-000344	DIODE-ZENER
ZD401	0403-000361	DIODE-ZENER
Q302	0501-000331	TR-SMALL SIGNAL
Q301	0501-000610	TR-SMALL SIGNAL
R110	2001-000331	R-CARBON
R806	2001-000429	R-CARBON
R808	2001-000429	R-CARBON
R809	2001-000429	R-CARBON
R206	2001-000515	R-CARBON
R302	2001-001006	R-CARBON
R301	2008-000140	R-FUSIBLE
C122	2202-000780	C-CERAMIC,MLC-AXIAL
C605A	2202-000780	C-CERAMIC,MLC-AXIAL
C401	2202-000797	C-CERAMIC,MLC-AXIAL
C104	2401-000244	C-AL
C123	2401-000244	C-AL
C124	2401-000244	C-AL
C133	2401-000244	C-AL
C209	2401-000244	C-AL
C212	2401-000244	C-AL
C214	2401-000244	C-AL
C302	2401-000244	C-AL
C310	2401-000244	C-AL
C115	2401-000918	C-AL
C301	2401-001102	C-AL
C605	2401-001511	C-AL
C103	2401-001627	C-AL
C501L	2401-001952	C-AL
C501R	2401-001952	C-AL
C110	2401-001965	C-AL
C112	2401-001965	C-AL
LB501	3301-000297	CORE-FERRITE BEAD
Q101	0501-000314	TR-SMALL SIGNAL
WIC201	0904-001524	IC-DSP
WIC301	1003-000179	IC-MOTOR DRIVER
WIC101	1204-001799	IC-ASP
JW900	2007-000029	R-CHIP
R124	2007-000029	R-CHIP
R813	2007-000029	R-CHIP
R101	2007-000070	R-CHIP
R106	2007-000070	R-CHIP
R125	2007-000070	R-CHIP
R134	2007-000070	R-CHIP
R204	2007-000070	R-CHIP
R601	2007-000070	R-CHIP
R202	2007-000074	R-CHIP
R502L	2007-000074	R-CHIP
R502R	2007-000074	R-CHIP
R205	2007-000078	R-CHIP
R804	2007-000078	R-CHIP
R805	2007-000078	R-CHIP
R807	2007-000078	R-CHIP
R810	2007-000078	R-CHIP
R811	2007-000078	R-CHIP
R812	2007-000078	R-CHIP
DR1	2007-000084	R-CHIP
DR2	2007-000084	R-CHIP
R111	2007-000090	R-CHIP
R112	2007-000090	R-CHIP
R105	2007-000092	R-CHIP
R108	2007-000093	R-CHIP
R114	2007-000094	R-CHIP
R114	2007-000097	R-CHIP
R116	2007-000097	R-CHIP
R119	2007-000097	R-CHIP
R122	2007-000097	R-CHIP
R126	2007-000098	R-CHIP
R127	2007-000098	R-CHIP
R128	2007-000098	R-CHIP
R129	2007-000098	R-CHIP
R120	2007-000100	R-CHIP
R113	2007-000101	R-CHIP
R130	2007-000101	R-CHIP
R131	2007-000101	R-CHIP
R601L	2007-000102	R-CHIP
R601R	2007-000102	R-CHIP
R107	2007-000104	R-CHIP
R109	2007-000109	R-CHIP
R201	2007-000109	R-CHIP
R132	2007-000115	R-CHIP
R121	2007-000129	R-CHIP
R104	2007-000132	R-CHIP

# Location no. Code no. Description & Specification Remarks

R814	2007-000300	R-CHIP	10Kohm,5%,1/10W,DA,TP,2012
R815	2007-000300	R-CHIP	10Kohm,5%,1/10W,DA,TP,2012
R123	2007-000308	R-CHIP	10ohm,5%,1/10W,DA,TP,2012
R102	2007-000355	R-CHIP	12Kohm,5%,1/10W,DA,TP,2012
R900	2007-000444	R-CHIP	180Kohm,5%,1/10W,DA,TP,2012
R118	2007-000778	R-CHIP	330Kohm,5%,1/10W,DA,TP,2012
R107	2007-001179	R-CHIP	8.2Kohm,5%,1/16W,DA,TP,1608
C130	2203-000140	C-CERAMIC,CHIP	1.5nF,10%,50V,X7R,TP,1608,-
C108	2203-000206	C-CERAMIC,CHIP	100nF,10%,50V,X7R,2012,-,TP
C111	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C113	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C129	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C131	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C206	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C207	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C208	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C210	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C211	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C213	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C215	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C216	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C304	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608
C107	2203-000440	C-CERAMIC,CHIP	1nF,10%,50V,X7R,TP,1608,-
C125	2203-000440	C-CERAMIC,CHIP	1nF,10%,50V,X7R,TP,1608,-
C502L	2203-000440	C-CERAMIC,CHIP	1nF,10%,50V,X7R,TP,1608,-
C502R	2203-000440	C-CERAMIC,CHIP	1nF,10%,50V,X7R,TP,1608,-
C503	2203-000440	C-CERAMIC,CHIP	1nF,10%,50V,X7R,TP,1608,-
C118	2203-000491	C-CERAMIC,CHIP	2.2nF,10%,50V,X7R,1608,-
CMLT1	2203-000626	C-CERAMIC,CHIP	22pF,5%,50V,NPO,TP,1608,-
C204	2203-000681	C-CERAMIC,CHIP	27pF,5%,50V,NPO,TP,1608,-
C205	2203-000681	C-CERAMIC,CHIP	27pF,5%,50V,NPO,TP,1608,-
C109	2203-000800	C-CERAMIC,CHIP	33nF,10%,25V,X7R,TP,1608
C126	2203-000800	C-CERAMIC,CHIP	33nF,10%,25V,X7R,TP,1608
C303	2203-000851	C-CERAMIC,CHIP	0.039nF,5%,50V,NPO,TP,1608
C101	2203-000888	C-CERAMIC,CHIP	4.7nF,10%,50V,X7R,TP,1608
C102	2203-000888	C-CERAMIC,CHIP	4.7nF,10%,50V,X7R,TP,1608
C116	2203-000972	C-CERAMIC,CHIP	47nF,10%,16V,X7R,TP,1608
C116A	2203-000972	C-CERAMIC,CHIP	47nF,10%,16V,X7R,TP,1608
C114	2203-001140	C-CERAMIC,CHIP	68nF,10%,16V,X7R,TP,1608,-
C132	2203-001140	C-CERAMIC,CHIP	68nF,10%,16V,X7R,TP,1608,-
C201	2203-001222	C-CERAMIC,CHIP	820pF,10%,50V,X7R,TP,1608,-
CMCK1	2203-001636	C-CERAMIC,CHIP	33pF,5%,50V,NPO,TP,1608,1.6mm
CMDT1	2203-001636	C-CERAMIC,CHIP	33pF,5%,50V,NPO,TP,1608,1.6mm
C117	2203-001640	C-CERAMIC,CHIP	390pF,10%,50V,X7R,TP,1608
C119	2203-001640	C-CERAMIC,CHIP	390pF,10%,50V,X7R,TP,1608
C105	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
C106	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
C120	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
C121	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
C127	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
C128	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
C202	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
C203	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
C250	2203-005005	C-CERAMIC,CHIP	100nF,10%,16C,X7R,TP,1608
	3809-001188	CABLE-FLAT	16P,1.25MM,240MM,A-TYPE

## G3HI-SLIM/MP3 CD PACK ASSY ; 3.5 SLIM-MP3 MM-ZL7

3809-001188 CABLE-FLAT:30V,80C,240mm,16P,1.25mm,UL2896

## AH92-00923A ASSY PCB-CD:G3HI-SLIM,3.5S

WIC401	1003-001162	IC-MOTOR DRIVER,KA3082,SIP,10PIN,25MIL,DOUBLE
X201	2802-000211	RESONATOR-CERAMIC;51015-08,51004-08,8P,300MM,1007#28
CW105	3708-000451	CONNECTOR-FPC/FC/PIC;16P,1.25MM,STRAIGHT
CW101	3708-001388	CONNECTOR-FPC/FC/PIC;16P,1MM,ANGLE,SN
CW107	3711-000906	CONNECTOR-HEADER;BOX,3P,1R,2mm,ANGLE,SN
CW102	3711-004381	CONNECTOR-HEADER;BOX,6P,1R,1.5MM,STRAIGHT,SN
CW106	AH39-00060A	LEAD CONNECTOR-ASSY;-51015-08,51004-08,8P,300MM,1007#28
CW103	AH39-00300A	LEAD CONNECTOR ASSY;G3HI-SLIM,-,2P,250MM,-,51004,35023,U
D301	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,TP
ZD301	0403-000344	DIODE-ZENER;UZ3.9B,3.9V,3.7-4.1V,500mW
ZD401	0403-000361	DIODE-ZENER;UZ6.2BSB,6.2V,5.99-6.24V,50
Q302	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-92,TP,120-240
Q301	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160
R110	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM
R207	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
R806	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
R808	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
R809	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
R206	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM
R302	2001-001006	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM
R301	2008-000140	R-FUSIBLE;2.2OHM,5%,1/2W,AA,TP,3.5X9.4MM
C122	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5V,3.5X19,-
C401	2202-000797	C-CERAMIC,MLC-AXIAL;10nF,30%,16V,Y5S,TP,3.5X1.9MM,-
C250	2203-000178	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,1608,
C104	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7.5
C123	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7.5
C124	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7.5
C133	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7.5
C212	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7.5
C214	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7.5
C219	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7.5
C302	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7.5
C310	2401-000244	C-AL;100uF,20%,10V,GP,TP,6.3x7.5
C115	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7.5

Location no.	Code no.	Description & Specification	Remarks
C301	2401-001102	C-AL:330UF,20%,16V,GPTP,8X12,5	
C605	2401-001511	C-AL:47UF,20%,16V,GP,-,6X7,5	
C103	2401-001627	C-AL:6.8UF,20%,50V,GP,TP,6.3X7,2,5M	
C501L	2401-001952	C-AL:4.7UF,20%,50V,-,TP,6.3X7,5	
C501R	2401-001952	C-AL:4.7UF,20%,50V,-,TP,6.3X7,5	
C110	2401-001965	C-AL:470NF,20%,50V,-,BK,4X7MM,1,5MM	
C112	2401-001965	C-AL:470NF,20%,50V,-,BK,4X7MM,1,5MM	
LB501	3301-000297	CORE-FERRITE BEAD:AA,3.6x1.2x5.7mm,1400,2900G	
Q101	0501-000314	TR-SMALL SIGNAL:KSAB12,PNP,150mW,SOT-23,TP,90-	
WIC201	0904-001524	IC-DSP:SL9290,-,QFP,48P,472MIL,16.9344MHz,TR,CM	
WIC301	1003-000179	IC-MOTOR DRIVER:KA9258D,SOP,28P,-,SINGLE,-,ST,	
WIC101	1204-001799	IC-ASP:KB9226,LQFP,48P,393MIL,PLASTIC,5.5V,-,2	
R124	2007-000029	R-CHIP:0OHM,5%,1/10W,DA,TP,2012	
R813	2007-000029	R-CHIP:0OHM,5%,1/10W,DA,TP,2012	
R106	2007-000070	R-CHIP:0ohm,5%,1/16W,DA,TP,1608	
R125	2007-000070	R-CHIP:0ohm,5%,1/16W,DA,TP,1608	
R134	2007-000070	R-CHIP:0ohm,5%,1/16W,DA,TP,1608	
R204	2007-000070	R-CHIP:0ohm,5%,1/16W,DA,TP,1608	
R601	2007-000070	R-CHIP:0ohm,5%,1/16W,DA,TP,1608	
R202	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R502L	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R502R	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R205	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R804	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R805	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R807	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R610	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R611	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R612	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R101	2007-000079	R-CHIP:1.8Kohm,5%,1/16W,DA,TP,1608	
R102	2007-000090	R-CHIP:10Kohm,5%,1/16W,DA,TP,1608	
R111	2007-000090	R-CHIP:10Kohm,5%,1/16W,DA,TP,1608	
R112	2007-000090	R-CHIP:10Kohm,5%,1/16W,DA,TP,1608	
R814	2007-000090	R-CHIP:10Kohm,5%,1/16W,DA,TP,1608	
R105	2007-000092	R-CHIP:15Kohm,5%,1/16W,DA,TP,1608	
R108	2007-000093	R-CHIP:20Kohm,5%,1/16W,DA,TP,1608	
R115	2007-000094	R-CHIP:22Kohm,5%,1/16W,DA,TP,1608	
R114	2007-000097	R-CHIP:47Kohm,5%,1/16W,DA,TP,1608	
R116	2007-000097	R-CHIP:47Kohm,5%,1/16W,DA,TP,1608	
R119	2007-000097	R-CHIP:47Kohm,5%,1/16W,DA,TP,1608	
R122	2007-000097	R-CHIP:47Kohm,5%,1/16W,DA,TP,1608	
R126	2007-000098	R-CHIP:56Kohm,5%,1/16W,DA,TP,1608	
R127	2007-000098	R-CHIP:56Kohm,5%,1/16W,DA,TP,1608	
R128	2007-000098	R-CHIP:56Kohm,5%,1/16W,DA,TP,1608	
R129	2007-000098	R-CHIP:56Kohm,5%,1/16W,DA,TP,1608	
R120	2007-000100	R-CHIP:68Kohm,5%,1/16W,DA,TP,1608	
R113	2007-000101	R-CHIP:82Kohm,5%,1/16W,DA,TP,1608	
R130	2007-000101	R-CHIP:82Kohm,5%,1/16W,DA,TP,1608	
R131	2007-000101	R-CHIP:82Kohm,5%,1/16W,DA,TP,1608	
R501L	2007-000102	R-CHIP:100Kohm,5%,1/16W,DA,TP,1608	
R501R	2007-000102	R-CHIP:100Kohm,5%,1/16W,DA,TP,1608	
R117	2007-000104	R-CHIP:150Kohm,5%,1/16W,DA,TP,1608	
R109	2007-000109	R-CHIP:1Mohm,5%,1/16W,DA,TP,1608	
R201	2007-000109	R-CHIP:1Mohm,5%,1/16W,DA,TP,1608	
R132	2007-000115	R-CHIP:82ohm,5%,1/16W,DA,TP,1608	
R121	2007-000129	R-CHIP:27Kohm,5%,1/16W,DA,TP,1608	
R104	2007-000132	R-CHIP:180Kohm,5%,1/16W,DA,TP,1608	
R123	2007-000308	R-CHIP:10OHM,5%,1/10W,DA,TP,2012	
R118	2007-000778	R-CHIP:330Kohm,5%,1/10W,DA,TP,2012	
R107	2007-001179	R-CHIP:8.2Kohm,5%,1/16W,DA,TP,1608	
C130	2203-000140	C-CERAMIC,CHIP:1.5nF,10%,50V,X7R,TP,1608,-	
C108	2203-000206	C-CERAMIC,CHIP:100nF,10%,50V,X7R,TP,2012	
C111	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C113	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C129	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C131	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C206	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C207	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C208	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C210	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C211	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C213	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C215	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C216	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C304	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608	
C107	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	
C125	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	
C502L	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	
C502R	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	
C503	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	
C118	2203-000491	C-CERAMIC,CHIP:2.2nF,10%,50V,X7R,TP,1608,-	
C204	2203-000681	C-CERAMIC,CHIP:0.027nF,5%,50V,NP0,TP,1608	
C205	2203-000681	C-CERAMIC,CHIP:0.027nF,5%,50V,NP0,TP,1608	
C109	2203-000800	C-CERAMIC,CHIP:33nF,10%,25V,X7R,TP,1608	
C126	2203-000800	C-CERAMIC,CHIP:33nF,10%,25V,X7R,TP,1608	
C303	2203-000851	C-CERAMIC,CHIP:0.039nF,5%,50V,NP0,TP,1608	
C101	2203-000888	C-CERAMIC,CHIP:4.7nF,10%,50V,X7R,TP,1608	
C102	2203-000888	C-CERAMIC,CHIP:4.7nF,10%,50V,X7R,TP,1608	
C116	2203-000972	C-CERAMIC,CHIP:47nF,10%,16V,X7R,TP,1608	
C114	2203-001140	C-CERAMIC,CHIP:68nF,10%,16V,X7R,TP,1608,-	
C132	2203-001140	C-CERAMIC,CHIP:68nF,10%,16V,X7R,TP,1608,-	
C201	2203-001222	C-CERAMIC,CHIP:820pF,10%,50V,X7R,TP,1608,-	
CMCK1	2203-001636	C-CERAMIC,CHIP:0.033nF,5%,50V,NP0,TP,1608	

Location no.	Code no.	Description & Specification	Remarks
CMDT1	2203-001636	C-CERAMIC,CHIP:0.033nF,5%,50V,NP0,TP,1608	
CMLT1	2203-001636	C-CERAMIC,CHIP:0.033nF,5%,50V,NP0,TP,1608	
C117	2203-001640	C-CERAMIC,CHIP:0.39nF,10%,50V,X7R,TP,1608	
C119	2203-001640	C-CERAMIC,CHIP:0.39nF,10%,50V,X7R,TP,1608	
C105	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
C106	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
C120	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
C121	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
C127	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
C128	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
C202	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
C203	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
WIC602	1105-001339	IC-DRAM:11L1644,4Mx4Bit,TSOP,24P,300MIL,50ns,3.3	
WIC601	1204-001798	IC-DECODER:SSL9274X01-EOR0,LQFP,64P,-,PLASTIC,3.3V,	
R207	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R208	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R209	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R621	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R602	2007-000070	R-CHIP:0ohm,5%,1/16W,DA,TP,1608	
R607	2007-000070	R-CHIP:0ohm,5%,1/16W,DA,TP,1608	
R203	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R608	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R609	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R610	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R611	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R612	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R613	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R614	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R615	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R616	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R617	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R618	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R619	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R620	2007-000074	R-CHIP:100ohm,5%,1/16W,DA,TP,1608	
R604	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R605	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R606	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R801	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R802	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R803	2007-000078	R-CHIP:1Kohm,5%,1/16W,DA,TP,1608	
R603	2007-000572	R-CHIP:220OHM,5%,1/10W,DA,TP,2012	
C603	2203-001222	C-CERAMIC,CHIP:820pF,10%,50V,X7R,TP,1608,-	
C606	2203-002041	C-CERAMIC,CHIP:0.47nF,10%,50V,X7R,TP,1608	
C607	2203-002041	C-CERAMIC,CHIP:0.47nF,10%,50V,X7R,TP,1608	
C602	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
C604	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
C609	2203-005005	C-CERAMIC,CHIP:100nF,10%,16V,X7R,TP,1608	
C601	2401-001511	C-AL:47UF,20%,16V,GP,-,6X7,5	

AH81-00380A A/S PART-SPEAKER SYST PS L7E,-,SPEAKER SYSTEM,-

AH81-00380B A/S PART-SPEAKER SYST PS ZL7E,-,SPEAKER SYSTEM,-