

TC	IC751 SDRAM		SIGNAL NAME	IC801 RIPPING AUDIO LSI	
	PORT NAME	PIN NO		PIN NO	PORT NAME
1	A0	23	A0	5	SDRA0
	A1	24	A1	4	SDRA1
	A2	25	A2	3	SDRA2
	A3	26	A3	2	SDRA3
	A4	29	A4	7	SDRA4
	A5	30	A5	8	SDRA5
	A6	31	A6	9	SDRA6
	A7	32	A7	10	SDRA7
	A8	33	A8	15	SDRA8
	A9	34	A9	16	SDRA9
	A10	22	A10	11	SDRA10
	A11	35	A11	17	SDRA11
	A12	36	A12	18	SDRA12

TC	IC751 SDRAM		SIGNAL NAME	IC801 RIPPING AUDIO LSI	
	PORT NAME	PIN NO		PIN NO	PORT NAME
2	DQ0	2	DQ0	48	SDRD0
	DQ1	4	DQ1	47	SDRD1
	DQ2	5	DQ2	46	SDRD2
	DQ3	7	DQ3	45	SDRD3
	DQ4	8	DQ4	37	SDRD4
	DQ5	10	DQ5	36	SDRD5
	DQ6	11	DQ6	35	SDRD6
	DQ7	13	DQ7	34	SDRD7
	DQ8	42	DQ8	39	SDRD8
	DQ9	44	DQ9	40	SDRD9
	DQ10	45	DQ10	41	SDRD10
	DQ11	47	DQ11	42	SDRD11
	DQ12	48	DQ12	50	SDRD12
	DQ13	50	DQ13	51	SDRD13
	DQ14	51	DQ14	52	SDRD14
	DQ15	53	DQ15	53	SDRD15

TC	IC701 FLASH MEMORY		SIGNAL NAME	IC801 RIPPING AUDIO LSI	
	PORT NAME	PIN NO		PIN NO	PORT NAME
3	DQ15	45	FA0	154	HIR0
	A0	25	FA1	155	HIR1
	A1	24	FA2	156	HIR2
	A2	23	FA3	158	HIB0
	A3	22	FA4	149	NHINT
	A4	21	FA5	165	DACK1
	A5	20	FA6	164	DRQ1
	A6	19	FA7	162	DACK2
	A7	18	FA8	161	DRQ2
	A8	8	FA9	159	GPIO5
	A9	7	FA10	160	GPIO4
	A10	6	FA11	168	RCVCLK
	A11	5	FA12	169	RCVSTART
	A12	4	FA13	170	RCVDATA
	A13	3	FA14	171	RCVWAIT
	A14	2	FA15	138	HID8
	A15	1	FA16	139	HID9
	A16	48	FA17	142	HID10
	A17	17	FA18	143	HID11
	A18	16	FA19	144	HID12
	A19	9	FA20	145	HID13
	A20	10	FA21	147	HID14
	A21	13	FA22	148	HID15

TC	IC701 FLASH MEMORY		SIGNAL NAME	IC801 RIPPING AUDIO LSI	
	PORT NAME	PIN NO		PIN NO	PORT NAME
4	DQ0	29	FD0	128	HID0
	DQ1	31	FD1	129	HID1
	DQ2	33	FD2	130	HID2
	DQ3	35	FD3	132	HID3
	DQ4	38	FD4	133	HID4
	DQ5	40	FD5	135	HID5
	DQ6	42	FD6	136	HID6
	DQ7	44	FD7	137	HID7