

7 Electrical Parts List

* You can search for updated part codes through ITSELF web site.

URL : <http://itself.sec.samsung.co.kr/>

7-1-1 LE15V* Main PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
0	LE15VS				
1	SN-LE15VS	-	1	SDD,NORMAL	-
3	BH94-00975A	-	ASSY PCB MAIN-SN	LE15VS	SNA
4	2306-000248	C503	C-FILM,LEAD-PPF	680nF,5%,250V,BK,26.5x16.5mm,2	SA
4	2301-001195	C601	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2301-001195	C602	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2401-003392	C605	C-AL	180uF,20%,450V,GP,BK,25x45,10	SA
4	BH63-00134A	CIS1	SHIELD-BOTTOM	LE17KS,SECC,T1.0	SNA
4	6502-000001	CIS11	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	6502-000001	CIS12	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	BH39-00323D	CIS13	LEAD CONNECTOR-ASSY	0T17L0,8.0*0.16TA*16,150MM,35068-9822,35750-1010,BK,8.0*0.16TA*16	SA
4	0204-001527	CIS4	FLUX	DF-201TVS,MIX,0.820,FLUX 13%,14KG	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	0204-000442	CIS5	SOLVENT	1M-1000,C3H7OH,96,-	SNA
4	3711-003895	CN201	CONNECTOR-HEADER	BOX,13P,1R,2mm,STRAIGHT,SN	SA
4	3711-003873	CN202	CONNECTOR-HEADER	BOX,7P,1R,2mm,STRAIGHT,SN	SA
4	3711-004379	CN203	CONNECTOR-HEADER	BOX,4P,1R,2MM,STRAIGHT,SN	SA
4	3711-005055	CN401	CONNECTOR-HEADER	1WALL,4P,1R,10MM/8.0MM,STRAIGHT,SN-PB,WHT	SA
4	BH39-00401A	CN501	LEAD CONNECTOR-ASSY	DT15LT,UL1007#22,UL/CSA,2P,170MM,BLK,#22,YBNH250-02,BK,1007#22	SA
4	3721-001053	CN601	PLUG-AC POWER	3P,-,NI	SNA
4	0402-001295	D405	DIODE-RECTIFIER	GUR460L-5700,600V,4A,DO-201AD,BK	SA
4	0402-001025	D406	DIODE-RECTIFIER	ERD07-15,1.5KV,1.5A,-,TP	SA
4	0402-001407	D601	DIODE-BRIDGE	G2SB60,600V,1.5A,SIP-4,BK	SA
4	0402-000005	D625	DIODE-RECTIFIER	31DF4,400V,3A,DO-201AD,BK	SA
4	3301-000233	FBT_CORE	CORE-FERRITE	AC,18X9.6X12MM,1500,2800GAUSS	SA
4	6003-000122	FBT+H/S	SCREW-TAPTITE	BH,+B,M4,L12,ZPC(YEL),SWRCH18	SNA
4	3601-001302	FH1	FUSE-AXIAL LEAD	250V,3.15A,SLOW-BLOW,CERAMIC,5X20MM	SA
4	BH63-00124A	HS401	SHIELD-IC	LE17KS,SPTe,T0.2	SNA
4	3704-001071	IC201_SOC	SOCKET-IC	42P,DIP,SN,1.778mm	SA
4	1204-002259	IC401	IC-DEF. PROCESSOR	STV9118,SDIP,32P,27.94x8.89mm,PLASTIC,13.2V,-,0to+70C,ST,IC-DEF. PROCESSOR	△ SNA
4	1203-003240	IC621	IC-POS.FIXED REG.	L78M05,IPAK,3P,6.5x6.1mm,PLASTIC,4.75/5.25V,-,0to+150C,0.5A,-,ST	SA
4	1203-000243	IC622	IC-POS.FIXED REG.	7812,TO-220,3P,-,PLASTIC,11.5/12.5V,-,16W,0to+125C,1A,-,ST	SA
4	BH27-00131A	L411	COIL CHOKE	150UH,AN17K,150UH,10%,0.350HM,2.5A,AR8X25,72.5TS,18X39MM,11MM,BK	SA
4	BH27-00137A	L441	COIL LINEARITY	6.1UH,6.1UH,DR12X15,7MM,15X15X37MM,12X37,4T,32TS,TR,12%,0.050HM,USTC0.12X30	SA
4	BH27-00131A	L501	COIL CHOKE	150UH,AN17K,150UH,10%,0.350HM,2.5A,AR8X25,72.5TS,18X39MM,11MM,BK	SA
4	BH29-00002A	L601	FILTER LINE NOISE	AN15VS,20MH,0.420HM,1.5KV,20MH,22X17X34MM,220V,TR,20MH,100MOHM,-,10CTO+85C	SA
4	6003-001023	M/PCB+SH/BTM	SCREW-TAPTITE	RWH,+B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	0505-001675	Q451	FET-SILICON	IRF630B,N,200V,9A,0.40HM,72W,TO-220	SA
4	0505-001675	Q452	FET-SILICON	IRF630B,N,200V,9A,0.40HM,72W,TO-220	SA
4	3501-001111	RL601	RELAY-POWER	12VDC,250MW,5000MA,1FORMA,15MS,5MS	SA
4	6003-000133	SH/BTM+AC/SOCK	SCREW-TAPTITE	BH,+S,M4,L8,ZPC(YEL),SWRCH18A,-	SNA
4	BH39-00451A	SIGNAL	CBF SIGNAL	LE17JS,15P/06P,07P,20276-N,1830mm,UL20276,BLACK,D-SUB /MALE,BLACK,30V,ATT. TYPE	SNA
4	BH26-00027A	T401	TRANS-HOR.DRIVE	FQB-17A001,PL-3,EI1916,310UH	△ SA
4	BH26-00162A	T501	TRANS FBT	FSA0210,AN15V,1.97mH,HV45,HV45,32.5,0.44ohm,164.5,12P,-10~55,BK,26KV	△ SA
4	BH26-00164A	T601	TRANS POWER	ER-3435,CU17KS,350uH,15,90-264V,80V,10-55,FERRITE,ER-3435,0.05ohm/0.350ohm,8uH M	SA
4	BH26-00163A	T602	TRANS	UU-1116,CU17K,5,18mH min,18mH max,2.7ohm MAX,10~55,FERRITE,UU-1116 SB-5S	SA
4	1404-001264	TH601	THERMISTOR-PTC	4.50HM,+30/-20%,220V,290VAC,21A,-,TR	SA
4	1404-001020	TH602	THERMISTOR-NTC	8ohm,15%,-,17mW/C,BK	SA
4	BH97-00505A	MICOM	ASSY MICOM	LE15VS	SA
5	0903-001194	IC201	IC-MICROCONTROLLER	3P863,8Bit,SDIP,42P,600MIL,12MHz,ST,CMOS,PLASTIC,5V,-,40to+85C,1040BYTE,48KBYTE	△ SNA
5	BH82-00020G	CIS	A/S MICOM	LE15VS	SNA
4	BH97-00507A	-	ASSY AUTO-(MAIN)SN	LE15VS	SNA
5	3301-001450	BD401	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA

Level	Loc. No.	CodeNo.	Description	Specification	Remarks
5	3301-001450	BD402	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD431	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD501	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD502	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD601	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD621	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD622	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2202-002037	C201	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2202-000205	C202	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-000205	C203	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-000121	C205	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
5	2202-000796	C206	C-CERAMIC,MLC-AXIAL	1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	SA
5	2202-000121	C207	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
5	2401-000603	C208	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C209	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-002299	C210	C-AL	4.7uF,20%,50V,GP,TP,5x7,5	SA
5	2401-002299	C211	C-AL	4.7uF,20%,50V,GP,TP,5x7,5	SA
5	2301-000148	C213	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2401-000039	C301	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2301-000519	C302	C-FILM,LEAD-PEF	3.3nF,5%,100V,TP,5.8x3x12.5,5m	SA
5	2305-000665	C303	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000148	C304	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2305-000237	C305	C-FILM,LEAD-PEF	1uF,5%,63V,TP,7.5x15.5mm,5mm	SA
5	2401-000852	C306	C-AL	220uF,20%,35V,GP,TP,8x11.5mm,5	SA
5	2202-002008	C307	C-CERAMIC,MLC-AXIAL	10nF,+80-20%,50V,Y5V,TP,2.3X3.	SA
5	2305-000196	C331	C-FILM,LEAD-PEF	150nF,5%,63V,TP,-,5mm	SA
5	2305-000412	C332	C-FILM,LEAD-PEF	470nF,5%,63V,TP,-,5mm	SA
5	2401-002144	C333	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2401-001334	C401	C-AL	0.47uF,20%,50V,GP,TP,5X11,2,5	SA
5	2401-001220	C402	C-AL	4.7uF,20%,160V,GP,TP,8x11,5,5	SA
5	2301-000010	C403	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2301-001463	C404	C-FILM,LEAD-PPF	4nF,5%,630V,TP,17X9X5,7,5	SA
5	2303-001023	C405	C-FILM,LEAD-PEF	2.2nF,5%,2.5KV,TP,23x13x19,7,5	△ SA
5	2303-001023	C406	C-FILM,LEAD-PEF	2.2nF,5%,2.5KV,TP,23x13x19,7,5	△ SA
5	2401-001914	C411	C-AL	1uF,20%,50V,BP,TP,5x11,5	SA
5	2201-000471	C412	C-CERAMIC,DISC	0.33nF,10%,50V,Y5P,TP,4X3.5MM,5	SA
5	2301-000016	C413	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2301-000005	C414	C-FILM,LEAD-PEF	33nF,5%,100V,TP,5.8x12.5x3,5	SA
5	2401-001012	C415	C-AL	3.3uF,20%,50V,BP,TP,16X25,7,5	SA
5	2401-000025	C431	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2305-000665	C432	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000148	C433	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2202-000573	C434	C-CERAMIC,MLC-RADIAL	0.82nF,5%,50V,C0G,TP,5.1X3.2X5.1MM,5	SA
5	2301-000148	C435	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2401-000660	C436	C-AL	2.2uF,20%,50V,GP,TP,5x11,5	SA
5	2401-000603	C437	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-002144	C438	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2201-000672	C441	C-CERAMIC,DISC	0.82nF,10%,500V,Y5P,TP,6.5X3MM,5	SA
5	2301-001162	C451	C-FILM,LEAD-PPF	370nF,5%,250V,TP,19x18.5x12,5,	SA
5	2306-000131	C452	C-FILM,LEAD-PPF	150nF,5%,250V,TP,19x16x7,5,7,5	SA
5	2306-000171	C455	C-FILM,LEAD-PPF	270nF,5%,250V,TP,21.5x12.5mm,7	SA
5	2401-000603	C456	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C457	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-003826	C501	C-AL	220uF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000291	C502	C-CERAMIC,DISC	1nF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2401-002267	C505	C-AL	2.2uF,20%,250V,GP,TP,8x11,5,5	SA
5	2301-000294	C521	C-FILM,LEAD-PEF	56nF,5%,100V,TP,9.5x12.5mm,5mm	SA
5	2202-002037	C531	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2301-000188	C532	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6,5,5	SA
5	2401-000758	C533	C-AL	0.22uF,20%,50V,GP,TP,5X11,5	SA
5	2301-000005	C534	C-FILM,LEAD-PEF	33nF,5%,100V,TP,5.8x12.5x3,5	SA
5	2301-000188	C535	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6,5,5	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2301-000203	C536	C-FILM,LEAD-PEF	2.7nF,5%,100V,TP,7x3.0x6.5mm,5	SA
5	2202-002037	C537	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3	SA
5	2201-000023	C603	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2201-000023	C604	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-000970	C606	C-AL	22uF,20%,50V,WT,TP,5x11,5	SA
5	2202-002037	C607	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3	SA
5	2201-000325	C608	C-CERAMIC,DISC	2.2NF,10%,500V,Y5P,TP,9.5X4MM,5	SA
5	2201-000129	C609	C-CERAMIC,DISC	0.1NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2301-000188	C610	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2401-000611	C611	C-AL	1uF,20%,50V,WT,TP,5x11,5	SA
5	2305-000665	C613	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000284	C614	C-FILM,LEAD-PEF	47nF,5%,100V,TP,8.5x12.5mm,5mm	SA
5	2401-001513	C615	C-AL	47uF,20%,16V,WT,TP,5x11,5	SA
5	2202-002037	C616	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3	SA
5	2201-000023	C617	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-003046	C618	C-AL	47uF,20%,50V,WT,TP,6.3x11,2.5	SA
5	2201-000291	C619	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2201-000325	C620	C-CERAMIC,DISC	2.2NF,10%,500V,Y5P,TP,9.5X4MM,5	SA
5	2305-000178	C621	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-,5mm	SA
5	2401-000039	C622	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C624	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000025	C625	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-002463	C626	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2401-000039	C627	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-002300	C628	C-AL	47uF,20%,50V,GP,TP,6.3x11,5	SA
5	2401-003826	C629	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000469	C630	C-CERAMIC,DISC	0.33NF,10%,500V,Y5P,TP,5.5X3MM,5	SA
5	2401-000039	C631	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C632	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2301-000010	C633	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
4	BN61-01137A	CIS16	SUPPORT-CLIP	IBM E74,NYLON 66,1.0,NTR	SNA
5	0203-001199	CIS7	TAPE-KRAFT	#53110,T0.1,W6,L2000M,BRN	SNA
5	0203-001200	CIS8	TAPE-PAPER	#53128,T0.15,W5.5,L2000M,BEIGE	SNA
5	3711-000217	CN602	CONNECTOR-HEADER	1WALL,2P,1R,7.92MM,STRAIGHT,SN,NTR	SA
5	0401-000005	D201	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000128	D301	DIODE-RECTIFIER	1N4002GP,100V,1A,DO-41,TP	SA
5	0402-000546	D302	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D341	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D401	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	D402	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0402-000208	D403	DIODE-RECTIFIER	EK-04,40V,1A,DO-41,TP	SA
5	0402-000274	D404	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000005	D411	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D412	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D413	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D414	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000274	D441	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000006	D451	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000006	D452	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000546	D455	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-001118	D501	DIODE-RECTIFIER	UF1G,400V,1.2A,DO-204AC,TP	SA
5	0402-000274	D502	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000546	D504	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D511	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D512	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D521	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D522	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D523	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	D531	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	D532	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	D533	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000012	D603	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0402-000012	D604	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000546	D605	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D606	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D607	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D608	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D621	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001194	D622	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000274	D623	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000274	D624	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000012	D626	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-001194	D627	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000546	D628	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	6042-000001	EY301	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY302	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY401	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY402	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY403	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY404	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY405	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY406	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY441	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY442	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY501	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY502	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY503	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY504	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY505	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY506	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY507	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY601	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY602	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY603	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY604	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY605	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY606	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY607	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY608	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY621	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY622	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	BH71-40300A	GT601	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT602	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	1103-001149	IC241	IC-EEPROM	KS24C041C,512X8BIT,DIP,8P,9.2X6.4MM,-,2.7/5.5V,-,PLASTIC,-25TO+70C,5UA,CMOS,ST	△ △ SA
5	BH39-40305U	JP1	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP10	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP11	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP12	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP13	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP14	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP15	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP16	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP17	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP18	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP19	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP2	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP20	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP21	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP22	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP23	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP24	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP25	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP26	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP27	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH39-40305U	JP3	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP31	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP32	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP33	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP34	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP35	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP37	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP38	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP4	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP5	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP6	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP7	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP8	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP9	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH41-00268A	MP1.0	PCB MAIN	LE17JS,FR-1,1,1.0,1.6T,247*247,LE17,MAIN	SNA
5	0501-000372	Q401	TR-SMALL SIGNAL	KSC2383-Y,NPN,90000mW,TO-92L,TP,160-320	Y
5	0501-000303	Q411	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q412	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000140	Q413	TR-SMALL SIGNAL	2N5551,NPN,625mW,TO-92,TP,80-250	SA
5	0501-000412	Q455	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000412	Q456	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000586	Q501	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q502	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q511	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000143	Q512	TR-SMALL SIGNAL	2N6520,PNP,625mW,TO-92,TP,30-200	SA
5	0501-000122	Q601	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000010	Q621	TR-SMALL SIGNAL	KSC1008,NPN,800mW,TO-92,TP,120-240	SA
5	0501-000586	Q622	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000404	Q623	TR-SMALL SIGNAL	KSD1616-Y,NPN,750mW,TO-92,TP,135-270	SA
5	0501-000586	Q624	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-002228	Q625	TR-SMALL SIGNAL	KTA1281,PNP,1000mW,TO-92L,TP,120-240	SA
5	2001-000869	R201	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R202	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000008	R203	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000008	R204	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R205	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R206	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R207	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R209	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R210	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R211	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R212	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R213	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R214	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000554	R215	R-CARBON	2700HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R216	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R217	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R218	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R219	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R220	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R221	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R222	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R223	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	R224	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000435	R225	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R231	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R232	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R241	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R242	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R243	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000539	R302	R-CARBON	24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001329	R303	R-METAL	9.1Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000628	R304	R-CARBON	3000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000481	R305	R-METAL	2.4Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000970	R306	R-METAL	470ohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001022	R307	R-METAL	5.6Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-004014	R308	R-METAL	2.4ohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-004014	R309	R-METAL	2.4ohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-001111	R310	R-CARBON(S)	2400HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000908	R311	R-CARBON	62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001053	R312	R-CARBON(S)	1.5OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R331	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000010	R332	R-CARBON	68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000702	R333	R-CARBON	39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R334	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001178	R401	R-CARBON(S)	680OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000110	R402	R-CARBON	100HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000429	R403	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000773	R404	R-CARBON	470KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001078	R405	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000736	R406	R-METAL OXIDE(S)	560ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000438	R407	R-METAL OXIDE(S)	1.5ohm,5%,3W,AA,TP,6x16mm	SA
5	2001-000020	R408	R-CARBON(S)	220HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2004-000979	R411	R-METAL	47Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000262	R412	R-METAL	120Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000216	R415	R-METAL	10Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001060	R416	R-METAL	51Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000397	R417	R-CARBON	180KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000613	R418	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000327	R419	R-METAL	150Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000698	R420	R-METAL	3.3Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000344	R421	R-METAL	15Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001254	R431	R-METAL	8.2Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000449	R432	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000650	R441	R-METAL OXIDE(S)	330ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000290	R451	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R452	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R453	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R454	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R455	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R456	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001099	R501	R-CARBON(S)	2.7KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000145	R502	R-METAL OXIDE	100ohm,5%,1W,AA,TP,4.3x12mm	SA
5	2001-000333	R503	R-CARBON	120HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000522	R504	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000703	R505	R-METAL OXIDE(S)	470ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000407	R506	R-METAL OXIDE(S)	0.6ohm,5%,2W,AA,TP,4x12mm	△ SA
5	2001-000107	R507	R-CARBON(S)	150KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	R508	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	△ SA
5	2001-000786	R511	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001071	R512	R-CARBON(S)	12KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2002-001099	R514	R-COMPOSITION	68KOHM,5%,1/2W,AA,TP,3.0X9.0MM	SNA
5	2002-001097	R515	R-COMPOSITION	33KOHM,5%,1/2W,AA,TP,4X12MM	SA
5	2004-000825	R521	R-METAL	36Kohm,1%,1/4W,AB,TP,2.4x6.4mm	SA
5	2004-000861	R522	R-METAL	39Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000008	R523	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R524	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000337	R525	R-CARBON	130KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000864	R531	R-CARBON	56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R532	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000478	R533	R-CARBON	2.7OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000890	R534	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000995	R535	R-CARBON	820OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000861	R536	R-METAL	39Kohm,1%,1/4W,AA,TP,2.4x6.4mm	△ SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2004-000218	R537	R-METAL	10Kohm,1%,1/8W,AA,TP,1.8x3.2mm	△ SA
5	2004-000284	R538	R-METAL	12Kohm,1%,1/4W,AA,TP,2.4x6.4mm	△ SA
5	2001-000008	R539	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	△ SA
5	2004-000458	R540	R-METAL	2.2Kohm,1%,1/4W,AA,TP,2.4x6.4mm	△ SA
5	2001-000356	R541	R-CARBON	150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000319	R542	R-CARBON	120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	R601	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001129	R602	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000738	R603	R-METAL OXIDE(S)	56Kohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000014	R604	R-METAL OXIDE(S)	10Kohm,5%,3W,AA,TP,6x16mm	SA
5	2002-001103	R605	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2002-001103	R606	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2001-001116	R607	R-CARBON(S)	270HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R608	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000780	R609	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R610	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R611	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-001126	R620	R-CARBON(S)	300OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000023	R621	R-CARBON	470HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000027	R622	R-CARBON	100OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000613	R623	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R624	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R625	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000290	R626	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001088	R628	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000786	R629	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000062	R630	R-CARBON	470OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2003-000471	R631	R-METAL OXIDE(S)	10ohm,5%,2W,AA,TP,4x12mm	SA
5	6042-000002	TP501	EYELET	ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	SNA
5	2801-000006	X201	CRYSTAL-UNIT	12MHz,50ppm,28-AAM,S,35ohm,BK	SA
5	0403-000348	ZD201	DIODE-ZENER	UZ36B,33-39V,500MW,DO-35,TP	SA
5	0403-001068	ZD202	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA
5	0403-000361	ZD211	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD212	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD221	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD222	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD223	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD224	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD225	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD226	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD241	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD242	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000355	ZD514	DIODE-ZENER	UZ5.1BSB,5-5.2V,500MW,DO-35,TP	SA
5	0403-001221	ZD601	DIODE-ZENER	UZ39BSB,35.36-37.19V,500MW,DO-34,TP	SA
5	0403-000361	ZD602	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
4	BP96-00064C	HS601	ASSY HEAT SINK P	BH62-00004A,SPRING,8S0765RC,RUBBER SILICON	SNA
5	BH13-00045A	CIS	IC HYBRID	FS8S0765RCYDTU,CU17KS,5,-25 to 85,TO-220(FORMING),35,ST	SA
5	BH61-00004A	CIS	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,TO.5,-,-,-	SNA
5	BH62-00004A	CIS	HEAT SINK-POWER	,-T1,-,A1050S,DA/DB	SNA
5	BH62-20001B	CIS	TUBE-RUBBER	CSQ4357,W25*120*TO.45,-,-,-,-	SNA
4	BP96-00065B	HS301	ASSY HEAT SINK P	BH62-00003B,SPRING,STV9325,OIL SILICON	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	1204-002262	H/S	IC-VERTICAL DEF.	STV9325,HEPTAWATT,7P,15.45x10.22mm,PLASTIC,35V,-,-40to+150C,ST,IC-VERTICAL DEF.	SNA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+2S,M3,L6,ZPC(YEL),SWRCH18	SNA
5	BH62-00003B	H/S	HEAT SINK-VERT	A1050S,T1.0,T1.0,-,DA,DB	SNA
4	BP96-00066R	HS490	ASSY HEAT SINK P	BH62-00015A,SPRING,KTD2058,FFPF04F150S,2001HI,OIL SILICON	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	0402-001495	H/S	DIODE-RECTIFIER	FFPF04F150S,1500V,4A,DO-204AC,ST	SA
5	0502-000465	H/S	TR-POWER	KTD2058,NPN,25000mW,TO-220IS,ST,100-200	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0502-001232	H/S	TR-POWER	ST2001HI,NPN,55000MW,ISOWATT218,ST,5-10	SA
5	BH61-00004A	H/S	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,-,TO.5,-,-,-	SNA
5	BH61-70003A	H/S	SPRING ETC	CVT4857,STS304-W1/2H,W3.8,-,L30,L30,-,TO.5,DEGRE,W3.8,STS304-W1/2H	SNA
5	BH62-00015A	H/S	HEAT SINK-FBT	A1050S,T1.0,T1.0,-,-	SNA
4	BP96-00072A	HS590	ASSY HEAT SINK P	H/S TR,SPRING,IRF630B,OIL SILICON	SNA
5	0205-001027	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001675	CIS	FET-SILICON	IRF630B,N,200V,9A,0.40HM,72W,TO-220	SA
5	BH61-00004A	CIS	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,-,TO.5,-,-,-	SNA
5	BH62-00016A	CIS	HEAT SINK-TR	A1050S,T1.0,-,DP17MO	SNA

7-1-2 LE15V* SN Video PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH94-00977A	-	ASSY PCB VIDEO-SN	LE15VS	SNA
4	BH63-00131A	CIS1	SHIELD-VIDEO	LE17KS,SPTe,TO.2	SNA
4	6502-000001	CIS10	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	BH39-00412A	CIS11	LEAD CONNECTOR	AN17K*,8*0.16*16TA,160MM,35750-1010,YRT187L,BK	SA
4	BH39-00134A	CIS12	CBF-HARNESS	DT15LT,3*0.16TA,100MM,BLK,AWG18,35068-9822,EARTH CLIP,BK	SA
4	0204-001527	CIS3	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG	SNA
4	0204-000442	CIS4	SOLVENT	1M-1000,C3H7OH,96,-	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	BH61-70003A	CIS5	SPRING ETC	CVT4857,STS304-W1/2H,W3.8,-,L30,L30,-,TO.5,DEGRE,W3.8,STS304-W1/2H	SNA
4	3711-004236	CN101	CONNECTOR-HEADER	BOX,6P,1R,2MM,STRAIGHT,SN	SNA
4	BH39-00015A	CN102	CBF-HARNESS	13P/14P,200MM,WHT/BLK/RED/BLU,UL1007,AWG26,SMH200-13/YBNH200-14	SA
4	BH13-00050A	IC102	IC HYBRID	NT6813K-30031,NT6813K-30031,24P,-55 to +150,240mA,-0.5 to 6V,ST	SA
4	3704-001201	SK101	SOCKET-CRT	10P,22.5PI,22.5PI,NH+SN,-	SA
4	BH96-00284A	HS106	ASSY HEAT SINK P	BH62-00053A,SCREW,STV9588,OIL SILICON,BRKT-VIDEO	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	1201-002113	H/S	IC-VIDEO AMP	SAM9588,CLIPWATT,19P,19.85x10.7mm,-,26,PLASTIC,110V,3W,0ta+70C,-,-,-,-,-,ST	SA
5	6003-000333	H/S	SCREW-TAPTITE	RH,+,2S,M3,L10,ZPC(YEL),SWRCH1	SNA
5	BH61-00048A	H/S	BRACKET-VIDEO	andromeda,SECC,0.8	SNA
5	BH62-00053A	H/S	HEAT SINK-PS	LEO,A1050S,1.0,112,25	SNA
4	BH97-00509A	-	ASSY AUTO-(VIDEO)SN	LE15VS	SNA
5	3301-001450	BD102	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD103	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD104	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD105	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-000011	BD106	BEAD-AXIAL	,3.5x1.0x5.7mm,,BK,,,	SA
5	3301-001450	BD107	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2301-000014	C101	C-FILM,LEAD-PEF	6.8nF,5%,100V,TP,5.8x12.5mm,5m	SA
5	2401-000025	C103	C-AL	100uF,20%,16V,GP,TP,6.3x11.5	SA
5	2401-000758	C104	C-AL	0.22UF,20%,50V,GP,TP,5X11.5	SA
5	2201-000370	C105	C-CERAMIC,DISC	0.22NF,10%,50V,Y5P,TP,4X3.5MM,5	SA
5	2201-000019	C106	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2401-002463	C111	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2201-000119	C112	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C113	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2201-000119	C114	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C115	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C116	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000383	C117	C-FILM,LEAD-PEF	10nF,5%,50V,TP,6x7x3.2mm,5mm	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2202-002009	C118	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C119	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C120	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	C121	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C122	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2301-000010	C123	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-001218	C124	C-AL	4.7uF,20%,100V,WT,TP,5x11,5	SA
5	2202-002009	C125	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000019	C131	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2201-002110	C132	C-CERAMIC,DISC	1.8nF,10%,1kV,Y5P,TP,10x5mm,5	SA
5	2201-000288	C133	C-CERAMIC,DISC	1NF,10%,2KV,Y5P,TP,9X5MM,7.5	SA
5	2202-002009	CB01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CB03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CB04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2201-000247	CB05	C-CERAMIC,DISC	0.015NF,5%,50V,C0G,TP,5X3MM,5	SA
5	2202-002009	CG01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CG03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CG04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2201-000247	CG05	C-CERAMIC,DISC	0.015NF,5%,50V,C0G,TP,5X3MM,5	SA
5	0203-001199	CIS6	TAPE-KRAFT	#53110,T0.1,W6,L2000M,BRN	SNA
5	0203-001200	CIS7	TAPE-PAPER	#53128,T0.15,W5.5,L2000M,BEIGE	SNA
5	BH71-40300A	CN_G2	PIN-HINGE	BRASS,D2.361,HEAT/SINK,SN	SNA
5	BH71-40300A	CN_GND	PIN-HINGE	BRASS,D2.361,HEAT/SINK,SN	SNA
5	2202-002009	CR01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CR03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CR04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2201-000247	CR05	C-CERAMIC,DISC	0.015NF,5%,50V,C0G,TP,5X3MM,5	SA
5	0401-000005	DB01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DB02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DB03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DB05	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DG01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DG02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DG03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DG05	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DR01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DR02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DR03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DR05	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	6042-000001	EY1	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY2	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY3	EYELET	ID1.5,OD2.12.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY4	EYELET	ID1.5,OD2.12.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY5	EYELET	ID1.5,OD2.12.8,NI+SN,BSP3-1/2H	SNA
5	BH39-40305U	JP5	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP6	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP7	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2701-000189	LB01	INDUCTOR-AXIAL	0.47uH,10%,2534	SA
5	2701-000189	LG01	INDUCTOR-AXIAL	0.47uH,10%,2534	SA
5	2701-000189	LR01	INDUCTOR-AXIAL	0.47uH,10%,2534	SA
5	BH41-00273A	MP1.0	PCB-VIDEO	LE15VS,FR1,1L,1.0,1.6T,123.5 * 82.3,VIDEO ASS,6,247*247	SNA
5	2001-000084	R101	R-CARBON	100Kohm,5%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-001192	R102	R-CARBON(S)	820OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	R103	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000660	R104	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R105	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R106	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000016	R107	R-CARBON(S)	1OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000435	R111	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000812	R112	R-CARBON	5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R113	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R114	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R115	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R116	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R121	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000419	R122	R-METAL OXIDE(S)	1.2ohm,5%,1W,AA,TP,3.3x9mm	SA
5	2001-001148	R131	R-CARBON(S)	4300HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000037	R132	R-CARBON(S)	3300HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RB01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000376	RB02	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000780	RB03	R-CARBON	4700HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000376	RB04	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000028	RB06	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RB07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000028	RB08	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RB09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000376	RG02	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000780	RG03	R-CARBON	4700HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000376	RG04	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000028	RG06	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RG07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000028	RG08	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RG09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000376	RR02	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000780	RR03	R-CARBON	4700HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000376	RR04	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000028	RR06	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RR07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000028	RR08	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RR09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	1405-001064	SK104	SURGE ABSORBER	400V,20%,--,AXIAL	SA
5	4715-001065	SK105	SURGE ABSORBER	200V,20%,--,RADIAL	SNA
5	4715-001055	SK108	SURGE ABSORBER	1kV,+50-10%,--,RADIAL	SNA
5	4715-001065	SKB01	SURGE ABSORBER	200V,20%,--,RADIAL	SNA
5	4715-000102	SKG01	SURGE ABSORBER	200V,20%,1000A,--,RADIAL	SNA
5	4715-000102	SKR01	SURGE ABSORBER	200V,20%,1000A,--,RADIAL	SNA
5	0403-000361	ZD102	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD103	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000509	ZD105	DIODE-ZENER	MTZJ5.6B,5.4-5.7V,500MW,DO-34,TP	SA
5	0403-000361	ZD106	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA

7-1-3 LE15V* SZ Video PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BH94-00997E	-	ASSY PCB VIDEO-SZ	LE15VS	SNA
3	0202-001362	CIS1	SOLDER-WIRE	-.S63S,D3,63Sn/37Pb,-	SNA
3	6502-000001	CIS10	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
3	0202-001366	CIS2	SOLDER-WIRE FLUX	-.RS60S,D1.2,63Sn/37Pb,-	SNA
3	0204-002420	CIS3	SOLVENT	1M-1000,C3H7OH,96,-,-	SNA
3	0204-002426	CIS4	FLUX	DF-201TVS,MIX,0.820,FLUX 13%, 14KG,-	SNA
3	BH63-00131A	CIS7	SHIELD-VIDEO	LE17KS,SPT,E,T0.2	SNA
3	BH68-00001A	CIS8	LABEL-MARK CDT	ART-PAPER 100G,-,WHT,BLK,-,ALL,CDT	SNA
3	3711-004236	CN101	CONNECTOR-HEADER	BOX,6P,1R,2MM,STRAIGHT,SN	SNA
3	BH39-00015A	CN102	CBF-HARNESS	13P/14P,200MM,WHT/BLK/RED/BLU,UL1007,AWG26,SMH200-13/YBNH200-14	SA
3	BH13-00053A	IC102	IC HYBRID-AMP/OSD	LM1236DEM,LE15V,24P,0 to +70,Plastic,200mA,4.75V to 5.25V,STICK	SNA
3	BH13-00022A	IC104	IC HYBRID-BIAS CLAMP	LM2480NA,PN15H/17L,8P,0to+70C,DIP,3mA,85V,ST	SA
3	6003-001023	SH/VID+H/S	SCREW-TAPTITE	PWH,+B,M3,L10,ZPC(YEL),SWRCH18A,-	SNA
3	3704-001201	SK101	SOCKET-CRT	10P,22.5PI,22.5PI,NI+SN,-	SNA
3	BH96-00284B	HS106	ASSY HEAT SINK P	BH62-00053A,SCREW,LM2470TA,OIL SILICON,BRACKET-IC	SNA
4	0205-001154	H/S	OIL-SILICON	G746,-,-	SNA
4	1201-002155	H/S	IC-VIDEO AMP	LM2470TA,T0-220,9P,-,-,-,PLASTIC,90V,4.3W,-20to+100C,-,-,-,-,ST	SNA
4	6003-000334	H/S	SCREW-TAPTITE	RH,+2S,M3,L6,ZPC(YEL),SWRCH18	SA
4	BH62-00053A	H/S	HEAT SINK-VIDEO	LEO,A1050S,1.0,112,25	SNA
3	BH97-00521Z	-	ASSY AUTO-VIDEO-AUTO	LE15VS	SNA
4	3301-001450	BD101	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,...	SNA
4	3301-001450	BD102	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,...	SNA
4	3301-001450	BD104	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,...	SNA
4	2301-000010	C101	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
4	2401-002463	C103	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
4	2401-001340	C104	C-AL	0.47UF,20%,50V,WT,TP,5X11,5	SA
4	2201-000019	C106	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
4	2401-000287	C111	C-AL	100uF,20%,16V,WT,TP,6.3x11,5	SA
4	2202-002009	C112	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
4	2201-000119	C114	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
4	2305-000178	C117	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-,5mm	SA
4	2202-000121	C118	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
4	2301-000188	C119	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
4	2202-000121	C120	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
4	2401-000287	C121	C-AL	100uF,20%,16V,WT,TP,6.3x11,5	SA
4	2202-002009	C122	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
4	2301-000010	C123	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
4	2401-000049	C124	C-AL	47uF,20%,100V,WT,TP,10x16,5	SA
4	2201-000119	C126	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
4	2201-000019	C131	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
4	2201-002110	C132	C-CERAMIC,DISC	1.8nF,10%,1kV,Y5P,TP,10x5mm,5	SA
4	2201-000288	C133	C-CERAMIC,DISC	1NF,10%,2KV,Y5P,TP,9X5MM,7.5	SA
4	2202-002009	CB01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
4	2202-002009	CB02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
4	2301-000010	CB03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
4	2401-003911	CB04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
4	2202-000162	CB05	C-CERAMIC,MLC-AXIAL	0.015NF,5%,50V,SL,TP,3.5X1.9MM,-	SA
4	2202-002009	CG01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
4	2202-002009	CG02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
4	2301-000010	CG03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
4	2401-003911	CG04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
4	2202-000162	CG05	C-CERAMIC,MLC-AXIAL	0.015NF,5%,50V,SL,TP,3.5X1.9MM,-	SA
4	0203-001599	CIS5	TAPE-KRAFT	#53110,0.1,6,2000M,BRN	SNA
4	0203-001600	CIS6	TAPE-PAPER	#53128,0.15,5.5,2000M,BEIGE	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	BH71-40300A	CN_G2	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
4	BH71-40300A	CN_GND1	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
4	2202-002009	CR01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
4	2202-002009	CR02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
4	2301-000010	CR03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
4	2401-003911	CR04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
4	2202-000162	CR05	C-CERAMIC,MLC-AXIAL	0.015NF,5%,50V,SL,TP,3.5X1.9MM,-	SA
4	0401-000005	DB01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
4	0401-000005	DB02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
4	0401-000004	DB03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
4	0401-000004	DB04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
4	0401-000004	DB05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
4	0401-000005	DG01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
4	0401-000005	DG02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
4	0401-000004	DG03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
4	0401-000004	DG04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
4	0401-000004	DG05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
4	0401-000005	DR01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
4	0401-000005	DR02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
4	0401-000004	DR03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
4	0401-000004	DR04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
4	0401-000004	DR05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
4	6042-000002	EY3	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
4	6042-000002	EY5	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
4	6042-000002	EY7	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
4	BH39-40305U	JP_15	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
4	BH39-40305U	JP103	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
4	BH39-40305U	JP106	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
4	BH39-40305U	JP107	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
4	BH39-40305U	JP108	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
4	BH39-40305U	JP109	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
4	BH39-40305U	JP110	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
4	BH39-40305U	JP114	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
4	BH39-40305U	JP115	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
4	2701-001078	LB01	INDUCTOR-AXIAL	680NH,10%,2534	SA
4	2701-001078	LG01	INDUCTOR-AXIAL	680NH,10%,2534	SA
4	2701-001078	LR01	INDUCTOR-AXIAL	680NH,10%,2534	SA
4	BH41-00273A	MP1.0	PCB-VIDEO	LE15VS,FR1,1L,1.0,1.6T,123.5 * 82.3,VIDEO ASS,6,247*247	SNA
4	2001-000800	R102	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000429	R103	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000660	R105	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000429	R106	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000016	R107	R-CARBON(S)	10HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	2001-000780	R108	R-CARBON	4700HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000290	R111	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000878	R112	R-CARBON	6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000429	R113	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000429	R114	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-001138	R131	R-CARBON(S)	3900HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	2001-000037	R132	R-CARBON(S)	3300HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	2001-000009	R134	R-CARBON	20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000084	R135	R-CARBON	100Kohm,5%,1/4W,AA,TP,2.4x6.4mm	SA
4	2001-000969	RB01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000969	RB02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000429	RB03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000028	RB05	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	2001-000429	RB06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-001129	RB07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	2001-000376	RB08	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000028	RB09	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	2001-000969	RG01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000969	RG02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000429	RG03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000028	RG05	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	2001-000429	RG06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-001129	RG07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	2001-000376	RG08	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000028	RG09	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	2001-000969	RR01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000969	RR02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000429	RR03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000028	RR05	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	2001-000429	RR06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-001129	RR07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	2001-000376	RR08	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
4	2001-000028	RR09	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
4	4715-001076	SK104	SURGE ABSORBER	400V,20%,-,-,RADIAL	SNA
4	4715-001055	SK108	SURGE ABSORBER	1kV,+50-10%,-,-,RADIAL	SNA
4	4715-001065	SKB01	SURGE ABSORBER	200V,20%,-,-,RADIAL	SNA
4	4715-000102	SKG01	SURGE ABSORBER	200V,20%,1000A,-,RADIAL	SA
4	4715-001065	SKR01	SURGE ABSORBER	200V,20%,-,-,RADIAL	SNA

7-1-4 LE15V* Others

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BH90-00587A	-	ASSY COVER REAR	LE15VS,EDC	SNA
3	BH63-00123A	C/R	COVER-REAR	LE15VS,ABS V0,IV16	SNA
2	BH90-00598A	-	ASSY STAND	LE17JS/LE15VS,EDC	SNA
3	BH96-00272A	STD	ASSY STAND P	LE17KS,ABS HB IV16	SNA
4	6902-000109	STD	BAG PE	HDPE,T0.015,L430,W350,TRP,28,2,PE MARK	SNA
4	BH60-00030A	STD	FASTENER-BAND	PN17LT,ST+PVC,P0.4,-,150,YELLOW,-,-,-	SNA
4	BH61-00049A	STD	STAND-BASE	LE17KS,ABS HB,IV16	SNA
4	BH61-00050A	STD	STAND-TOP	LE17KS,ABS HB,IV16	SNA
4	BH61-40002A	STD	FOOT-RUBBER	-,NR,PMS428U,GA4237,-,-,-	SNA
4	BH63-30103A	STD	FELT-STAND	MCM1755,FELT,T1.0,W10,L4	SNA
4	BH68-20366A	STD	LABEL-MARK STAND	,ART PAPER100(S),WHT	SNA
4	BH68-70306A	STD	CARD-STAND	CVM4967PWS(SKD),WONSTROW,CHAIN	SNA
2	BH90-00654A	-	ASSY COVER FRONT	LE15VS,EDC	SNA
3	6003-000009	C/F+C/R	SCREW-TAPTITE	BH,+B,M4,L16,ZPC(YEL),SWRCH18	SNA
3	6006-001119	C/F+CDT	SCREW-ASS'Y TAPT	WC,BH,+M5,L25,ZPC(YEL),SWRCH18A	SNA
3	BH96-00270A	C/F	ASSY COVER P-FRONT	LE15VS,ABS V0 IV16	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	6003-001023	C/F	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	BH63-00122A	C/F	COVER-FRONT	LE15VS,ABS V0,IV16	SNA
4	BH64-00151A	C/F	KNOB-FUNCTION	LE17KS,ABS,HB,IV16	SNA
4	BH67-00045A	C/F	LENS-LED	LE17KS,ACRYL,CLEAR,SYNCMASER	SNA
4	BH72-00298A	C/F	GUIDE-CDT	,ABS,IV16,PN17LT,HB	SNA
4	BH96-00287A	C/F	ASSY BOARD P-FUNCTION	LE19IS,FUNTION	SNA
2	BH91-00843R	-	ASSY CDT-SN	LE15VS	SNA
3	0201-001576	CDT	ADHESIVE-RBR	DC-3140_RTV#0414,TRP,-,-	SNA
3	0203-000005	CDT	TAPE-ACETATE	SGT730,T0.26,W19,L3000,BLK	SNA
3	3302-000006	CDT	MAGNET-RUBBER	AF,14G,1620-1980G,0.58-0.9MGOe	SA
3	3309-000002	CDT	MAGNET-SHEET	5x20x80mm,UL94V-0,2	SA
3	6502-001019	CDT	CABLE CLAMP	DAMC-10,ID9.9,T7.1,NYLON6.6,GRAY	SNA
3	BH03-10014A	CDT	CDT-SN	M36KUM35X02,-,15,0.28,-,MS-GUN,-,-,-,-,VLMF,4	SA
3	BH68-30003C	CDT	LABEL-00,HIGH,VOLTAGE	SS,ART100G,30*33,YEL	SNA
3	BH96-00291A	CDT	ASSY D-COIL P	15INCH,BH27-00149A,BH96-00286A	SNA
2	BH91-00945A	-	ASSY CHASSIS-SN	LE15VS	SA
2	BH92-01073A	-	ASSY P/MATERIAL	LE15VS	SNA
3	0203-001100	P/M	TAPE-OPP MASKING	OPP/W75/CLR,T0.05,W75,L800000,CLR	SNA
3	0203-001159	P/M	TAPE-FILAMENT	#8915,T0.15,W12,L55000,CLR	SNA
3	6902-000001	P/M	BAG AIR	LDPE,T0.2,L1800,W1000,TRP,,,LDPE ONLY	SNA
3	6902-000379	P/M	BAG AIR	HDPE,T0.2,L1800,W1000,TRP,,,PAPER	SNA
3	6902-000523	P/M	BAG PE	HDPE,T0.015,W900,L800,TRP,28 LANGUAGE,2-	SNA
3	6902-000576	P/M	BAG ROLL	LDPE,T0.05,W2400,L1000,TRP,-,-	SNA
3	BH69-00560A	P/M	CUSHION	CUSHION,EPS M50	SNA
3	BH69-40380A	P/M	PACKING-PAD	DW-2,500X2200X200,-,CGK5527	SNA
2	BH92-01092A	-	ASSY BOX	LE15VS,EDC	SNA
3	BH68-00329A	BOX	LABEL BAR CODE-02	ALL,MPRII,DOM,EXPORT,MOJO 90G,WHT	SNA
3	BH69-00571A	BOX	BOX	S/M591S(LE15VS) W/W,CB-SW4,YEL,A-1,W427*D452*H352	SNA
2	BH92-01093A	-	ASSY LABEL	LEO-PJT(15/17/19)	SAN
3	BH68-00565D	LABEL	LABEL RATING-00	ALL,SS,PE,T0.05,90*65,BLK,POLYESTER,EDC	SNA
2	BH92-01147A	-	ASSY ACCESSORY	LE15VS/17LS/17KS/17J	SNA
3	BH96-00297A	UNIT/ACCESSORY	ASSY ACCESSORY	LEO	-
4	0203-000214	ACCESSORY	TAPE-OPP MASKING	OPP/W50/CLR,T0.05,W50,L400000,	SNA
4	6902-000110	ACCESSORY	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
4	BH39-10339H	ACCESSORY	CBF POWER CORD	DET,H05VV-F,250V/10,16A,BLK,25	SA
4	BH68-70418A	ACCESSORY	CARD-EU BLOC WARR-07	SyncMaster,BASIC,EU,MOJO,100G,	SNA
4	BH96-00296A	ACCESSORY	ASSY MANUAL P-IB+QSG	795DF,SyncMaster,W/W,27Lang,BH59-362A+BH68-376J	-
5	BH59-00362A	I/B	S/W DRIVER-00,IB	793S,795DF,W/W,SYNCMASER,27LANG	SNA
5	BH68-00376J	QUICK	MANUAL-01	AN_QUICK SETUP GUIDE,SYNCMASER,E/F/S/G/P/L,14LANGS,W/W,MOJO100G,298,420	SNA

7-2-1 LE17LS(LE17LT) Main PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
0	LE17LS7B/EDC				
1	SC-LE17LS7B/EDC	-	1	SDI,HIGH-CON	-
3	BH94-00989A	-	ASSY PCB MAIN-SX	LEO	SNA
4	2301-001125	C451	C-FILM,LEAD-PPF	600nF,5%,250V,TP,26x20x11.5,20	SA
4	2306-000147	C503	C-FILM,LEAD-PPF	1uF,5%,250V,BK,26x24x15,22.5mm	SA
4	2301-001195	C601	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2301-001195	C602	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2401-003391	C605	C-AL	220uF,20%,450V,GP,BK,25x50,10	SA
4	BH63-00134A	CIS1	SHIELD-BOTTOM	LE17KS,SECC,T1.0	SNA
4	BH39-00323D	CIS10	LEAD CONNECTOR-ASSY	0T17L0,8.0*0.16TA*16,150MM,35068-9822,35750-1010,BK,8.0*0.16TA*16	SA
4	BH39-00323D	CIS11	LEAD CONNECTOR-ASSY	0T17L0,8.0*0.16TA*16,150MM,35068-9822,35750-1010,BK,8.0*0.16TA*16	SA
4	BH63-00143A	CIS3	COVER-PCB R	LE17KS,ABS PC,IV16	SNA
4	BH63-00144A	CIS4	COVER-PCB L	LE17KS,ABS PC,IV16	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	0204-001527	CIS6	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG	SNA
4	0204-000442	CIS7	SOLVENT	1M-1000,C3H7OH,96,-	SNA
4	3711-003895	CN201	CONNECTOR-HEADER	BOX,13P,1R,2mm,STRAIGHT,SN	SA
4	3711-003873	CN202	CONNECTOR-HEADER	BOX,7P,1R,2mm,STRAIGHT,SN	SA
4	3711-004379	CN203	CONNECTOR-HEADER	BOX,4P,1R,2MM,STRAIGHT,SN	SA
4	3711-005055	CN401	CONNECTOR-HEADER	1WALL,4P,1R,10MM/8.0MM,STRAIGHT,SN-PB,WHT	SA
4	3721-001053	CN601	PLUG-AC POWER	3P,-,NI	SNA
4	0402-001295	D405	DIODE-RECTIFIER	GUR460L-5700,600V,4A,DO-201AD,BK	SA
4	0402-001025	D406	DIODE-RECTIFIER	ERD07-15,1.5KV,1.5A,-,TP	SA
4	0402-001407	D601	DIODE-BRIDGE	G2SB60,600V,1.5A,SIP-4,BK	SA
4	0402-000005	D625	DIODE-RECTIFIER	31DF4,400V,3A,DO-201AD,BK	SA
4	6003-000122	FBT+H/S	SCREW-TAPTITE	BH,+B,M4,L12,ZPC(YEL),SWRCH18	SNA
4	3601-001302	FH1	FUSE-AXIAL LEAD	250V,3.15A,SLOW-BLOW,CERAMIC,5X20MM	SA
4	BH63-00124A	HS401	SHIELD-IC	LE17KS,SPT,TO.2	SNA
4	6502-000001	HS490_CIS1	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	6502-000001	HS490_CIS2	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	3704-001071	IC201_SOCKET	SOCKET-IC	42P,DIP,SN,1.778mm	△ SA
4	1204-002259	IC401	IC-DEF. PROCESSOR	STV9118,SDIP,32P,27.94x8.89mm,PLASTIC,13.2V,-,0to+70C,ST,IC-DEF. PROCESSOR	△ SA
4	1203-003240	IC621	IC-POS.FIXED REG.	L78M05,IPAK,3P,6.5x6.1mm,PLASTIC,4.75/5.25V,-,0to+150C,0.5A,-,ST	SA
4	1203-000243	IC622	IC-POS.FIXED REG.	7812,TO-220,3P,-,PLASTIC,11.5/12.5V,-,16W,0to+125C,1A,-,ST	SA
4	BH27-00135A	L411	COIL CHOKE	120UH,CDTMO,120UH,10%,0.23OHM,5A,AR8X25,65.5TS,18X40MM,11MM,USTC0.12X20,TR,10CT	SA
4	BH27-00139A	L441	COIL LINEARITY	6.4UH,6.4UH,DR1215 C:4.5,7.0MM,13.8X14.5X46MM,12X8T,25TS,BK,12%,0.04OHM,USTC0.12	SA
4	BH27-00134A	L501	COIL CHOKE	100UH,CDTMO,100UH,10%,0.20HM,5.0A,AR8X25,60.5TS,18X40MM,11MM,USTC0.12X20,TR,10C	SA
4	BH27-00007A	L601	COIL-LINE FILTER	SQE2424,25mH MIN,-,SQE 2424,-,PHENAL,-,0.32ohm,21*27*33,-,BULK	SA
4	6003-001023	M/PCB+SH/BTM	SCREW-TAPTITE	RWH,+B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	0505-001309	Q452	FET-SILICON	IRF630,N,200V,10A,0.4OHM,100W,TO-220	SA
4	0505-001309	Q453	FET-SILICON	IRF630,N,200V,10A,0.4OHM,100W,TO-220	SA
4	3501-001111	RL601	RELAY-POWER	12VDC,250MMW,5000MA,1FORMA,15MS,5MS	SA
4	6003-000133	SH/BTM+AC/SOCK	SCREW-TAPTITE	BH,+S,M4,L8,ZPC(YEL),SWRCH18A,-	SNA
4	BH39-00451A	SIGNAL	CBF SIGNAL	LE17JS,15P/06P,07P,20276-N,1830mm,UL20276,BLACK,D-SUB /MALE,BLACK,30V,ATT. TYPE	SNA
4	BH26-00027A	T401	TRANS-HOR.DRIVE	FQB-17A001,PL-3,EI1916,310UH	△ SA
4	BH26-00171A	T501	TRANS FBT	CF2166,LE17JS,1.50mH,FERRITE,0.32OHM,BULK,14P,-10--+60,26.3kV	△ SNA
4	BH26-00114A	T561	TRANS-FOUCS	EE-1916,PN17L,5P,1.7mH,-,70mH,-,0.85ohm/8.5ohm,-,PL3,DMR30,EE-1916,20uH MAX,	SA
4	BH26-00164A	T601	TRANS POWER	ER-3435,CU17KS,350uH,15,90-264V,80V,10-55,FERRITE,ER-3435,0.05ohm/0.35ohm,8uH M	SA
4	BH26-00163A	T602	TRANS	UU-1116,CU17K,5,18mH min,18mH min,2.7ohm MAX,10 - 55,FERRITE,UU-1116 SB-5S	SA
4	1404-001264	TH601	THERMISTOR-PTC	4.5OHM,+30/-20%,220V,290VAC,21A,-,TR	SA
4	1404-001020	TH602	THERMISTOR-NTC	8ohm,15%,-,17mW/C,BK	SA
4	BH97-00505B	MICOM	ASSY MICOM	LE17JS	SA
5	BH82-00020H	CIS	A/S MICOM	LE17JS	SNA
5	0903-001194	IC201	IC-MICROCONTROLLER	3P863,8Bit,SDIP,42P,600MIL,12MHz,ST,CMOS,PLASTIC,5V,-,40to+85C,1040BYTE,48KBYTE	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	BH97-00521A	-	ASSY AUTO-MAIN-AUTO	LEO	SNA
5	3301-001450	BD321	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD401	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD402	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD431	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD501	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD502	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD601	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD621	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD622	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2202-002037	C201	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2202-000205	C202	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-000205	C203	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2401-000603	C204	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2202-000121	C205	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
5	2202-000796	C206	C-CERAMIC,MLC-AXIAL	1NF,10%,50V,Y5P,TP,3.5X1.9MM,-	SA
5	2202-000121	C207	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
5	2401-000603	C208	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C209	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-002299	C210	C-AL	4.7uF,20%,50V,GP,TP,5x7,5	SA
5	2401-002299	C211	C-AL	4.7uF,20%,50V,GP,TP,5x7,5	SA
5	2202-000205	C212	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2401-002463	C301	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2301-000148	C302	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2305-000665	C303	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000014	C304	C-FILM,LEAD-PEF	6.8nF,5%,100V,TP,5.8x12.5mm,5m	SA
5	2305-000289	C305	C-FILM,LEAD-PEF	220nF,5%,63V,TP,-,5mm	SA
5	2401-000852	C306	C-AL	220uF,20%,35V,GP,TP,8x11.5mm,5	SA
5	2202-002008	C307	C-CERAMIC,MLC-AXIAL	10nF,+80-20%,50V,Y5V,TP,2.3X3.	SA
5	2202-002037	C321	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2401-000480	C322	C-AL	10uF,20%,50V,GP,TP,5x11,5	SA
5	2305-000196	C331	C-FILM,LEAD-PEF	150nF,5%,63V,TP,-,5mm	SA
5	2305-000412	C332	C-FILM,LEAD-PEF	470nF,5%,63V,TP,-,5mm	SA
5	2401-002144	C333	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2401-001334	C401	C-AL	0.47UF,20%,50V,GP,TP,5X11,2.5	SA
5	2401-001220	C402	C-AL	4.7uF,20%,160V,GP,TP,8x11.5,5	SA
5	2301-000010	C403	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2303-001029	C404	C-FILM,LEAD-PPF	5.2nF,5%,630V,TP,19x7x13,7.5	SA
5	2309-000106	C405	C-FILM,LEAD-OTHER	2.2nF,5%,1.6KV,TP,23x16x9,7.5m	△ SA
5	2309-000106	C406	C-FILM,LEAD-OTHER	2.2nF,5%,1.6KV,TP,23x16x9,7.5m	△ SA
5	2305-000178	C407	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-,5mm	SA
5	2401-001914	C411	C-AL	1uF,20%,50V,BP,TP,5x11,5	SA
5	2201-000471	C412	C-CERAMIC,DISC	0.33NF,10%,50V,Y5P,TP,4X3.5MM,5	SA
5	2301-000016	C413	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2305-000470	C414	C-FILM,LEAD-PEF	68nF,5%,100V,TP,-,5mm	SA
5	2401-001012	C415	C-AL	3.3UF,20%,50V,BP,TP,16X25,7.5	SA
5	2401-000025	C431	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2305-000665	C432	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000148	C433	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2202-000573	C434	C-CERAMIC,MLC-RADIAL	0.82NF,5%,50V,COG,TP,5.1X3.2X5.1MM,5	SA
5	2301-000148	C435	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2401-000660	C436	C-AL	2.2uF,20%,50V,GP,TP,5x11,5	SA
5	2401-000603	C437	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-002144	C438	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2305-001033	C443	C-FILM,LEAD-PEF	15nF,10%,250V,TP,13X9.0X4.5mm,	SA
5	2306-000137	C452	C-FILM,LEAD-PPF	180nF,5%,250V,TP,19x16.5x8,7.5	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2301-001324	C453	C-FILM,LEAD-PPF	200nF,5%,250V,TP,17.5x7x13mm,7.5	SA
5	2306-000169	C455	C-FILM,LEAD-PPF	250nF,5%,250V,TP,19x18x9.5,7.5	SA
5	2401-000603	C456	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C457	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C458	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA
5	2401-003826	C501	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000291	C502	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2401-002267	C504	C-AL	2.2uF,20%,250V,GP,TP,8x11.5,5	SA
5	2401-002267	C505	C-AL	2.2uF,20%,250V,GP,TP,8x11.5,5	SA
5	2301-000294	C521	C-FILM,LEAD-PEF	56nF,5%,100V,TP,9.5x12.5mm,5mm	SA
5	2202-002037	C531	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2301-000106	C532	C-FILM,LEAD-PEF	1.5nF,0.05,100V,TP,10.5*12.5*6	SA
5	2401-000758	C533	C-AL	0.22UF,20%,50V,GP,TP,5X11,5	SA
5	2301-000016	C534	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2301-000106	C535	C-FILM,LEAD-PEF	1.5nF,0.05,100V,TP,10.5*12.5*6	SA
5	2301-000110	C536	C-FILM,LEAD-PEF	1.8nF,5%,100V,TP,7x3.0x6.5mm,5	SA
5	2202-002037	C537	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2401-000480	C551	C-AL	10uF,20%,50V,GP,TP,5x11,5	SA
5	2201-000291	C552	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2201-000132	C553	C-CERAMIC,DISC	0.1NF,10%,500V,Y5P,TP,6.5X3MM,5	SA
5	2201-000291	C561	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2201-000023	C603	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2201-000023	C604	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-000970	C606	C-AL	22uF,20%,50V,WT,TP,5x11,5	SA
5	2202-002037	C607	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2201-000325	C608	C-CERAMIC,DISC	2.2NF,10%,500V,Y5P,TP,9.5X4MM,5	SA
5	2201-000129	C609	C-CERAMIC,DISC	0.1NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2301-000188	C610	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2401-000611	C611	C-AL	1uF,20%,50V,WT,TP,5x11,5	SA
5	2305-000665	C613	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000284	C614	C-FILM,LEAD-PEF	47nF,5%,100V,TP,8.5x12.5mm,5mm	SA
5	2401-001513	C615	C-AL	47uF,20%,16V,WT,TP,5x11,5	SA
5	2202-002037	C616	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2201-000023	C617	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-003046	C618	C-AL	47uF,20%,50V,WT,TP,6.3x11,2.5	SA
5	2201-000291	C619	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2305-000178	C621	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-5mm	SA
5	2401-000039	C622	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C624	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000025	C625	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-002463	C626	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2401-000039	C627	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-002300	C628	C-AL	47uF,20%,50V,GP,TP,6.3x11,5	SA
5	2401-003826	C629	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000469	C630	C-CERAMIC,DISC	0.33NF,10%,500V,Y5P,TP,5.5X3MM,5	SA
5	2401-000039	C631	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C632	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	3711-000197	CN321	CONNECTOR-HEADER	1WALL,3P,1R,2.5mm,STRAIGHT,SN	SA
5	3711-000217	CN602	CONNECTOR-HEADER	1WALL,2P,1R,7.92MM,STRAIGHT,SN,NTR	SA
5	0401-000005	D201	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000128	D301	DIODE-RECTIFIER	1N4002GP,100V,1A,DO-41,TP	SA
5	0402-000546	D302	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D341	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D401	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	D402	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0402-000208	D403	DIODE-RECTIFIER	EK-04,40V,1A,DO-41,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0402-000274	D404	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000005	D411	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D412	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D413	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D414	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000274	D441	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000006	D451	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000006	D452	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000006	D453	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000546	D455	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-001118	D501	DIODE-RECTIFIER	UF1G,400V,1.2A,DO-204AC,TP	SA
5	0402-000274	D502	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000546	D503	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D504	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D511	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D512	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D521	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D522	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D523	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	D531	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	D532	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	D533	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000012	D603	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000012	D604	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000546	D605	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D606	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D607	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D608	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D621	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001194	D622	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000274	D623	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000274	D624	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000012	D626	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-001194	D627	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000274	D628	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	6042-000001	EY301	EYELET	ID2.2,0D2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY302	EYELET	ID2.2,0D2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY401	EYELET	ID2.2,0D2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY402	EYELET	ID2.2,0D2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY403	EYELET	ID2.2,0D2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY404	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY405	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY406	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY441	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY442	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY501	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY502	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY503	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY504	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY505	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY506	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY507	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY601	EYELET	ID2.2,0D2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY602	EYELET	ID2.2,0D2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY603	EYELET	ID2.2,0D2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY604	EYELET	ID2.2,0D2.7,L3.1,NI+SN,BSP3-1/2H	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	6042-000001	EY605	EYELET	ID2.2,OD2.7,L3.1,Ni+SN,BSP3-1/2H	SNA
5	6042-000001	EY606	EYELET	ID2.2,OD2.7,L3.1,Ni+SN,BSP3-1/2H	SNA
5	6042-000002	EY607	EYELET	ID1.5,OD2,L2.8,Ni+SN,BSP3-1/2H	SNA
5	6042-000002	EY608	EYELET	ID1.5,OD2,L2.8,Ni+SN,BSP3-1/2H	SNA
5	6042-000002	EY621	EYELET	ID1.5,OD2,L2.8,Ni+SN,BSP3-1/2H	SNA
5	6042-000002	EY622	EYELET	ID1.5,OD2,L2.8,Ni+SN,BSP3-1/2H	SNA
5	BH71-40300A	GT601	PIN-HINGE	BRASS,D2.361,HEAT/SINK,SN	SNA
5	BH71-40300A	GT602	PIN-HINGE	BRASS,D2.361,HEAT/SINK,SN	SNA
5	1103-001150	IC241	IC-EEPROM	24C081,1Kx8,DIP,8P,9.2x6.4mm,2.7/5.5V,-25to+70C	△ △ SA
5	BH39-40305U	JP1	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP10	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP11	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP12	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP13	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP14	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP15	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP16	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP17	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP18	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP19	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP2	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP20	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP21	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP22	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP23	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP24	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP25	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP26	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	3301-001450	JP27	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	BH39-40305U	JP3	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP31	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP32	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP33	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP34	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP35	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP37	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP38	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP4	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP5	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP6	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP7	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP8	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP9	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH41-00268A	MP1.0	PCB MAIN	LE17JS,FR-1,1,1.0,1.6T,247*247,LE17,MAIN	SNA
5	0501-000122	Q321	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000581	Q322	TR-SMALL SIGNAL	2N3906,PNP,625mW,TO-92,TP,100-300	SA
5	0501-000122	Q323	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000372	Q401	TR-SMALL SIGNAL	KSC2383-Y,NPN,900000mW,TO-92L,TP,160-320	SA
5	0501-000303	Q411	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q412	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000140	Q413	TR-SMALL SIGNAL	2N5551,NPN,625mW,TO-92,TP,80-250	SA
5	0501-000412	Q455	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000412	Q456	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000412	Q457	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000586	Q501	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q502	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0501-000586	Q511	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000143	Q512	TR-SMALL SIGNAL	2N6520,PNP,625mW,TO-92,TP,30-200	SA
5	0501-000413	Q551	TR-SMALL SIGNAL	KSP44,NPN,625mW,TO-92,TP,50-200	SA
5	0501-000122	Q601	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000010	Q621	TR-SMALL SIGNAL	KSC1008,NPN,800mW,TO-92,TP,120-240	SA
5	0501-000586	Q622	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000404	Q623	TR-SMALL SIGNAL	KSD1616-Y,NPN,750mW,TO-92,TP,135-270	SA
5	0501-000586	Q624	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-002228	Q625	TR-SMALL SIGNAL	KTA1281,PNP,1000mW,TO-92L,TP,120-240	SA
5	2001-000869	R201	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R202	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000008	R203	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000008	R204	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R205	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R206	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R207	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R208	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R209	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R210	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R211	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R212	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R213	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R214	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000554	R215	R-CARBON	2700HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000591	R216	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R217	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R218	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R219	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R220	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000515	R221	R-CARBON	2200HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R222	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R223	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	R224	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000435	R225	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R231	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R232	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R241	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R242	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R243	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000009	R302	R-CARBON	20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001254	R303	R-METAL	8.2Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000734	R304	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000616	R305	R-METAL	24Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001005	R306	R-METAL	5.1Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001022	R307	R-METAL	5.6Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-004014	R308	R-METAL	2.4ohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001794	R309	R-METAL	2.2ohm,1%,1/4W,AA,TP,2.4x7mm	SA
5	2001-001126	R310	R-CARBON(S)	3000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000908	R311	R-CARBON	62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001053	R312	R-CARBON(S)	1.5OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000290	R321	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000878	R322	R-CARBON	6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000302	R323	R-CARBON	10OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000273	R324	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000042	R325	R-CARBON	1KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000281	R326	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-001079	R327	R-CARBON(S)	150HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001079	R328	R-CARBON(S)	150HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R331	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000319	R332	R-CARBON	120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000864	R333	R-CARBON	56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R334	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001088	R401	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000110	R402	R-CARBON	100HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000429	R403	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000319	R404	R-CARBON	120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001078	R405	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000703	R406	R-METAL OXIDE(S)	470ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000407	R407	R-METAL OXIDE(S)	0.6ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000020	R408	R-CARBON(S)	220HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000019	R409	R-CARBON(S)	100HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2004-000193	R411	R-METAL	100Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-000327	R412	R-METAL	150Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001349	R415	R-METAL	91Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000298	R416	R-METAL	130Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000531	R417	R-CARBON	240KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000221	R418	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000327	R419	R-METAL	150Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-000176	R420	R-METAL	1.8Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001254	R421	R-METAL	8.2Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001254	R431	R-METAL	8.2Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000449	R432	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000525	R441	R-METAL OXIDE(S)	180ohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000471	R445	R-METAL OXIDE(S)	10ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000290	R451	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R452	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R453	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R454	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R455	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R456	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R457	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R458	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R459	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001099	R501	R-CARBON(S)	2.7KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000145	R502	R-METAL OXIDE	100ohm,5%,1W,AA,TP,4.3x12mm	SA
5	2001-000333	R503	R-CARBON	120HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000522	R504	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000703	R505	R-METAL OXIDE(S)	470ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000407	R506	R-METAL OXIDE(S)	0.6ohm,5%,2W,AA,TP,4x12mm	△ SA
5	2001-000107	R507	R-CARBON(S)	150KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	R508	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	△ SA
5	2001-000786	R511	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001088	R513	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2002-001093	R514	R-COMPOSITION	24KOHM,5%,1/2W,AA,TP,3X9MM	SA
5	2002-001094	R515	R-COMPOSITION	22KOHM,5%,1/2W,AA,TP,3X9MM	SA
5	2004-001164	R521	R-METAL	62Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000327	R522	R-METAL	150Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000660	R523	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R524	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000531	R525	R-CARBON	240KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001000	R531	R-CARBON	82KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R532	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000478	R533	R-CARBON	2.70HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000890	R534	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000995	R535	R-CARBON	8200HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000825	R536	R-METAL	36Kohm,1%,1/4W,AB,TP,2.4x6.4mm	△ SA
5	2004-000218	R537	R-METAL	10Kohm,1%,1/8W,AA,TP,1.8x3.2mm	△ SA
5	2004-000284	R538	R-METAL	12Kohm,1%,1/4W,AA,TP,2.4x6.4mm	△ SA
5	2001-000008	R539	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	△ SA
5	2004-000458	R540	R-METAL	2.2Kohm,1%,1/4W,AA,TP,2.4x6.4m	△ SA
5	2001-000645	R541	R-CARBON	330KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000273	R542	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R551	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000530	R553	R-CARBON	240KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000537	R554	R-CARBON	24KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000042	R555	R-CARBON	1KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-001113	R556	R-CARBON(S)	270KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000316	R557	R-CARBON	120KOHM,5%,1/2W,AA,TP,3.3X9MM	SA
5	2001-000316	R558	R-CARBON	120KOHM,5%,1/2W,AA,TP,3.3X9MM	SA
5	2003-000650	R561	R-METAL OXIDE(S)	330ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-001129	R601	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001129	R602	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000738	R603	R-METAL OXIDE(S)	56Kohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000014	R604	R-METAL OXIDE(S)	10Kohm,5%,3W,AA,TP,6x16mm	SA
5	2002-001103	R605	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2002-001103	R606	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2001-001116	R607	R-CARBON(S)	270HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R608	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000780	R609	R-CARBON	4700HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R610	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R611	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000023	R621	R-CARBON	470HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000027	R622	R-CARBON	1000HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000613	R623	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R624	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R625	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000290	R626	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001088	R628	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000786	R629	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000062	R630	R-CARBON	4700HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2003-000471	R631	R-METAL OXIDE(S)	10ohm,5%,2W,AA,TP,4x12mm	SA
5	4715-001055	SK561	SURGE ABSORBER	1kv,+50-10%,-,-,RADIAL	SNA
5	6042-000002	TP501	EYELET	ID1.5,0D2,I2.8,NI+SN,BSP3-1/2H	SNA
5	2801-000006	X201	CRYSTAL-UNIT	12MHz,50ppm,28-AAM,S,35ohm,BK	SA
5	0403-000348	ZD201	DIODE-ZENER	UZ36B,33-39V,500MW,DO-35,TP	SA
5	0403-001068	ZD202	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA
5	0403-000361	ZD211	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD212	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD213	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD214	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD221	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD222	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD223	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD224	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD225	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD226	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD241	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD242	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0403-000355	ZD514	DIODE-ZENER	UZ5.1BSB,5-5.2V,500MW,DO-35,TP	SA
5	0403-001221	ZD601	DIODE-ZENER	UZ39BSB,35.36-37.19V,500MW,DO-34,TP	SA
5	0403-000361	ZD602	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
4	BH99-00006A	HS451	ASSY HEAT/SINK	H/S,SCREW+NUT,IRF630,-,-,OIL SILICON,-,-	SNA
5	0205-001027	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001309	CIS	FET-SILICON	IRF630,N,200V,10A,0.40HM,100W,TO-220	SA
5	6006-001008	CIS	SCREW-ASS'Y MACH	WSP,BH,+,M3,L10,ZPC(YEL),SWRCH	SNA
5	6021-000118	CIS	NUT-HEXAGON	1C,M3,ZPC(YEL),SM20C	SNA
5	BH62-30024A	CIS	HEAT SINK-TR	SPC,T1,SN,CFX1577L	SNA
4	BN61-01137A	CIS16	SUPPORT-CLIP	IBM E74,NYLON 66,1.0,NTR	SNA
4	BP96-00064C	HS601	ASSY HEAT SINK P	BH62-00004A,SPRING,8S0765RC,RUBBER SILICON	SNA
5	BH13-00045A	CIS	IC HYBRID	FS8S0765RCYDTU,CU17KS,5,-25 to 85,TO-220(FORMING),35,ST	SA
5	BH61-00004A	CIS	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,TO.5,-,-,-	SNA
5	BH62-00004A	CIS	HEAT SINK-POWER	-,T1,-,A1050S,DA/DB	SNA
5	BH62-20001B	CIS	TUBE-RUBBER	CS04357,W25*L20*TO.45,-,-,-,-	SNA
4	BP96-00065B	HS301	ASSY HEAT SINK P	BH62-00003B,SPRING,STV9325,OIL SILICON	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	1204-002262	H/S	IC-VERTICAL DEF.	STV9325,HEPTAWATT,7P,15.45x10.22mm,PLASTIC,35V,-,40to+150C,ST,IC-VERTICAL DEF.	SNA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+,2S,M3,L6,ZPC(YEL),SWRCH18	SNA
5	BH62-00003B	H/S	HEAT SINK-VERT	A1050S,T1.0,T1.0,-,DA,DB	SNA
4	BP96-00066S	HS490	ASSY HEAT SINK P	BH62-00015A,SPRING,KTD2058,FF06F150S,ST2310HI,OIL SILICON	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	0402-001386	H/S	DIODE-RECTIFIER	FFP06F150S,1500V,6A,DO-214AB,ST	SA
5	0502-000465	H/S	TR-POWER	KTD2058,NPN,25000mW,TO-220IS,ST,100-200	SA
5	0502-001225	H/S	TR-POWER	ST2310HI,NPN,55000MW,ISOWATT218,ST,6.5-9.5	SA
5	BH61-00004A	H/S	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,TO.5,-,-,-	SNA
5	BH61-70003A	H/S	SPRING ETC	CVT4857,STS304-W1/2H,W3.8,-,L30,L30,-,TO.5,DEGRE,W3.8,STS304-W1/2H	SNA
5	BH62-00015A	H/S	HEAT SINK-FBT	A1050S,T1.0,T1.0,-,-	SNA
4	BP96-00072E	HS590	ASSY HEAT SINK P	H/S TR,SPRING,IRF630,OIL SILICON	SNA
5	0205-001027	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001309	CIS	FET-SILICON	IRF630,N,200V,10A,0.40HM,100W,TO-220	SA
5	BH61-00004A	CIS	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,TO.5,-,-,-	SNA
5	BH62-00016A	CIS	HEAT SINK-TR	A1050S,T1.0,-,DP17M0	SNA
2	BH91-00970A	-	ASSY CDT-SC	LEO	SNA
3	0201-001576	CDT	ADHESIVE-RBR	DC-3140_RTV#0414,TRP,-,-	SNA
3	0203-000005	CDT	TAPE-ACETATE	SGT730,TO.26,W19,L3000,BLK	SNA
3	3302-000006	CDT	MAGNET-RUBBER	AF,14G,1620-1980G,0.58-0.9MGOe	SA
3	3309-000002	CDT	MAGNET-SHEET	5x20x80mm,UL94V-0,2	SA
3	BH03-00070A	CDT	CDT-SC	M41QAR361X115(T4),70,17,0.27,29.1,FST,H/C,NH,TCO,TILT,4	SA
3	BH68-30003C	CDT	LABEL-00,HIGH,VOLTAGE	SS,ART100G,30*33,YEL	SNA
3	BH96-00292A	CDT	ASSY D-COIL P	17 inch,BH27-00148A,BH96-00289A	SNA

7-2-2 LE17LS(LE17LT) SN Video PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH94-00888B	-	ASSY PCB VIDEO	T117JOIJ	SNA
4	BH63-00131A	CIS1	SHIELD-VIDEO	LE17KS,SPT,E,T0.2	SNA
4	6502-000001	CIS10	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	0204-001527	CIS3	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG	SNA
4	0204-000442	CIS4	SOLVENT	1M-1000,C3H7OH,96,-	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	BH61-70003A	CIS5	SPRING ETC	CVT4857,STS304-W1/2H,W3.8,-,L30,L30,-,T0.5,DEGRE,W3.8,STS304-W1/2H	SNA
4	3711-004236	CN101	CONNECTOR-HEADER	BOX,6P,1R,2MM,STRAIGHT,SN	SNA
4	BH39-00015A	CN102	CBF-HARNESS	13P/14P,200MM,WHT/BLK/RED/BLU,UL1007,AWG26,SMH200-13/YBNH200-14	SA
4	BH13-00050A	IC102	IC HYBRID	NT6813K-30031,NT6813K-30031,24P,-55 to +150,240mA,-0.5 to 6V,ST	SA
4	3704-001170	SK101	SOCKET-CRT	10P,22.5PI,25.6PI,NI+SN,-	SA
4	BH96-00283A	HS106	ASSY HEAT SINK P	BH62-00054A,SCREW,STV9588,OIL SILICON,BRKT-VIDEO	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	1201-002113	H/S	IC-VIDEO AMP	SAM9588,CLIPWATT,19P,19.85x10.7mm,-,-26,PLASTIC,110V,3W,0to+70C,-,-,-,-,-,ST	SA
5	6003-000333	H/S	SCREW-TAPTITE	RH,+2S,M3,L10,ZPC(YEL),SWRCH1	SNA
5	BH61-00048A	H/S	BRACKET-VIDEO	andromeda,SECC,0.8	SNA
5	BH62-00054A	H/S	HEAT SINK-PS	LEO,A1050S,2.0,112,25	SNA
4	BH97-00512A	-	ASSY AUTO-(VIDEO)ST	LE17JS	SNA
5	3301-001450	BD102	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD103	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD104	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD105	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD106	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD107	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2301-000014	C101	C-FILM,LEAD-PEF	6.8nF,5%,100V,TP,5.8x12.5mm,5m	SA
5	2401-000025	C103	C-AL	100uF,20%,16V,GP,TP,6.3x11.5	SA
5	2401-000603	C104	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2201-000376	C105	C-CERAMIC,DISC	0.22NF,5%,50V,SL,TP,6.3X3.5MM,5	SA
5	2201-000019	C106	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2401-002463	C111	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2201-000119	C112	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C113	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2201-000119	C114	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C115	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C116	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002008	C117	C-CERAMIC,MLC-AXIAL	10nF,+80-20%,50V,Y5V,TP,2.3X3	SA
5	2202-002009	C118	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C119	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C120	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	C121	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C122	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2301-000010	C123	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-001218	C124	C-AL	4.7uF,20%,100V,WT,TP,5x11,5	SA
5	2202-002009	C125	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000019	C131	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2201-002147	C132	C-CERAMIC,DISC	2.7NF,10%,500V,Y5P,TP,10X4MM,5	SA
5	2201-000288	C133	C-CERAMIC,DISC	1NF,10%,2KV,Y5P,TP,9X5MM,7.5	SA
5	2202-002009	CB01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CB03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CB04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2202-002009	CG01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CG03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CG04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	0203-001199	CIS6	TAPE-KRAFT	#53110,T0.1,W6,L2000M,BRN	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0203-001200	CIS7	TAPE-PAPER	#53128,T0.15,W5.5,L2000M,BEIGE	SNA
5	BH71-40300A	CN_G2	PIN-HINGE	BRASS,D2.361,HEAT/SINK,SN	SNA
5	BH71-40300A	CN_GND	PIN-HINGE	BRASS,D2.361,HEAT/SINK,SN	SNA
5	2202-002009	CR01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CR03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CR04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	0401-000005	DB01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DB02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DB03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DG01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DG02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DG03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DR01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DR02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DR03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	6042-000001	EY1	EYELET	ID2.2,OD2.7,L3.1,Ni+SN,BSP3-1/2H	SNA
5	6042-000001	EY2	EYELET	ID2.2,OD2.7,L3.1,Ni+SN,BSP3-1/2H	SNA
5	6042-000002	EY3	EYELET	ID1.5,OD2.12.8,Ni+SN,BSP3-1/2H	SNA
5	6042-000002	EY4	EYELET	ID1.5,OD2.12.8,Ni+SN,BSP3-1/2H	SNA
5	6042-000002	EY5	EYELET	ID1.5,OD2.12.8,Ni+SN,BSP3-1/2H	SNA
5	BH39-40305U	JP101	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP102	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP103	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP104	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2701-000172	LB01	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LB02	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LG01	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LG02	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LR01	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LR02	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	BH41-00269A	MP1.0	PCB-VIDEO	LE17JS,FR-1,1.1,1.0,1.6T,81.7*123.5,LE17,6,VIDEO	SNA
5	2001-000076	R101	R-CARBON	47KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000857	R102	R-CARBON	560OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R103	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000702	R104	R-CARBON	39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R105	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R106	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000016	R107	R-CARBON(S)	1OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000435	R111	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000812	R112	R-CARBON	5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R113	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R114	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R121	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000419	R122	R-METAL OXIDE(S)	1.2ohm,5%,1W,AA,TP,3.3x9mm	SA
5	2001-001138	R131	R-CARBON(S)	390OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000037	R132	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RB01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RB02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	RB03	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001026	RB04	R-CARBON	910OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000117	RB06	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RB07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000117	RB08	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RB09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	RG03	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001026	RG04	R-CARBON	9100HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000117	RG06	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RG07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000117	RG08	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RG09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	RR03	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001026	RR04	R-CARBON	9100HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000117	RR06	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RR07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000117	RR08	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RR09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	1405-001064	SK104	SURGE ABSORBER	400V,20%,-- ,AXIAL	SA
5	4715-001065	SK105	SURGE ABSORBER	200V,20%,-- ,RADIAL	SNA
5	4715-001055	SK108	SURGE ABSORBER	1kV,+50-10%,-- ,RADIAL	SNA
5	4715-001065	SKB01	SURGE ABSORBER	200V,20%,-- ,RADIAL	SNA
5	4715-000102	SKG01	SURGE ABSORBER	200V,20%,1000A,- ,RADIAL	SNA
5	4715-000102	SKR01	SURGE ABSORBER	200V,20%,1000A,- ,RADIAL	SNA
5	0403-000361	ZD102	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD103	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD104	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000509	ZD105	DIODE-ZENER	MTZJ5.6B,5.4-5.7V,500MW,DO-34,TP	SA
5	0403-000361	ZD106	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA

7-2-3 LE17LS(LE17LT) SZ Video PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH94-00997K	-	ASSY PCB VIDEO-SZ	LEO	SNA
4	2201-000288	BOTTOM	C-CERAMIC,DISC	1NF,10%,2KV,Y5P,TP,9X5MM,7.5	SA
4	0202-001362	CIS1	SOLDER-WIRE	-,S63S,D3,63Sn/37Pb,-	SNA
4	6502-000001	CIS10	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	0202-001366	CIS2	SOLDER-WIRE FLUX	-,RS60S,D1.2,63Sn/37Pb,-	SNA
4	0204-002420	CIS3	SOLVENT	1M-1000,C3H7OH,96,-,-	SNA
4	0204-002426	CIS4	FLUX	DF-201TVS,MIX,0.820,FLUX 13%, 14KG,-	SNA
4	BH63-00131A	CIS7	SHIELD-VIDEO	LE17KS,SPT,TO.2	SNA
4	BH68-00001A	CIS8	LABEL-MARK CDT	ART-PAPER 100G,-,WHT,BLK,-,ALL,CDT	SNA
4	3711-004236	CN101	CONNECTOR-HEADER	BOX,6P,1R,2MM,STRAIGHT,SN	SA
4	BH39-00015A	CN102	CBF-HARNESS	13P/14P,200MM,WHT/BLK/RED/BLU,UL1007,AWG26,SMH200-13/YBNH200-14	SA
4	BH13-00053A	IC102	IC HYBRID-AMP/OSD	LM1236DEM,LE15V,24P,0 to +70,Plastic,200mA,4.75V to 5.25V,STICK	SA
4	BH13-00022A	IC104	IC HYBRID-BIAS CLAMP	LM2480NA,PN15H/17L,8P,0to+70C,DIP,3mA,85V,ST	SA
4	6003-001023	SH/VID+H/S	SCREW-TAPTITE	PWH,+ ,B,M3,L10,ZPC(YEL),SWRCH18A,-	SNA
4	3704-001203	SK101	SOCKET-CRT	9P,29PI,22.5PI,NI+SN,-	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	BH96-00283C	HS106	ASSY HEAT SINK P	BH62-00054A,SCREW,LM2470TA,OIL SILICON	SNA
5	0205-001154	H/S	OIL-SILICON	G746,-,-	SNA
5	1201-002155	H/S	IC-VIDEO AMP	LM2470TA,TO-220,9P,-,-,-,PLASTIC,90V,4.3W,-20to+100C,-,-,-,-,ST	SA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+,2S,M3,L6,ZPC(YEL),SWRCH18	SNA
5	BH62-00054A	H/S	HEAT SINK-VIDEO	LEO,A1050S,2.0,112,25	SNA
4	BH97-00513P	-	ASSY AUTO-(VIDEO)SZ	LEO*	SNA
5	3301-001450	BD101	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD102	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD104	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2301-000010	C101	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-002463	C103	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2401-001340	C104	C-AL	0.47UF,20%,50V,WT,TP,5X11,5	SA
5	2201-000019	C106	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2401-000287	C111	C-AL	100uF,20%,16V,WT,TP,6.3x11,5	SA
5	2202-002009	C112	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000119	C114	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2301-000294	C117	C-FILM,LEAD-PEF	56nF,5%,100V,TP,9.5x12.5mm,5mm	SA
5	2202-000121	C118	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
5	2301-000188	C119	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2202-000121	C120	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
5	2401-000287	C121	C-AL	100uF,20%,16V,WT,TP,6.3x11,5	SA
5	2202-002009	C122	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	C123	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-000049	C124	C-AL	47uF,20%,100V,WT,TP,10x16,5	SA
5	2201-000119	C126	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2201-000119	C131	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2201-002110	C132	C-CERAMIC,DISC	1.8nF,10%,1kV,Y5P,TP,10x5mm,5	SA
5	2201-000288	C133	C-CERAMIC,DISC	1NF,10%,2KV,Y5P,TP,9X5MM,7.5	SA
5	2202-002009	CB01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CB02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CB03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CB04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2202-000162	CB05	C-CERAMIC,MLC-AXIAL	0.015NF,5%,50V,SL,TP,3.5X1.9MM,-	SA
5	2202-002009	CG01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CG02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CG03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CG04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2202-000162	CG05	C-CERAMIC,MLC-AXIAL	0.015NF,5%,50V,SL,TP,3.5X1.9MM,-	SA
5	0203-001599	CIS5	TAPE-KRAFT	#53110,0.16,2000M,BRN	SNA
5	0203-001600	CIS6	TAPE-PAPER	#53128,0.15,5.5,2000M,BEIGE	SNA
5	BH71-40300A	CN_G2	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	CN_GND	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	2202-002009	CR01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	CR02	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CR03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CR04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2202-000162	CR05	C-CERAMIC,MLC-AXIAL	0.015NF,5%,50V,SL,TP,3.5X1.9MM,-	SA
5	0401-000005	DB01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DB02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0401-000004	DB03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DG01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DG02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DG03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DR01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DR02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DR03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	6042-000002	EY3	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY4	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY5	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	BH39-40305U	JP_17	CBF HARNESS	52MM,AWG22(0.6PI),-,AWG22(0.	SA
5	BH39-40305U	JP103	CBF HARNESS	52MM,AWG22(0.6PI),-,AWG22(0.	SA
5	BH39-40305U	JP106	CBF HARNESS	52MM,AWG22(0.6PI),-,AWG22(0.	SA
5	BH39-40305U	JP107	CBF HARNESS	52MM,AWG22(0.6PI),-,AWG22(0.	SA
5	BH39-40305U	JP108	CBF HARNESS	52MM,AWG22(0.6PI),-,AWG22(0.	SA
5	BH39-40305U	JP109	CBF HARNESS	52MM,AWG22(0.6PI),-,AWG22(0.	SA
5	BH39-40305U	JP110	CBF HARNESS	52MM,AWG22(0.6PI),-,AWG22(0.	SA
5	BH39-40305U	JP114	CBF HARNESS	52MM,AWG22(0.6PI),-,AWG22(0.	SA
5	BH39-40305U	JP115	CBF HARNESS	52MM,AWG22(0.6PI),-,AWG22(0.	SA
5	2701-000319	LB01	INDUCTOR-AXIAL	0.47UH,10%,3070	SA
5	2701-000319	LG01	INDUCTOR-AXIAL	0.47UH,10%,3070	SA
5	2701-000319	LR01	INDUCTOR-AXIAL	0.47UH,10%,3070	SA
5	BH41-00273A	MP1.0	PCB-VIDEO	LE15VS,FR1,1L,1.0,1.6T,123.5 * 82.3,VIDEO ASS,6,247*247	SNA
5	2001-000800	R102	R-CARBON	5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R103	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000660	R105	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R106	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000016	R107	R-CARBON(S)	10HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000780	R108	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R111	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000878	R112	R-CARBON	6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R113	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R114	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001138	R131	R-CARBON(S)	390OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000037	R132	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000009	R134	R-CARBON	20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000084	R135	R-CARBON	100Kohm,5%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000969	RB01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RB02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RB03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001195	RB05	R-CARBON(S)	820HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RB06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RB07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000376	RB08	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000117	RB09	R-CARBON(S)	68ohm,5%,1/2W,AA,TP,2.4x6.4mm	SA
5	2001-000969	RG01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RG03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000028	RG05	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RG06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RG07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000376	RG08	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001070	RG09	R-CARBON(S)	1200HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RR01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	RR03	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000028	RR05	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	RR06	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001129	RR07	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000376	RR08	R-CARBON	150HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000028	RR09	R-CARBON(S)	1000HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	4715-001076	SK104	SURGE ABSORBER	400V,20%,-- ,RADIAL	SNA
5	4715-001055	SK108	SURGE ABSORBER	1kV,+50-10%,-- ,RADIAL	SNA
5	4715-001065	SKB01	SURGE ABSORBER	200V,20%,-- ,RADIAL	SNA
5	4715-000102	SKG01	SURGE ABSORBER	200V,20%,1000A-- ,RADIAL	SNA
5	4715-001065	SKR01	SURGE ABSORBER	200V,20%,-- ,RADIAL	SNA

7-2-4 LE17LS(LE17LT) Others

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BH90-00592A	-	ASSY COVER REAR	LE17JS,EDC	SNA
3	BH63-00130A	C/R	COVER-REAR	LE17KS,ABS HB,IV16	SNA
2	BH90-00598A	-	ASSY STAND	LE17JS/LE15VS,EDC	SNA
3	BH96-00272A	STD	ASSY STAND P	LE17KS,ABS HB IV16	SNA
4	6902-000109	STD	BAG PE	HDPE,T0.015,L430,W350,TRP,28,2,PE MARK	SNA
4	BH60-00030A	STD	FASTENER-BAND	PN17LT,ST+PVC,P0.4-- ,150,YELLOW-- ,--	SNA
4	BH61-00049A	STD	STAND-BASE	LE17KS,ABS HB,IV16	SNA
4	BH61-00050A	STD	STAND-TOP	LE17KS,ABS HB,IV16	SNA
4	BH61-40002A	STD	FOOT-RUBBER	-- ,NR,PMS428U,GA4237-- ,--	SNA
4	BH63-30103A	STD	FELT-STAND	MCM1755,FELT,T1.0,W10,L4	SNA
4	BH68-20366A	STD	LABEL-MARK STAND	,ART PAPER100(S),WHT	SNA
4	BH68-70306A	STD	CARD-STAND	CVM4967PWS(SKD),WONSTROW,CHAIN	SNA
2	BH90-00686A	-	ASSY COVER FRONT	LEO	SNA
3	6003-000009	C/F+C/R	SCREW-TAPTITE	BH,+ ,B,M4,L16,ZPC(YEL),SWRCH18	SNA
3	6006-001119	C/F+CDT	SCREW-ASSY TAPT	WC,BH,+ ,M5,L25,ZPC(YEL),SWRCH18A	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH96-00276B	C/F	ASSY COVER P-FRONT	LE17LS,ABS HB IV16	SNA
2	BH91-00870A	-	ASSY SHIELD	LE17JS	SNA
3	0201-001059	CIS	ADHESIVE-SIL	#9590,WHT,-,CARTRIGE	SNA
3	6003-001023	SH/COV+SH/BTM	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
3	BH96-00281A	CIS	ASSY MISC P-SHIELD COVER	LE17KS,SECC TO.5,AL TO.25	SNA
4	BH63-00132A	CIS	SHIELD-COVER TOP	LE17KS,AL,TO.25	SNA
4	BH63-00133A	CIS	SHIELD-COVER REAR	LE17KS,SECC,TO.5	SNA
4	BH63-00145A	CIS	SHEET-ANODE	LE17KS,PP V2,T1.0,WHITE	SNA
2	BH91-00969A	-	ASSY CHASSIS-SC	LEO	SNA
2	BH92-00894A	-	ASSY P/MATERIAL	TI17JO	SNA
3	0203-001100	P/M	TAPE-OPP MASKING	OPP/W75/CLR,TO.05,W75,L800000,CLR	SNA
3	0203-001159	P/M	TAPE-FILAMENT	#8915,TO.15,W12,L55000,CLR	SNA
3	6902-000001	P/M	BAG AIR	LDPE,TO.2,L1800,W1000,TRP,,,LDPE ONLY	SNA
3	6902-000379	P/M	BAG AIR	HDPE,TO.2,L1800,W1000,TRP,,,PAPER	SNA
3	6902-000523	P/M	BAG PE	HDPE,TO.015,W900,L800,TRP,28 LANGUAGE,2-	SNA
3	6902-000576	P/M	BAG ROLL	LDPE,TO.05,W2400,L1000,TRP,-,-	SNA
3	BH69-00563A	P/M	CUSHION	LE17LS,EPS M50,FST	SNA
3	BH69-40380A	P/M	PACKING-PAD	DW-2,500X2200X200,-,CGK5527	SNA
2	BH92-01093A	-	ASSY LABEL	LEO-PJT(15/17/19)	SNA
3	BH68-00565D	LABEL	LABEL RATING-00	ALL,SS,PE,TO.05,90*65,BLK,POLYESTER,EDC	SNA
2	BH92-01161A	-	ASSY BOX	LEO	SNA
3	BH68-00530A	BOX	LABEL BOX-01	LABEL-BARCODE,CE+TC003,MOJO 90G,WHT	SNA
3	BH69-00573A	BOX	BOX	S/M793S(LE17LS),W/W,CB-SW4,YEL,A-1,W452*D486*H435	SNA
2	BH92-01162A	-	ASSY ACCESSORY	LEO	SNA
3	BH96-00297A	UNIT/ACCESSORY	ASSY ACCESSORY	LEO	-
4	0203-000214	ACCESSORY	TAPE-OPP MASKING	OPP/W50/CLR,TO.05,W50,L400000,	SNA
4	6902-000110	ACCESSORY	BAG PE	LDPE,TO.05,L356,W240,TRP,28,2,PE MARK	SNA
4	BH39-10339H	ACCESSORY	CBF POWER CORD	DET,H05VV-F,250V/10,16A,BLK,25	SA
4	BH68-70418A	ACCESSORY	CARD-EU BLOC WARR-07	SyncMaster,BASIC,EU,MOJO,100G,	SNA
4	BH96-00296A	ACCESSORY	ASSY MANUAL P-IB+QSG	795DF,SyncMaster,W/W,27Lang,BH59-362A+BH68-376J	-
5	BH59-00362A	I/B	S/W DRIVER-00,IB	793S,795DF,W/W,SYNCMaster,27LANG	SNA
5	BH68-00376J	QUICK	MANUAL-01	AN_QUICK SETUP GUIDE,SYNCMaster,E/F/S/G/P/L,14LANGS,W/W,MOJO100G,238,420	SNA

7-3-1 LE17KS(LE17KT) Main PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
0	LE17KSBB/EDC	-	1	SDI,HIGH-CON(DF-T)	-
1	ST-LE17KSBB/EDC	-			
3	BH94-00979B	-	ASSY PCB MAIN	LE17KS	SNA
4	2306-000234	C451	C-FILM,LEAD-PPF	560nF,5%,250V,BK,26x20x13,20	SA
4	2306-000147	C503	C-FILM,LEAD-PPF	1uF,5%,250V,BK,26x24x15,22.5mm	SA
4	2301-001195	C601	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2301-001195	C602	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2401-003391	C605	C-AL	220uF,20%,450V,GP,BK,25x50,10	SA
4	BH63-00134A	CIS1	SHIELD-BOTTOM	LE17KS,SECC,T1.0	SNA
4	BH39-00323D	CIS10	LEAD CONNECTOR-ASSY	OT17LO,8.0*0.16TA*16,150MM,35068-9822,35750-1010,BK,8.0*0.16TA*16	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	BH63-00143A	CIS3	COVER-PCB R	LE17KS,ABS PC,IV16	SNA
4	BH63-00144A	CIS4	COVER-PCB L	LE17KS,ABS PC,IV16	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	0204-001527	CIS6	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG	SNA
4	0204-000442	CIS7	SOLVENT	1M-1000,C3H7OH,96,-	SNA
4	3711-003895	CN201	CONNECTOR-HEADER	BOX,13P,1R,2mm,STRAIGHT,SN	SA
4	3711-003873	CN202	CONNECTOR-HEADER	BOX,7P,1R,2mm,STRAIGHT,SN	SA
4	3711-004379	CN203	CONNECTOR-HEADER	BOX,4P,1R,2MM,STRAIGHT,SN	SA
4	3711-005055	CN401	CONNECTOR-HEADER	1WALL,4P,1R,10MM/8.0MM,STRAIGHT,SN-PB,WHT	SA
4	3721-001053	CN601	PLUG-AC POWER	3P,-,-,NI	SNA
4	0402-001295	D405	DIODE-RECTIFIER	GUR460L-5700,600V,4A,DO-201AD,BK	SA
4	0402-001025	D406	DIODE-RECTIFIER	ERD07-15,1.5KV,1.5A,-,TP	SA
4	0402-001407	D601	DIODE-BRIDGE	G2SB60,600V,1.5A,SIP-4,BK	SA
4	0402-000005	D625	DIODE-RECTIFIER	31DF4,400V,3A,DO-201AD,BK	SA
4	6003-000122	FBT+H/S	SCREW-TAPTITE	BH,-,B,M4,L12,ZPC(YEL),SWRCH18	SNA
4	3601-001302	FH1	FUSE-AXIAL LEAD	250V,3.15A,SLOW-BLOW,CERAMIC,5X20MM	SA
4	BH63-00124A	HS401	SHIELD-IC	LE17KS,SPT,TO.2	SNA
4	6502-000001	HS490_CIS1	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	6502-000001	HS490_CIS2	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	3704-001071	IC201_SOCKET	SOCKET-IC	42P,DIP,SN,1.778mm	SA
4	1103-001106	IC241	IC-EEPROM	24C080,1Kx8Bit,DIP,8P,9.6x6.4mm,-,2.7/5.5V,-,-,25to+70C,10uA,-,ST	△ SNA
4	1204-002259	IC401	IC-DEF. PROCESSOR	STV9118,SDIP,32P,27.94x8.89mm,PLASTIC,13.2V,-,0to+70C,ST,IC-DEF. PROCESSOR	△ SNA
4	1203-003240	IC621	IC-POSI.FIXED REG.	L78M05,IPAK,3P,6.5x6.1mm,PLASTIC,4.75/5.25V,-,0to+150C,0.5A,-,ST	SA
4	1203-000243	IC622	IC-POSI.FIXED REG.	7812,TO-220,3P,-,PLASTIC,11.5/12.5V,-,16W,0to+125C,1A,-,ST	SA
4	BH27-00135A	L411	COIL CHOKE	120UH,CDTMO,120UH,10%,0.23OHM,5A,AR8X25.65.5TS,18X40MM,11MM,USTCO,12X20,TR,-10CT	SA
4	BH27-00132A	L441	COIL LINEARITY	5.4UH,5.4UH,DR12X15 C:4.5,7MM,15X15X35MM,12X8T,23.0TS,TR,12%,0.03OHM	SA
4	BH27-00134A	L501	COIL CHOKE	100UH,CDTMO,100UH,10%,0.20HM,5.0A,AR8X25.60.5TS,18X40MM,11MM,USTCO,12X20,TR,-10C	SA
4	BH27-00007A	L601	COIL-LINE FILTER	SQE2424,25mH MIN,-,SQE 2424,-,PHENAL,-,-,0.32ohm,21*27*33,-,-,BULK	SA
4	6003-001023	M/PCB+SH/BTM	SCREW-TAPTITE	RWH,-,B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	0505-001309	Q452	FET-SILICON	IRF630,N,200V,10A,0.40HM,100W,TO-220	SA
4	0505-001309	Q453	FET-SILICON	IRF630,N,200V,10A,0.40HM,100W,TO-220	SA
4	3501-001111	RL601	RELAY-POWER	12VDC,250MMW,5000MA,1FORMA,15MS,5MS	SA
4	6003-000133	SH/BTM+AC/SOCK	SCREW-TAPTITE	BH,-,S,M4,L8,ZPC(YEL),SWRCH18A,-	SNA
4	BH39-00451A	SIGNAL	CBF SIGNAL	LE17JS,15P,06P,07P,20276-N,1830mm,UL20276,BLACK,D-SUB /MALE,BLACK,30V,ATT. TYPE	SNA
4	BH26-00027A	T401	TRANS-HOR.DRIVE	FQB-17A001,PL-3,EL1916,310UH	△ SA
4	BH26-00171A	T501	TRANS FBT	CF2166,LE17JS,1.50mH,FERRITE,0.32OHM,BULK,14P,-,10--+60,26.3kV	△ SNA
4	BH26-00089A	T561	TRANS-FOCUS	EE-1916,AQ1916,5P,1.7mH,-,-,105mH,-,-,0.85ohm,-,PL-3,DMR30,TP-3,J2A,-,-,-,-	SA
4	BH26-00164A	T601	TRANS POWER	ER-3435,CU17KS,350UH,15.90-264V,80V,10-55,FERRITE,ER-3435,0.05ohm/0.35ohm,8uH M	SA
4	BH26-00163A	T602	TRANS	UU-1116,CU17K,5,18mH min,18mH min,2.7ohm MAX,10 ~ 55,FERRITE,UU-1116 SB-5S	SA
4	1404-001264	TH601	THERMISTOR-PTC	4.5OHM,+30/-20%,220V,290VAC,21A,-,TR	SA
4	1404-001020	TH602	THERMISTOR-NTC	8ohm,15%,-,17mW/C,BK	SA
4	BH97-00505B	MICOM	ASSY MICOM	LE17JS	SA
5	BH82-00020H	CIS	A/S MICOM	LE17JS	SNA
5	0903-001194	IC201	IC-MICROCONTROLLER	3P863,8Bit,SDIP,42P,600MIL,12MHz,ST,CMOS,PLASTIC,5V,-,-40to+85C,1040BYTE,48KBYTE	△ SNA
4	BH97-00511B	-	ASSY AUTO-(MAIN)	LE17KS	SNA
5	3301-001450	BD321	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD401	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD402	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD431	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD501	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD502	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD601	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD621	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD622	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2202-002037	C201	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2202-000205	C202	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-000205	C203	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2401-000603	C204	C-AL	1UF,20%,50V,GP,TP,5X11,2	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2202-000121	C205	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
5	2202-000796	C206	C-CERAMIC,MLC-AXIAL	1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	SA
5	2202-000121	C207	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
5	2401-000603	C208	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C209	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-002299	C210	C-AL	4.7uF,20%,50V,GP,TP,5x7,5	SA
5	2401-002299	C211	C-AL	4.7uF,20%,50V,GP,TP,5x7,5	SA
5	2202-000205	C212	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2401-002463	C301	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2301-000148	C302	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2305-000665	C303	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000014	C304	C-FILM,LEAD-PEF	6.8nF,5%,100V,TP,5.8x12.5mm,5m	SA
5	2305-000289	C305	C-FILM,LEAD-PEF	220nF,5%,63V,TP,-,5mm	SA
5	2401-000852	C306	C-AL	220uF,20%,35V,GP,TP,8x11.5mm,5	SA
5	2202-000208	C307	C-CERAMIC,MLC-AXIAL	10nF,80-20%,50V,Y5V,TP,2.3X3.	SA
5	2202-002037	C321	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2401-000480	C322	C-AL	10uF,20%,50V,GP,TP,5x11,5	SA
5	2305-000196	C331	C-FILM,LEAD-PEF	150nF,5%,63V,TP,-,5mm	SA
5	2305-000412	C332	C-FILM,LEAD-PEF	470nF,5%,63V,TP,-,5mm	SA
5	2401-002144	C333	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2401-001334	C401	C-AL	0.47uF,20%,50V,GP,TP,5X11,2.5	SA
5	2401-001220	C402	C-AL	4.7uF,20%,160V,GP,TP,8x11.5,5	SA
5	2301-000010	C403	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2301-001463	C404	C-FILM,LEAD-PPF	4nF,5%,630V,TP,17X9X5,7.5	SA
5	2301-001304	C405	C-FILM,LEAD-PPF	1.5nF,5%,2.5KV,TP,23X17X11MM,7.5	△ SA
5	2301-001441	C406	C-FILM,LEAD-PPF	2nF,3%,1.6kV,TP,20x2.5x11mm,7.5	△ SA
5	2305-000178	C407	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-,5mm	SA
5	2401-001914	C411	C-AL	1uF,20%,50V,BP,TP,5x11,5	SA
5	2201-000471	C412	C-CERAMIC,DISC	0.33nF,10%,50V,Y5P,TP,4X3.5MM,5	SA
5	2301-000016	C413	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2305-000470	C414	C-FILM,LEAD-PEF	68nF,5%,100V,TP,-,5mm	SA
5	2401-001012	C415	C-AL	3.3uF,20%,50V,BP,TP,16X25,7.5	SA
5	2401-000025	C431	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2305-000665	C432	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000148	C433	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2202-000573	C434	C-CERAMIC,MLC-RADIAL	0.82nF,5%,50V,COG,TP,5.1X3.2X5.1MM,5	SA
5	2301-000148	C435	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2401-000660	C436	C-AL	2.2uF,20%,50V,GP,TP,5x11,5	SA
5	2401-000603	C437	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-002144	C438	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2305-001033	C443	C-FILM,LEAD-PEF	15nF,10%,250V,TP,13X9.0X4.5mm,	SA
5	2306-000137	C452	C-FILM,LEAD-PPF	180nF,5%,250V,TP,19x16.5x8,7.5	SA
5	2306-000119	C453	C-FILM,LEAD-PPF	100nF,5%,250V,TP,19x14.5x6.5,7	SA
5	2306-000164	C455	C-FILM,LEAD-PPF	220nF,5%,250V,TP,19x22x10,7.5m	SA
5	2401-000603	C456	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C457	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-000603	C458	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2401-003826	C501	C-AL	220uF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000291	C502	C-CERAMIC,DISC	1nF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2401-002267	C504	C-AL	2.2uF,20%,250V,GP,TP,8x11.5,5	SA
5	2401-002267	C505	C-AL	2.2uF,20%,250V,GP,TP,8x11.5,5	SA
5	2301-000294	C521	C-FILM,LEAD-PEF	56nF,5%,100V,TP,9.5x12.5mm,5mm	SA
5	2202-002037	C531	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2301-000106	C532	C-FILM,LEAD-PEF	1.5nF,0.05,100V,TP,10.5*12.5*6	SA
5	2401-000758	C533	C-AL	0.22uF,20%,50V,GP,TP,5X11,5	SA
5	2301-000016	C534	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2301-000106	C535	C-FILM,LEAD-PEF	1.5nF,0.05,100V,TP,10.5*12.5*6	SA
5	2301-000110	C536	C-FILM,LEAD-PEF	1.8nF,5%,100V,TP,7x3.0x6.5mm,5	SA
5	2202-002037	C537	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2401-000480	C551	C-AL	10uF,20%,50V,GP,TP,5x11,5	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2201-000291	C552	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2201-000132	C553	C-CERAMIC,DISC	0.1NF,10%,500V,Y5P,TP,6.5X3MM,5	SA
5	2201-000291	C561	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2201-000023	C603	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2201-000023	C604	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-000970	C606	C-AL	22uF,20%,50V,WT,TP,5x11,5	SA
5	2202-002037	C607	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2201-000325	C608	C-CERAMIC,DISC	2.2NF,10%,500V,Y5P,TP,9.5X4MM,5	SA
5	2201-000129	C609	C-CERAMIC,DISC	0.1NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2301-000188	C610	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2401-000611	C611	C-AL	1uF,20%,50V,WT,TP,5x11,5	SA
5	2305-000665	C613	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000284	C614	C-FILM,LEAD-PEF	47nF,5%,100V,TP,8.5x12.5mm,5mm	SA
5	2401-001513	C615	C-AL	47uF,20%,16V,WT,TP,5x11,5	SA
5	2202-002037	C616	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2201-000023	C617	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-003046	C618	C-AL	47uF,20%,50V,WT,TP,6.3x11,2.5	SA
5	2201-000291	C619	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2305-000178	C621	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-,5mm	SA
5	2401-000039	C622	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C624	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000025	C625	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-002463	C626	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2401-000039	C627	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-002300	C628	C-AL	47uF,20%,50V,GP,TP,6.3x11,5	SA
5	2401-003826	C629	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000469	C630	C-CERAMIC,DISC	0.33NF,10%,500V,Y5P,TP,5.5X3MM,5	SA
5	2401-000039	C631	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C632	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	3711-000197	CN321	CONNECTOR-HEADER	1WALL,3P,1R,2.5mm,STRAIGHT,SN	SA
5	3711-000217	CN602	CONNECTOR-HEADER	1WALL,2P,1R,7.92MM,STRAIGHT,SN,NTR	SA
5	0401-000005	D201	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000128	D301	DIODE-RECTIFIER	1N4002GP,100V,1A,DO-41,TP	SA
5	0402-000546	D302	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D341	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D401	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	D402	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0402-000208	D403	DIODE-RECTIFIER	EK-04,40V,1A,DO-41,TP	SA
5	0402-000274	D404	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000005	D411	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D412	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D413	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D414	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000274	D441	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000006	D451	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000006	D452	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000006	D453	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000546	D455	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-001118	D501	DIODE-RECTIFIER	UF1G,400V,1.2A,DO-204AC,TP	SA
5	0402-000274	D502	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000546	D503	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D504	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D511	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D512	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D521	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D522	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D523	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	D531	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	D532	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	D533	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0402-000012	D603	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000012	D604	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000546	D605	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D606	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D607	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D608	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D621	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001194	D622	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000274	D623	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000274	D624	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000012	D626	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-001194	D627	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000274	D628	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	6042-000001	EY301	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY302	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY401	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY402	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY403	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY404	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY405	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY406	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY441	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY442	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY501	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY502	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY503	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY504	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY505	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY506	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY507	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY601	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY602	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY603	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY604	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY605	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY606	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY607	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY608	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY621	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY622	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	BH71-40300A	GT601	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT602	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH39-40305U	JP1	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP10	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP11	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP12	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP13	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP14	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP15	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP16	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP17	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP18	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP19	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP2	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP20	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP21	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP22	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP23	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP24	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA
5	BH39-40305U	JP25	CBF HARNESS	52MM,AWG22(0.6PI),--,AWG22(0.	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH39-40305U	JP26	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	3301-001450	JP27	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	BH39-40305U	JP3	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP31	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP32	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP33	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP34	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP35	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP37	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP38	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP4	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP5	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP6	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP7	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP8	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP9	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH41-00268A	MP1.0	PCB MAIN	LE17JS,FR-1,1,1.0,1.6T,247*247,LE17,MAIN	SNA
5	0501-000122	Q321	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000581	Q322	TR-SMALL SIGNAL	2N3906,PNP,625mW,TO-92,TP,100-300	SA
5	0501-000122	Q323	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000372	Q401	TR-SMALL SIGNAL	KSC2383-Y,NPN,900000mW,TO-92L,TP,160-320	SA
5	0501-000303	Q411	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q412	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000140	Q413	TR-SMALL SIGNAL	2N5551,NPN,625mW,TO-92,TP,80-250	SA
5	0501-000412	Q455	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000412	Q456	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000412	Q457	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000586	Q501	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q502	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q511	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000143	Q512	TR-SMALL SIGNAL	2N6520,PNP,625mW,TO-92,TP,30-200	SA
5	0501-000413	Q551	TR-SMALL SIGNAL	KSP44,NPN,625mW,TO-92,TP,50-200	SA
5	0501-000122	Q601	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000010	Q621	TR-SMALL SIGNAL	KSC1008,NPN,800mW,TO-92,TP,120-240	SA
5	0501-000586	Q622	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000404	Q623	TR-SMALL SIGNAL	KSD1616-Y,NPN,750mW,TO-92,TP,135-270	SA
5	0501-000586	Q624	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-002228	Q625	TR-SMALL SIGNAL	KTA1281,PNP,1000mW,TO-92L,TP,120-240	SA
5	2001-000869	R201	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R202	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000008	R203	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000008	R204	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R205	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R206	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R207	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R208	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R209	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R210	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R211	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R212	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R213	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R214	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000554	R215	R-CARBON	2700HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000591	R216	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R217	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R218	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R219	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R220	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000515	R221	R-CARBON	2200HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R222	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000290	R223	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	R224	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000435	R225	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R231	R-CARBON	56OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R232	R-CARBON	56OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R241	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R242	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R243	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000009	R302	R-CARBON	20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001254	R303	R-METAL	8.2Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000734	R304	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000616	R305	R-METAL	24Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001005	R306	R-METAL	5.1Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001022	R307	R-METAL	5.6Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001409	R308	R-METAL	2.7ohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001794	R309	R-METAL	2.2ohm,1%,1/4W,AA,TP,2.4x7mm	SA
5	2001-001126	R310	R-CARBON(S)	300OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000908	R311	R-CARBON	62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001053	R312	R-CARBON(S)	1.5OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000290	R321	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000878	R322	R-CARBON	6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000302	R323	R-CARBON	10OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000273	R324	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000042	R325	R-CARBON	1KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000281	R326	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001079	R327	R-CARBON(S)	150HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001079	R328	R-CARBON(S)	15OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R331	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000319	R332	R-CARBON	120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000908	R333	R-CARBON	62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R334	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001088	R401	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000110	R402	R-CARBON	10OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000429	R403	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000319	R404	R-CARBON	120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001078	R405	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000703	R406	R-METAL OXIDE(S)	470ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000407	R407	R-METAL OXIDE(S)	0.6ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000020	R408	R-CARBON(S)	220HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000019	R409	R-CARBON(S)	10OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2004-000193	R411	R-METAL	100Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-000327	R412	R-METAL	150Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001349	R415	R-METAL	91Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000298	R416	R-METAL	130Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000531	R417	R-CARBON	240KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000221	R418	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000327	R419	R-METAL	150Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-000176	R420	R-METAL	1.8Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001254	R421	R-METAL	8.2Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001254	R431	R-METAL	8.2Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000449	R432	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000525	R441	R-METAL OXIDE(S)	180ohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000471	R445	R-METAL OXIDE(S)	10ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000290	R451	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R452	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R453	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R454	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R455	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R456	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R457	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000449	R458	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R459	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001099	R501	R-CARBON(S)	2.7KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000145	R502	R-METAL OXIDE	100ohm,5%,1W,AA,TP,4.3x12mm	SA
5	2001-000333	R503	R-CARBON	120HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000522	R504	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000703	R505	R-METAL OXIDE(S)	470ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000407	R506	R-METAL OXIDE(S)	0.6ohm,5%,2W,AA,TP,4x12mm	△ SA
5	2001-000107	R507	R-CARBON(S)	150KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	R508	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	△ SA
5	2001-000786	R511	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001088	R513	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2002-001099	R514	R-COMPOSITION	68KOHM,5%,1/2W,AA,TP,3.0X9.0MM	SNA
5	2002-001072	R515	R-COMPOSITION	15Kohm,5%,1/2W,AA,TP,4.0x12mm	SA
5	2004-001164	R521	R-METAL	62Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000327	R522	R-METAL	150Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000660	R523	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R524	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000531	R525	R-CARBON	240KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001000	R531	R-CARBON	82KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R532	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000478	R533	R-CARBON	2.7OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000890	R534	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000995	R535	R-CARBON	820OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000825	R536	R-METAL	36Kohm,1%,1/4W,AB,TP,2.4x6.4mm	△ SA
5	2004-000218	R537	R-METAL	10Kohm,1%,1/8W,AA,TP,1.8x3.2mm	△ SA
5	2004-000284	R538	R-METAL	12Kohm,1%,1/4W,AA,TP,2.4x6.4mm	△ SA
5	2001-000008	R539	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	△ SA
5	2004-000458	R540	R-METAL	2.2Kohm,1%,1/4W,AA,TP,2.4x6.4m	△ SA
5	2001-000645	R541	R-CARBON	330KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000273	R542	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R551	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000530	R553	R-CARBON	240KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000537	R554	R-CARBON	24KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000042	R555	R-CARBON	1KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-001113	R556	R-CARBON(S)	270KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000316	R557	R-CARBON	120KOHM,5%,1/2W,AA,TP,3.3X9MM	SA
5	2001-000316	R558	R-CARBON	120KOHM,5%,1/2W,AA,TP,3.3X9MM	SA
5	2003-000650	R561	R-METAL OXIDE(S)	330ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-001129	R601	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001129	R602	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000738	R603	R-METAL OXIDE(S)	56Kohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000014	R604	R-METAL OXIDE(S)	10Kohm,5%,3W,AA,TP,6x16mm	SA
5	2002-001103	R605	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2002-001103	R606	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2001-001116	R607	R-CARBON(S)	27OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R608	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000780	R609	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R610	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R611	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000023	R621	R-CARBON	47OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000027	R622	R-CARBON	100OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000613	R623	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R624	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R625	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000290	R626	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001088	R628	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000786	R629	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000062	R630	R-CARBON	470OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2003-000471	R631	R-METAL OXIDE(S)	10ohm,5%,2W,AA,TP,4x12mm	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	4715-001055	SK561	SURGE ABSORBER	1kV,+50-10%,,-,RADIAL	SNA
5	6042-000002	TP501	EYELET	ID1.5,0D2,L2.8,NI+SN,BSP3-1/2H	SNA
5	2801-000006	X201	CRYSTAL-UNIT	12MHz,50ppm,28-AAM,S,35ohm,BK	SA
5	0403-000348	ZD201	DIODE-ZENER	UZ36B,33-39V,500MW,DO-35,TP	SA
5	0403-001068	ZD202	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA
5	0403-000361	ZD211	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD212	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD213	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD214	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD221	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD222	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD223	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD224	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD225	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD226	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD241	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD242	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000355	ZD514	DIODE-ZENER	UZ5.1BSB,5-5.2V,500MW,DO-35,TP	SA
5	0403-001221	ZD601	DIODE-ZENER	UZ39BSB,35.36-37.19V,500MW,DO-34,TP	SA
5	0403-000361	ZD602	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
4	BH99-00006A	HS451	ASSY HEAT/SINK	H/S,SCREW+NUT,IRF630,-,-,OIL SILICON,-,-	SNA
5	0205-001027	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001309	CIS	FET-SILICON	IRF630,N,200V,10A,0.4OHM,100W,TO-220	SA
5	6006-001008	CIS	SCREW-ASS'Y MACH	WSP,BH,+M3,L10,ZPC(YEL),SWRCH	SNA
5	6021-000118	CIS	NUT-HEXAGON	1C,M3,ZPC(YEL),SM20C	SNA
5	BH62-30024A	CIS	HEAT SINK-TR	SPC,T1,SN,CFX1577L	SNA
4	BN61-01137A	CIS16	SUPPORT-CLIP	IBM E74,NYLON 66,1.0,NTR	SNA
4	BP96-00064C	HS601	ASSY HEAT SINK P	BH62-00004A,SPRING,8S0765RC,RUBBER SILICON	SNA
5	BH13-00045A	CIS	IC HYBRID	FS8S0765RCYDTU,CU17KS,5,-25 to 85,TO-220(FORMING),35,ST	SA
5	BH61-00004A	CIS	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,TO.5,-,-,-	SNA
5	BH62-00004A	CIS	HEAT SINK-POWER	-T1,-,A1050S,DA/DB	SNA
5	BH62-20001B	CIS	TUBE-RUBBER	CSQ4357,W25*L20*TO.45,-,-,-,-	SNA
4	BP96-00065B	HS301	ASSY HEAT SINK P	BH62-00003B,SPRING,STV9325,OIL SILICON	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	1204-002262	H/S	IC-VERTICAL DEF.	STV9325,HEPTAWATT,7P,15.45x10.22mm,PLASTIC,35V,-,40to+150C,ST,IC-VERTICAL DEF.	SNA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+2S,M3,L6,ZPC(YEL),SWRCH18	SNA
5	BH62-00003B	H/S	HEAT SINK-VERT	A1050S,T1.0,T1.0,-,DA,DB	SNA
4	BP96-00066S	HS490	ASSY HEAT SINK P	BH62-00015A,SPRING,KTD2058,FF06F150S,ST2310HI,OIL SILICON	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	0402-001386	H/S	DIODE-RECTIFIER	FFPF06F150S,1500V,6A,DO-214AB,ST	SA
5	0502-000465	H/S	TR-POWER	KTD2058,NPN,25000mW,TO-220IS,ST,100-200	SA
5	0502-001225	H/S	TR-POWER	ST2310HI,NPN,55000MW,ISOWATT218,ST,6.5-9.5	SA
5	BH61-00004A	H/S	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,TO.5,-,-,-	SNA
5	BH61-70003A	H/S	SPRING ETC	CVT4957,STS304-W1/2H,W3.8,-,L30,L30,-,TO.5,DEGRE,W3.8,STS304-W1/2H	SNA
5	BH62-00015A	H/S	HEAT SINK-FBT	A1050S,T1.0,T1.0,-,-	SNA
4	BP96-00072E	HS590	ASSY HEAT SINK P	H/S TR,SPRING,IRF630,OIL SILICON	SNA
5	0205-001027	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001309	CIS	FET-SILICON	IRF630,N,200V,10A,0.4OHM,100W,TO-220	SA
5	BH61-00004A	CIS	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,TO.5,-,-,-	SNA
5	BH62-00016A	CIS	HEAT SINK-TR	A1050S,T1.0,-,DP17MO	SNA

7-3-2 LE17KS(LE17KT) Video PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH94-00980A	-	ASSY PCB VIDEO-ST	LE17JS	SNA
4	BH63-00131A	CIS1	SHIELD-VIDEO	LE17KS,SPT,E,T0.2	SNA
4	6502-000001	CIS10	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	0204-001527	CIS3	FLUX	DF-201TVS,MIX,0.820,FLUX13%,14KG	SNA
4	0204-000442	CIS4	SOLVENT	1M-1000,C3H7OH,96,-	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER100G,-,WHT,BLK,-,ALL,CDT	SNA
4	BH61-70003A	CIS5	SPRING ETC	CVT4857,STS304-W1/2H,W3.8,-,L30,L30,-,T0.5,DEGRE,W3.8,STS304-W1/2H	SNA
4	3711-004236	CN101	CONNECTOR-HEADER	BOX,6P,1R,2MM,STRAIGHT,SN	SNA
4	BH39-00015A	CN102	CBF-HARNESS	13P/14P,200MM,WHT/BLK/RED/BLU,UL1007,AWG26,SMH200-13/YBNH200-14	SA
4	BH13-00050A	IC102	IC HYBRID	NT6813K-30031,NT6813K-30031,24P,-55 to +150,240mA,-0.5 to 6V,ST	SA
4	3704-001170	SK101	SOCKET-CRT	10P,22.5PI,25.6PI,NL+SN,-	SA
4	BH96-00283A	HS106	ASSY HEAT SINK P	BH62-00054A,SCREW,STV9588,OIL SILICON,BRKT-VIDEO	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	1201-002113	H/S	IC-VIDEO AMP	SAM9588,CLIPWATT,19P,19.85x10.7mm,-,26,PLASTIC,110V,3W,Qto+70C,-,-,-,ST	SA
5	6003-000333	H/S	SCREW-TAPTITE	RH,+,2S,M3,L10,ZPC(YEL),SWRCH1	SNA
5	BH61-00048A	H/S	BRACKET-VIDEO	andromeda,SECC,0.8	SNA
5	BH62-00054A	H/S	HEAT SINK-PS	LEO,A1050S,2.0,112,25	SNA
4	BH97-00512A	-	ASSY AUTO-(VIDEO)ST	LE17JS	SNA
5	3301-001450	BD102	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD103	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD104	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD105	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD106	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD107	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	2301-000014	C101	C-FILM,LEAD-PEF	6.8nF,5%,100V,TP,5.8x12.5mm,5m	SA
5	2401-000025	C103	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000603	C104	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2201-000376	C105	C-CERAMIC,DISC	0.22NF,5%,50V,SL,TP,6.3X3.5MM,5	SA
5	2201-000019	C106	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2401-002463	C111	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2201-000119	C112	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C113	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2201-000119	C114	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C115	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C116	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002008	C117	C-CERAMIC,MLC-AXIAL	10nF,+80-20%,50V,Y5V,TP,2.3X3.	SA
5	2202-002009	C118	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C119	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C120	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	C121	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C122	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2301-000010	C123	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-001218	C124	C-AL	4.7uF,20%,100V,WT,TP,5x11,5	SA
5	2202-002009	C125	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000019	C131	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2201-002147	C132	C-CERAMIC,DISC	2.7NF,10%,500V,Y5P,TP,10X4MM,5	SA
5	2201-000288	C133	C-CERAMIC,DISC	1NF,10%,2KV,Y5P,TP,9X5MM,7.5	SA
5	2202-002009	CB01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CB03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CB04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2202-002009	CG01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CG03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CG04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	0203-001199	CIS6	TAPE-KRAFT	#53110,T0.1,W6,L2000M,BRN	SNA
5	0203-001200	CIS7	TAPE-PAPER	#53128,T0.15,W5.5,L2000M,BEIGE	SNA
5	BH71-40300A	CN_G2	PIN-HINGE	BRASS,D2.361,HEAT/SINK,SN	SNA
5	BH71-40300A	CN_GND	PIN-HINGE	BRASS,D2.361,HEAT/SINK,SN	SNA
5	2202-002009	CR01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2301-000010	CR03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CR04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	0401-000005	DB01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DB02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DB03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DG01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DG02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DG03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DR01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DR02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DR03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	6042-000001	EY1	EYELET	ID2.2,0D2.7,L3.1,Ni+SN,BSP3-1/2H	SNA
5	6042-000001	EY2	EYELET	ID2.2,0D2.7,L3.1,Ni+SN,BSP3-1/2H	SNA
5	6042-000002	EY3	EYELET	ID1.5,0D2,L2.8,Ni+SN,BSP3-1/2H	SNA
5	6042-000002	EY4	EYELET	ID1.5,0D2,L2.8,Ni+SN,BSP3-1/2H	SNA
5	6042-000002	EY5	EYELET	ID1.5,0D2,L2.8,Ni+SN,BSP3-1/2H	SNA
5	BH39-40305U	JP101	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP102	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP103	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP104	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2701-000172	LB01	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LB02	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LG01	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LG02	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LR01	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LR02	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	BH41-00269A	MP1.0	PCB-VIDEO	LE17JS,FR-1,1,1.0,1.6T,81.7*123.5,LE17.6,VIDEO	SNA
5	2001-000076	R101	R-CARBON	47KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000857	R102	R-CARBON	560OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R103	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000702	R104	R-CARBON	39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R105	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R106	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000016	R107	R-CARBON(S)	10HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000435	R111	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000812	R112	R-CARBON	5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R113	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R114	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R121	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000419	R122	R-METAL OXIDE(S)	1.2ohm,5%,1W,AA,TP,3.3x9mm	SA
5	2001-001138	R131	R-CARBON(S)	390OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000037	R132	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RB01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RB02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	RB03	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001026	RB04	R-CARBON	910OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000117	RB06	R-CARBON(S)	68OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RB07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000117	RB08	R-CARBON(S)	68OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RB09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG01	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG02	R-CARBON	75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	RG03	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001026	RG04	R-CARBON	910OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000117	RG06	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RG07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000117	RG08	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RG09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	RR03	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001026	RR04	R-CARBON	9100HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000117	RR06	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RR07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000117	RR08	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RR09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	1405-001064	SK104	SURGE ABSORBER	400V,20%,-- ,AXIAL	SA
5	4715-001065	SK105	SURGE ABSORBER	200V,20%,-- ,RADIAL	SNA
5	4715-001055	SK108	SURGE ABSORBER	1kV,+50-10%,-- ,RADIAL	SNA
5	4715-001065	SKB01	SURGE ABSORBER	200V,20%,-- ,RADIAL	SNA
5	4715-000102	SKG01	SURGE ABSORBER	200V,20%,1000A,- ,RADIAL	SNA
5	4715-000102	SKR01	SURGE ABSORBER	200V,20%,1000A,- ,RADIAL	SNA
5	0403-000361	ZD102	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD103	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD104	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000509	ZD105	DIODE-ZENER	MTZJ5.6B,5.4-5.7V,500MW,DO-34,TP	SA
5	0403-000361	ZD106	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA

7-3-3 LE17KS(LE17KT) Others

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BH90-00592A	-	ASSY COVER REAR	LE17JS,EDC	SNA
3	BH63-00130A	C/R	COVER-REAR	LE17KS,ABS HB,IV16	SNA
2	BH90-00598A	-	ASSY STAND	LE17JS/LE15VS,EDC	SNA
3	BH96-00272A	STD	ASSY STAND P	LE17KS,ABS HB IV16	SNA
4	6902-000109	STD	BAG PE	HDPE,T0.015,L430,W350,TRP,28,2,PE MARK	SNA
4	BH60-00030A	STD	FASTENER-BAND	PN17LT,ST+PVC,P0.4,-,150,YELLOW,-,-,-	SNA
4	BH61-00049A	STD	STAND-BASE	LE17KS,ABS HB,IV16	SNA
4	BH61-00050A	STD	STAND-TOP	LE17KS,ABS HB,IV16	SNA
4	BH61-40002A	STD	FOOT-RUBBER	- ,NR,PMS428U,GA4237,-,-,-	SNA
4	BH63-30103A	STD	FELT-STAND	MCM1755,FELT,T1.0,W10,L4	SNA
4	BH68-20366A	STD	LABEL-MARK STAND	,ART PAPER100(S),WHT	SNA
4	BH68-70306A	STD	CARD-STAND	CVM4967PWS(SKD),WONSTROW,CHAIN	SNA
2	BH90-00686C	-	ASSY COVER FRONT	LEO	SNA
3	6003-000009	C/F+C/R	SCREW-TAPTITE	BH,+ ,B,M4,L16,ZPC(YEL),SWRCH18	SNA
3	6006-001119	C/F+CDT	SCREW-ASS'Y TAPT	WC,BH,+ ,M5,L25,ZPC(YEL),SWRCH18A	SNA
3	BH96-00274E	-	ASSY COVER P-FRONT	LE17KS (S/M 793DF),ABS HB IV16,TC003	SNA
2	BH91-00843M	-	ASSY CDT-ST	OZ17LOM	SNA
3	0201-001576	CDT	ADHESIVE-RBR	DC-3140_RTV#0414,TRP,-,-	SNA
3	0203-000005	CDT	TAPE-ACETATE	SGT730,T0.26,W19,L3000,BLK	SNA
3	3302-000006	CDT	MAGNET-RUBBER	AF,14G,1620-1980G,0.58-0.9MGOe	SA
3	3309-000002	CDT	MAGNET-SHEET	5x20x80mm,UL94V-0,2	SA
3	BH03-00076A	CDT	CDT-ST	M41QCJ761X702(T4),70,17,0.25,29.1,IFT,H/C,NH,TCO,TILT,4	SA
3	BH68-30003C	CDT	LABEL-00,HIGH,VOLTAGE	SS,ART100G,30*33,YEL	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH96-00292A	CDT	ASSY D-COIL P	17 inch,BH27-00148A,BH96-00289A	SNA
2	BH91-00870A	-	ASSY SHIELD	LE17JS	SNA
3	0201-001059	CIS	ADHESIVE-SIL	#9590,WHT,-,CARTRIGE	SNA
3	6003-001023	SH/COV+SH/BTM	SCREW-TAPTITE	RWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
3	BH96-00281A	CIS	ASSY MISC P-SHIELD COVER	LE17KS,SECC TO.5,AL TO.25	SNA
4	BH63-00132A	CIS	SHIELD-COVER TOP	LE17KS,AL,TO.25	SNA
4	BH63-00133A	CIS	SHIELD-COVER REAR	LE17KS,SECC,TO.5	SNA
4	BH63-00145A	CIS	SHEET-ANODE	LE17KS,PP V2,T1.0,WHITE	SNA
2	BH91-00964B	-	ASSY CHASSIS	LE17KS	SNA
2	BH92-01069A	-	ASSY P/MATERIAL	LE17JS	SNA
3	0203-001100	P/M	TAPE-OPP MASKING	OPP/W75/CLR,TO.05,W75,L800000,CLR	SNA
3	0203-001159	P/M	TAPE-FILAMENT	#8915,TO.15,W12,L55000,CLR	SNA
3	6902-000001	P/M	BAG AIR	LDPE,TO.2,L1800,W1000,TRP,,,LDPE ONLY	SNA
3	6902-000379	P/M	BAG AIR	HDPE,TO.2,L1800,W1000,TRP,,,PAPER	SNA
3	6902-000523	P/M	BAG PE	HDPE,TO.015,W900,L800,TRP,28 LANGUAGE,2-	SNA
3	6902-000576	P/M	BAG ROLL	LDPE,TO.05,W2400,L1000,TRP,-,-	SNA
3	BH69-00561A	P/M	CUSHION	LE17KS,EPS M50,DF	SNA
3	BH69-40380A	P/M	PACKING-PAD	DW-2,500X2200X200,-,CGK5527	SNA
2	BH92-01093A	-	ASSY LABEL	LEO-PJT(15/17/19)	SNA
3	BH68-00565D	LABEL	LABEL RATING-00	ALL,SS,PE,TO.05,90*65,BLK,POLYESTER,EDC	SNA
2	BH92-01161B	-	ASSY BOX	LEO	SNA
3	BH68-00530A	BOX	LABEL BOX-01	LABEL-BARCODE,CE+TC003,MOJO 90G,WHT	SNA
3	BH69-00570A	BOX	BOX	S/M793DF(LE17KS),W/W,CB-SW4,YEL,A-1,W452*D506*H435	SNA
2	BH92-01162A	-	ASSY ACCESSORY	LEO	SNA
3	BH96-00297A	UNIT/ACCESSORY	ASSY ACCESSORY	LEO	-
4	0203-000214	ACCESSORY	TAPE-OPP MASKING	OPP/W50/CLR,TO.05,W50,L400000,	SNA
4	6902-000110	ACCESSORY	BAG PE	LDPE,TO.05,L356,W240,TRP,28,2,PE MARK	SNA
4	BH39-10339H	ACCESSORY	CBF POWER CORD	DET,H05VV-F,250V/10,16A,BLK,25	SA
4	BH68-70418A	ACCESSORY	CARD-EU BLOC WARR-07	SyncMaster,BASIC,EU,MOJO,100G,	SNA
4	BH96-00296A	ACCESSORY	ASSY MANUAL P-IB+QSG	795DF,SyncMaster,W/W,27Lang,BH59-362A+BH68-376J	-
5	BH59-00362A	I/B	S/W DRIVER-00,IB	793S,795DF,W/W,SYNCMaster,27LANG	SNA
5	BH68-00376J	QUICK	MANUAL-01	AN_QUICK SETUP GUIDE,SYNCMaster,E/F/S/G/P/L.14LANGS,W/W,MOJO100G,298,420	SNA

7-4-1 LE17JS(LE17JT) Main PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
0	LE17JSBB/EDC				
1	CC-LE17JSBB/EDC	-	3	CPT,HIGH-CON	-
3	BH94-00989R	-	ASSY PCB MAIN-SX	LEO	SNA
4	2306-000234	C451	C-FILM,LEAD-PPF	560nF,5%,250V,BK,26x20x13,20	SA
4	2306-000147	C503	C-FILM,LEAD-PPF	1uF,5%,250V,BK,26x24x15,22.5mm	SA
4	2301-001195	C601	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2301-001195	C602	C-FILM,LEAD-PPF	150nF,10%,275VAC,BK,26x16.5x7,	SA
4	2401-003391	C605	C-AL	220uF,20%,450V,GP,BK,25x50,10	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
4	BH63-00134A	CIS1	SHIELD-BOTTOM	LE17KS,SECC,T1.0	SNA
4	BH39-00323D	CIS10	LEAD CONNECTOR-ASSY	OT17L0,8.0*0.16TA*16,150MM,35068-9822,35750-1010,BK,8.0*0.16TA*16	SA
4	BH63-00143A	CIS3	COVER-PCB R	LE17KS,ABS PC,IV16	SNA
4	BH63-00144A	CIS4	COVER-PCB L	LE17KS,ABS PC,IV16	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER 100G,-,WHT,BLK,-,ALL,CDT	SNA
4	0202-000008	CIS5	SOLDER-WIRE	HI-FLO,3.0,-,D3.0,63SN/37PB,-	SNA
4	0204-001527	CIS6	FLUX	DF-201TVS,MIX,0.820,FLUX 13%, 14KG	SNA
4	0204-000442	CIS7	SOLVENT	1M-1000,C3H7OH,96,-	SNA
4	0202-000187	CIS8	SOLDER-WIRE FLUX	-,D1.2,63SN/37PB RA,-	SNA
4	3711-003895	CN201	CONNECTOR-HEADER	BOX,13P,1R,2mm,STRAIGHT,SN	SA
4	3711-003873	CN202	CONNECTOR-HEADER	BOX,7P,1R,2mm,STRAIGHT,SN	SA
4	3711-004379	CN203	CONNECTOR-HEADER	BOX,4P,1R,2MM,STRAIGHT,SN	SA
4	3711-005055	CN401	CONNECTOR-HEADER	1WALL,4P,1R,10MM/8.0MM,STRAIGHT,SN-PB,WHT	SA
4	3721-001053	CN601	PLUG-AC POWER	3P,-,NI	SNA
4	0402-001295	D405	DIODE-RECTIFIER	GUR460L-5700,600V,4A,DO-201AD,BK	SA
4	0402-001313	D406	DIODE-RECTIFIER	ERD07-15AL,1.7VK,1.5A,DO-204AC,BK	SA
4	0402-001407	D601	DIODE-BRIDGE	G2SB60,600V,1.5A,SIP-4,BK	SA
4	0402-000005	D625	DIODE-RECTIFIER	31DF4,400V,3A,DO-201AD,BK	SA
4	6003-000122	FBT+H/S	SCREW-TAPTITE	BH,+B,M4,L12,ZPC(YEL),SWRCH18	SNA
4	3601-001302	FH1	FUSE-AXIAL LEAD	250V,3.15A,SLOW-BLOW,CERAMIC,5X20MM	SA
4	BH63-00124A	HS401	SHIELD-IC	LE17KS,SPT,TO.2	SNA
4	6502-000001	HS490_CIS1	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	6502-000001	HS490_CIS2	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	3704-001071	IC201_SOCKET	SOCKET-IC	42P,DIP,SN,1.778mm	SA
4	1103-001106	IC241	IC-EEPROM	24C080,1Kx8Bit,DIP,8P,9.6x6.4mm,-,2.7/5.5V,-,25to+70C,10uA,-,ST	△ SNA
4	1204-002259	IC401	IC-DEF. PROCESSOR	STV9118,SDIP,32P,27.94x8.89mm,PLASTIC,13.2V,-,0to+70C,ST,IC-DEF. PROCESSOR	△ SNA
4	1203-003240	IC621	IC-POSIFIXED REG.	L78M05,IPAK,3P,6.5x6.1mm,PLASTIC,4.75/5.25V,-,0to+150C,0.5A,-,ST	SA
4	1203-000243	IC622	IC-POSIFIXED REG.	7812,TO-220,3P,-,PLASTIC,11.5/12.5V,-,16W,0to+125C,1A,-,ST	SA
4	BH27-00135A	L411	COIL CHOKE	120UH,CDTMO,120UH,10%,0.23OHM,5A,AR8X25,65.5TS,18X40MM,11MM,USTCO.12X20,TR,-10CT	SA
4	BH27-00132A	L441	COIL LINEARITY	5.4UH,5.4UH,DR12X15 C:4.5,7MM,15X15X35MM,12X8T,23.0TS,TR,12%,0.03OHM	SA
4	BH27-20342U	L442	COIL-CHOKE	-8.2MH(250KHz),10%,DR8*11,-,-,-,10.5OHM,-,-,-,BULK	SA
4	BH27-00134A	L501	COIL CHOKE	100UH,CDTMO,100UH,10%,0.2OHM,5.0A,AR8X25,60.5TS,18X40MM,11MM,USTCO.12X20,TR,-10C	SA
4	BH27-00007A	L601	COIL-LINE FILTER	SQE2424,25mH MIN,-,SQE 2424,-,PHENAL,-,0.32ohm,21*27*33,-,BULK	SA
4	6003-001023	M/PCB+SH/BTM	SCREW-TAPTITE	RWH,+B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	0505-001309	Q453	FET-SILICON	IRF630,N,200V,10A,0.4OHM,100W,TO-220	SA
4	0505-001685	Q454	FET-SILICON	STD7NS20-1,N,200V,7A,0.4OHM,45W,I-PAK	SA
4	3501-001111	RL601	RELAY-POWER	12VDC,250MW,5000MA,1FORMA,15MS,5MS	SA
4	6003-000133	SH/BTM+AC/SOCK	SCREW-TAPTITE	BH,+S,M4,L8,ZPC(YEL),SWRCH18A,-	SNA
4	BH39-00451A	SIGNAL	CBF SIGNAL	LE17JS,15P/06P,07P,20276-N,1830mm,UL20276,BLACK,D-SUB /MALE,BLACK,30V,ATT. TYPE	SA
4	BH26-00027A	T401	TRANS-HOR.DRIVE	FQB-17A001,PL-3,El 1916,310UH	△ SNA
4	BH26-00171A	T501	TRANS FBT	CF2166,LE17JS,1.50mH,FERRITE,0.32OHM,BULK,14P,-,10-+60,26.3kV	△ SNA
4	BH26-00089A	T561	TRANS-FOCUS	EE-1916,AQ1916,5P,1.7mH,-,105mH,-,0.85ohm,-,PL-3,DMR30,TP-3,J2A,-,-,-,-	SA
4	BH26-00164A	T601	TRANS POWER	ER-3435,CU17KS,350uH,15,90-264V,80V,10-55,FERRITE,ER-3435,0.05ohm/0.350ohm,8uH M	SA
4	BH26-00163A	T602	TRANS	UU-1116,CU17K,5,18mH min,18mH min,2.7ohm MAX,10 ~ 55,FERRITE,UU-1116 SB-5S	SA
4	1404-001264	TH601	THERMISTOR-PTC	4.5OHM,+30/-20%,220V,290VAC,21A,-,TR	SA
4	1404-001020	TH602	THERMISTOR-NTC	8ohm,15%,-,17mW/C,BK	SA
4	2103-001049	VR441	VR-SEMI	100ohm,30%,1/5W,SIDE	SA
4	BH97-00505B	MICOM	ASSY MICOM	LE17JS	SA
5	BH82-00020H	CIS	A/S MICOM	LE17JS	SNA
5	0903-001194	IC201	IC-MICROCONTROLLER	3P863,8Bit,SDIP,42P,600MIL,12MHz,ST,CMOS,PLASTIC,5V,-,40to+85C,1040BYTE,48KBYTE	△ SNA
4	BH97-00521E	-	ASSY AUTO-MAIN-AUTO	LE0	SNA
5	3301-001450	BD321	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD401	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD402	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD431	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD501	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD502	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD601	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	3301-001450	BD621	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,...	SNA
5	3301-001450	BD622	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,...	SNA
5	2202-002037	C201	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2202-000205	C202	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2202-000205	C203	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2401-000603	C204	C-AL	1uF,20%,50V,GP,TP,5x11,2	SA
5	2202-000121	C205	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
5	2202-000796	C206	C-CERAMIC,MLC-AXIAL	1nF,10%,50V,Y5P,TP,3.5X1.9MM,-	SA
5	2202-000121	C207	C-CERAMIC,MLC-AXIAL	100pF,10%,50V,Y5P,TP,1.9x3.5,-	SA
5	2401-000603	C208	C-AL	1uF,20%,50V,GP,TP,5x11,2	SA
5	2401-000603	C209	C-AL	1uF,20%,50V,GP,TP,5x11,2	SA
5	2401-002299	C210	C-AL	4.7uF,20%,50V,GP,TP,5x7,5	SA
5	2401-002299	C211	C-AL	4.7uF,20%,50V,GP,TP,5x7,5	SA
5	2202-000205	C212	C-CERAMIC,MLC-AXIAL	22pF,5%,50V,SL,TP,1.9x3.5,-	SA
5	2401-002463	C301	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2301-000148	C302	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2305-000665	C303	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000014	C304	C-FILM,LEAD-PEF	6.8nF,5%,100V,TP,5.8x12.5mm,5m	SA
5	2305-000289	C305	C-FILM,LEAD-PEF	220nF,5%,63V,TP,-,5mm	SA
5	2401-000852	C306	C-AL	220uF,20%,35V,GP,TP,8x11.5mm,5	SA
5	2202-002008	C307	C-CERAMIC,MLC-AXIAL	10nF,+80-20%,50V,Y5V,TP,2.3X3.	SA
5	2202-002037	C321	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2401-000480	C322	C-AL	10uF,20%,50V,GP,TP,5x11,5	SA
5	2305-000196	C331	C-FILM,LEAD-PEF	150nF,5%,63V,TP,-,5mm	SA
5	2305-000412	C332	C-FILM,LEAD-PEF	470nF,5%,63V,TP,-,5mm	SA
5	2401-002144	C333	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2401-001334	C401	C-AL	0.47uF,20%,50V,GP,TP,5x11,2.5	SA
5	2401-001220	C402	C-AL	4.7uF,20%,160V,GP,TP,8x11.5,5	SA
5	2301-000010	C403	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2301-001463	C404	C-FILM,LEAD-PPF	4nF,5%,630V,TP,17X9X5,7,5	SA
5	2301-001304	C405	C-FILM,LEAD-PPF	1.5nF,5%,2.5KV,TP,23X17X11MM,7,5	△ SA
5	2301-001169	C406	C-FILM,LEAD-PPF	1.8nF,5%,2.5KV,TP,22.5x20x12.5	△ SA
5	2305-000178	C407	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-,5mm	SA
5	2401-001914	C411	C-AL	1uF,20%,50V,BP,TP,5x11,5	SA
5	2201-000471	C412	C-CERAMIC,DISC	0.33nF,10%,50V,Y5P,TP,4X3.5MM,5	SA
5	2301-000016	C413	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2305-000470	C414	C-FILM,LEAD-PEF	68nF,5%,100V,TP,-,5mm	SA
5	2401-001012	C415	C-AL	3.3uF,20%,50V,BP,TP,16X25,7,5	SA
5	2401-000025	C431	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2305-000665	C432	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000148	C433	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2202-000573	C434	C-CERAMIC,MLC-RADIAL	0.82nF,5%,50V,COG,TP,5.1X3.2X5.1MM,5	SA
5	2301-000148	C435	C-FILM,LEAD-PEF	10nF,5%,100V,TP,7x3.2x7mm,5mm	SA
5	2401-000660	C436	C-AL	2.2uF,20%,50V,GP,TP,5x11,5	SA
5	2401-000603	C437	C-AL	1uF,20%,50V,GP,TP,5x11,2	SA
5	2401-002144	C438	C-AL	47uF,20%,16V,GP,TP,5x11,5	SA
5	2305-001033	C442	C-FILM,LEAD-PEF	15nF,10%,250V,TP,13X9.0X4.5mm,	SA
5	2305-001033	C443	C-FILM,LEAD-PEF	15nF,10%,250V,TP,13X9.0X4.5mm,	SA
5	2306-000164	C452	C-FILM,LEAD-PPF	220nF,5%,250V,TP,19x22x10,7,5m	SA
5	2306-000125	C453	C-FILM,LEAD-PPF	120nF,5%,250V,TP,19x15x7,7,5mm	SA
5	2301-001249	C454	C-FILM,LEAD-PPF	68nF,5%,400V,TP,19x7x15mm,7,5	SA
5	2306-000131	C455	C-FILM,LEAD-PPF	150nF,5%,250V,TP,19x16x7,5,7,5	SA
5	2401-000603	C456	C-AL	1uF,20%,50V,GP,TP,5x11,2	SA
5	2401-000603	C457	C-AL	1uF,20%,50V,GP,TP,5x11,2	SA
5	2401-000603	C458	C-AL	1uF,20%,50V,GP,TP,5x11,2	SA
5	2401-000603	C459	C-AL	1uF,20%,50V,GP,TP,5x11,2	SA
5	2401-003826	C501	C-AL	220uF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000291	C502	C-CERAMIC,DISC	1nF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2401-002267	C504	C-AL	2.2uF,20%,250V,GP,TP,8x11.5,5	SA
5	2401-002267	C505	C-AL	2.2uF,20%,250V,GP,TP,8x11.5,5	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2301-000294	C521	C-FILM,LEAD-PEF	56nF,5%,100V,TP,9.5x12.5mm,5mm	SA
5	2202-002037	C531	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2301-000106	C532	C-FILM,LEAD-PEF	1.5nF,0.05,100V,TP,10.5*12.5*6	SA
5	2401-000758	C533	C-AL	0.22UF,20%,50V,GP,TP,5X11,5	SA
5	2301-000016	C534	C-FILM,LEAD-PEF	22nF,5%,100V,TP,7.2x4.5x9.0mm,	SA
5	2301-000106	C535	C-FILM,LEAD-PEF	1.5nF,0.05,100V,TP,10.5*12.5*6	SA
5	2301-000110	C536	C-FILM,LEAD-PEF	1.8nF,5%,100V,TP,7x3.0x6.5mm,5	SA
5	2202-002037	C537	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2401-000480	C551	C-AL	10uF,20%,50V,GP,TP,5x11,5	SA
5	2201-000291	C552	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2201-000132	C553	C-CERAMIC,DISC	0.1NF,10%,500V,Y5P,TP,6.5X3MM,5	SA
5	2201-000291	C561	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2201-000023	C603	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2201-000023	C604	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-000970	C606	C-AL	22uF,20%,50V,WT,TP,5x11,5	SA
5	2202-002037	C607	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2201-000325	C608	C-CERAMIC,DISC	2.2NF,10%,500V,Y5P,TP,9.5X4MM,5	SA
5	2201-000129	C609	C-CERAMIC,DISC	0.1NF,10%,1KV,Y5P,TP,7X4MM,5	SA
5	2301-000188	C610	C-FILM,LEAD-PEF	1nF,5%,100V,TP,10.5x12.5x6.5,5	SA
5	2401-000611	C611	C-AL	1uF,20%,50V,WT,TP,5x11,5	SA
5	2305-000665	C613	C-FILM,LEAD-PEF	100nF,5%,63V,TP,7.5x4.0x5.0mm,	SA
5	2301-000284	C614	C-FILM,LEAD-PEF	47nF,5%,100V,TP,8.5x12.5mm,5mm	SA
5	2401-001513	C615	C-AL	47uF,20%,16V,WT,TP,5x11,5	SA
5	2202-002037	C616	C-CERAMIC,MLC-AXIAL	100nF,80-20%,50V,Y5V,TP,2.2x3.	SA
5	2201-000023	C617	C-CERAMIC,DISC	2.2NF,20%,250V,Y5U,TP,11X7MM,5	SA
5	2401-003046	C618	C-AL	47uF,20%,50V,WT,TP,6.3x11,2.5	SA
5	2201-000291	C619	C-CERAMIC,DISC	1NF,10%,500V,Y5P,TP,7.5X3.5MM,5	SA
5	2305-000178	C621	C-FILM,LEAD-PEF	10nF,5%,100V,TP,-,5mm	SA
5	2401-000039	C622	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C624	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000025	C625	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-002463	C626	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2401-000039	C627	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-002300	C628	C-AL	47uF,20%,50V,GP,TP,6.3x11,5	SA
5	2401-003826	C629	C-AL	220UF,20%,63V,LR,TP,10X25MM,5	SA
5	2201-000469	C630	C-CERAMIC,DISC	0.33NF,10%,500V,Y5P,TP,5.5X3MM,5	SA
5	2401-000039	C631	C-AL	1000uF,20%,16V,GP,TP,10x16,5	SA
5	2401-000025	C632	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	3711-000197	CN321	CONNECTOR-HEADER	1WALL,3P,1R,2.5mm,STRAIGHT,SN	SA
5	3711-000217	CN602	CONNECTOR-HEADER	1WALL,2P,1R,7.92MM,STRAIGHT,SN,NTR	SA
5	0401-000005	D201	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000128	D301	DIODE-RECTIFIER	1N4002GP,100V,1A,DO-41,TP	SA
5	0402-000546	D302	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D341	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D401	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	D402	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0402-000208	D403	DIODE-RECTIFIER	EK-04,40V,1A,DO-41,TP	SA
5	0402-000274	D404	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0401-000005	D411	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D412	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D413	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D414	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000274	D441	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000546	D442	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D443	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000006	D451	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000006	D452	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000006	D453	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000006	D454	DIODE-RECTIFIER	1N4007GP,1KV,1A,DO-41,TP	SA
5	0402-000546	D455	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	0402-001118	D501	DIODE-RECTIFIER	UF1G,400V,1.2A,DO-204AC,TP	SA
5	0402-000274	D502	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000546	D503	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D504	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D511	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D512	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D521	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D522	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D523	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	D531	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	D532	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	D533	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-000012	D603	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000012	D604	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-000546	D605	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0402-000546	D606	DIODE-RECTIFIER	TVR10G,400V,1.0A,DO-41,TP	SA
5	0401-000005	D607	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D608	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	D621	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0402-001194	D622	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000274	D623	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000274	D624	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	0402-000012	D626	DIODE-RECTIFIER	UF4007,1KV,1A,DO-41,TP	SA
5	0402-001194	D627	DIODE-RECTIFIER	UG2D,200V,2A,-,TP	SA
5	0402-000274	D628	DIODE-RECTIFIER	UF4004,400V,1A,DO-41,TP	SA
5	6042-000001	EY301	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY302	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY401	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY402	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY403	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY404	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY405	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY406	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY441	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY442	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY501	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY502	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY503	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY504	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY505	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY506	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY507	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY601	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY602	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY603	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY604	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY605	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY606	EYELET	ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY607	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY608	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY621	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY622	EYELET	ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	SNA
5	BH71-40300A	GT601	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	GT602	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH39-40305U	JP1	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP10	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP11	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP12	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP13	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP14	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH39-40305U	JP15	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP16	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP17	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP18	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP19	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP2	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP20	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP21	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP22	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP23	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP24	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP25	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP26	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	3301-001450	JP27	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	BH39-40305U	JP3	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP31	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP32	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP33	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP34	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP35	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP37	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP38	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP4	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP5	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP6	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP7	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP8	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP9	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH41-00268A	MP1.0	PCB MAIN	LE17JS,FR-1,1,1.0,1.6T,247*247,LE17,MAIN	SNA
5	0501-000122	Q321	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000581	Q322	TR-SMALL SIGNAL	2N3906,PNP,625mW,TO-92,TP,100-300	SA
5	0501-000122	Q323	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000372	Q401	TR-SMALL SIGNAL	KSC2383-Y,NPN,900000mW,TO-92L,TP,160-320	SA
5	0501-000303	Q411	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q412	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000140	Q413	TR-SMALL SIGNAL	2N5551,NPN,625mW,TO-92,TP,80-250	SA
5	0501-000412	Q455	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000412	Q456	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000412	Q457	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000412	Q458	TR-SMALL SIGNAL	KSP42,NPN,625mW,TO-92,-,40	SA
5	0501-000586	Q501	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000303	Q502	TR-SMALL SIGNAL	KSA733,PNP,250mW,TO-92,TP,120-240	SA
5	0501-000586	Q511	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000143	Q512	TR-SMALL SIGNAL	2N6520,PNP,625mW,TO-92,TP,30-200	SA
5	0501-000413	Q551	TR-SMALL SIGNAL	KSP44,NPN,625mW,TO-92,TP,50-200	SA
5	0501-000122	Q601	TR-SMALL SIGNAL	2N3904,NPN,625mW,TO-92,TP,100-300	SA
5	0501-000010	Q621	TR-SMALL SIGNAL	KSC1008,NPN,800mW,TO-92,TP,120-240	SA
5	0501-000586	Q622	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-000404	Q623	TR-SMALL SIGNAL	KSD1616-Y,NPN,750mW,TO-92,TP,135-270	SA
5	0501-000586	Q624	TR-SMALL SIGNAL	KSC945,NPN,250mW,TO-92,TP,120-240	SA
5	0501-002228	Q625	TR-SMALL SIGNAL	KTA1281,PNP,1000mW,TO-92L,TP,120-240	SA
5	2001-000869	R201	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R202	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000008	R203	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000008	R204	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R205	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R206	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R207	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R208	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R209	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2001-000734	R210	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R211	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000734	R212	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R213	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R214	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000554	R215	R-CARBON	270OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000591	R216	R-CARBON	3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R217	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R218	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R219	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R220	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000515	R221	R-CARBON	220OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R222	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R223	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	R224	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000435	R225	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R231	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000869	R232	R-CARBON	560HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R241	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R242	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R243	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000009	R302	R-CARBON	20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-001254	R303	R-METAL	8.2Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-000734	R304	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000616	R305	R-METAL	24Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001005	R306	R-METAL	5.1Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001022	R307	R-METAL	5.6Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001409	R308	R-METAL	2.7ohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000481	R309	R-METAL	2.4Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2001-001126	R310	R-CARBON(S)	300OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000908	R311	R-CARBON	62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001053	R312	R-CARBON(S)	1.5OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000290	R321	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000878	R322	R-CARBON	6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000302	R323	R-CARBON	10OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000273	R324	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000042	R325	R-CARBON	1KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000281	R326	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001079	R327	R-CARBON(S)	150HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001079	R328	R-CARBON(S)	150HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R331	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000979	R332	R-METAL	47Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000908	R333	R-CARBON	62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R334	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001088	R401	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000110	R402	R-CARBON	10OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000429	R403	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000319	R404	R-CARBON	120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001078	R405	R-CARBON(S)	15KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-002108	R406	R-METAL OXIDE(S)	300ohm,5%,3W,AA,TP,15x5.5mm	SA
5	2005-001163	R407	R-WIRE WOUND,NON	0.68ohm,1%,3W,AA,TP,5.5x15mm	SA
5	2001-000020	R408	R-CARBON(S)	22OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000019	R409	R-CARBON(S)	10OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2004-000193	R411	R-METAL	100Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-000327	R412	R-METAL	150Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA
5	2004-001349	R415	R-METAL	91Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000979	R416	R-METAL	47Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000531	R417	R-CARBON	240KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000221	R418	R-CARBON	1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000327	R419	R-METAL	150Kohm,1%,1/4W,AA,TP,2.4x6.4m	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2004-000176	R420	R-METAL	1.8Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001254	R421	R-METAL	8.2Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-001254	R431	R-METAL	8.2Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000449	R432	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000525	R441	R-METAL OXIDE(S)	180ohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000514	R442	R-METAL OXIDE(S)	15ohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000514	R443	R-METAL OXIDE(S)	15ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000016	R444	R-CARBON(S)	10HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000471	R445	R-METAL OXIDE(S)	10ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-000290	R451	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R452	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R453	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R454	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R455	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R456	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R457	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R458	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R459	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R460	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000449	R461	R-CARBON	2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000786	R462	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001099	R501	R-CARBON(S)	2.7KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2003-000145	R502	R-METAL OXIDE	100ohm,5%,1W,AA,TP,4.3x12mm	SA
5	2001-000333	R503	R-CARBON	120HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000522	R504	R-CARBON	22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000703	R505	R-METAL OXIDE(S)	470ohm,5%,3W,AA,TP,6x16mm	SA
5	2003-000407	R506	R-METAL OXIDE(S)	0.6ohm,5%,2W,AA,TP,4x12mm	△ SA
5	2001-000107	R507	R-CARBON(S)	150KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000429	R508	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	△ SA
5	2001-000786	R511	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001088	R513	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2002-001099	R514	R-COMPOSITION	68KOHM,5%,1/2W,AA,TP,3.0X9.0MM	SNA
5	2001-001164	R515	R-CARBON(S)	56KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000084	R521	R-CARBON	100Kohm,5%,1/4W,AA,TP,2.4x6.4mm	SA
5	2004-000327	R522	R-METAL	150Kohm,1%,1/4W,AA,TP,2.4x6.4mm	SA
5	2001-000660	R523	R-CARBON	33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R524	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000531	R525	R-CARBON	240KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001000	R531	R-CARBON	82KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R532	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000478	R533	R-CARBON	2.70HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000890	R534	R-CARBON	6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000995	R535	R-CARBON	820OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2004-000825	R536	R-METAL	36Kohm,1%,1/4W,AB,TP,2.4x6.4mm	△ SA
5	2004-000218	R537	R-METAL	10Kohm,1%,1/8W,AA,TP,1.8x3.2mm	△ SA
5	2004-000284	R538	R-METAL	12Kohm,1%,1/4W,AA,TP,2.4x6.4mm	△ SA
5	2001-000008	R539	R-CARBON	15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	△ SA
5	2004-000458	R540	R-METAL	2.2Kohm,1%,1/4W,AA,TP,2.4x6.4mm	△ SA
5	2001-000645	R541	R-CARBON	330KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000273	R542	R-CARBON	100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R551	R-CARBON	1000HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000530	R553	R-CARBON	240KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000537	R554	R-CARBON	24KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000042	R555	R-CARBON	1KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-001113	R556	R-CARBON(S)	270KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000316	R557	R-CARBON	120KOHM,5%,1/2W,AA,TP,3.3X9MM	SA
5	2001-000316	R558	R-CARBON	120KOHM,5%,1/2W,AA,TP,3.3X9MM	SA
5	2003-000650	R561	R-METAL OXIDE(S)	330ohm,5%,2W,AA,TP,4x12mm	SA
5	2001-001129	R601	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001129	R602	R-CARBON(S)	330KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	2003-000738	R603	R-METAL OXIDE(S)	56Kohm,5%,2W,AA,TP,4x12mm	SA
5	2003-000014	R604	R-METAL OXIDE(S)	10Kohm,5%,3W,AA,TP,6x16mm	SA
5	2002-001103	R605	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2002-001103	R606	R-COMPOSITION	300Kohm,5%,1/2W,AA,TP,3.7x10.0mm	SA
5	2001-001116	R607	R-CARBON(S)	270HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	R608	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000780	R609	R-CARBON	470OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000281	R610	R-CARBON	100OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R611	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000023	R621	R-CARBON	470HM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000027	R622	R-CARBON	100OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000613	R623	R-CARBON	3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R624	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	BH39-40305U	R625	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2001-000290	R626	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001088	R628	R-CARBON(S)	1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000786	R629	R-CARBON	47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000062	R630	R-CARBON	470OHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2003-000471	R631	R-METAL OXIDE(S)	10ohm,5%,2W,AA,TP,4x12mm	SA
5	4715-001055	SK561	SURGE ABSORBER	1kV,+50-10%,-,-,RADIAL	SNA
5	6042-000002	TP501	EYELET	ID1.5,0D2,L2.8,Ni+SN,BSP3-1/2H	SNA
5	2801-000006	X201	CRYSTAL-UNIT	12MHz,50ppm,28-AAM,S,35ohm,BK	SA
5	0403-000348	ZD201	DIODE-ZENER	UZ36B,33-39V,500MW,DO-35,TP	SA
5	0403-001068	ZD202	DIODE-ZENER	UZ4.7BSA,4.44-4.68V,500MW,DO-34,TP	SA
5	0403-000361	ZD211	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD212	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD213	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD214	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD221	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD222	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD223	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD224	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD225	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD226	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD241	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD242	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000355	ZD514	DIODE-ZENER	UZ5.1BSB,5-5.2V,500MW,DO-35,TP	SA
5	0403-001221	ZD601	DIODE-ZENER	UZ39BSB,35.36-37.19V,500MW,DO-34,TP	SA
5	0403-000361	ZD602	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
4	BH99-00006A	HS451	ASSY HEAT/SINK	H/S,SCREW+NUT,IRF630,-,-,OIL SILICON,-,-	SNA
4	BH99-00006A	HS452	ASSY HEAT/SINK	H/S,SCREW+NUT,IRF630,-,-,OIL SILICON,-,-	SNA
5	0205-001027	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001309	CIS	FET-SILICON	IRF630,N,200V,10A,0.40HM,100W,TO-220	SA
5	6006-001008	CIS	SCREW-ASS'Y MACH	WSP,BH,+,M3,L10,ZPC(YEL),SWRCH	SNA
5	6021-000118	CIS	NUT-HEXAGON	1C,M3,ZPC(YEL),SM20C	SNA
5	BH62-30024A	CIS	HEAT SINK-TR	SPC,T1,SN,CFX1577L	SNA
4	BN61-01137A	CIS16	SUPPORT-CLIP	IBM E74,NYLON 66,1.0,NTR	SNA
4	BP96-00064C	HS601	ASSY HEAT SINK P	BH62-00004A,SPRING,8S0765RC,RUBBER SILICON	SNA
5	BH13-00045A	CIS	IC HYBRID	FS8S0765RCYDTU,CU17KS,5,-25 to 85,TO-220(FORMING),35,ST	SA
5	BH61-00004A	CIS	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,T0.5,-,-,-	SNA
5	BH62-00004A	CIS	HEAT SINK-POWER	-,-,T1,-,-,A1050S,DA/DB	SNA
5	BH62-20001B	CIS	TUBE-RUBBER	CSQ4357,W25*L20*T0.45,-,-,-,-	SNA
4	BP96-00065B	HS301	ASSY HEAT SINK P	BH62-00003B,SPRING,STV9325,OIL SILICON	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	1204-002262	H/S	IC-VERTICAL DEF.	STV9325,HEPTAWATT,7P,15.45x10.22mm,PLASTIC,35V,-,-,40to+150C,ST,(C-VERTICAL DEF.	SNA
5	6003-000334	H/S	SCREW-TAPTITE	RH,+,2S,M3,L6,ZPC(YEL),SWRCH18	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH62-00003B	H/S	HEAT SINK-VERT	A1050S,T1.0,T1.0,-,DA,DB	SNA
4	BP96-00066K	HS490	ASSY HEAT SINK P	HS FBT,SPRING,2SC5931,DTV1500HFP,KTD2058,OIL SILICON,	SNA
5	0205-001027	CIS	OIL-SILICON	G746,-,-	SNA
5	0402-001507	CIS	DIODE-RECTIFIER	DTV1500HFP,1500,6A,SMB,ST	SA
5	0502-000465	CIS	TR-POWER	KTD2058,NPN,25000mW,T0-220IS,ST,100-200	SA
5	0502-001243	CIS	TR-POWER	2SC5931,NPN,60000mW,TOP-3,ST,8-11	SA
5	BH61-00004A	CIS	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,T0.5,-,-,-	SNA
5	BH61-70003A	CIS	SPRING ETC	CVT4857,STS304-W1/2H,W3.8,-,L30,L30,-,T0.5,DEGRE,W3.8,STS304-W1/2H	SNA
5	BH62-00015A	CIS	HEAT SINK-FBT	A1050S,T1.0,T1.0,-,-	SNA
4	BP96-00072C	HS590	ASSY HEAT SINK P	H/S TR,SPRING,IRF634B,OIL SILICON	SNA
5	0205-001027	CIS	OIL-SILICON	G746,-,-	SNA
5	0505-001707	CIS	FET-SILICON	IRF634B,N,250V,8.1A,0.45 OHM,74W,T0-220	SA
5	BH61-00004A	CIS	SPRING ETC-TR	CDA,CDB,SUS304,-,-,-,-,T0.5,-,-,-	SNA
5	BH62-00016A	CIS	HEAT SINK-TR	A1050S,T1.0,-,DP17MO	SNA
2	BH91-00970W	-	ASSY CDT-CC	LEO	SNA
3	0201-001576	CDT	ADHESIVE-RBR	DC-3140_RTV#0414,TRP,-,-	SNA
3	0203-000005	CDT	TAPE-ACETATE	SGT730,T0.26,W19,L3000,BLK	SNA
3	3302-000006	CDT	MAGNET-RUBBER	AF,14G,1620-1980G,0.58-0.9MGOe	SA
3	3309-000002	CDT	MAGNET-SHEET	5x20x80mm,UL94V-0,2	SA
3	BH03-00060B	CDT	CDT-CC	M41AJR53X46(LL),70,17,0.25,29.1,IFT,H/C,NH,TCO,TILT,4	SA
3	BH68-30003C	CDT	LABEL-00,HIGH,VOLTAGE	SS,ART 100G,30*33,YEL	SNA
3	BH96-00292A	CDT	ASSY D-COIL P	17 inch,BH27-00148A,BH96-00289A	SNA

7-4-2 LE17JS(LE17JT) Video PCB Parts

Level	Loc. No.	Code No.	Description	Specification	Remarks
3	BH94-00980A	-	ASSY PCB VIDEO-ST	LE17JS	SNA
4	BH63-00131A	CIS1	SHIELD-VIDEO	LE17KS,SPTE,T0.2	SNA
4	6502-000001	CIS10	CABLE CLAMP	DAWH-5NB,D15,L35,NYLON66,NTR	SNA
4	0202-000008	CIS2	SOLDER-WIRE	HI-FLO,3.0,-,D3.0,63SN/37PB,-	SNA
4	0204-001527	CIS3	FLUX	DF-201TVS,MIX,0.820,FLUX 13%, 14KG	SNA
4	0204-000442	CIS4	SOLVENT	1M-1000,C3H7OH,96,-	SNA
4	BH68-00001A	CIS40	LABEL-MARK CDT	ART-PAPER 100G,-,WHT,BLK,-,ALL,CDT	SNA
4	0202-000187	CIS5	SOLDER-WIRE FLUX	-,-,D1.2,63SN/37PB RA,-	SNA
4	BH61-70003A	CIS5	SPRING ETC	CVT4857,STS304-W1/2H,W3.8,-,L30,L30,-,T0.5,DEGRE,W3.8,STS304-W1/2H	SNA
4	3711-004236	CN101	CONNECTOR-HEADER	BOX,6P,1R,2MM,STRAIGHT,SN	SNA
4	BH39-00015A	CN102	CBF-HARNESS	13P/14P,200MM,WHT/BLK/RED/BLU,UL1007,AWG26,SMH200-13/YBNH200-14	SA
4	BH13-00050A	IC102	IC HYBRID	NT6813K-30031,NT6813K-30031,24P,-55 to +150,240mA,-0.5 to 6V,ST	SA
4	3704-001170	SK101	SOCKET-CRT	10P,22.5PI,25.6PI,NI+SN,-	SA
4	BH96-00283A	HS106	ASSY HEAT SINK P	BH62-00054A,SCREW,STV9588,OIL SILICON,BRKT-VIDEO	SNA
5	0205-001027	H/S	OIL-SILICON	G746,-,-	SNA
5	1201-002113	H/S	IC-VIDEO AMP	SAM9588,CLIPWATT,19P,19.85x10.7mm,-,-26,PLASTIC,110V,3W,0to+70C,-,-,-,-,ST	SA
5	6003-000333	H/S	SCREW-TAPTITE	RH,+,2S,M3,L10,ZPC(YEL),SWRCH1	SNA
5	BH61-00048A	H/S	BRACKET-VIDEO	andromeda,SECC,0.8	SNA
5	BH62-00054A	H/S	HEAT SINK-PS	LEO,A1050S,2.0,112,25	SNA
4	BH97-00512A	-	ASSY AUTO-(VIDEO)ST	LE17JS	SNA
5	3301-001450	BD102	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD103	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA
5	3301-001450	BD104	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,,,	SNA

7 Electrical Parts List

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	3301-001450	BD105	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,...	SNA
5	3301-001450	BD106	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,...	SNA
5	3301-001450	BD107	BEAD-AXIAL	45ohm,3.5x0.6x5.7mm,50mA,TP,...	SNA
5	2301-000014	C101	C-FILM,LEAD-PEF	6.8nF,5%,100V,TP,5.8x12.5mm,5m	SA
5	2401-000025	C103	C-AL	100uF,20%,16V,GP,TP,6.3x11,5	SA
5	2401-000603	C104	C-AL	1uF,20%,50V,GP,TP,5X11,2	SA
5	2201-000376	C105	C-CERAMIC,DISC	0.22NF,5%,50V,SL,TP,6.3X3.5MM,5	SA
5	2201-000019	C106	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2401-002463	C111	C-AL	470uF,20%,16V,GP,TP,8x11.5,5	SA
5	2201-000119	C112	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C113	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2201-000119	C114	C-CERAMIC,DISC	100NF,+80-20%,50V,Y5V,TP,8X3MM,5	SA
5	2401-003036	C115	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C116	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002008	C117	C-CERAMIC,MLC-AXIAL	10nF,+80-20%,50V,Y5V,TP,2.3X3	SA
5	2202-002009	C118	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C119	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2202-002009	C120	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2202-002009	C121	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2401-003036	C122	C-AL	100uF,20%,16V,GP,TP,5X11mm,5mm	SA
5	2301-000010	C123	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-001218	C124	C-AL	4.7uF,20%,100V,WT,TP,5x11,5	SA
5	2202-002009	C125	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2201-000019	C131	C-CERAMIC,DISC	10nF,+80-20%,500V,Y5V,TP,13.5x4mm,5	SA
5	2201-002147	C132	C-CERAMIC,DISC	2.7NF,10%,500V,Y5P,TP,10X4MM,5	SA
5	2201-000288	C133	C-CERAMIC,DISC	1NF,10%,2KV,Y5P,TP,9X5MM,7.5	SA
5	2202-002009	CB01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CB03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CB04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	2202-002009	CG01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CG03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CG04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	0203-001199	CIS6	TAPE-KRAFT	#53110,T0.1,W6,L2000M,BRN	SNA
5	0203-001200	CIS7	TAPE-PAPER	#53128,T0.15,W5.5,L2000M,BEIGE	SNA
5	BH71-40300A	CN_G2	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	BH71-40300A	CN_GND	PIN-HINGE	BRASS,D2.36!,HEAT/SINK,SN	SNA
5	2202-002009	CR01	C-CERAMIC,MLC-AXIAL	100NF,+80-20%,50V,Y5V,TP,2.3X3.0MM,-	SA
5	2301-000010	CR03	C-FILM,LEAD-PEF	100nF,5%,100V,TP,11.5x12.5mm,5	SA
5	2401-003911	CR04	C-AL	1uF,20%,160V,BP,TP,6.3x11mm,5	SA
5	0401-000005	DB01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DB02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DB03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DB05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DG01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DG02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DG03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DG05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000005	DR01	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000005	DR02	DIODE-SWITCHING	1N4148,75V,150MA,DO-35,TP	SA
5	0401-000004	DR03	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR04	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	0401-000004	DR05	DIODE-SWITCHING	1SS244,220V,200MA,DO-34,TP	SA
5	6042-000001	EY1	EYELET	ID2.2,0D2.7,I3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000001	EY2	EYELET	ID2.2,0D2.7,I3.1,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY3	EYELET	ID1.5,0D2,I2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY4	EYELET	ID1.5,0D2,I2.8,NI+SN,BSP3-1/2H	SNA
5	6042-000002	EY5	EYELET	ID1.5,0D2,I2.8,NI+SN,BSP3-1/2H	SNA
5	BH39-40305U	JP101	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA

Level	Loc. No.	Code No.	Description	Specification	Remarks
5	BH39-40305U	JP102	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP103	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	BH39-40305U	JP104	CBF HARNESS	52MM,AWG22(0.6PI),-,-,AWG22(0.	SA
5	2701-000172	LB01	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LB02	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LG01	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LG02	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LR01	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	2701-000172	LR02	INDUCTOR-AXIAL	0.33uH,10%,3070	SA
5	BH41-00269A	MP1.0	PCB-VIDEO	LE17JS,FR-1,1,1.0,1.6T,81.7*123.5,LE17,6,VIDEO	SNA
5	2001-000076	R101	R-CARBON	47KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SA
5	2001-000857	R102	R-CARBON	560OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R103	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000702	R104	R-CARBON	39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000331	R105	R-CARBON	12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R106	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000016	R107	R-CARBON(S)	10HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000435	R111	R-CARBON	1MOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000812	R112	R-CARBON	5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R113	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000429	R114	R-CARBON	1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000290	R121	R-CARBON	10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2003-000419	R122	R-METAL OXIDE(S)	1.2ohm,5%,1W,AA,TP,3.3x9mm	SA
5	2001-001138	R131	R-CARBON(S)	390OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000037	R132	R-CARBON(S)	330OHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000969	RB01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RB02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	RB03	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001026	RB04	R-CARBON	910OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000117	RB06	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RB07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000117	RB08	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RB09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RG02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	RG03	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001026	RG04	R-CARBON	910OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000117	RG06	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RG07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000117	RG08	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RG09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR01	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000969	RR02	R-CARBON	750HM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000241	RR03	R-CARBON	1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-001026	RR04	R-CARBON	910OHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	2001-000117	RR06	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-001161	RR07	R-CARBON(S)	560KOHM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000117	RR08	R-CARBON(S)	680HM,5%,1/2W,AA,TP,2.4X6.4MM	SA
5	2001-000734	RR09	R-CARBON	4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SA
5	1405-001064	SK104	SURGE ABSORBER	400V,20%,-,-,AXIAL	SA
5	4715-001065	SK105	SURGE ABSORBER	200V,20%,-,-,RADIAL	SNA
5	4715-001055	SK108	SURGE ABSORBER	1kV,+50-10%,-,-,RADIAL	SNA
5	4715-001065	SKB01	SURGE ABSORBER	200V,20%,-,-,RADIAL	SNA
5	4715-000102	SKG01	SURGE ABSORBER	200V,20%,1000A,-,RADIAL	SNA
5	4715-000102	SKR01	SURGE ABSORBER	200V,20%,1000A,-,RADIAL	SNA
5	0403-000361	ZD102	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD103	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000361	ZD104	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA
5	0403-000509	ZD105	DIODE-ZENER	MTZJ5.6B,5.4-5.7V,500MW,DO-34,TP	SA
5	0403-000361	ZD106	DIODE-ZENER	UZ6.2BSB,5.96-6.27V,500MW,DO-34,TP	SA

7-4-3 LE17JS(LE17JT) Others

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BH90-00592A	-	ASSY COVER REAR	LE17JS,EDC	SNA
3	BH63-00130A	C/R	COVER-REAR	LE17KS,ABS HB,IV16	SNA
2	BH90-00598A	-	ASSY STAND	LE17JS/LE15VS,EDC	SNA
3	BH96-00272A	STD	ASSY STAND P	LE17KS,ABS HB IV16	SNA
4	6902-000109	STD	BAG PE	HDPE,T0.015,L430,W350,TRP,28,2,PE MARK	SNA
4	BH60-00030A	STD	FASTENER-BAND	PN17LT,ST+PVC,PO.4,-,150,YELLOW,-,-,-	SNA
4	BH61-00049A	STD	STAND-BASE	LE17KS,ABS HB,IV16	SNA
4	BH61-00050A	STD	STAND-TOP	LE17KS,ABS HB,IV16	SNA
4	BH61-40002A	STD	FOOT-RUBBER	-,NR,PMS428U,GA4237,-,-,-	SNA
4	BH63-30103A	STD	FELT-STAND	MCM1755,FELT,T1.0,W10,L4	SNA
4	BH68-20366A	STD	LABEL-MARK STAND	,ART PAPER 100(S),WHT	SNA
4	BH68-70306A	STD	CARD-STAND	CVM4967PWS(SKD),WONSTROW,CHAIN	SNA
2	BH90-00686D	-	ASSY COVER FRONT	LEO	SNA
3	6003-000009	C/F+C/R	SCREW-TAPTITE	BH,+B,M4,L16,ZPC(YEL),SWRCH18	SNA
3	6006-001119	C/F+CDT	SCREW-ASS'Y TAPT	WC,BH,+B,M5,L25,ZPC(YEL),SWRCH18A	SNA
3	BH96-00274F	C/F	ASSY COVER P-FRONT	LE17JS (S/M 795DF),ABS HB IV16,TC003	SNA
2	BH91-00870A	-	ASSY SHIELD	LE17JS	SNA
3	0201-001059	CIS	ADHESIVE-SIL	#9590,WHT,-,CARTRIGE	SNA
3	6003-001023	SH/COV+SH/BTM	SCREW-TAPTITE	RWH,+B,M3,L10,ZPC(YEL),SWRCH1	SNA
3	BH96-00281A	CIS	ASSY MISC P-SHIELD COVER	LE17KS,SECC T0.5,AL T0.25	SNA
4	BH63-00132A	CIS	SHIELD-COVER TOP	LE17KS,AL,T0.25	SNA
4	BH63-00133A	CIS	SHIELD-COVER REAR	LE17KS,SECC,T0.5	SNA
4	BH63-00145A	CIS	SHEET-ANODE	LE17KS,PP V2,T1.0,WHITE	SNA
2	BH91-00969U	-	ASSY CHASSIS-LC	LEO	SNA
2	BH92-01069A	-	ASSY P/MATERIAL	LE17JS	SNA
3	0203-001100	P/M	TAPE-OPP MASKING	OPP/W75/CLR,T0.05,W75,L800000,CLR	SNA
3	0203-001159	P/M	TAPE-FILAMENT	#8915,T0.15,W12,L55000,CLR	SNA
3	6902-000001	P/M	BAG AIR	LDPE,T0.2,L1800,W1000,TRP,,,LDPE ONLY	SNA
3	6902-000379	P/M	BAG AIR	HDPE,T0.2,L1800,W1000,TRP,,,PAPER	SNA
3	6902-000523	P/M	BAG PE	HDPE,T0.015,W900,L800,TRP,28 LANGUAGE,2-	SNA
3	6902-000576	P/M	BAG ROLL	LDPE,T0.05,W2400,L1000,TRP,-,-	SNA
3	BH69-00561A	P/M	CUSHION	LE17KS,EPS M50,DF	SNA
3	BH69-40380A	P/M	PACKING-PAD	DW-2,500X2200X200,-,CGK5527	SNA
2	BH92-01093A	-	ASSY LABEL	LEO-PJT(15/17/19)	SNA
3	BH68-00565D	LABEL	LABEL RATING-00	ALL,SS,PE,T0.05,90*65,BLK,POLYESTER,EDC	SNA
2	BH92-01161C	-	ASSY BOX	LEO	SNA
3	BH68-00530A	BOX	LABEL BOX-01	LABEL-BARCODE,CE+TC003,MOJO 90G,WHT	SNA
3	BH69-00574A	BOX	BOX-00,MONITOR	S/M795DF(LE17JS) W/W,CB-SW4,YEL,A-1,W452*D506*H435	SNA
2	BH92-01162A	-	ASSY ACCESSORY	LEO	SNA
3	BH96-00297A	UNIT/ACCESSORY	ASSY ACCESSORY	LEO	-
4	0203-000214	ACCESSORY	TAPE-OPP MASKING	OPP/W50/CLR,T0.05,W50,L400000,	SNA
4	6902-000110	ACCESSORY	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
4	BH39-10339H	ACCESSORY	CBF POWER CORD	DET,H05VV-F,250V/10,16A,BLK,25	SA
4	BH68-70418A	ACCESSORY	CARD-EU BLOC WARR-07	SyncMaster,BASIC,EU,MOJO,100G,	SNA
4	BH96-00296A	ACCESSORY	ASSY MANUAL P-IB+QSG	795DF,SyncMaster,W/W,27Lang,BH59-362A+BH68-376J	-
1	LC-LE17JSBB/EDC	-	2	LG,HIGH-CON	-
5	BH59-00362A	I/B	S/W DRIVER-00,IB	793S,795DF,W/W,SYNCMaster,27LANG	SNA
5	BH68-00376J	QUICK	MANUAL-01	AN_QUICK SETUP GUIDE,SYNCMaster,E/F/S/G/P/L.14LANGS,W/W,MOJO100G,298,420	SNA

7-5-1 LE15V* Mechanically Different Part List

DESCRIPTION	Code No	SPEC	Q'TY	NEW/Common	REMARK
1. ASS'Y/COVER-FRONT	BH96-00270A	ABS VO IV16	1	NEW	LE15VS
1-1. COVER FRONT(15 only)	BH63-00122A		1		
1-2. KNOB FUNCTION	BH64-00151A	ABS HB IV16	1	NEW	ALL(Sync.Sam) Common(15.17.19)
1-3. FUNCTION PCB	BH96-00287A	LEO	1		
1-4. LENS LED	BH67-00045A	ACRYL CLEAR	1	NEW	Syncmaster(15.17.19)
1-5. SCREW	6003-000259	BH,+,B,M3,L8,ZPC(YEL)	2		
1-6. SUPPER CDT	BH72-00298A	ABS HB IV16	2		
2. COVER REAR(15 only)	BH63-00123A	ABS VO IV16	1	NEW	
3. ASS'Y/STAND	BH96-00272A	ABS HB IV16	1		Sync.SAM15.17 Common
1-1. STAND TOP	BH61-00050A	ABS HB IV16	1	NEW	
1-2. STAND BASE	BH61-00049A	ABS HB IV16	1		
1-3. RUBBER FOOT	BH61-40002A	NEOPRENE HB BGE	3	AQ Common	
1-4. PE BAG	6902-000109	HDPE T0.015 L430 W350 TRP 28 2PE MARK	1		
1-5. MANUAL STAND	BH68-70306A	ART PAPER150(S)	1		
1-6. LABEL STICKER	BH68-20366A	ART PAPER100(S)	1		
1-7. FELT	BH63-30103A	NITTO NO.5000	3		
4. SHIELD VIDEO	BH63-00131A	SPTC T0.2	1	NEW	ALL(Sync.Sam) Common(15.17.19)
5. SHIELD BOTTOM	BH63-00134A	SECC T1.0	1	NEW	ALL(Sync.Sam) Common(15.17.19)
6. SHIELD IC	BH63-00124A	SPTC T0.2	1	NEW	ALL(Sync.Sam) Common(15.17.19)
7. CUSHION	BH69-00560A	EPS M50, WHITE, C=0.02	1	NEW	LE15VS
8. BOX	BH69-00571A	S/M591S(LE15VS) W/W,CB-SW4,YEL,A-1,W427*D452*H352	1		
9. HEAT SINK					
POWER H/SINK	BH62-00004A			AQ Common	ALL(Sync.Sam) Common(15.17.19)
H OUT H/SINK	BH62-00015A				LE15VS.LE17L*/K*/J*
	BH62-00038A				LE17IS.LE19I*
STEP UP H/SINK	BH62-30024B				LE15VS.LE17IS.LE19I*
	BH62-00016A				LE17L*/K*/J*
V OUT H/SINK	BH62-00003B				ALL(Sync.Sam) Common(15.17.19)
CRT Driver H/SINK	BH62-00053A			NEW	(Prearrange Develop)
10. SCREW	6003-000009	BH,+,B,M4,L16,ZPC(YEL),SWRCH18	2		FRONT COVER + REAR COVER
	6003-000010	BWH,+,B,M3,L10,ZPC(YEL),SWRCH1	6		SHIELD BOTTOM + MAIN PCB
	6003-000133	BH,+,S,M4,L8,ZPC(YEL),SWRCH18A,-	1		SHIELD BOTTOM + AC SOCKET
	6006-001119	WC,BH,+,M5,L25,ZPC(YEL),SWRCH18A	4		FRONT COVER + CRT
	6003-000010	BWH,+,B,M3,L10,ZPC(YEL),SWRCH1	1		VIDEO PCB + VIDEO SHIELD
	6003-000122	BH,+,S,M4,L8,ZPC(YEL),SWRCH18A,-	1		FBT+H/SINK

7-5-2 LE17LS/LE17LT/LE17KT/LE17JT Mechanically Different Part List

DESCRIPTION	Code No	SPEC	Q'TY	NEW/Common	REMARK
1. ASS'Y/COVER-FRONT	BH96-00274A	ABS HB IV16	1	NEW	LE17JS
1. ASS'Y/COVER-FRONT	BH96-00274B	ABS HB IV16	1	NEW	LE17KS
1. ASS'Y/COVER-FRONT	BH96-00274C	ABS HB IV16	1	NEW	LE17IS
1-1. COVER FRONT	BH63-00126A		1		
1-2. KNOB FUNCTION	BH64-00151A	ABS HB IV16	1	NEW	ALL(Sync.Sam) Common(15.17.19)
1-3. LENS LED	BH67-00045A	ACRYL CLEAR	1	NEW	Syncmaster(15.17.19)
	BH67-00046A				Samtron(15.17.19)
1-5. CAP BOSS	BH72-60491B	CGK5517,TPE,80,GRAY,CDT SETTING	2	AQ Common	
1-6. SCREW	6003-001023	BH,+,B,M3,L10,ZPC(YEL)	2		
1-7. SCREW	6006-001119	5*25			
2. COVER REAR	BH63-00130A	ABS HB IV16	1	NEW	Change core (SAMSUNG)
3. ASS'Y/STAND	BH96-00272A	ABS HB IV16	1		Sync.SAM15.17 Common
1-1. STAND TOP	BH61-00050A	ABS HB IV16	1	NEW	
1-2. STAND BASE	BH61-00049A	ABS HB IV16	1		
1-3. RUBBER FOOT	BH61-40002A	NEOPRENE HB BGE	3	AQCommon	
1-4. PE BAG	6902-000109	HDPE T0.015 L430 W350 TRP 28 2PE MARK	1		
1-5. MANUAL STAND	BH68-70306A	ART PAPER150(S)	1		
1-6. LABEL STICKER	BH68-20366A	ART PAPER100(S)	1		
1-7. FELT	BH63-30103A	NITTO NO.5000	3		
4. ASS'Y SHIELD COVER	BH96-00281A		1		
1-1. SHIELD-COVER REAR	BH63-00133A	SECC T0.5	1	NEW	
1-2. SHIELD COVER TOP	BH63-00132A	AL T0.25	1		
1-3. ANODE CAP	BH63-00145A	PP V2 NTL T1.0	1		ALL(Sync.Sam) Common(17.19)
5. SHIELD VIDEO	BH63-00131A	SPTT T0.2	1	NEW	ALL(Sync.Sam) Common(15.17.19)
6. SHIELD BOTTOM	BH63-00134A	SECC T1.0	1	NEW	ALL(Sync.Sam) Common(15.17.19)
7. SHIELD IC	BH63-00124A	SPTT T0.2	1	NEW	ALL(Sync.Sam) Common(15.17.19)
8. COVER PCB R	BH63-00143A	ABS+PC 5V IV16	1	NEW	ALL(Sync.Sam) Common(17.19)
9. COVER PCB L	BH63-00144A	ABS+PC 5V IV16	1	NEW	ALL(Sync.Sam) Common(17.19)
10. CUSHION	BH69-00561A	EPS M50,WHITE,C=0.02	1	NEW	LE17KS.LE17JS.LE17IS
11. HEAT SINK					
POWER H/SINK	BH62-00004A		1	AQ Common	ALL(Sync.Sam) Common(15.17.19)
H OUT H/SINK	BH62-00015A		1		LE15VS.LE17L*/K*/J*
	BH62-00038A		1		LE17IS.LE19I*
STEP UP H/SINK	BH62-30024B		1		LE15VS.LE17IS.LE19I*
	BH62-00016A		1		LE17L*/K*/J*
V OUT H/SINK	BH62-00003B		1		ALL(Sync.Sam) Common(15.17.19)
CRT Driver H/SINK	BH62-00053A		1	NEW	
FBT	BH62-00055A				
12. SCREW	6003-000009	BH,+,B,M4,L16,ZPC(YEL),SWRCH18	2		FRONT COVER + REAR COVER
	6003-000010	BWH,+,B,M3,L10,ZPC(YEL),SWRCH1	6		SHIELD BOTTOM + MAIN PCB
	6003-000010	BWH,+,B,M3,L10,ZPC(YEL),SWRCH1	2		SHIELD BOTTOM + SHIELD COVER
	6006-001103	SPRING+W,BWH,+,M3,L28(3),YEL,SWRCH18A+SUS+RUB	1		SHIELD BOTTOM + MAIN PCB
	6003-000133	BH,+,S,M4,L8,ZPC(YEL),SWRCH18A,-	1		SHIELD BOTTOM + AC SOCKET
	6006-001119	WC,BH,+,M5,L25,ZPC(YEL),SWRCH18A	4		FRONT COVER + CRT
	6003-000010	BWH,+,B,M3,L10,ZPC(YEL),SWRCH1	1		VIDEO PCB + VIDEO SHIELD
SUPPORT-CLIP	BN61-01137A	IBM E74,NYLON 66,1.0,NTR	1		

7-5-3 LE17KS/LE17JS Mechanically Different Part List

DESCRIPTION	Code No	SPEC	Q'TY	NEW/Common	REMARK
1. ASS'Y/COVER-FRONT	BH96-00277A	ABS VO IV16	1		LE17LT
1-1. COVER FRONT	BH63-00129A		1		
1-2. KNOB FUNCTION	BH64-00151A	ABS HB IV16	1	NEW	ALL(Sync.Sam) (15.17.19)
1-4. LENS LED	BH67-00046A	ACRYL CLEAR	1	NEW	Samtron(15.17.19)
1-5. CAP BOSS	BH72-60491B	CGK5517,TPE,80,GRAY,CDT SETTING	2	AQ Common	
1-6. SCREW	6003-001023	RWH,+,B,M3,L10,ZPC(YEL)	2		
2. COVER REAR	BH63-00130D	ABS VO IV16	1	NEW	Change core(SAMTRON)
3. ASS'Y/STAND	BH96-00272A	ABS HB IV16	1		Sync.SAM15.17 Common
1-1. STAND TOP	BH61-00050A	ABS HB IV16	1	NEW	
1-2. STAND BASE	BH61-00049A	ABS HB IV16	1		
1-3. RUBBER FOOT	BH61-40002A	NEOPRENE HB BGE	3	AQ Common	
1-4. PE BAG	6902-000109	HDPE T0.015 L430 W350 TRP 28 2PE MARK	1		
1-5. MANUAL STAND	BH68-70306A	ART PAPER150(S)	1		
1-6. LABEL STICKER	BH68-20366A	ART PAPER100(S)	1		
1-7. FELT	BH63-30103A	NITTO NO.5000	3		
5. SHIELD VIDEO	BH63-00131A	SPTT T0.2	1	NEW	ALL(Sync.Sam) Common(15.17.19)
6. SHIELD BOTTOM	BH63-00134A	SECC T1.0	1	NEW	ALL(Sync.Sam) Common(15.17.19)
7. SHIELD IC	BH63-00124A	SPTT T0.2	1	NEW	ALL(Sync.Sam) Common(15.17.19)
8. CUSHION	BH69-00563A				LE17LS,LE17LT
9. HEAT SINK					
POWER H/SINK	BH62-00004A		1	AQ Common	ALL(Sync.Sam) Common(15.17.19)
H OUT H/SINK	BH62-00055A		1		LE17IS,LE19I*
STEP UP H/SINK	BH62-00016A		1		LE17L*/K*/J*
V OUT H/SINK	BH62-00003B		1		ALL(Sync.Sam) Common(15.17.19)
CRT Driver H/SINK	BH62-00054A		1	NEW	
10. SCREW	6003-000009	BH,+,B,M4,L16,ZPC(YEL),SWRCH18	2		FRONT COVER + REAR COVER
	6003-001023	RWH,+,B,M3,L10,ZPC(YEL)	6		SHIELD BOTTOM + MAIN PCB
	6003-000133	BH,+,S,M4,L8,ZPC(YEL),SWRCH18A,-	1		SHIELD BOTTOM + AC SOCKET
	6003-000122	BH,+,B,M4,L12,ZPC(YEL),SWRCH18A,-	1		FBT+H/S
	6006-001119	WC,BH,+,M5,L25,ZPC(YEL),SWRCH18A	4		FRONT COVER + CRT
	6003-001023	RWH,+,B,M3,L10,ZPC(YEL)	2		VIDEO SHIELD +H/SINK
SUPPORT-CLIP	BN61-01137A	IBM E74,NYLON 66,1.0,NTR	1		

Memo