

REPLACEMENT PARTS

BEFORE REPLACING PARTS, READ THE FOLLOWING:

Approved Substitute Stock Numbers - Before ordering stock numbers in the part list, look for an approved substitute stock number in the current Price Schedule. This will minimize your service time and avoid ordering parts you already have in stock.

PRODUCT SAFETY NOTE: Components marked with a critical safety symbol have special characteristics important to safety. Before replacing any of these components, carefully read the **PRODUCT SAFETY NOTICE** in the basic service data. Do not degrade the safety of the set through improper servicing. Although assemblies as a whole may not be marked with a critical safety symbol, replacement of assemblies with other assemblies not approved may result in a safety hazard.

Critical Safety Symbol





- Not Eligible For Warranty

Warranty Status of Assemblies and Parts - All assemblies and components shown in this part list are eligible for warranty exchange or replacement except those with a dot shown to the left of the Description. Assemblies and components with a dot to the left of the Description are NOT eligible for warranty exchange or replacement.

Warranty replacement of cabinet parts requires the approval of a Thomson Consumer Electronics Field Service Manager.

Warranty Status and Specifications of assemblies and components are subject to change without notice. Consult the TCE Parts Pricing Microfiche for the latest warranty status information.

@NOTE: When ordering components that are listed more than once in this part list, always adhere to the serial number application guidelines given in the description column. If a serial number application guideline is not given, always select the component with a value, rating, other specification or identification marking(s) that match those of the corresponding component in the instrument you are servicing.

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
<u>Common Circuit Parts</u>			
A/V IN JACKS			
BE10	260598	60455920	CONNECTOR, 4-PIN (S)
BE11	251369	2108531A	 SOCKET CONNECTOR FRONT AV
CABLE	251368	21091060	CABLE 4P (H,M)
CABLE	260588	2109106A	CABLE, CHASSIS - FRONT A/V CBA (S)
CIRCUIT	251333	21091380	 CIRCUIT FRONT AV BOARD
RE10	235851	10113540	RES CF 1/4W 0% 0R (H,M)
RE12	235851	10113540	RES CF 1/4W 0% 0R (H,M)
CHASSIS			
BA03	248839	80408595	CONNECTOR 3 PIN (G,F,D,B,C)
BA07	248799	20345310	JACK, HEADPHONE (K,J,D)
BD01	248788	21037120	CONNECTOR 2 PIN (K,D)
BD70	248788	21037120	CONNECTOR 2 PIN (K,D)
BE01	244946	25344530	SOCKET A/V IN 1 (D,C,B)
BE02	232321	80445660	CONNECTOR 4 PIN (S,H,M)
BE11	251369	2108531A	SOCKET CONNECTOR FRONT AV (H)
BL01	244851	20978450	CONNECTOR 4 PIN
BP01	256968	21148540	 CABLE, AC POWER: GREY (S)
BP01	248816	21024560	 CABLE, AC POWER (M)
BP02	248788	21037120	CONNECTOR 2 PIN (S,R,K,J,H,G,F,C,B,E,A,M)
BV03	248806	67186011	CONNECTOR 4 PIN
CA05	232251	13040160	CAP LYTC 47UF M 16V
CA06	248753	13039870	CAP LYTC 2200PF M 16V

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CA08	175820	10244360	CAP LYTC 220UF M 25V (S,R,J,H,G,F,C,B,E,A,M)
CA08	232768	80434340	CAP LYTC 470UF M 16V (K,D)
CA12	194673	10120960	CAP LYTC 1UF M 50V
CA14	194253	15002560	CAP LYTC 22UF M 16V
CA501	222008	15041170	CAPCC .1UF K X7R 25V
CA504	197609	20226180	CAPCC .015UF K X7R 50V (R)
CA504	197609	50882800	CAPCC 1500PF K X7R 50V (S,M)
CA504	211509	20226180	CAPCC .015UF K X7R 50V (K,J,H,G,F,D,C,B,E,A)
CA507	251314	14035670	CAPCC 100NF +80% -20% 25V (R,S,H,M)
CA507	219215	20230650	CAPCC .1UF Z Y5V 25V (K,J,G,F,D,C,B,E,A)
CA508	195689	11059340	CAPCC .01UF K X7R 50V (S,M)
CA508	212434	20229450	CAPCC .01UF K X7R 50V (R,K,J,H,G,D,F,C,B,E,A)
CA511	200469	20225890	CAPCC 1000PF J N750 50V (K,D)
CA511	243790	20228250	CAPCC 220PF K X7R 50V (R,J,H,G,F,C,B,E,A,M)
CA511	260599	80436100	CAPCC 220PF 10% 50V N150 (S)
CA515	227413	15041140	CAPCC .15UF Z Y5V 50V
CA518	200469	20225890	CAPCC 1000PF J N750 50V (K,J,E,A)
CA519	200469	20225890	CAPCC 1000PF J N750 50V (K,J,E,A)
CA521	221512	20227170	CAPCC 220PF J NPO 50V (R,J,H,G,F,C,B,E,A)
CA521	200469	20225890	CAPCC 1000PF J N750 50V (K,D)

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CA521	205551	30938730	CCC FLT 220P J NPO 50V (M)	CH501	197600	11059320	CAPCC 1000PF K X7R 50V (K,J,G,F,D,C,B,E,A,S,M)
CA521	225541	30938730	CCC FLT 220P J NPO 50V (S)	CH501	212288	20231250	CAPCC 1000PF K X7R 50V (H,R)
CABLE	251370	2103150A	CABLE 6P FLAT WITH CONNECTORS (H)	CH502	200535	40438660	CAPCC 3.3PF C NPO 50V (K,J,G,F,D,C,B,E,A,S,M)
CABLE	251355	21031440	CABLE 5WAY L 300MM (R,H)	CH502	251316	20228890	CAPCC 3.3PF +/- .25PFP 50V NPO (H,R)
CABLE	251368	21091060	CABLE 4P (H,M)	CH503	245039	20947590	CAPCC .47UF K X7R 16V
CABLE	251354	25433960	CABLE, 6-WAY 420MM (R)	CH506	195689	11059340	CAPCC .01UF K X7R 50V (K,J,G,F,D,C,B,E,A,S,M)
CD01	247364	21021200	△ CAP LYTC .0015UF M 35V (K,D)	CH506	212434	20229450	CAPCC .01UF K X7R 50V (H,R)
CD09	247365	10077660	CAP POLY .056UF J 250V (K,D)	CH509	248754	11058770	CAPCC 220PF J N220 50V
CD12	240935	11055530	CAPCD 1500PF K Y5P 50V (K,D)	CH510	248754	11058770	CAPCC 220PF J N220 50V (K,J,G,F,D,C,B,E,A)
CD572	232611	20230610	CAPCC .01UF K X7R 25V (K,D)	CH510	214741	20227150	CAPCC 56PF J NPO 50V (H,R)
CD61	248808	20833260	CAPCD 2200PF K R 1KV (K,D)	CH510	214741	80436520	CAPCC 56PF J NPO 50V (S,M)
CD70	225628	20298330	CAPCD .01UF M Y5U 250V (K,D)	CH511	232747	20787740	CAPCC .01UF K X7R 50V (K,J,G,F,D,C,B,E,A,S,M)
CD71	248890	21068380	CAP LYTC 10UF M 250VNP (K,D)	CH511	232611	20230610	CAPCC .01UF K X7R 25V (H,R)
CD82	230972	14035840	CAPCD 330PF M Y5U 1KV (K,D)	CH512	197601	20873660	CAPCC .022UF K X7R 50V (H,R)
CD88	198570	14008530	CAPCD 1000PF K Y5U 1KV (K,D)	CH512	197601	30939240	CAPCC .022UF K X7R 50V (K,J,G,F,D,C,B,E,A,S,M)
CE502	221512	20227170	CAPCC 220PF J NPO 50V (R,K,J,H,G,F,D,C,B,E,A)	CH515	205227	20227180	CAPCC 330PF J NPO 50V (H,R)
CE502	205551	30938730	CCC FLT 220P J NPO 50V (M)	CH515	205227	20468970	CAPCC 330PF J NPO 50V (K,J,G,F,D,C,B,E,A,S,M)
CE502	206301	70434250	RES CMF 1/10W 5% 15K (S)	CI02	256799	13071680	CAP POLY .47UF J 63V (S,R,M)
CF01	220632	20467040	CAPACITOR (K,J,H,G,F,D,C,B,E,A,M)	CI02	222519	13071680	CAP POLY .47UF J 63V (K,J,H,G,F,D,C,B,E,A)
CF01	200141	20467040	CAP POLY .1UF K 63V (S,R)	CI03	233441	13070470	CAP LYTC 4.7UF M 16VC
CF02	190518	15001360	CAP POLY .033UF K 63V (S,R)	CI04	185862	13039570	CAP LYTC 1000UF M 16V (H,R)
CF02	198556	20467030	CAP POLY .068UF K 63V (K,J,H,G,F,D,C,B,E,A,M)	CI04	230957	13039530	CAP LYTC 1000UF M 16V (K,J,G,F,D,C,B,E,A,S,M)
CF05	232348	10122860	CAP LYTC 1000UF M 25V (S,K,J,G,F,D,C,B,E,A,M)	CI07	189983	13074220	CAP LYTC .47UF M 50V
CF05	230958	13039590	CAP LYTC 1000UF M 35V (H)	CI24	230978	15002000	CAP LYTC 100UF M 16V
CF05	246593	13039590	CAT LYTC 1000UF 35V (R)	CI25	230978	15002000	CAP LYTC 100UF M 16V (K,D)
CF07	152239	13074790	CAP LYTC 3.3UF M 50V	CI25	232768	80434340	CAP LYTC 470UF M 16V
CF09	152239	13074790	CAP LYTC 3.3UF M 50V	CI501	197600	11059320	CAPCC 1000PF K X7R 50V (K,J,G,F,D,C,B,E,A,S,M)
CF11	193043	13070520	CAP LYTC 47UF M 25V	CI501	212288	20231250	CAPCC 1000PF K X7R 50V (H,R)
CF15	178836	15002930	CAP LYTC 470UF M 25V	CI505	232747	20787740	CAPCC .01UF K X7R 50V (K,J,G,F,D,C,B,E,A,S,M)
CF17	232346	13070890	CAP LYTC 100UF M 35V	CI505	232611	20230610	CAPCC .01UF K X7R 25V (H,R)
CF503	206215	11058940	CAPCC 100PF J N750 50V (S,M)	CI506	232616	14006170	CAPCC 2200PF J NPO 50V (K,J,G,F,D,C,B,E,A,S,M)
CF503	200548	20265960	CAPCC 100PF J N750 50V (K,J,G,F,D,C,B,E,A)	CI506	243790	20226980	CAPCC 220PF K X7R 50V (H,R)
CF503	219208	20227710	CAPCC 100PF J NPO 50V (H,R)	CI508	197601	20873660	CAPCC .022UF K X7R 50V (H,R)
CF511	212434	20229450	CAPCC .01UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)	CI508	197601	30939240	CAPCC .022UF K X7R 50V (K,J,G,F,D,C,B,E,A,S,M)
CF511	195689	11059340	CAPCC .01UF K X7R 50V (S,M)	CI517	232611	20230610	CAPCC .01UF K X7R 25V (H,R)
CF513	207857	30939280	CAPCC .047UF Z Y5V 50V (S,M)	CI517	232747	20787740	CAPCC .01UF K X7R 50V (K,J,G,F,D,C,B,E,A,S,M)
CF513	200487	20228300	CAPCC .047UF Z Y5V 50V (K,J,H,G,F,D,C,B,E,A,R)	CI521	210689	40435180	CAPCC 47PF J NPO 50V (K,J,G,F,D,C,B,E,A,S,M)
CH07	230973	13074920	CAP LYTC 4.7UF M 50V	CI521	216021	20226560	CAPCC 47PF J NPO 50V (H,R)
CH14	231605	13073550	CAP LYTC 470UF M 10V				

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CI522	216021	20226560	CAPCC 47PF J NPO 50V (H,R)	CL06	253161	13057680	CAP POLY .047UF J 250V (H,F,E,D,G,B,C,A,S,R,M)
CI522	210689	40435180	CAPCC 47PF J NPO 50V (K,J,G,F,D,C,B,E,A,S,M)	CL09	232364	13040240	CAP LYTC 47UF M 35V
CI523	232747	20787740	CAPCC .01UF K X7R 50V (K,J,G,F,D,C,B,E,A,S,M)	CL10	244853	14006050	CAPCD 470PF K Y5R 3KV (H,H,F,F,E,E,D,D,G,G,B,B,C,C,A ,A,R,S,M,M)
CI523	232611	20230610	CAPCC .01UF K X7R 25V (H,R)	CL10	250513	20207210	CAPCD 560PF 10% 2KV (H,G,F,E,D,B,C,A,M)
CI525	219200	20225180	CAPCC 18PF J NPO 50V (H,R)	CL10	248752	20248410	CAPCD 680PF K Y5P 3KV (K,J,H,G,F,E,D,B,C,A,M)
CI525	232619	30938880	CAPCC 18PF J N470 50V (K,J,G,F,D,C,B,E,A,S,M)	CL12	200141	20467040	CAP POLY .1UF K 63V (R,S)
CI526	205227	20227180	CAPCC 330PF J NPO 50V(USED WITH CTF5800 TUNER) (M,H)	CL12	220632	20467040	CAPACITOR (K,J,H,G,F,D,C,B,E,A,M)
CI526	205227	20468970	CAPCC 330PF J NPO 50V(USED WITH CTF5800 TUNER) (K,J,G,F,D,C,B,E,A,S)	CL13	223809	13039430	CAP LYTC 10UF M 250V
CI526	N/S/P	00000000	NOT PRESENT WHEN CTT5050 TUNER IS USED (A,B,C,D,E,F,G,H,J,K,M)	CL20	223809	13039430	CAP LYTC 10UF M 250V
CI531	205230	20469340	CAPCC 4700PF K X7R 50V (K,J,G,F,D,C,B,E,A,S,M)	CL45	DISCON_ST K	14030320	CAPCD 330PF K Y5P 1KV (S,R)
CI531	218720	20226210	CAPCC 4700PF K X7R 50V (H,R)	CL45	235815	14030320	CAPCD 330PF K Y5P 1KV (K,J,H,G,F,D,C,B,E,A,M)
CK01	193043	15003100	CAP LYTC 47UF M 50V	CL47	178815	80434620	CAPCD 39PF J NPO 50V (H,S,R,M)
CK501	200548	20265960	CAPCC 100PF J N750 50V (K,J,G,F,D,C,B,E,A)	CL47	244854	14033680	CAPCD 39PF J N750 50V (K,J,G,F,D,C,B,E,A)
CK501	206215	11058940	CAPCC 100PF J N750 50V (S,M)	CL48	232364	13040240	CAP LYTC 47UF M 35V
CK501	219208	20227710	CAPCC 100PF J NPO 50V (H,R)	CL501	195689	11059340	CAPCC .01UF K X7R 50V (S,M)
CK502	221512	20227170	CAPCC 220PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)	CL501	212434	20229450	CAPCC .01UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)
CK502	225541	30938730	CCC FLT 220P J NPO 50V (S)	CL502	232616	14006170	CAPCC 2200PF J NPO 50V
CK502	205551	30938730	CCC FLT 220P J NPO 50V (M)	CL503	195689	11059340	CAPCC .01UF K X7R 50V (S,M)
CL04	228280	20849480	CAP PROP .007UF 3.5% 1.6KV (S,R)	CL503	212434	20229450	CAPCC .01UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)
CL04	257212	20760110	CAP PROP .0078UF 3.5% 1.6KV (R,S)	CL60	244855	20512960	CAP POLY .022UF K 100V (K,J,G,F,D,C,B,E,A,S,M)
CL04	232534	11007716	CAP POLY 6200PF E 1.6KV (R,S)	CL60	232365	70427760	CAP POLY .022UF K 100V (H,R)
CL04	198562	20972000	CAP POLY 6600PF HP 1.6KV (A,D,D,G,G,H,H,G,E,E,E,D,F, F,F,C,C,C,B,B,A,A,B,M,M,M)	CL61	233441	13070470	CAP LYTC 4.7UF M 16VC (S,R)
CL04	250512	21087890	CAP PROP .0092UF 3.5% 1.6KV (H,E,F,C,A,B,M)	CL61	194253	15002560	⚠ CAP LYTC 22UF M 16V (K,J,H,G,F,D,C,B,E,A,M)
CL04	240846	20597810	⚠ CAP POLY .006UF HP 1.6KV (K,J)	CLIP	244842	10260630	CLIP, FUSEHOLDER (R,R,S,M)
CL05	198567	20954380	CAP POLY .36UF J 250V (K,J,H,F,E,D,G,C,A,B,M)	CP01	220625	20955480	CAP POLY .1UF M 250V (S,R,H,M)
CL05	232358	20053100	CAP POLY .39UF J 250V (H,F,E,D,G,C,A,B,R,S,M)	CP01	256793	10684780	⚠ CAP PROP .1UF +20% -20% (S)
CL05	235469	20775350	CAPACITOR (H,H,E,E,D,D,G,G,F,F,C,C,A,A,B ,B,R,S,M,M)	CP01	220625	20157420	⚠ CAP POLY .1UF M 250V (K,J,G,F,D,C,B,E,A)
CL06	244852	15326100	CAP POLY .039UF J 250V (S,R)	CP02	220625	20157420	⚠ CAP POLY .1UF M 250V (D)
CL06	249270	90568450	CAP POLY .033UF J 250V (H,H,F,F,E,E,D,D,G,G,B,B,C,C,A ,A,M,M)	CP04	232366	14001660	CAPCD .01UF FS Y5U 1KV
CL06	244852	11054600	CAP POLY .039UF J 250V (K,J,H,F,E,D,G,B,C,A,M)	CP05	198565	20338740	CAPCD 1500PF K Y5P 1KV
				CP06	198565	20338740	CAPCD 1500PF K Y5P 1KV
				CP08	248748	21065550	⚠ CAP LYTC 220UF M 200V (K,J,H,G,D,F,C,B,E,A,M)
				CP08	182286	20552180	⚠ CAP LYTC 330UF M 200V (S,R,M)
				CP09	248749	21065640	CAP POLY 2200PF J 630V
				CP09	244827	10345050	CAP POLY 2200PF K 630V (S,M)
				CP15	248747	21079000	⚠ CAPCD 2200PF M Y5V 125VAC (J,G,F,D,C,B,M)
				CP15	244828	10442780	⚠ CAPCD 2200PF M Y5U 400V (R,S,K,J,H,D,E,A,M)

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CP16	251353	10442650	⚠ CAP CD 1NF 20% 400.0 V Y5U (R)	CP597	214731	80436850	CAPCC .015UF K X7R 50V (S,G,F,C,B,M)
CP24	193643	13074930	CAP LYTC 22UF M 50V	CP61	232251	13040160	CAP LYTC 47UF M 16V
CP25	193643	13074930	CAP LYTC 22UF M 50V	CP63	230977	15002760	CAP LYTC 2.2UF M 50V
CP26	198571	14033600	CAPCD 2200PF K Y5R 50V	CP65	232251	13040160	CAP LYTC 47UF M 16V
CP38	251318	50880580	CAPCD 180PF 5% 50.0V N150 (R,S,H,M)	CP67	232251	13040160	CAP LYTC 47UF M 16V
CP38	251576	11079100	CAP CC 180PF 5% 50V N470 (S,K,J,G,F,D,C,B,E,A,M)	CP80	260601	10509060	CAP LYTC 100UF 160V 85C (S)
CP40	194557	13082060	CAP LYTC 10UF M 50V	CP80	236052	13039340	CAP LYTC 100UF FS 250V (R,J,K,H,G,F,D,C,B,E,A,M)
CP522	235812	30939170	CAPCC 470PF K N750 50V (S,G,F,C,B,M)	CP88	248750	20555220	CAPCD 1500PF K R 1KV
CP522	DISCON_ST K	20229420	CAPCC 470PF K X7R 50V (R)	CP90	248753	13039870	CAP LYTC 2200PF M 16V (K,D)
CP522	211541	20229420	CAPCC 470PF K X7R 50V (K,J,H,D,E,A)	CP90	230957	13039530	CAP LYTC 1000UF M 16V (R,S,J,H,G,F,C,B,E,A,M)
CP523	232616	14006170	CAPCC 2200PF J NPO 50V (S)	CP91	248751	20833060	⚠ CAPCD 2200PF K R 250V
CP523	223775	20230030	CAPCC 330PF K X7R 50V (K,J,H,H,H,G,G,G,F,F,F,E,E,E,D,D,C,C,C,D,B,B,A,A,A,M,M,M,M)	CP93	194557	13082060	CAP LYTC 10UF M 50V
CP523	243790	20226980	CAPCC 220PF K X7R 50V (R,H,G,F,E,C,D,B,A,M)	CR01	232251	13040160	CAP LYTC 47UF M 16V
CP533	214742	20229440	CAPCC 3300PF K X7R 50V (R,K,J,H,D,E,A)	CR08	193579	15002470	CAP LYTC 220UF M 10V
CP533	214742	60441440	CAPCC 3300PF K X7R 50V (S,G,F,C,B,M)	CR15	194673	10120960	CAP LYTC 1UF M 50V
CP534	197609	50882800	CAPCC 1500PF K X7R 50V (S,G,F,C,B,M)	CR16	189981	15002130	CAP LYTC 10UF M 16V
CP534	DISCON_ST K	20226180	CAPCC .015UF K X7R 50V (R)	CR501	221512	20227170	CAPCC 220PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)
CP534	211509	20226180	CAPCC .015UF K X7R 50V (K,J,H,D,E,A)	CR501	205551	30938730	CCC FLT 220P J NPO 50V (M)
CP537	DISCON_ST K	20226180	CAPCC .015UF K X7R 50V (R)	CR501	225541	30938730	CCC FLT 220P J NPO 50V (S)
CP537	197609	50882800	CAPCC 1500PF K X7R 50V (S,G,F,C,B,M)	CR502	232616	14006170	CAPCC 2200PF J NPO 50V (S,M)
CP537	211509	20226180	CAPCC .015UF K X7R 50V (K,J,H,D,E,A)	CR502	243790	20226980	CAPCC 220PF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)
CP539	211039	80436530	CAPCC 180PF J NPO 50V (R,S,H,M)	CR504	206232	20230080	CAPCC .022UF Z Y5V 50V (K,J,H,G,F,D,C,B,E,A,R)
CP550	DISCON_ST K	20229420	CAPCC 470PF K X7R 50V (R)	CR504	206232	11059400	CAPCC .022UF Z Y5V 50V (S,M)
CP550	235812	30939170	CAPCC 470PF K N750 50V (S,G,F,C,B,M)	CR505	216021	20226560	CAPCC 47PF J NPO 50V (H,R)
CP550	211541	20229420	CAPCC 470PF K X7R 50V (K,J,H,D,E,A)	CR505	210689	40435180	CAPCC 47PF J NPO 50V (S,M)
CP567	232747	20787740	CAPCC .01UF K X7R 50V (S,G,F,C,B,M)	CR505	212291	20228330	CAPCC 22PF J NPO 50V (K,J,G,F,D,C,B,E,A)
CP567	232611	20230610	CAPCC .01UF K X7R 25V (R,K,J,H,D,E,A)	CR506	214741	20227150	CAPCC 56PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)
CP568	222008	15041170	CAPCC .1UF K X7R 25V	CR506	214741	80436520	CAPCC 56PF J NPO 50V (S,M)
CP592	248757	21031050	CAPCC .22UF K X7R 50V	CR507	214741	80436520	CAPCC 56PF J NPO 50V (S,M)
CP595	232611	20230610	CAPCC .01UF K X7R 25V (R,K,J,H,D,E,A)	CR507	214741	20227150	CAPCC 56PF J NPO 50V (K,J,H,G,F,D,C,B,A,E,R)
CP595	232747	20787740	CAPCC .01UF K X7R 50V (S,G,F,C,B,M)	CR508	219215	20230650	CAPCC .1UF Z Y5V 25V (K,J,G,F,D,C,B,A,E)
CP597	226432	20230630	CAPCC .015UF K X7R 50V (R,K,J,H,D,E,A)	CR508	251314	14035670	CAPCC 100NF +80% -20% 25V (H,R,S,M)
				CR509	226503	50882590	CAPACITOR (S,M)
				CR509	200469	20225890	CAPCC 1000PF J N750 50V (K,J,H,G,F,D,C,B,E,A,R)
				CR511	226503	50882590	CAPACITOR (S,M)
				CR511	200469	20225890	CAPCC 1000PF J N750 50V (K,J,H,G,F,D,C,B,E,A,R)
				CR512	226503	50882590	CAPACITOR (S,M)
				CR512	200469	20225890	CAPCC 1000PF J N750 50V (K,J,H,G,F,D,C,B,E,A,R)
				CR516	211541	20229420	CAPCC 470PF K X7R 50V (K,J,G,F,D,C,B,E,A)

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CR516	235812	30939170	CAPCC 470PF K N750 50V (H,S,R,M)	CR540	211541	20229420	CAPCC 470PF K X7R 50V (K,J,H,G,F,D,C,B,E,A)
CR518	206215	11058940	CAPCC 100PF J N750 50V (S,M)	CR540	235812	30939170	CAPCC 470PF K N750 50V (M,S)
CR518	200548	20265960	CAPCC 100PF J N750 50V (K,J,G,F,D,C,B,E,A)	CR541	235812	30939170	CAPCC 470PF K N750 50V (M,S)
CR518	219208	20227710	CAPCC 100PF J NPO 50V (H,R)	CR541	DISCON_ST K	20229420	CAPCC 470PF K X7R 50V (R)
CR519	219208	20227710	CAPCC 100PF J NPO 50V (H,R)	CR541	211541	20229420	CAPCC 470PF K X7R 50V (K,J,H,G,F,D,C,B,E,A)
CR519	206215	11058940	CAPCC 100PF J N750 50V (S,M)	CR550	206232	11059400	CAPCC .022UF Z Y5V 50V (H,M,S,R)
CR519	200548	20265960	CAPCC 100PF J N750 50V (K,J,G,F,D,C,B,E,A)	CV02	189983	13074220	CAP LYTC .47UF M 50V
CR520	195689	11059340	CAPCC .01UF K X7R 50V (S,M)	CV12	247160	10257660	CAP LYTC 2.2UF M 63V
CR520	212434	20229450	CAPCC .01UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)	CV13	230977	15002760	CAP LYTC 2.2UF M 50V
CR521	219215	20230650	CAPCC .1UF Z Y5V 25V (K,J,G,F,D,C,B,E,A)	CV15	189978	15002430	CAP LYTC 220UF M 16V
CR521	251314	14035670	CAPCC 100NF +80% -20% 25V (H,S,R,M)	CV18	189981	15002130	CAP LYTC 10UF M 16V
CR522	200548	20265960	CAPCC 100PF J N750 50V (K,J,G,F,D,C,B,E,A)	CV20	230977	15002760	CAP LYTC 2.2UF M 50V
CR522	206215	11058940	CAPCC 100PF J N750 50V (S,M)	CV21	194673	10120960	CAP LYTC 1UF M 50V
CR522	219208	20227710	CAPCC 100PF J NPO 50V (H,R)	CV22	194673	10120960	CAP LYTC 1UF M 50V
CR523	245039	20947590	CAPCC .47UF K X7R 16V	CV23	152239	13074790	CAP LYTC 3.3UF M 50V
CR524	235812	30939170	CAPCC 470PF K N750 50V (H,S,R,M)	CV23	194673	10120960	CAP LYTC 1UF M 50V (R,S)
CR524	211541	20229420	CAPCC 470PF K X7R 50V (K,J,G,F,D,C,B,E,A)	CV24	194673	10120960	CAP LYTC 1UF M 50V
CR525	197601	20873660	CAPCC .022UF K X7R 50V (H,R)	CV25	189981	15002130	CAP LYTC 10UF M 16V
CR525	206232	11059400	CAPCC .022UF Z Y5V 50V (S,M)	CV26	194673	10120960	CAP LYTC 1UF M 50V
CR525	206232	20230080	CAPCC .022UF Z Y5V 50V (K,J,G,F,D,C,B,E,A)	CV27	220632	20467040	CAPACITOR (K,J,H,G,F,D,C,M,B,E,A)
CR526	207876	60441430	CAPCC 560PF K X7R 50V (M)	CV27	200141	20467040	CAP POLY .1UF K 63V (S,R)
CR526	216306	60441430	CAPCC 560PF K X7R 50V (S)	CV28	230978	15002000	CAP LYTC 100UF M 16V (K,D)
CR526	212433	20229430	CAPCC 560PF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)	CV28	232768	80434340	CAP LYTC 470UF M 16V (K,D)
CR527	200548	20265960	CAPCC 100PF J N750 50V (K,J,G,F,D,C,B,E,A)	CV30	233441	13070470	CAP LYTC 4.7UF M 16VC
CR527	219208	20227710	CAPCC 100PF J NPO 50V (H,R)	CV32	189983	13074220	CAP LYTC .47UF M 50V
CR527	206215	11058940	CAPCC 100PF J N750 50V (S,M)	CV501	197601	30939240	CAPCC .022UF K X7R 50V (M,S)
CR528	214741	20227150	CAPCC 56PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)	CV501	197601	20873660	CAPCC .022UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)
CR528	214741	80436520	CAPCC 56PF J NPO 50V (S,M)	CV502	219231	20230140	CAPCC 180PF J NPO 50V (K,J)
CR529	214741	20227150	CAPCC 56PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)	CV502	200548	20265960	CAPCC 100PF J N750 50V (K,J,G,F,D,C,B,E,A)
CR529	214741	80436520	CAPCC 56PF J NPO 50V (S,M)	CV502	206215	11058940	CAPCC 100PF J N750 50V (M,S)
CR530	214741	80436520	CAPCC 56PF J NPO 50V (M,S)	CV502	219208	20227710	CAPCC 100PF J NPO 50V (H,R)
CR530	214741	20227150	CAPCC 56PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)	CV503	242262	20227680	CAPCC 12PF J NPO 50V (R)
CR531	232611	20230610	CAPCC .01UF K X7R 25V (K,J,H,G,F,D,C,B,E,A,R)	CV503	242262	80436490	CAPCC 12PF J NPO 50V (M,S)
CR531	232747	20787740	CAPCC .01UF K X7R 50V (M,S)	CV503	219205	20227680	CAPCC 12PF J NPO 50V (K,J,H,G,F,D,C,B,E,A)
CR540	DISCON_ST K	20229420	CAPCC 470PF K X7R 50V (R)	CV504	216021	20226560	CAPCC 47PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)
				CV504	210689	40435180	CAPCC 47PF J NPO 50V (M,S)
				CV505	197601	20873660	CAPCC .022UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)
				CV505	197601	30939240	CAPCC .022UF K X7R 50V (M,S)
				CV506	210689	40435180	CAPCC 47PF J NPO 50V (M,S)
				CV506	216021	20226560	CAPCC 47PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CV507	197601	30939240	CAPCC .022UF K X7R 50V (M,S)	DD03	232545	11073660	DIODE ZENER 8.2V .5W (K,D)
CV507	197601	20873660	CAPCC .022UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)	DD12	248809	21031930	DIODE (K,D)
CV508	210689	40435180	CAPCC 47PF J NPO 50V (M,S)	DD61	244834	10351230	DIODE (K,D)
CV508	216021	20226560	CAPCC 47PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)	DD68	220638	50890650	DIODE ZENER 6.8V .5W (K,D)
CV509	197601	30939240	CAPCC .022UF K X7R 50V (M,S)	DD73	230757	16007470	DIODE (K,D)
CV509	197601	20873660	CAPCC .022UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)	DD75	230757	16007470	DIODE (D,K)
CV510	216021	20226560	CAPCC 47PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)	DD80	244834	10351230	DIODE (K,D)
CV510	210689	40435180	CAPCC 47PF J NPO 50V (M,S)	DE01	198589	70436540	DIODE
CV511	195689	11059340	CAPCC .01UF K X7R 50V (M,S)	DE502	232709	16012480	DIODE (K,J,G,F,D,C,B,M,E,A,S)
CV511	212434	20229450	CAPCC .01UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)	DE502	254715	15580280	DIODE (M,S)
CV514	212434	20229450	CAPCC .01UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)	DE502	248798	21030100	DIODE
CV514	195689	11059340	CAPCC .01UF K X7R 50V (M,S)	DF01	244856	10455310	DIODE
CV515	260599	80436100	CAPCC 220PF 10% 50V N150 (S)	DF03	198589	70436540	DIODE
CV515	243790	20228250	CAPCC .22UF K X7R 50V (K,J,H,G,F,D,C,B,M,E,A,R)	DF05	198589	70436540	DIODE
CV516	206215	11058940	CAPCC 100PF J N750 50V (M,S)	DH01	215489	21121690	D-ZENER BZX55B33 (M,S)
CV516	200548	20265960	CAPCC 100PF J N750 50V (K,J,H,G,F,D,C,B,E,A,R)	DH01	215489	80442730	DIODE ZENER 33V .5W
CV517	206215	11058940	CAPCC 100PF J N750 50V (M,S)	DL01	198589	70436540	DIODE
CV517	200548	20265960	CAPCC 100PF J N750 50V (K,J,H,G,F,D,C,B,E,A,R)	DL04	248797	21031980	DIODE
CV519	214731	80436850	CAPCC .015UF K X7R 50V (M,S)	DL05	244856	10455310	DIODE
CV519	226432	20230630	CAPCC .015UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)	DL06	244856	10455310	DIODE
CV529	222008	15041170	CAPCC .1UF K X7R 25V	DL07	248797	21031980	DIODE
CV530	197601	30939240	CAPCC .022UF K X7R 50V (M,S)	DL08	198589	70436540	DIODE
CV530	197601	20873660	CAPCC .022UF K X7R 50V (K,J,H,G,F,D,C,B,E,A,R)	DL09	198589	70436540	DIODE
CV532	197609	50882800	CAPCC 1500PF K X7R 50V (S)	DL20	244870	10459090	DIODE
CV532	200148	20226330	CAPCC 4700PF M X7R 50V (K,J,H,G,D,F,C,B,E,A,R)	DL45	244870	10459090	DIODE
CV532	200485	14030290	CAPCC 4700PF M Y5P 50V (M)	DL548	248798	21030100	DIODE
CV533	219231	20230140	CAPCC 180PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)	DL548	254715	15580280	DIODE (M,S)
CV533	211039	80436530	CAPCC 180PF J NPO 50V (M,S)	DL548	232709	16012480	DIODE (K,J,G,F,D,C,M,B,E,A,S)
CV535	260599	80436100	CAPCC 220PF 10% 50V N150 (S)	DL560	232709	16012480	DIODE (K,J,G,F,D,C,M,B,E,A,S)
CV535	243790	20228250	CAPCC .22UF K X7R 50V (K,J,H,G,F,D,C,B,M,E,A,R)	DL560	254715	15580280	DIODE (M,S)
CV536	194911	50882360	CAPCC 33PF J NPO 50V (M,S)	DL560	248798	21030100	DIODE
CV536	194911	20226540	CAPCC 33PF J NPO 50V (K,J,H,G,F,D,C,B,E,A,R)	DL563	248798	21030100	DIODE (K,J,H,G,F,D,M,B,E,A,S,R)
CZ01	153925	20467110	CAP POLY .1UF K 100V	DL563	254715	15580280	DIODE (M,S)
CZ08	194673	10120960	CAP LYTC 1UF M 50V	DL563	232709	16012480	DIODE (K,J,G,F,D,M,B,E,A,S)
DA90	244834	10351230	DIODE (K,D)	DL563	227961	60447770	DIODE ZENER 3.9V .5W (C)
DD02	198597	16008160	DIODE (K,D)	DL62	227961	60447770	DIODE ZENER 3.9V .5W
				DL64	198589	70436540	DIODE
				DL65	220635	20475400	DIODE ZENER 4.7V .5W
				DL68	198589	70436540	DIODE
				DP01	251348	25365510	DIODE GP20M 1KV 2.0A (R,S)
				DP01	256839	21130230	DIODE (S)
				DP01	209919	60447780	DIODE (K,J,H,G,F,D,C,B,M,E,A)
				DP02	209919	60447780	DIODE (K,J,H,G,F,D,C,B,M,E,A)
				DP02	251348	25365510	DIODE GP20M 1KV 2.0A (S,R)
				DP02	256839	21130230	DIODE (S)
				DP03	251348	25365510	DIODE GP20M 1KV 2.0A (S,R)
				DP03	209919	60447780	DIODE (K,J,H,G,F,D,C,B,M,E,A)
				DP03	256839	21130230	DIODE (S)
				DP04	251348	25365510	DIODE GP20M 1KV 2.0A (R,S)
				DP04	256839	21130230	DIODE (S)
				DP04	209919	60447780	DIODE (K,J,H,G,F,D,C,B,M,E,A)
				DP23	232545	11073660	DIODE ZENER 8.2V .5W

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
DP25	244834	10351230	DIODE	DV509	232709	16012480	DIODE (K,J,G,F,D,C,M,B,E,A,S)
DP26	244834	10351230	DIODE	DV509	254715	15580280	DIODE (M,S)
DP27	244836	21121730	D-ZENER BZX55B24 24.0V 1/2W (M,S)	DZ01	244870	10459090	DIODE
DP27	244836	11073440	DIODE ZENER 24V .5W	DZ03	260589	21121740	DIDOE, ZENER 10V 1/2W (S)
DP30	232545	11073660	DIODE ZENER 8.2V .5W	DZ03	226456	90578020	⚠ DIODE ZENER 10W .5W
DP33	223694	80444020	DIODE ZENER 15V .5W	DZ05	198589	70436540	DIODE
DP37	198589	70436540	DIODE	FA01	248812	10529770	PROTECTOR IC (K,D)
DP40	244836	21121730	D-ZENER BZX55B24 24.0V 1/2W (M)	FD01	248810	21029750	⚠ PROTECTOR (K,D)
DP40	244836	11073440	DIODE ZENER 24V .5W (K,J,H,G,F,D,C,B,M,E,A)	FP01	198605	20828870	⚠ FUSE 2.5A 250V (K,J,H,G,F,D,C,M,B,E,A,R)
DP40	244835	20475330	DIODE ZENER 27V .5W (S,R)	FP01	198605	50366200	⚠ FUSE 2.5A 250V (S)
DP57	223783	20475410	DIODE ZENER 6.2V .5W	FP01A	244842	10260630	CLIP, FUSEHOLDER (H,B)
DP57	260590	21121750	DIODE, ZENER 6.2V 1/2W (S)	FP01A/B	244842	10260630	CLIP, FUSEHOLDER (K,J,G,F,D,C,E,A)
DP60	198597	16008160	DIODE	FP01B	244842	10260630	CLIP, FUSEHOLDER (H)
DP61	198602	21121710	DIODE ZENER BZX55C5V1 (M,S)	HA02	232317	11038995	CONNECTOR 2 PIN
DP61	198602	80444140	DIODE ZENER 5.1V .5W	IA01	244225	20797360	IC
DP62	198597	16008160	DIODE	IF01	244861	20902690	IC
DP63	198597	16008160	DIODE (J,H,G,F,C,B,M,E,A,R,S)	IK01	230986	21012940	IC REMOTE RCVR (G,D,C,B)
DP69	223083	30948670	DIODE ZENER 4.7V .5W	IK02	230986	21012940	IC REMOTE RCVR (K,J,E,A)
DP80	244834	10351230	DIODE	IK02	251320	21088850	IC-REMOTE TSOP1356KA1 RECEIVER (H,M,R,S)
DP87	198589	70436540	DIODE (K,D)	IP01	244839	20827900	⚠ IC OPTO-ISOLATOR (K,J,H,G,F,D,C,M,B,E,A,R)
DP87	NONSTK	10448530	WIREBARE 22 (H,M,S,R)	IP01	257786	10547560	⚠ IC, PHOTOCOUPLER (S)
DP88	NONSTK	10448530	WIREBARE 22 (H,M,S,R)	IP50	231525	15069010	IC REGULATOR
DP88	198589	70436540	DIODE (K,D)	IR01	248908	21074170	IC MICROCONTROLLER (G,F)
DP90	251868	16009040	DIODE BYW100-200 200V (C,H,F,D,B,M,G,A,E,S)	IR01	257199	21134960	IC-MICROCONT ST9294J5B1 TX808- (M,S)
DP90	244834	10351230	DIODE (K,J,F,G,D,C,C,C,F,B,D,D,B,B,F, G,G,M,M,M,H,E,E,A,A,A,E,H,H, R)	IR01	248803	21074160	IC MICROCONTROLLER (K,J,H,D,C,B,E,A,R)
DP91	244834	10351230	DIODE	IR02	248804	20967700	IC EEPROM
DP92	244834	10351230	DIODE (M,K,J,H,G,F,D,C,B,E,A,R)	IV01	245055	20885570	IC Y-C PROCESSOR
DP95	198589	70436540	DIODE	JA05	NONSTK	10448530	WIREBARE 22
DP96	198602	80444140	DIODE ZENER 5.1V .5W	JA07	NONSTK	10448530	WIREBARE 22
DP96	198602	21121710	DIODE ZENER BZX55C5V1 (M)	JA08	NONSTK	10448530	WIREBARE 22
DR501	254715	15580280	DIODE (M,S)	JA09	NONSTK	10448530	WIREBARE 22
DR501	248798	21030100	DIODE	JA14	NONSTK	10448530	WIREBARE 22 (J,H,G,F,C,M,B,E,A,S,R)
DR501	232709	16012480	DIODE (K,J,G,F,D,C,M,B,E,A,S)	JA501	205408	20283320	WIREBARE 22
DV01	242705	30948660	DIODE ZENER 3.3V .5W	JA501	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)
DV01	242705	21121760	D-ZENER BZX55B3V3 3.3V (M,S)	JA501	205408	80440510	RES CMF 1/10W 0% 0R (M,S)
DV03	198589	70436540	DIODE	JA503	219215	20230650	CAPCC .1UF Z Y5V 25V (K,J,G,F,D,C,B,E,A)
DV04	242705	21121760	D-ZENER BZX55B3V3 3.3V (M,S)	JA503	251314	14035670	CAPCC 100NF +80% -20% 25V (H,M,S,R)
DV04	242705	30948660	DIODE ZENER 3.3V .5W	JA506	205408	80440510	RES CMF 1/10W 0% 0R (M,S)
DV05	198589	70436540	DIODE	JA506	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)
DV11	220635	20475400	DIODE ZENER 4.7V .5W	JA507	205408	20283320	RES CMF 1/10W 0% 0R (K,J,G,H,F,D,C,B,E,A,R)
DV508	248798	21030100	DIODE	JA507	205408	80440510	RES CMF 1/10W 0% 0R (M,S)
DV508	254715	15580280	DIODE (M,S)	JA513	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)
DV508	232709	16012480	DIODE (K,J,G,F,D,C,M,B,E,A,S)	JA513	205408	80440510	RES CMF 1/10W 0% 0R (M,S)
DV509	248798	21030100	DIODE				

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
JA90	NONSTK	10448530	WIREBARE 22 (J,H,G,F,C,M,B,E,A,S,R)	JP18	NONSTK	10448530	WIREBARE 22
JD01	NONSTK	10448530	WIREBARE 22 (K,D)	JP19	NONSTK	10448530	WIREBARE 22
JD02	NONSTK	10448530	WIREBARE 22 (K,D)	JP21	NONSTK	10448530	WIREBARE 22
JD03	NONSTK	10448530	WIREBARE 22 (K,D)	JP22	NONSTK	10448530	WIREBARE 22
JD05	NONSTK	10448530	WIREBARE 22 (K,D)	JP23	NONSTK	10448530	WIREBARE 22
JD06	NONSTK	10448530	WIREBARE 22 (K,D)	JP24	NONSTK	10448530	WIREBARE 22
JD10	NONSTK	10448530	WIREBARE 22 (K,D)	JP25	NONSTK	10448530	WIREBARE 22
JE02	NONSTK	10448530	WIREBARE 22	JP503	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,D,E,A,R)
JE03	NONSTK	10448530	WIREBARE 22	JP503	205408	80440510	RES CMF 1/10W 0% 0R (G,F,C,M,B,S)
JE501	205408	20283320	RES CMF 1/10W 0% 0R (K,J,G,H,F,D,C,B,E,A,R)	JP551	205408	80440510	RES CMF 1/10W 0% 0R (G,F,C,M,B,S)
JE501	205408	80440510	RES CMF 1/10W 0% 0R (M,S)	JP551	205408	20283320	RES CMF 1/10W 0% 0R (J,H,E,A,R)
JF01	NONSTK	10448530	WIREBARE 22	JP80	NONSTK	10448530	WIREBARE 22
JF02	NONSTK	10448530	WIREBARE 22	JR02	NONSTK	10448530	WIREBARE 22
JF04	NONSTK	10448530	WIREBARE 22	JR03	NONSTK	10448530	WIREBARE 22
JF05	NONSTK	10448530	WIREBARE 22	JR05	NONSTK	10448530	WIREBARE 22
JF07	NONSTK	10448530	WIREBARE 22	JR06	NONSTK	10448530	WIREBARE 22
JF10	NONSTK	10448530	WIREBARE 22	JR07	NONSTK	10448530	WIREBARE 22
JF11	NONSTK	10448530	WIREBARE 22	JR08	NONSTK	10448530	WIREBARE 22
JF501	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)	JR09	NONSTK	10448530	WIREBARE 22
JF501	205408	80440510	RES CMF 1/10W 0% 0R (M,S)	JR10	NONSTK	10448530	WIREBARE 22
JH01	NONSTK	10448530	WIREBARE 22	JR11	235851	10113540	RES CF 1/4W 0% 0R (G,F,M)
JH02	NONSTK	10448530	WIREBARE 22	JR13	NONSTK	10448530	WIREBARE 22
JH502	205408	20283320	RES CMF 1/10W 0% 0R (H,R)	JR14	NONSTK	10448530	WIREBARE 22
JH502	205408	80440510	RES CMF 1/10W 0% 0R (K,J,G,F,D,C,M,B,E,A,S)	JR15	NONSTK	10448530	WIREBARE 22
JI01	NONSTK	10448530	WIREBARE 22	JR18	NONSTK	10448530	WIREBARE 22
JI02	NONSTK	10448530	WIREBARE 22	JR20	NONSTK	10448530	WIREBARE 22
JI03	NONSTK	10448530	WIREBARE 22	JR21	NONSTK	10448530	WIREBARE 22
JI04	NONSTK	10448530	WIREBARE 22	JR23	NONSTK	10448530	WIREBARE 22
JI05	NONSTK	10448530	WIREBARE 22	JR30	NONSTK	10448530	WIREBARE 22 (K,J,H,E,A,M,S,R)
JI06	NONSTK	10448530	WIREBARE 22	JR501	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)
JI08	NONSTK	10448530	WIREBARE 22	JR501	205408	80440510	RES CMF 1/10W 0% 0R (M,S)
JI09	NONSTK	10448530	WIREBARE 22	JR502	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)
JL01	NONSTK	10448530	WIREBARE 22	JR502	205408	80440510	RES CMF 1/10W 0% 0R (M,S)
JL02	NONSTK	10448530	WIREBARE 22	JR503	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)
JL07	NONSTK	10448530	WIREBARE 22	JR503	205408	80440510	RES CMF 1/10W 0% 0R (M,S)
JL08	NONSTK	10448530	WIREBARE 22	JR505	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)
JP01	NONSTK	10448530	WIREBARE 22	JR505	205408	80440510	RES CMF 1/10W 0% 0R (M,S)
JP02	NONSTK	10448530	WIREBARE 22	JR507	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)
JP03	235858	10258390	BEAD	JR507	205408	80440510	RES CMF 1/10W 0% 0R (M,S)
JP04	NONSTK	10448530	WIREBARE 22	JR521	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)
JP05	NONSTK	10448530	WIREBARE 22	JR521	205408	80440510	RES CMF 1/10W 0% 0R (M,S)
JP06	NONSTK	10448530	WIREBARE 22	JV01	NONSTK	10448530	WIREBARE 22
JP08	NONSTK	10448530	WIREBARE 22	JV02	NONSTK	10448530	WIREBARE 22
JP09	NONSTK	10448530	WIREBARE 22	JV03	NONSTK	10448530	WIREBARE 22
JP11	NONSTK	10448530	WIREBARE 22	JV04	NONSTK	10448530	WIREBARE 22
JP12	NONSTK	10448530	WIREBARE 22				
JP14	NONSTK	10448530	WIREBARE 22				
JP15	NONSTK	10448530	WIREBARE 22				
JP16	NONSTK	10448530	WIREBARE 22				
JP17	NONSTK	10448530	WIREBARE 22				

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
JV05	NONSTK	10448530	WIREBARE 22	LP02	228335	20322540	⚠ TRANSFORMER AC IN (K,J,M,M,M,H,H,H,G,G,G,F,F,F, D,D,D,E,E,E,C,C,C,B,B,B,A,A,A)
JV06	NONSTK	10448530	WIREBARE 22	LP02	250516	21087160	COIL, LINE FILTER (M,H,G,F,D,E,C,S,R,B,A)
JV07	NONSTK	10448530	WIREBARE 22	LP03	250515	21067530	TRANSFORMER (M,H,G,E,F,D,C,S,R,B,A)
JV08	NONSTK	10448530	WIREBARE 22	LP03	248776	21023380	⚠ TRANSFORMER SMT (K,J,M,M,M,H,H,H,G,G,G,F,E,E, E,F,F,D,D,D,C,C,C,B,B,B,A,A,A)
JV10	NONSTK	10448530	WIREBARE 22	LP07	248793	13055850	COIL 39UH
JV11	248858	15008450	RES CF 1/4W 5% 47R (S,R)	LP20	244840	10258380	BEAD FERRITE
JV11	NONSTK	10448530	WIREBARE 22 (K,J,H,G,F,D,C,B,E,A,M)	LP21	224167	47033300	BEAD (J,H,G,F,D,C,B,E,A,M,S,R)
JV12	NONSTK	10448530	WIREBARE 22	LP26	244840	10258380	BEAD FERRITE
JV13	NONSTK	10448530	WIREBARE 22	LP27	244840	10258380	BEAD FERRITE
JV15	NONSTK	10448530	WIREBARE 22	LP63	235858	10258390	BEAD
JV18	NONSTK	10448530	WIREBARE 22	LP81	244840	10258380	BEAD FERRITE
JV19	NONSTK	10448530	WIREBARE 22	LP90	NONSTK	10448530	WIREBARE 22 (M,R,S)
JV20	NONSTK	10448530	WIREBARE 22	LR01	214580	15039640	COIL 10UH
JV502	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)	LR02	214580	15039640	COIL 10UH
JV502	205408	80440510	RES CMF 1/10W 0% 0R (M,S)	LR03	232633	15040110	COIL 3.3UH
JV503	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)	LR04	232633	15040110	COIL 3.3UH
JV503	205408	80440510	RES CMF 1/10W 0% 0R (M,S)	LR05	235858	10258390	BEAD
JV505	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)	LR06	235858	10258390	BEAD
JV505	205408	80440510	RES CMF 1/10W 0% 0R (M,S)	LR07	235858	10258390	BEAD
LA01	244900	20801900	COIL 10UH (H,J,G,F,C,B,E,A,M,S,R)	LR08	244840	10258380	BEAD FERRITE
LD01	244840	10258380	BEAD FERRITE (K,D)	LV01	244900	20801900	COIL 10UH
LD04	248811	21029670	⚠ TRANSFORMER SMT (K,D)	LV02	197614	90574550	COIL 4.7UH
LD21	232427	47035600	BEAD (D)	LV08	248793	13055850	COIL 39UH
LD22	232427	47035600	BEAD (D,K)	NH01	246418	20739350	⚠ TUNER - CTT5050(REPLACE TUNER WITH ORIGINAL TYPE) (K,J,H,G,F,D,C,B,E,A)
LD61	244840	10258380	BEAD FERRITE (K,D)	NH01	251356	21070490	CIRCUIT TUNER 56D86G3 (R)
LH01	195713	11066650	COIL 47UH	NH01	248782	21027220	⚠ TUNER - CTF5800(REPLACE TUNER WITH ORIGINAL TYPE) (K,J,H,G,F,D,C,B,E,A,M,S)
LH02	235858	10258390	BEAD	QC02	232441	10557190	RESONATOR 503KHZ
LH03	235858	10258390	BEAD	QI01	245046	20909290	FILTER SAW 45.75MHZ
LI01	248755	13052910	COIL 1UH	QI02	219313	20750370	FILTER CERAMIC 4.5MHZ
LI02	248800	50890770	COIL 68UH	QI03	219314	20696180	FILTER TRAP 4.5MHZ
LI04	248801	21057650	COIL ADJUSTABLE	QR01	235882	10254430	FILTER QUARTZ 8MHZ
LI04	245045	20977670	COIL ADJUSTABLE (K,J,G,F,D,C,B,E,A)	QV01	245056	20780850	FILTER QUARTZ 3.579545MHZ
LI05	245047	20908900	COIL ADJUSTABLE	RA01	235851	10113540	RES CF 1/4W 0% 0R (K,H,J,E,A,M,R,S)
LI20	248802	20755240	COIL 22UH	RA02	235851	10113540	RES CF 1/4W 0% 0R (H,G,F,C,B,E,A,M,S,R)
LI21	206370	13055220	COIL 22UH	RA03	245064	15050270	RES CF 1/2W 5% 1R (H,J,G,F,C,B,E,A,M,R,S)
LI22	149167	50886760	COIL 68UH	RA03	248813	20474080	RES MFFP 2W 5% 2.7R (K,D)
LK01	235858	10258390	BEAD	RA08	220663	15007290	RES CF 1/4W 5% 22K
LL01	244857	20936440	TRANSFORMER DRIVER	RA501	212393	20224010	RES CMF 1/10W 5% 12K (K,J,H,G,F,D,C,B,E,A,R)
LL02	244858	11066780	COIL .33UH	RA501	200169	20471990	RES CMF 1/10W 5% 12K (M,S)
LL05	248780	21044450	⚠ TRANSFORMER IHVT (J,K)	RA505	212398	20224140	RES CMF 1/10W 5% 4.7K (K,J,H,G,F,D,C,B,E,A,R)
LL05	247260	2096566B	⚠ TRANSFORMER, IHVT (S)				
LL05	244859	2097364A	⚠ TRANSFORMER, IHVT (A,M)				
LL05	247260	2096566A	⚠ TRANSFORMER IHVT (R)				
LL05	244859	20973640	⚠ TRANSFORMER IHVT (H,G,F,D,C,B,E)				
LL09	232428	10557180	COIL 50UH				
LL10	230992	15039610	COIL 100UH				
LP01	235858	10258390	BEAD				

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
RA505	192097	30944310	RES CMF 1/10W 5% 4.7K (M,S)	RF501	212399	20224570	RES CMF 1/10W 5% 100R (K,J,H,G,F,D,C,B,E,A,R)
RA506	197471	11066500	RES CMF 1/10W 5% 68K (M,S)	RF503	197640	60444420	RES CMF 1/10W 5% 150K (M,S)
RA506	197471	20225010	RES CMF 1/10W 5% 68K (K,J,H,G,F,D,C,B,E,A,R)	RF503	197640	20224160	RES CMF 1/10W 5% 150K (K,J,H,G,F,D,C,B,E,A,R)
RA507	197636	70434230	RES CMF 1/10W 5% 1.2K (M,S)	RF506	192070	60444400	RES CMF 1/10W 5% 22K (M,S)
RA507	212384	20224810	RES CMF 1/10W 5% 1.2K (K,J,H,G,F,D,C,B,E,A,R)	RF506	212400	20223760	RES CMF 1/10W 5% 22K (K,J,H,G,F,D,C,B,E,A,R)
RA509	200504	70434170	RES CMF 1/10W 5% 12R (M,S)	RF509	192087	40438300	RES CMF 1/10W 5% 6.8K (M,S)
RA509	200504	20223130	RES CMF 1/10W 5% 12R (K,J,H,G,F,D,C,B,E,A,R)	RF509	212437	20224600	RES CMF 1/10W 5% 6.8K (K,J,H,G,F,D,C,B,E,A,R)
RA511	212406	20224590	RES CMF 1/10W 5% 5.6K (K,J,H,G,F,D,C,B,E,A)	RF510	192100	20471950	RES CMF 1/10W 5% 1K (M,S)
RA511	205346	80440400	RES CMF 1/10W 5% 5.6K (M,S)	RF510	192100	20223980	RES CMF 1/10W 5% 1K (K,J,H,G,F,D,C,B,E,A,R)
RA511	230610	20224590	RES CMF 1/10W 5% 5.6K (R)	RF511	206005	50886620	RES CMF 1/10W 5% 39K (M,S)
RA513	211623	20224230	RES CMF 1/10W 5% 220R (J,H,G,F,C,B,E,A,R)	RF511	206005	20224150	RES CMF 1/10W 5% 39K (J,K,H,G,F,D,C,B,E,A,R)
RA513	205408	20283320	RES CMF 1/10W 0% 0R (K,D)	RF513	192084	50886630	RES CMF 1/10W 5% 100K (M,S)
RA513	215195	20471920	RES CMF 1/10W 5% 220R (M,S)	RF513	211656	20224460	RES CMF 1/10W 5% 100K (J,K,H,G,F,D,C,B,E,A,R)
RA514	206303	30944340	RES CMF 1/10W 5% 27K (M,S)	RF515	197471	20225010	RES CMF 1/10W 5% 68K (K,J,H,G,F,D,C,B,E,A,R)
RA514	212447	20223770	RES CMF 1/10W 5% 27K (K,J,H,G,F,D,C,B,E,A,R)	RF515	197471	11066500	RES CMF 1/10W 5% 68K (M,S)
RA515	195937	50886610	RES CMF 1/10W 5% 10K (M,S)	RF517	194926	90574400	RES CMF 1/10W 5% 470R (M,S)
RA515	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,B,E,A,R)	RF517	212392	20224780	RES CMF 1/10W 5% 470R (K,J,H,G,F,D,C,B,E,A,R)
RA516	211623	20224230	RES CMF 1/10W 5% 220R (K,J,E,A)	RF521	212399	20224570	RES CMF 1/10W 5% 100R (K,J,H,G,F,D,C,B,E,A,R)
RA517	211623	20224230	RES CMF 1/10W 5% 220R (K,J,E,A)	RF521	218508	70434200	RES CMF 1/10W 5% 100R (M,S)
RA519	211623	20224230	RES CMF 1/10W 5% 220R (J,H,G,F,C,B,E,A,R)	RF523	212437	20224600	RES CMF 1/10W 5% 6.8K (K,J,H,G,F,D,C,B,E,A,R)
RA519	215195	20471920	RES CMF 1/10W 5% 220R (M,S)	RF523	192087	40438300	RES CMF 1/10W 5% 6.8K (M,S)
RD05	198644	15007580	RES CF 1/4W 5% 2.7K (D,K)	RH07	248783	13003310	RES CF .43W 5% 12K
RD502	212398	20224140	RES CMF 1/10W 5% 4.7K (D,K)	RH09	248783	13003310	RES CF .43W 5% 12K
RD503	212398	20224140	RES CMF 1/10W 5% 4.7K (D,K)	RH501	192070	60444400	RES CMF 1/10W 5% 22K (K,J,G,F,D,C,B,E,A,M,S)
RD572	212382	20224240	RES CMF 1/10W 5% 10K (D,K)	RH501	212400	20223760	RES CMF 1/10W 5% 22K (H,R)
RD60	244838	20751370	⚠ PROTECTOR IC (K,D)	RH502	218508	70434200	RES CMF 1/10W 5% 100R (K,J,G,F,D,C,B,E,A,M,S)
RD68	198707	15006730	RES CF 1/4W 5% 1K (D,K)	RH502	212399	20224570	RES CMF 1/10W 5% 100R (H,R)
RD70	198718	15006350	RES CF 1/4W 5% 12K (K,D)	RI22	245049	15007800	RES CF 1/4W 5% 330R(USED WITH CTT5050 TUNER) (A,B,C,D,E,M,F,G,H,J,K,R)
RD73	198707	15006730	RES CF 1/4W 5% 1K (K,D)	RI22	220648	15007430	RES CF 1/4W 5% 270R(USED WITH CTF5800 TUNER) (K,J,H,G,F,D,C,B,E,A,M,S)
RE10	235851	10113540	RES CF 1/4W 0% 0R (H)	RI502	212447	20223770	RES CMF 1/10W 5% 27K (H,R)
RE12	235851	10113540	RES CF 1/4W 0% 0R (H)	RI502	206303	30944340	RES CMF 1/10W 5% 27K (K,J,G,F,D,C,B,E,A,M,S)
RE509	194926	90574400	RES CMF 1/10W 5% 470R (M,S)	RI503	212404	20224760	RES CMF 1/10W 5% 330R (H,R)
RE509	212392	20224780	RES CMF 1/10W 5% 470R (K,J,G,H,F,D,C,B,E,A,R)	RI503	194914	50886540	RES CMF 1/10W 5% 330R (K,J,G,F,D,C,B,E,A,M,S)
RF01	220618	15009870	⚠ RES CFFP .3W 5% 2.2R	RI504	200177	60444380	RES CMF 1/10W 5% 270R (K,J,G,F,D,C,B,E,A,M,S)
RF02	190556	13083620	RES MF 1W 5% 390R	RI504	212445	20224440	RES CMF 1/10W 5% 270R (H,R)
RF04	220667	15007960	RES CF 1/4W 5% 390R	RI505	205408	20283320	RES CMF 1/10W 0% 0R (H,R)
RF05	235947	20649310	RES MF 1/2W 5% 1.8R (K,J,H,G,F,D,C,B,E,A,M)	RI505	205408	80440510	RES CMF 1/10W 0% 0R (K,J,G,D,F,C,B,E,A,M,S)
RF05	DISCON_ST K	20649310	RES MF 1/2W 5% 1.8R (R,S)				
RF10	235953	13001770	RES MF 2W 5% 470R				
RF12	244863	20955090	RES MF 1/2W 5% 150R				
RF14	198722	15008490	RES CF 1/4W 5% 4.7K				
RF501	218508	70434200	RES CMF 1/10W 5% 100R (M,S)				

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
RI516	193344	80440420	RES CMF 1/10W 5% 33K (K,J,G,F,D,C,B,E,A,M,S)	RL14	NONSTK	10448530	WIREBARE 22 (R,S)
RI516	212396	20224990	RES CMF 1/10W 5% 33K (H,R)	RL14	247264	15042720	RES MF 1W 5% .47R (M,H,F,D,C,G,E,B,A)
RI517	212447	20223770	RES CMF 1/10W 5% 27K (H,R)	RL14	233165	20470270	RES MFFP 1W 5% 1R (K,J,M,M,M,H,H,F,F,F,D,D,C, C,C,G,G,G,E,E,E,D,B,B,A,A,A)
RI517	206303	30944340	RES CMF 1/10W 5% 27K (K,J,G,F,D,C,B,E,A,M,S)				RES MF 1/2W 5% .39R (S,R)
RI523	192100	20223980	RES CMF 1/10W 5% 1K (H,R)	RL14	251351	20917230	
RI523	192100	20471950	RES CMF 1/10W 5% 1K (K,J,G,F,D,C,B,E,A,M,S)	RL20	244866	20923340	⚠ RES CFF .35W 5% 47R
RI524	192100	20223980	RES CMF 1/10W 5% 1K (H,R)	RL46	247263	10305450	⚠ RES CFF .35W 5% .22R
RI524	192100	20471950	RES CMF 1/10W 5% 1K (K,J,G,F,D,C,B,E,A,M,S)	RL502	212399	20224570	RES CMF 1/10W 5% 100R (K,J,H,G,F,D,C,B,E,A,R)
RI525	192100	20223980	RES CMF 1/10W 5% 1K (H,R)	RL502	218508	70434200	RES CMF 1/10W 5% 100R (M,S)
RI525	192100	20471950	RES CMF 1/10W 5% 1K (K,J,G,F,D,C,B,E,A,M,S)	RL503	192100	20223980	RES CMF 1/10W 5% 1K (K,J,H,G,F,D,C,B,E,A,R)
RI526	200177	60444380	RES CMF 1/10W 5% 270R (S)	RL503	192100	20471950	RES CMF 1/10W 5% 1K (M,S)
RI526	205408	20283320	RES CMF 1/10W 0% 0R(USED WITH CTT5050 TUNER) (G,H,J,K,A,B,C,D,E,F,M,R)	RL507	218508	70434200	RES CMF 1/10W 5% 100R (M,S)
RI526	212445	20224440	RES CMF 1/10W 5% 270R(USED WITH CTF5800 TUNER) (K,J,H,G,F,D,C,B,E,A,M)	RL507	212399	20224570	RES CMF 1/10W 5% 100R (K,J,H,G,F,D,C,B,E,A,R)
RI528	212385	20224130	RES CMF 1/10W 5% 1.5K (H,R)	RL509	212392	20224780	RES CMF 1/10W 5% 470R (K,J,H,G,F,D,C,B,E,A,R)
RI528	192082	40438290	RES CMF 1/10W 5% 1.5K (K,J,G,F,D,C,B,E,A,M,S)	RL509	194926	90574400	RES CMF 1/10W 5% 470R (M,S)
RI529	192077	11066440	RES CMF 1/10W 5% 3.3K (K,J,G,F,D,C,B,E,A,M,S)	RL523	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RI529	241755	20223750	RES CMF 1/10W 5% 3.3K (H,R)	RL523	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,B,E,A,R)
RI530	195935	90574370	RES CMF 1/10W 5% 82R (K,J,G,F,D,C,B,E,A,M,S)	RL524	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RI530	251317	20224560	RESCMF 82 OHM +5% -5% 1/10W (H,R)	RL524	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,E,B,A,R)
RI531	192082	40438290	RES CMF 1/10W 5% 1.5K (K,J,G,F,D,C,B,E,A,M,S)	RL547	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RI531	212385	20224130	RES CMF 1/10W 5% 1.5K (H,R)	RL547	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,E,B,A,R)
RI532	192100	20471950	RES CMF 1/10W 5% 1K (K,J,G,F,D,C,B,E,A,M,S)	RL548	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,E,B,A,R)
RI532	192100	20223980	RES CMF 1/10W 5% 1K (H,R)	RL548	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RK02	236055	15007330	RES CF 1/4W 5% 22R (K,J,H,G,F,D,C,B,E,A)	RL561	193344	80440420	RES CMF 1/10W 5% 33K (M)
RK02	243090	15007330	RES CF 1/4W 5% 22R (M,R,S)	RL561	197471	20225010	RES CMF 1/10W 5% 68K (R)
RK501	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,B,E,A,R)	RL561	197471	11066500	RES CMF 1/10W 5% 68K (S)
RK501	195937	50886610	RES CMF 1/10W 5% 10K (M,S)	RL561	212396	20224990	RES CMF 1/10W 5% 33K (K,J,H,G,F,D,C,B,E,A)
RL01	198707	15006730	RES CF 1/4W 5% 1K	RL60	241312	15006130	RES CF 1/4W 5% 10K
RL02	218494	40436300	RES MF 1/4W 1% 24.3K	RL62	233856	50883810	RES MF 1/4W 1% 100K (K,J)
RL05	251350	10133490	RES MFFP 68R +5% 1W (M,H,G,C,E,F,D,B,A,R,S)	RL62	247265	15020340	RES MF 1/4W 1% 68.1K (H,M,R,S)
RL05	248781	13063380	RES MF 1W 10% 150R (K,J,M,M,M,H,H,H,G,G,C,C,E, E,E,F,F,F,D,D,D,C,B,B,A,A,A)	RL62	176500	50883790	RES MF 1/4W 1% 41.2K (K,J,G,F,D,C,B,E,A)
RL12	216049	13000780	⚠ RES CFF 1/4W 5% .68R (K,J,M,M,M,H,H,H,F,F,G,G,C,C, C,G,E,E,E,F,D,D,D,B,B,A,A,A, S,R)	RL63	241312	15006130	RES CF 1/4W 5% 10K
RL12	247263	10305450	RES CFF .35W 5% .22R (M,H,F,C,G,E,D,B,A,R,S)	RL65	176500	50883790	RES MF 1/4W 1% 41.2K (H,M,S,R)
RL13	244865	10233220	RES CC 1/2W 5% 47R	RL65	196081	30940410	RES MF 1/4W 1% 26.7K (S,R)
				RL65	247265	15020340	RES MF 1/4W 1% 68.1K (K,J,G,F,D,C,B,E,A)
				RP01	248777	20781910	RES WW 5W 10% 2.7R (J,H,G,F,D,C,B,E,A,M,R,S)
				RP02	198688	90343700	⚠ RES POSISTOR (J,H,G,F,C,B,E,A,M)
				RP02	207768	30948690	THERMISTOR (R,S)
				RP02	260596	21242550	PTC THERMISTOR (S)

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
RP05	220644	15006280	RES CF 1/4W 5% 120K (J,H,G,F,D,C,B,E,A,M,S,R)	RP541	211652	20224490	RES CMF 1/10W 5% 30K (R)
RP06	220644	15006280	RES CF 1/4W 5% 120K (J,H,G,F,D,C,B,E,A,M,R,S)	RP541	212447	20223770	RES CMF 1/10W 5% 27K (D)
RP15	220333	15041120	△ RES CC 1/2W 10% 1.8M (J,H,G,F,D,B,C,E,A,M,R,S)	RP553	192087	40438300	RES CMF 1/10W 5% 6.8K (G,F,C,B,M,S)
RP20	244846	20822410	RES WW 2.5W 5% .68R (J,H,G,F,D,C,B,E,A,M,S,R)	RP553	212437	20224600	RES CMF 1/10W 5% 6.8K (J,H,D,E,A,R)
RP21	236055	15007330	RES CF 1/4W 5% 22R (J,H,G,F,D,C,B,E,A)	RP554	223788	20224660	RES CMF 1/10W 1% 2K (K,J,M,M,M,G,G,G,H,H,H,F,F,F, E,D,D,D,C,C,C,E,E,B,B,A,A,A, R)
RP21	243090	15007330	RES CF 1/4W 5% 22R (M,R,S)	RP554	223788	20474270	RES CMF 1/10W 1% 2K (S)
RP23	198646	15007540	RES CF 1/4W 5% 2.2K (J,H,G,F,D,C,B,E,A,M,R,S)	RP554	250517	20224540	RES CFMIN 1/10W 1% 1.96K (M,G,H,F,E,D,C,B,A)
RP26	198644	15007580	RES CF 1/4W 5% 2.7K (J,H,G,F,D,C,B,E,A,M,R,S)	RP555	192087	40438300	RES CMF 1/10W 5% 6.8K (G,F,C,B,M,S)
RP27	198646	15007540	RES CF 1/4W 5% 2.2K (J,H,G,F,D,C,B,E,A,M,R,S)	RP555	212437	20224600	RES CMF 1/10W 5% 6.8K (J,H,D,E,A,R)
RP28	243090	15007330	RES CF 1/4W 5% 22R (M,S,R)	RP556	228778	20474790	RES CMF 1/10W 1% 26.7K (H,G,F,C,M,R,S)
RP28	236055	15007330	RES CF 1/4W 5% 22R (J,H,G,F,D,C,B,E,A)	RP556	248778	21049020	RES CMF 1/10W 1% 26.7K (J,D,B,E,A)
RP30	198707	15006730	RES CF 1/4W 5% 1K (J,H,G,F,D,C,B,E,A,M,S,R)	RP557	211623	20224230	RES CMF 1/10W 5% 220R (J,H,D,B,E,A,R)
RP31	220568	15006180	RES CF 1/4W 5% 10R (J,H,G,F,D,C,B,E,A,M,R,S)	RP557	215195	20471920	RES CMF 1/10W 5% 220R (G,F,C,M,S)
RP40	198646	15007540	RES CF 1/4W 5% 2.2K (J,H,G,F,D,C,B,E,A,M,R,S)	RP558	248778	21049020	RES CMF 1/10W 1% 26.7K (J,D,B,E,A)
RP52	198644	15007580	RES CF 1/4W 5% 2.7K (J,H,G,F,D,C,B,E,A,M,R,S)	RP558	228778	20474790	RES CMF 1/10W 1% 26.7K (H,G,F,C,M,S,R)
RP525	195937	50886610	RES CMF 1/10W 5% 10K (G,F,C,B,M,S)	RP559	248778	21049020	RES CMF 1/10W 1% 26.7K (J,H,D,B,E,A,R)
RP525	212382	20224240	RES CMF 1/10W 5% 10K (J,H,D,E,A,R)	RP559	228778	20474790	RES CMF 1/10W 1% 26.7K (G,F,C,M,S)
RP529	192096	80440390	RES CMF 1/10W 5% 2.2K (G,F,C,B,M,S)	RP560	192081	50886590	RES CMF 1/10W 5% 2.7K (G,F,C,B,M)
RP529	192096	20223740	RES CMF 1/10W 5% 2.2K (J,H,D,E,A,R)	RP560	205346	80440400	RES CMF 1/10W 5% 5.6K (S)
RP53	220663	15007290	RES CF 1/4W 5% 22K (J,H,G,F,D,C,B,E,A,M,S,R)	RP560	192081	20224980	RES CMF 1/10W 5% 2.7K (J,H,D,E,A)
RP532	206005	20224150	RES CMF 1/10W 5% 39K (J,H,D,E,A,R)	RP560	230610	20224590	RES CMF 1/10W 5% 5.6K (R)
RP532	206005	50886620	RES CMF 1/10W 5% 39K (G,F,C,B,M,S)	RP565	192100	20223980	RES CMF 1/10W 5% 1K (J,H,D,E,A,R)
RP533	197633	11066480	RES CMF 1/10W 5% 47K (G,F,C,B,M)	RP565	192100	20471950	RES CMF 1/10W 5% 1K (G,F,C,B,M,S)
RP533	205364	11066480	RES CMF 1/10W 5% 47K (S)	RP592	205308	20224420	RES CMF 1/10W 5% 10R (J,H,D,E,A,R)
RP533	230592	20224260	RES CMF 1/10W 5% 47K (J,H,D,E,A,R)	RP592	205308	30944250	RES CMF 1/10W 5% 10R (G,F,C,B,M,S)
RP537	197621	90574430	RES CMF 1/10W 5% 18K (G,F,C,B,M,S)	RP593	205308	30944250	RES CMF 1/10W 5% 10R (G,F,C,B,M,S)
RP537	203786	20224250	RES CMF 1/10W 5% 18K (J,H,D,E,A,R)	RP593	205308	20224420	RES CMF 1/10W 5% 10R (J,H,D,E,A,R)
RP538	194926	90574400	RES CMF 1/10W 5% 470R (G,F,C,B,M,S)	RP599	192100	20471950	RES CMF 1/10W 5% 1K (G,F,C,B,M,S)
RP538	212392	20224780	RES CMF 1/10W 5% 470R (J,H,D,E,A,R)	RP599	192100	20223980	RES CMF 1/10W 5% 1K (J,H,D,E,A,R)
RP541	226489	60444410	RES CMF 1/10W 5% 30K (S)	RP61	179786	13001570	RES MF 2W 5% 22R (J,H,G,F,D,C,B,E,A,M,R,S)
RP541	206005	20224150	RES CMF 1/10W 5% 39K (J,H,E,A)	RP63	232521	15007260	RES CF 1/4W 5% 220R (J,H,G,F,D,C,B,E,A,M,R,S)
RP541	206005	50886620	RES CMF 1/10W 5% 39K (G,F,C,B,M)				

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
RP67	175758	80437010	RES CF 1/4W 5% 1.8K (J,H,G,F,D,C,B,E,A,M,R,S)	RR508	211623	20224230	RES CMF 1/10W 5% 220R (K,J,H,G,F,D,C,B,E,A,R)
RP70	198717	15008360	RES CF 1/4W 5% 470R (J,H,G,F,D,C,B,E,A,M,R,S)	RR508	215195	20471920	RES CMF 1/10W 5% 220R (M,S)
RP73	241312	15006130	RES CF 1/4W 5% 10K (J,H,G,F,D,C,B,E,A,M,R,S)	RR509	218508	70434200	RES CMF 1/10W 5% 100R (M,S)
RP75	241312	15006130	RES CF 1/4W 5% 10K (J,H,G,F,D,C,B,E,A,M,R,S)	RR509	212399	20224570	RES CMF 1/10W 5% 100R (K,J,H,G,F,D,C,B,E,A,R)
RP90	251349	10457130	⚠ PROTECTOR 1.6 A 65V (S,R)	RR510	218508	70434200	RES CMF 1/10W 5% 100R (M,S)
RP90	247263	10305450	⚠ RES CFF .35W 5% .22R (J,H,G,F,C,B,E,A,M)	RR510	212399	20224570	RES CMF 1/10W 5% 100R (K,J,H,G,F,D,C,B,E,A,R)
RP90	244838	20751370	⚠ PROTECTOR IC (D)	RR512	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RP91	179786	13001570	RES MF 2W 5% 22R (J,H,G,F,D,C,B,E,A,M,S,R)	RR512	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,B,E,A,R)
RP93	198717	15008360	RES CF 1/4W 5% 470R (J,H,G,F,D,C,B,E,A,M,R,S)	RR513	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,B,E,A,R)
RP95	198722	15008490	RES CF 1/4W 5% 4.7K (R,S)	RR513	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RP95	220662	15009090	RES CF 1/4W 5% 6.8K (J,H,G,F,D,C,B,E,A,M)	RR514	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RP96	198707	15006730	RES CF 1/4W 5% 1K (J,H,G,F,D,C,B,E,A,M,R,S)	RR514	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,B,E,A,R)
RP97	241312	15006130	RES CF 1/4W 5% 10K (J,H,G,F,D,C,B,E,A,M,S,R)	RR515	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,B,E,A,R)
RR02	248784	15006160	RES CF 1/4W 10% 10M	RR515	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RR10	198707	15006730	RES CF 1/4W 5% 1K	RR516	246465	70434290	RES CCF 220K +5% 1/10W (S)
RR12	198707	15006730	RES CF 1/4W 5% 1K	RR516	212383	20225020	RES CMF 1/10W 5% 220K (K,J,H,G,F,D,C,B,E,A,M,R)
RR21	198707	15006730	RES CF 1/4W 5% 1K	RR518	212398	20224140	RES CMF 1/10W 5% 4.7K (K,J,H,G,F,D,C,B,E,A,R)
RR22	198707	15006730	RES CF 1/4W 5% 1K	RR518	192097	30944310	RES CMF 1/10W 5% 4.7K (M,S)
RR23	198707	15006730	RES CF 1/4W 5% 1K	RR519	192081	50886590	RES CMF 1/10W 5% 2.7K (M,S)
RR27	241312	15006130	RES CF 1/4W 5% 10K	RR519	192081	20224980	RES CMF 1/10W 5% 2.7K (J,K,H,G,F,D,C,B,E,A,R)
RR28	241312	15006130	RES CF 1/4W 5% 10K	RR521	212396	20224990	RES CMF 1/10W 5% 33K (K,J,H,G,F,D,C,B,E,A,R)
RR29	241312	15006130	RES CF 1/4W 5% 10K	RR521	193344	80440420	RES CMF 1/10W 5% 33K (M,S)
RR38	198673	15008070	RES CF 1/4W 5% 3.3K	RR524	211656	20224460	RES CMF 1/10W 5% 100K (K,J,H,G,F,D,C,B,E,A,R)
RR39	198673	15008070	RES CF 1/4W 5% 3.3K	RR524	192084	50886630	RES CMF 1/10W 5% 100K (M,S)
RR40	198673	15008070	RES CF 1/4W 5% 3.3K	RR525	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RR41	198672	15006830	RES CF 1/4W 5% 1.5K	RR525	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,B,E,A,R)
RR501	212437	20224600	RES CMF 1/10W 5% 6.8K (K,J,H,G,F,D,C,B,E,A,R)	RR526	212382	20224240	RES CMF 1/10W 5% 10K (J,K,H,G,F,D,C,B,E,A,R)
RR501	192087	40438300	RES CMF 1/10W 5% 6.8K (M,S)	RR526	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RR502	192097	30944310	RES CMF 1/10W 5% 4.7K (M,S)	RR527	212382	20224240	RES CMF 1/10W 5% 10K(USED WITH CTF5800 TUNER)
RR502	212398	20224140	RES CMF 1/10W 5% 4.7K (K,J,H,G,F,D,C,B,E,A,R)	RR527	195937	50886610	RES CMF 1/10W 5% 10K (S)
RR503	206303	30944340	RES CMF 1/10W 5% 27K (M,S)	RR527	N/S/P	00000000	NOT PRESENT WHEN CTT5050 TUNER IS USED (A,B,C,D,E,F,G,H,J,K,M)
RR503	212447	20223770	RES CMF 1/10W 5% 27K (K,J,H,G,F,D,C,B,E,A,R)	RR528	N/S/P	00000000	NOT PRESENT WHEN CTF5800 TUNER IS USED (B,C,D,E,F,G,H,J,K,A,M)
RR504	192100	20223980	RES CMF 1/10W 5% 1K (K,J,H,G,F,D,C,B,E,A,R)	RR528	212382	20224240	RES CMF 1/10W 5% 10K(USED WITH CTT5050 TUNER)
RR504	192100	20471950	RES CMF 1/10W 5% 1K (M,S)	RR530	192097	30944310	RES CMF 1/10W 5% 4.7K (M,S)
RR505	192097	30944310	RES CMF 1/10W 5% 4.7K (M,S)	RR530	212398	20224140	RES CMF 1/10W 5% 4.7K (J,K,H,G,F,D,C,B,E,A,R)
RR505	212398	20224140	RES CMF 1/10W 5% 4.7K (K,J,H,G,F,D,C,B,E,A,R)				
RR506	194926	90574400	RES CMF 1/10W 5% 470R (M,S)				
RR506	212392	20224780	RES CMF 1/10W 5% 470R (K,J,H,G,F,D,C,B,E,A,R)				
RR507	193344	80440420	RES CMF 1/10W 5% 33K (M,S)				
RR507	212396	20224990	RES CMF 1/10W 5% 33K (K,J,H,G,F,D,C,B,E,A,R)				

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
RR531	218508	70434200	RES CMF 1/10W 5% 100R (M,S)	RV07	175054	60441580	RES CF 1/4W 5% 22K (K,J,H,G,F,D,C,B,E,A,M)
RR531	212399	20224570	RES CMF 1/10W 5% 100R (J,K,H,G,F,D,C,B,E,A,R)	RV09	232521	15007260	RES CF 1/4W 5% 220R
RR532	192100	20471950	RES CMF 1/10W 5% 1K (M,S)	RV10	232521	15007260	RES CF 1/4W 5% 220R
RR532	192100	20223980	RES CMF 1/10W 5% 1K (K,J,H,G,F,D,C,B,E,A,R)	RV24	198656	15006100	RES CF 1/4W 5% 100R
RR533	192100	20471950	RES CMF 1/10W 5% 1K (M,S)	RV27	198707	15006730	RES CF 1/4W 5% 1K
RR533	192100	20223980	RES CMF 1/10W 5% 1K (K,J,H,G,F,D,C,B,E,A,R)	RV28	175758	80437010	RES CF 1/4W 5% 1.8K
RR534	211611	20224970	RES CMF 1/10W 5% 820R (K,J,H,G,F,D,C,B,E,A,R)	RV29	248789	15009210	RES CF 1/4W 5% 75R
RR534	197644	70434220	RES CMF 1/10W 5% 820R (M,S)	RV501	192077	11066440	RES CMF 1/10W 5% 3.3K (M,S)
RR535	212440	20224960	RES CMF 1/10W 5% 680R (K,J,H,G,F,D,C,B,E,A,R)	RV501	241755	20223750	RES CMF 1/10W 5% 3.3K (K,J,H,G,F,D,C,B,E,A,R)
RR535	197637	20471940	RES CMF 1/10W 5% 680R (M,S)	RV502	218508	70434200	RES CMF 1/10W 5% 100R (M,S)
RR536	212440	20224960	RES CMF 1/10W 5% 680R (K,J,H,G,F,D,C,B,E,A,R)	RV502	212399	20224570	RES CMF 1/10W 5% 100R (K,J,H,G,F,D,C,B,E,A,R)
RR536	197637	20471940	RES CMF 1/10W 5% 680R (M,S)	RV508	206301	20223180	RES CMF 1/10W 5% 15K (K,J,H,G,F,D,C,B,E,A,R)
RR537	197637	20471940	RES CMF 1/10W 5% 680R (M,S)	RV508	206301	70434250	RES CMF 1/10W 5% 15K (M,S)
RR537	212440	20224960	RES CMF 1/10W 5% 680R (K,J,H,G,F,D,C,B,E,A,R)	RV509	205370	11066510	RES CMF 1/10W 5% 120K (M,S)
RR542	192077	11066440	RES CMF 1/10W 5% 3.3K (M,S)	RV509	205370	20224270	RES CMF 1/10W 5% 120K (K,J,H,G,F,D,C,B,E,A,R)
RR542	241755	20223750	RES CMF 1/10W 5% 3.3K (K,J,H,G,F,D,C,B,E,A,R)	RV510	212400	20223760	RES CMF 1/10W 5% 22K (K,J,H,G,F,D,C,B,E,A,R)
RR543	241755	20223750	RES CMF 1/10W 5% 3.3K (K,J,H,G,F,D,C,B,E,A,R)	RV510	192070	60444400	RES CMF 1/10W 5% 22K (M,S)
RR543	192077	11066440	RES CMF 1/10W 5% 3.3K (M,S)	RV511	211656	20224460	RES CMF 1/10W 5% 100K (K,J,H,G,F,D,C,B,E,A,R)
RR544	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)	RV511	192084	50886630	RES CMF 1/10W 5% 100K (M,S)
RR544	205408	80440510	RES CMF 1/10W 0% 0R (M,S)	RV512	205349	11066460	RES CMF 1/10W 5% 8.2K (M,S)
RR545	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)	RV512	212448	20223990	RES CMF 1/10W 5% 8.2K (K,J,H,G,F,D,C,B,E,A,R)
RR545	205408	80440510	RES CMF 1/10W 0% 0R (M,S)	RV513	211611	20224970	RES CMF 1/10W 5% 820R (K,J,H,G,F,D,C,B,E,A,R)
RR546	215195	20471920	RES CMF 1/10W 5% 220R (M,S)	RV513	197644	70434220	RES CMF 1/10W 5% 820R (M,S)
RR546	211623	20224230	RES CMF 1/10W 5% 220R (K,J,H,G,F,D,C,B,E,A,R)	RV514	192082	40438290	RES CMF 1/10W 5% 1.5K (M,S)
RR547	211623	20224230	RES CMF 1/10W 5% 220R (K,J,H,G,F,D,C,B,E,A,R)	RV514	212385	20224130	RES CMF 1/10W 5% 1.5K (K,J,H,G,F,D,C,B,E,A,R)
RR547	215195	20471920	RES CMF 1/10W 5% 220R (M,S)	RV515	206328	20223410	RES CMF 1/10W 5% 360R (K,J,H,G,F,D,C,B,E,A,R)
RR549	212398	20224140	RES CMF 1/10W 5% 4.7K (K,J,H,G,F,D,C,B,E,A,R)	RV515	206328	90574390	RES CMF 1/10W 5% 360R (M,S)
RR549	192097	30944310	RES CMF 1/10W 5% 4.7K (M,S)	RV516	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,B,E,A,R)
RR590	192098	60444350	RES CMF 1/10W 5% 47R (M,S)	RV516	195937	50886610	RES CMF 1/10W 5% 10K (M,S)
RR590	192081	20224430	RES CMF 1/10W 5% 47R (K,J,H,G,F,D,C,B,E,A,R)	RV517	246465	70434290	RES CCF 220K +5% 1/10W (S)
RR592	192077	11066440	RES CMF 1/10W 5% 3.3K (M,S)	RV517	212383	20225020	RES CMF 1/10W 5% 220K (K,J,H,G,F,D,C,B,E,A,M,R)
RR592	241755	20223750	RES CMF 1/10W 5% 3.3K (K,J,H,G,F,D,C,B,E,A,R)	RV518	212384	20224810	RES CMF 1/10W 5% 1.2K (K,J,H,G,F,D,C,B,E,A,R)
RR593	195937	50886610	RES CMF 1/10W 5% 10K (M,S)	RV518	197636	70434230	RES CMF 1/10W 5% 1.2K (M,S)
RR593	212382	20224240	RES CMF 1/10W 5% 10K (K,J,H,G,F,D,C,B,E,A,R)	RV519	206297	20471960	RES CMF 1/10W 5% 1.8K (M,S)
RV03	220646	15009390	RES CF 1/4W 5% 82R	RV519	206297	20224580	RES CMF 1/10W 5% 1.8K (K,J,H,G,F,D,C,B,E,A,R)
RV04	220646	15009390	RES CF 1/4W 5% 82R	RV520	205336	20224930	RES CMF 1/10W 5% 300R (K,J,H,G,F,D,C,B,E,A,R)
RV05	220646	15009390	RES CF 1/4W 5% 82R	RV520	205336	11066410	RES CMF 1/10W 5% 300R (M,S)
RV06	175758	80437010	RES CF 1/4W 5% 1.8K	RV521	207836	20224060	RES CMF 1/10W 5% 75K (K,J,H,G,F,D,C,B,E,A,R)
RV07	175351	40435660	RES CF 1/4W 5% 20K (S,R)	RV521	207836	40438330	RES CMF 1/10W 5% 75K (M,S)

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
RV525	192096	20223740	RES CMF 1/10W 5% 2.2K (K,J,H,G,F,D,C,B,E,A,R)	SK04	260595	21233160	△ SWITCH (S)
RV525	192096	80440390	RES CMF 1/10W 5% 2.2K (M,S)	SK04	215500	4044741A	SWITCH (K,J,H,G,F,D,C,B,E,A,M,R)
RV526	206297	20224580	RES CMF 1/10W 5% 1.8K (K,J,H,G,F,D,C,B,E,A,R)	SK05	215500	4044741A	SWITCH (K,J,H,G,F,D,C,B,E,A,M,R)
RV526	206297	20471960	RES CMF 1/10W 5% 1.8K (M,S)	SK05	260595	21233160	△ SWITCH (S)
RV529	200177	60444380	RES CMF 1/10W 5% 270R (M,S)	SK06	260595	21233160	△ SWITCH (S)
RV529	212445	20224440	RES CMF 1/10W 5% 270R (K,J,H,G,F,D,C,B,E,A,R)	SK06	215500	4044741A	SWITCH (K,J,H,G,F,D,C,B,E,A,M,R)
RV530	192098	60444350	RES CMF 1/10W 5% 47R (M,S)	SOCKET	248815	21036810	△ ASY AC/DC IN (K,D)
RV530	192081	20224430	RES CMF 1/10W 5% 47R (K,J,H,G,F,D,C,B,E,A,R)	SUPPOR T	248940	21039170	SUPPORT, DC/DC CONVERTOR (K,D)
RV532	205408	80440510	RES CMF 1/10W 0% 0R (M,S)	TA501	219349	16006290	TRANSISTOR
RV532	205408	20283320	RES CMF 1/10W 0% 0R (K,J,H,G,F,D,C,B,E,A,R)	TA502	206088	16007060	TRANSISTOR
RV533	212392	20224780	RES CMF 1/10W 5% 470R (K,J,H,G,F,D,C,B,E,A,R)	TA504	219349	16006290	TRANSISTOR
RV533	194926	90574400	RES CMF 1/10W 5% 470R (M,S)	TD20	247374	21011610	TRANSISTOR (K,D)
RV534	212400	20223760	RES CMF 1/10W 5% 22K (K,J,H,G,F,D,C,B,E,A,R)	TD501	219349	16006290	TRANSISTOR (K,D)
RV534	192070	60444400	RES CMF 1/10W 5% 22K (M,S)	TD502	219349	16006290	TRANSISTOR (K,D)
RV535	203786	20224250	RES CMF 1/10W 5% 18K (K,J,H,G,F,D,C,B,E,A,R)	TD68	230764	16001110	TRANSISTOR (K,D)
RV535	197621	90574430	RES CMF 1/10W 5% 18K (M,S)	TD69	230764	16001110	TRANSISTOR (K,D)
RV539	201140	11066400	RES CMF 1/10W 5% 240R (M,S)	TD72	198743	16000930	TRANSISTOR (K,D)
RV539	201140	20873340	RES CMF 1/10W 5% 240R (K,J,H,G,F,D,C,B,E,A,R)	TD73	247373	10259910	TRIAC (K,D)
RV540	192077	11066440	RES CMF 1/10W 5% 3.3K (M,S)	TF01	198743	16000930	TRANSISTOR
RV540	241755	20223750	RES CMF 1/10W 5% 3.3K (K,J,H,G,F,D,C,B,E,A,R)	TI20	198743	16000930	TRANSISTOR
RV542	192100	20223980	RES CMF 1/10W 5% 1K (K,J,H,G,F,D,C,B,E,A,R)	TI21	230764	16001110	TRANSISTOR
RV542	192100	20471950	RES CMF 1/10W 5% 1K (M,S)	TL01	248794	16000540	TRANSISTOR
RZ01	198656	15006100	RES CF 1/4W 5% 100R	TL02	256981	21153430	TRANSISTOR, HORIZ OUTPUT (M)
RZ03	210198	15006780	RES CF 1/4W 5% 1.2K	TL02	198794	20578720	TRANSISTOR HORIZ OUT (K,J,H,G,F,D,C,B,E,A,R,S)
RZ05	247153	15019650	RES MF .4W 1% 5.6K (H,M,M,G,G,H,F,F,E,E,D,D,C,C, B,B,A,A)	TL04	198743	16000930	TRANSISTOR
RZ05	248790	15018620	RES MF .4W 1% 4.32K	TL541	219349	16006290	TRANSISTOR
RZ05	256980	15017440	RES MF 3.92K OHM 1% .4W (R,S)	TP20	244844	20931410	△ TRANSISTOR (J,H,G,F,D,C,B,E,A,M,S,R)
RZ05	250518	15019580	RES MF .4W 1% 5.11K (H,M,G,F,E,D,C,B,A)	TP20	251872	20958630	TRANSISTOR STP6NB50FP 35W 3.4A (M)
RZ07	160155	15010340	RES MF .4W 1% 10K	TP22	198743	16000930	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,R,S)
RZ09	198728	15006080	RES CF 1/4W 5% 100K	TP23	248795	21039270	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,S,R)
RZ508	212400	20223760	RES CMF 1/10W 5% 22K (K,J,H,G,F,D,C,B,E,A,R)	TP25	230764	16001110	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,S,R)
RZ508	192070	60444400	RES CMF 1/10W 5% 22K (M,S)	TP52	198743	16000930	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,S,R)
SA01	248814	21030130	SWITCH SLIDE (K,D)	TP566	219348	16006330	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,R,S)
SK01	260595	21233160	△ SWITCH (S)	TP61	247372	16001230	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,R,S)
SK01	215500	4044741A	SWITCH (K,J,H,G,F,D,C,B,E,A,M,R)	TP63	230764	16001110	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,S,R)
SK02	215500	4044741A	SWITCH (K,J,H,G,F,D,C,B,E,A,M,R)	TP65	251883	55081790	TRANSISTOR KTA1046Y (M,S)
SK02	260595	21233160	△ SWITCH (S)	TP65	245066	20970660	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,S,R)
SK03	215500	4044741A	SWITCH (K,J,H,G,F,D,C,B,E,A,M,R)	TP69	198743	16000930	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,S,R)
SK03	260595	21233160	△ SWITCH (S)	TP93	198743	16000930	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,R,S)

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
TP95	248796	21051670	TRANSISTOR (J,H,G,F,D,C,B,E,A,M,S,R)
TR501	248805	90618810	TRANSISTOR
TV02	198743	16000930	TRANSISTOR
TV510	219348	16006330	TRANSISTOR
TV512	219348	16006330	TRANSISTOR
TV522	219348	16006330	TRANSISTOR
TV523	219348	16006330	TRANSISTOR
ZP01	260591	21175120	⚠ VARISTOR (S)
ZP01	247377	20648220	⚠ RES CONTROL (J,H,G,F,D,C,B,E,A,M,R)
DC - DC CONVERTER			
BD50	248881	21058800	⚠ CONNECTOR 8 PIN
CD23	247368	14033520	⚠ CAPCD 330PF K Y5R 50V
CD24	186750	20267760	CAP LYTC 22UF M 35V
CD36	247368	14033520	CAPCD 330PF K Y5R 50V
CD37	198559	14033560	CAPCD .001UF K Y5S 50V
CD38	198558	14033610	CAPCD .033UF K Y5R 50V
CD40	186750	20267760	CAP LYTC 22UF M 35V
CD522	211541	20229420	CAPCC 470PF K X7R 50V
CD55	198559	14033560	CAPCD .001UF K Y5S 50V
CIRCUIT	249099	20903450	CIRCUIT DC/DC CONVERTER
DD02	244856	10455310	DIODE
DD25	198589	70436540	DIODE
DD27	244835	20475330	DIODE ZENER 27V .5W
DD37	198589	70436540	DIODE
DD40	232545	11073660	DIODE ZENER 8.2V .5W
DD56	198589	70436540	DIODE
DD58	232591	20475420	DIODE ZENER 15V .5W
JD501	205408	20283320	RES CMF 1/10W 0% 0R
RD13	245049	15007800	RES CF 1/4W 5% 330R
RD26	198718	15006350	RES CF 1/4W 5% 12K
RD27	198717	15008360	RES CF 1/4W 5% 470R
RD28	236055	15007330	RES CF 1/4W 5% 22R
RD38	198717	15008360	RES CF 1/4W 5% 470R
RD40	198646	15007540	RES CF 1/4W 5% 2.2K
RD41	210181	15009420	RES CF 1/4W 5% 8.2K
RD41	241312	15006130	RES CF 1/4W 5% 10K
RD501	212400	20223760	RES CMF 1/10W 5% 22K
RD512	192100	20223980	RES CMF 1/10W 5% 1K
RD52	220662	15009090	RES CF 1/4W 5% 6.8K
RD520	212447	20223770	RES CMF 1/10W 5% 27K
RD521	212393	20224010	RES CMF 1/10W 5% 12K
RD525	212382	20224240	RES CMF 1/10W 5% 10K
RD529	225513	20223840	RES CMF 1/10W 5% 9.1K
RD537	197471	20225010	RES CMF 1/10W 5% 68K
RD555	212382	20224240	RES CMF 1/10W 5% 10K
TD11	247372	16001230	TRANSISTOR
TD22	198743	16000930	TRANSISTOR
TD23	220675	16000440	TRANSISTOR
TD25	230764	16001110	TRANSISTOR
TD55	198743	16000930	TRANSISTOR

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
HEADPHONE CBA			
BA08	248799	20345310	JACK, HEADPHONE
CA518	200469	20225890	CAPCC 1000PF J N750 50V
CA519	200469	20225890	CAPCC 1000PF J N750 50V
CIRCUIT	249097	21061560	CIRCUIT HEADPHONE JACK
HA03	249098	21034620	CABLE ASY, HEADPHONE CBA
RA516	211623	20224230	RES CMF 1/10W 5% 220R
RA517	211623	20224230	RES CMF 1/10W 5% 220R
KINE DRIVER			
BU01	250514	21071410	⚠ SOCKET, KINE (F,C,D,B,G,E,A,H,M)
BU01	224146	20174620	⚠ SOCKET PIX TUBE (K,J,H,G,F,C,D,B,E,A)
CABLE	251370	2103150A	CABLE 6P FLAT WITH CONNECTORS (K,J,H,G,F,C,D,B,E,A)
CABLE	251355	21031440	CABLE 5WAY L 300MM (K,J,H,G,F,C,D,B,E,A)
CIRCUIT	249095	21096500	⚠ CIRCUIT KINE DRIVER (K,J)
CIRCUIT	249096	21061550	⚠ CIRCUIT KINE DRIVER (H,G,F,C,D,B,E,A)
CU551	211541	20229420	CAPCC 470PF K X7R 50V (K,J,H,G,F,C,D,B,E,A,E,B,H,C,D ,F,G,A)
CU561	211541	20229420	CAPCC 470PF K X7R 50V (K,J,H,G,F,C,D,B,E,A,B,H,C,E,F, D,G,A)
CU571	212433	20229430	CAPCC 560PF K X7R 50V (K,J,H,G,F,C,D,B,E,A,B,F,D,H,G ,E,A,C)
CU591	193339	20230130	CAPCC 68PF J NPO 50V (K,J,H,G,F,C,D,B,E,A,C,G,A,D,F ,H,B,E)
CU81	189981	15002130	CAP LYTC 10UF M 16V (K,J,H,G,F,C,D,B,E,A,G,D,C,F,E ,H,B,A)
CU83	220627	13028880	CAP POLY .068UF M 250V (K,J,H,G,F,C,D,B,E,A,D,C,A,G,E ,F,H,B)
CU90	183147	14036020	CAPCD 2200PF FS Y5U 2KV (K,J,H,G,F,C,D,B,E,A,C,E,A,H,D ,G,F,B)
DU01	224937	60446590	DIODE ZENER 6.2V .5W (K,J,H,G,F,C,D,B,E,A,E,B,A,C,G, D,F,H)
DU502	248798	21030100	DIODE (K,J,H,G,F,C,D,B,E,A,E,A,C,F,G, H,D,B)
DU51	244870	10459090	DIODE (K,J,H,G,F,C,D,B,E,A,B,G,C,D,E ,H,A,F)
DU61	244870	10459090	DIODE (K,J,H,G,F,C,D,B,E,A,C,E,H,D,F, B,A,G)
DU71	244870	10459090	DIODE (K,J,H,G,F,C,D,B,E,A,E,D,B,G,H ,F,A,C)

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
HU01	251370	2103150A	CABLE 6P FLAT WITH CONNECTORS (E,F,B,G,A,C,H,D)	RU65	251315	80437190	RES CF 1/2W 5% 3.3K (K,J,G,H,F,C,D,B,E,A,E,A,F,H,C,G,D,B)
HU02	251355	21031440	CABLE 5WAY L 300MM (G,E,H,D,B,F,A,C)	RU71	248858	15008450	RES CF 1/4W 5% 47R (K,J,G,H,F,C,D,B,E,A,G,E,D,A,H,F,C,B)
JU01	NONSTK	10448530	WIREBARE 22 (K,J,G,H,F,C,D,B,E,A,G,D,A,C,F,E,B,H)	RU74	176656	13001230	RES MF 2W 5% 10K (K,J,G,H,F,C,D,B,E,A,B,D,H,A,E,G,F,C)
JU02	NONSTK	10448530	WIREBARE 22 (K,J,G,H,F,C,D,B,E,A,A,G,F,E,B,H,C,D)	RU75	251315	80437190	RES CF 1/2W 5% 3.3K (K,J,G,H,F,C,D,B,E,A,H,B,G,D,E,C,F,A)
LU51	206174	13020590	COIL 56UH (K,J,H,G,F,C,D,B,E,A,E,D,B,F,H,A,G,C)	RU90	244871	11058050	RES CC 1/2W 5% 1.5K (K,J,G,H,F,C,D,B,E,A,F,D,G,C,A,H,E,B)
RU51	248858	15008450	RES CF 1/4W 5% 47R (K,J,H,G,F,D,C,B,E,A,A,H,F,B,E,D,C,G)	RU91	198811	15006200	RES CF .7W 5% 10R (K,J,G,H,F,C,D,B,E,A,A,D,E,F,G,C,B,H)
RU54	176656	13001230	RES MF 2W 5% 10K (K,J,H,G,F,D,C,B,E,A,B,D,G,A,E,C,H,F)	TU51	185197	16003760	TRANSISTOR (K,J,G,H,F,C,D,B,E,A,D,A,E,C,F,B,H,G)
RU55	251315	80437190	△ RES CF 1/2W 5% 3.3K (K,J,H,G,F,D,C,B,E,A,G,B,A,C,H,F,D,E)	TU61	185197	16003760	TRANSISTOR (K,J,G,H,F,C,D,B,E,A,B,D,F,A,C,H,G,E)
RU552	212440	20224960	RES CMF 1/10W 5% 680R (K,J,H,G,F,D,C,B,E,A,B,D,H,C,E,A,F,G)	TU71	185197	16003760	TRANSISTOR (K,J,G,H,F,C,D,B,E,A,A,B,E,H,F,C,D,G)
RU553	212385	20224130	RES CMF 1/10W 5% 1.5K (K,J)	TU81	215977	16000450	TRANSISTOR (K,J,G,H,F,C,D,B,E,A,E,B,F,C,D,G,A,H)
RU553	212440	20224960	RES CMF 1/10W 5% 680R (H,G,F,D,C,B,E,A,D,A,G,C,H,F,E,B)	KINE DRIVER CBA			
RU562	212440	20224960	RES CMF 1/10W 5% 680R (K,J,H,G,F,C,D,B,E,A,F,E,B,H,A,C,G,D)	BU01	251319	21104250	△ SOCKET CRT (S,R)
RU563	212440	20224960	RES CMF 1/10W 5% 680R (H,G,F,C,D,B,E,A,D,C,F,E,H,B,G,A)	BU01	224146	20174620	△ SOCKET PIX TUBE (M)
RU563	212385	20224130	RES CMF 1/10W 5% 1.5K (K,J)	BU02	230935	20174650	△ SOCKET, PIX TUBE (S,R)
RU572	212440	20224960	RES CMF 1/10W 5% 680R (K,J,H,G,F,C,D,B,E,A,F,B,A,H,D,C,G,E)	CABLE	251355	21031440	CABLE 5WAY L 300MM (M)
RU573	212440	20224960	RES CMF 1/10W 5% 680R (H,G,F,C,D,B,E,A,F,E,B,C,G,D,A,H)	CABLE	251370	2103150A	CABLE 6P FLAT WITH CONNECTORS (M)
RU573	212385	20224130	RES CMF 1/10W 5% 1.5K (K,J)	CIRCUIT	249096	21061550	△ CIRCUIT KINE DRIVER (M)
RU581	212437	20224600	RES CMF 1/10W 5% 6.8K (K,J,G,H,F,C,D,B,E,A,B,E,C,A,G,F,H,D)	CU551	211541	20229420	CAPCC 470PF K X7R 50V (M)
RU582	212384	20224810	RES CMF 1/10W 5% 1.2K (K,J,G,H,F,C,D,B,E,A,D,E,A,F,G,H,B,C)	CU551	212433	20229430	CAPCC 560PF K X7R 50V (S,R)
RU583	211611	20224970	RES CMF 1/10W 5% 820R (K,J,G,H,F,C,D,B,E,A,A,G,B,D,F,H,E,C)	CU561	212433	20229430	CAPCC 560PF K X7R 50V (S,R)
RU592	212398	20224140	RES CMF 1/10W 5% 4.7K (K,J,G,H,F,C,D,B,E,A,A,D,G,B,H,F,E,C)	CU561	211541	20229420	CAPCC 470PF K X7R 50V (M)
RU61	248858	15008450	RES CF 1/4W 5% 47R (K,J,G,H,F,C,D,B,E,A,B,C,D,F,E,A,H,G)	CU571	212433	20229430	CAPCC 560PF K X7R 50V
RU64	176656	13001230	RES MF 2W 5% 10K (K,J,G,H,F,C,D,B,E,A,H,G,C,F,E,B,A,D)	CU591	193339	20230130	CAPCC 68PF J NPO 50V
				CU81	189981	15002130	CAP LYTC 10UF M 16V
				CU83	220627	13028880	CAP POLY .068UF M 250V
				CU90	227078	14036020	CAPCD 2200PF FS Y5U 2KV
				DU01	224937	60446590	DIODE ZENER 6.2V .5W
				DU502	248798	21030100	DIODE
				DU51	244870	10459090	DIODE
				DU61	244870	10459090	DIODE
				DU71	244870	10459090	DIODE
				HU01	251370	2103150A	CABLE 6P FLAT WITH CONNECTORS (M)
				HU01	251928	21115930	CABLE, 6-WAY FLAT 420MM (R,S)
				HU02	257213	25433950	CABLE, 5-WAY 420MM (S,R)

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
HU02	251355	21031440	CABLE 5WAY L 300MM
JU01	NONSTK	10448530	WIREBARE 22
JU02	NONSTK	10448530	WIREBARE 22
JU03	NONSTK	10448530	WIREBARE 22 (R,S)
JU04	NONSTK	10448530	WIREBARE 22 (R,S)
LU51	206174	13020590	COIL 56UH
RU51	248858	15008450	RES CF 1/4W 5% 47R
RU54	176656	13001230	RES MF 2W 5% 10K
RU55	251315	80437190	⚠ RES CF 1/2W 5% 3.3K
RU552	212440	20224960	RES CMF 1/10W 5% 680R
RU552	192104	20224770	RES CMF 1/10W 5% 390R (S,R)
RU553	212440	20224960	RES CMF 1/10W 5% 680R
RU562	212440	20224960	RES CMF 1/10W 5% 680R
RU562	192104	20224770	RES CMF 1/10W 5% 390R (R,S)
RU563	212440	20224960	RES CMF 1/10W 5% 680R
RU572	192104	20224770	RES CMF 1/10W 5% 390R (R,S)
RU572	212440	20224960	RES CMF 1/10W 5% 680R
RU573	212440	20224960	RES CMF 1/10W 5% 680R
RU581	212437	20224600	RES CMF 1/10W 5% 6.8K
RU582	212384	20224810	RES CMF 1/10W 5% 1.2K
RU583	211611	20224970	RES CMF 1/10W 5% 820R
RU592	212398	20224140	RES CMF 1/10W 5% 4.7K
RU61	248858	15008450	RES CF 1/4W 5% 47R
RU64	176656	13001230	RES MF 2W 5% 10K
RU65	251315	80437190	RES CF 1/2W 5% 3.3K
RU71	248858	15008450	RES CF 1/4W 5% 47R
RU74	176656	13001230	RES MF 2W 5% 10K
RU75	251315	80437190	RES CF 1/2W 5% 3.3K
RU90	244871	11058050	RES CC 1/2W 5% 1.5K
RU91	198811	15006200	RES CF .7W 5% 10R
TU51	185197	16003760	TRANSISTOR
TU61	185197	16003760	TRANSISTOR
TU71	185197	16003760	TRANSISTOR
TU81	215977	16000450	TRANSISTOR

09GP341(K)**INSTRUMENT ASSEMBLY**

ADAPTE R	193983	15045850	⚠ ADAPTER, 75-300 OHM
ANTENN A	220190	60409808	ANTENNA, UHF/VHF
BACK	BK2330	21048810	■ BACK, COVER
BUTTON	233620	20544630	BUTTON CLUSTER
CABLE	247290	21006800	⚠ CABLE, DC POWER
CABLE	247289	21006790	⚠ CABLE, AC POWER
COIL	198785	2012199A	⚠ COIL, DEGAUSSING
CRT	H27GDC85T C	20026330	⚠ CRT/YOKE ASY, HA27GDC85XTC
DOOR	226900	15208450	DOOR, BATTERY
FOOT	236156	20294570	FOOT, RUBBER
MASK	MK2329	21069180	■ MASK, CABT FRONT
REMOTE	240961	20316320	TRANSMITTER, REMOTE
RETAIN R	164699	90542011	⚠ RETAINER, WIRE TIE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	229242	20414970	SCREW, 4.9MMD X 20MM KINE MTG
SPEAKE R	247291	20901550	SPKR, 40MM X 70MM
SUPPOR T	248934	20530750	SUPPORT, STOPPER PCB
WINDOW	233662	2054471B	WINDOW, IR

INSTURMENT ASSEMBLY

CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
-------	--------	----------	-------------------------------

09GP344(J)**INSTRUMENT ASSEMBLY**

ADAPTE R	193983	15045850	⚠ ADAPTER, 75-300 OHM
ANTENN A	220190	60409808	ANTENNA, UHF/VHF
BACK	BK2330	21048810	■ BACK, COVER
BUTTON	233620	20544630	BUTTON CLUSTER
CABLE	248756	21057880	⚠ CABLE, AC POWER
CABLE	247290	21006800	⚠ CABLE, DC POWER
COIL	198785	2012199A	⚠ COIL, DEGAUSSING
CRT	H27GDC85T C	20026330	⚠ CRT/YOKE ASY, HA27GDC85XTC
DOOR	226900	15208450	DOOR, BATTERY
FOOT	236156	20294570	FOOT, RUBBER
MASK	MK2329	21069180	■ MASK, CABT FRONT
REMOTE	231032	21082740	TRANSMITTER, REMOTE CRK20A1W
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN
RETAIN R	164699	90542011	⚠ RETAINER, WIRE TIE
SCREW	229242	20414970	SCREW, 4.9MMD X 20MM KINE MTG
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SOCKET	248807	21057750	⚠ ASY AC/DC IN
SPEAKE R	247291	20901550	SPKR, 40MM X 70MM
SUPPOR T	248934	20530750	SUPPORT, STOPPER PCB
WINDOW	233662	2054471B	WINDOW, IR

INSTURMENT ASSEMBLY

CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
-------	--------	----------	-------------------------------

13GP341(A)**INSTRUMENT ASSEMBLY**

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
ADAPTE R	193983	15045850	▲ ADAPTER, 75-300 OHM
ANTENN A	220689	1070670B	ANTENNA, UHF/VHF
BACK	BK2342	21011480	■▲ BACK, COVER
BP01	248816	21024560	▲ CABLE, AC POWER
BUTTON	233723	2054286A	BUTTON, CLUSTER
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
DOOR	233721	20448060	■ DOOR, BATTERY
MASK	MK1986	2105868A	■▲ MASK
REMOTE	240961	21082840	TRANSMITTER, REMOTE CRK20A1
RETAINER	164699	90542011	▲ RETAINER, WIRE TIE
RETAINER	139301	67492300	RETAINER, BEAD CHAIN
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SPEAKER	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
SUPPORT	248934	20530750	SUPPORT, STOPPER PCB
T			
WINDOW	248895	2054288C	WINDOW, IR
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
13GP344(E)			
INSTRUMENT ASSEMBLY			
ADAPTE R	232919	20555560	▲ ADAPTER, 75-300 OHM (WHT)
ANTENN A	232920	2055258A	ANTENNA, VHF/UHF (WHT)
BACK	BK2344	21025770	■ BACK, COVER
BP01	248844	21024550	▲ CABLE, AC POWER
BUTTON	233718	20544610	BUTTON, CLUSTER
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
DOOR	233721	20448060	■ DOOR, BATTERY
MASK	MK2343	2104908A	■ MASK, CABT FRONT
REMOTE	231032	21082740	TRANSMITTER, REMOTE CRK20A1W
RETAINER	139301	67492300	RETAINER, BEAD CHAIN
RETAINER	164699	90542011	▲ RETAINER, WIRE TIE
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SPEAKER	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
SUPPORT	248934	20530750	SUPPORT, STOPPER PCB
T			
WINDOW	248895	2054288C	WINDOW, IR
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
13GP701(H)			
INSTRUMENT ASSEMBLY			
ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2423	21087170	■▲ BACKCOVER
BP01	248816	21024560	▲ CABLE, AC POWER
BUTTON	251334	2108744A	▲ BUTTON, CLUSTER
COIL	232781	20590120	COIL, DEGAUSSING
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
MASK	MK2422	2111660A	■▲ MASK, CABINET FRONT
RETAINER	139301	67492300	RETAINER, BEAD CHAIN
RETAINER	164699	90542011	RETAINER, WIRE TIE
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SPEAKER	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	233357	2055914D	▲ WINDOW IR
13GP701F11(H)			
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
<u>13GP711(H)</u>			
INSTRUMENT ASSEMBLY			
ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2420	21087200	■▲ BACKCOVER
BP01	248816	21024560	▲ CABLE, AC POWER
BUTTON	251340	2108743A	▲ BUTTON, CLUSTER
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
MASK	MK2421	2111661A	■▲ MASK, CABINET FRONT
REMOTE	251343	21118570	REMOTE CRK10L1
RETAIN R	164699	90542011	RETAINER, WIRE TIE
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	▲ SPRING, DEGAUSS MTG
WINDOW	233357	2055914D	▲ WINDOW IR
<u>13GP711F11(H)</u>			
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
<u>19GT243F11(R)</u>			
INSTRUMENT ASSEMBLY			
BACK	BK1907	2042135A	■▲ BACKCOVER
BP01	251352	8023120B	▲ CABLE, AC POWER
BUTTON	251346	2042133A	▲ BUTTON, CLUSTER
CABLE	251347	21025120	▲ CABLE, CRT GROUND
COIL	247230	21010510	▲ COIL, DEGAUSSING
CRT	A48QAD220 9	20734440	▲ PIX TUBE/YOKE ASY,A48QAD220X09
CRT	A48AGY135 5	20809380	▲ HA48AGY13X55 51
CRT	A48LGS300 3	20972640	▲ CRT/YOKE ASY, HA48LGS30X03
MASK	MK2424	2110072A	■▲ MASK, CABINET FRONT
REMOTE	240961	21082840	TRANSMITTER, REMOTE CRK20A1
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	247228	2042132A	■ SCREW, 7MMD X 28MM (KINE MTG)
SCREW	164100	9031330A	SPRING, DEGAUSS MTG

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
SPEAKE R	236014	2041942B	SPKR, 40MM X 70MM
WINDOW	230738	20421370	▲ WINDOW, IR
WIRE TIE	164699	90542011	RETAINER, WIRE TIE
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
<u>E09344(J)</u>			
INSTRUMENT ASSEMBLY			
ADAPTE R	232919	20555560	▲ ADAPTER, 75-300 OHM (WHT)
ANTENN A	233720	20608370	ANTENNA, UHF/VHF DUAL (WHT)
BACK	BK2328	21055330	■▲ BACK, COVER
BRACKE T	250107	70446950	BRACKET, MOUNTING
BRACKE T	248824	80428000	BRACKET, SWIVEL SUPPORT B
BRACKE T	248823	70421310	BRACKET, SWIVEL SUPPORT A
BUTTON	235438	2060506C	BUTTON, CLUSTER
CABLE	248756	21057880	▲ CABLE, AC POWER
COIL	198785	2012199A	▲ COIL, DEGAUSSING
CRT	H27GDC85T C	20026330	▲ CRT/YOKE ASY, HA27GDC85XTC
DOOR	235441	20390390	■ COVER, BATTERY
FOOT	236156	20294570	FOOT, RUBBER
MASK	MK2327	21077420	■ MASK, CABT FRONT
NUT	114918	70440540	NUT, TUNER MTG
OVERLA Y	244263	2060510C	OVERLAY, BUTTONS
REMOTE	233544	20572490	TRANSMITTER, REMOTE
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN
RETAIN R	164699	90542011	▲ RETAINER, WIRE TIE
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	220940	21004870	SCREW, 4.9MMD X 25.4MM (KINE)
SOCKET	248807	21057750	▲ ASY AC/DC IN
SPEAKE R	198787	57064400	SPEAKER, 16 OHM 2W
WINDOW	235436	2060508B	WINDOW, IR
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
<u>E13308(A)</u>			
INSTRUMENT ASSEMBLY			
ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2334	21026170	■▲ BACK, COVER

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
BP01	248816	21024560	⚠ CABLE, AC POWER
BUTTON	233358	2055953B	⚠ BUTTON, CLUSTER
COIL	232781	20590120	COIL, DEGAUSSING
CRT	4JXV701443	20809640	⚠ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37SX110Y22	21068360	⚠ PIX TUBE/YOKE 37SX110Y22DC08
CRT	37GDA86TC 2	21026720	⚠ PIX TUBE/YOKE HA37GDA86XTC02
CRT	A34AGT133 8	20786290	⚠ PIX TUBE/YOKE ASY,A34AGT13X38
DOOR	226900	15208450	DOOR, BATTERY
MASK	MK2333	21026190	■ MASK, CABT FRONT
REMOTE	240959	20316290	TRANSMITTER, REMOTE CRK10A1
RETAIN R	164699	90542011	RETAINER, WIRE TIE
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN
SCREW	235444	11097490	SCREW, 3.5MMDX13MM
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	233357	2055914B	⚠ WINDOW, IR

INSTURMENT ASSEMBLY

CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
-------	--------	----------	----------------------------------

E13309(A)**INSTRUMENT ASSEMBLY**

ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2334	21026170	■ ⚠ BACK, COVER
BP01	248816	21024560	⚠ CABLE, AC POWER
BUTTON	233744	2062325B	BUTTON, CLUSTER
COIL	232781	20590120	⚠ COIL, DEGAUSSING
CRT	4JXV701443	20809640	⚠ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37SX110Y22	21068360	⚠ PIX TUBE/YOKE 37SX110Y22DC08
CRT	A34AGT133 8	20786290	⚠ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	37GDA86TC 2	21026720	⚠ PIX TUBE/YOKE HA37GDA86XTC02
DOOR	226900	15208450	DOOR, BATTERY
MASK	MK2335	21035610	■ MASK, CABT FRONT
REMOTE	240959	20316290	TRANSMITTER, REMOTE CRK10A1
RETAIN R	164699	90542011	⚠ RETAINER, WIRE TIE
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	235444	11097490	SCREW, 3.5MMDX13MM
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	233357	2055914B	WINDOW, IR

INSTURMENT ASSEMBLY

CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
-------	--------	----------	----------------------------------

E13318(H)**INSTRUMENT ASSEMBLY**

ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2334	21026170	■ ⚠ BACK, COVER
BP01	248816	21024560	⚠ CABLE, AC POWER
BUTTON	233358	2055953B	⚠ BUTTON, CLUSTER
COIL	232781	20590120	⚠ COIL, DEGAUSSING
CRT	37GDA86TC 2	21026720	⚠ PIX TUBE/YOKE HA37GDA86XTC02
CRT	A34AGT133 8	20786290	⚠ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	4JXV701443	20809640	⚠ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37SX110Y22	21068360	⚠ PIX TUBE/YOKE 37SX110Y22DC08
MASK	MK2416	2109848A	■ ⚠ MASK, CABINET,FRONT
REMOTE	240959	21082860	TRANSMITTER, REMOTE CRK10A1
RETAIN R	164699	90542011	RETAINER, WIRE TIE
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG

INSTURMENT ASSEMBLY

CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
-------	--------	----------	----------------------------------

E13319(H)**INSTRUMENT ASSEMBLY**

ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2334	21026170	■ ⚠ BACK, COVER
BP01	248816	21024560	⚠ CABLE, AC POWER
BP02	248788	21037120	⚠ CONNECTOR 2 PIN
BUTTON	233744	2062325B	⚠ BUTTON, CLUSTER
COIL	232781	20590120	⚠ COIL, DEGAUSSING

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
MASK	MK2417	2109849A	■▲ MASK, CABINET FRONT
REMOTE	240959	21082860	TRANSMITTER, REMOTE CRK10A1
RETAIN R	164699	90542011	RETAINER, WIRE TIE
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	233357	2055914D	▲ WINDOW IR
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
<u>E13320(H)</u>			
INSTRUMENT ASSEMBLY			
ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2486	21143340	▲ BACK COVER
BP01	248816	21024560	▲ CABLE, AC POWER
BUTTON	253430	21143350	BUTTON CLUSTER
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
CABLE	253191	2027569B	CABLE ASSY, SPKR WIRE W/PLUG
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
MASK	MK2485	21143330	MASK, CABINET FRONT
REMOTE	240959	21082860	TRANSMITTER, REMOTE CRK10A1
RETAIN R	164699	90542011	▲ RETAINER, WIRE TIE
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN
SCREW	235444	11097490	SCREW, 3.5MMDX13MM
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	233357	2055914D	WINDOW IR
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
<u>E13341(B)</u>			
INSTRUMENT ASSEMBLY			
ADAPTE R	193983	15045850	▲ ADAPTER, 75-300 OHM
ANTENN A	220689	1070670B	ANTENNA, UHF/VHF
BACK	BK2337	2103825A	■▲ BACK, COVER
BP01	248816	21024560	▲ CABLE, AC POWER
BRACKE T	248837	21037580	BRKT, CHASSIS (R)
BRACKE T	248838	21037550	BRKT, CHASSIS (L)
BUTTON	248836	21037640	BUTTON, CLUSTER
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
DOOR	226900	15208450	DOOR, BATTERY
FOOT	236156	20294570	FOOT, RUBBER
MASK	MK2336	2106166C	■ MASK, CABT FRONT
REMOTE	240959	20316290	TRANSMITTER, REMOTE CRK10A1
RETAIN R	164699	90542011	▲ RETAINER, WIRE TIE
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	248835	21037610	WINDOW, IR
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
<u>E13342(B)</u>			
INSTRUMENT ASSEMBLY			
ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
BACK	BK2337	2103825A	BACK, COVER
BP01	248816	21024560	CABLE, AC POWER
BRACKET	248838	21037550	BRKT, CHASSIS (L)
BRACKET	248837	21037580	BRKT, CHASSIS (R)
BUTTON	248836	21037640	BUTTON, CLUSTER
COIL	232781	20590120	COIL, DEGAUSSING
CRT	37GDA86TC 2	21026720	PIX TUBE/YOKE HA37GDA86XTC02
CRT	37SX110Y22	21068360	PIX TUBE/YOKE 37SX110Y22DC08
CRT	A34AGT133 8	20786290	PIX TUBE/YOKE ASY,A34AGT13X38
CRT	4JXV701443	20809640	PIX TUBE/YOKE ASY,A34JXV70X14
DOOR	232540	20409520	COVER, BATTERY
FOOT	236156	20294570	FOOT, RUBBER
MASK	MK2336	2106166C	MASK, CABT FRONT
REMOTE	239118	20769290	TRANSMITTER, REMOTE CRK230DL
RETAINER	139301 R	67492300	RETAINER, BEAD CHAIN
RETAINER	164699 R	90542011	RETAINER, WIRE TIE
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SPEAKER	232316	2041186A R	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	248835	21037610	WINDOW, IR
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
E13344(C)			
INSTRUMENT ASSEMBLY			
ADAPTER	232919	20555560	ADAPTER, 75-300 OHM (WHT)
ANTENNA	232920	2055258A A	ANTENNA, VHF/UHF (WHT)
BACK	BK2339	2103822A	BACK, COVER
BP01	248844	21024550	CABLE, AC POWER
BRACKET	248837	21037580	BRKT, CHASSIS (R)
BRACKET	248838	21037550	BRKT, CHASSIS (L)
BUTTON	248843	21038160	BUTTON, CLUSTER
COIL	232781	20590120	COIL, DEGAUSSING
COVER	235441	20390390	COVER, BATTERY
CRT	4JXV701443	20809640	PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37GDA86TC 2	21026720	PIX TUBE/YOKE HA37GDA86XTC02

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CRT	37SX110Y22	21068360	PIX TUBE/YOKE 37SX110Y22DC08
CRT	A34AGT133 8	20786290	PIX TUBE/YOKE ASY,A34AGT13X38
FOOT	236156	20294570	FOOT, RUBBER
MASK	MK2338	2103819B	MASK, CABT FRONT
REMOTE	233544	21082720	TRANSMITTER, REMOTE CRK231C
RETAINER	139301 R	67492300	RETAINER, BEAD CHAIN
RETAINER	164699 R	90542011	RETAINER, WIRE TIE
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SPEAKER	232316	2041186A R	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	248835	21037610	WINDOW, IR
INSTURMENT ASSEMBLY			
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
E13345(D)			
INSTRUMENT ASSEMBLY			
ANTENNA	251276	21120980 A	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2341	2103767A	BACK, COVER
BRACKET	248837	21037580	BRKT, CHASSIS (R)
BRACKET	248838	21037550	BRKT, CHASSIS (L)
BUTTON	248836	21037640	BUTTON, CLUSTER
CABLE	247290	21006800	CABLE, DC POWER
CABLE	247289	21006790	CABLE, AC POWER
COIL	233965	20551750	COIL, DEGAUSSING
CRT	37GDA86TC 2	21026720	PIX TUBE/YOKE HA37GDA86XTC02
CRT	37SX110Y22	21068360	PIX TUBE/YOKE 37SX110Y22DC08
CRT	4JXV701443	20809640	PIX TUBE/YOKE ASY,A34JXV70X14
CRT	A34AGT133 8	20786290	PIX TUBE/YOKE ASY,A34AGT13X38
DOOR	226900	15208450	DOOR, BATTERY
FOOT	236156	20294570	FOOT, RUBBER
MASK	MK2340	2103771C	MASK, CABT FRONT
REMOTE	240959	21082860	TRANSMITTER, REMOTE CRK10A1
RETAINER	139301 R	67492300	RETAINER, BEAD CHAIN
RETAINER	164699 R	90542011	RETAINER, WIRE TIE
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SPEAKE R	247291	20901550	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	248835	21037610	WINDOW, IR

INSTURMENT ASSEMBLY

CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
-------	--------	----------	-------------------------------

E13700(A)**INSTRUMENT ASSEMBLY**

ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2423	21087170	■▲ BACKCOVER
BP01	248816	21024560	▲ CABLE, AC POWER
BUTTON	251334	2108744A	▲ BUTTON, CLUSTER
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
MASK	MK2431	21087230	■▲ MASK
REMOT	247905	21084940	REMOTE TRANSMITTER CRK10H1
RETAIN R	164699	90542011	RETAINER, WIRE TIE
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	233357	2055914D	▲ WINDOW IR

INSTURMENT ASSEMBLY

CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
-------	--------	----------	-------------------------------

E13701(H)**INSTRUMENT ASSEMBLY**

ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BP01	248816	21024560	▲ CABLE, AC POWER
BUTTON	251334	2108744A	▲ BUTTON, CLUSTER
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
MASK	MK2418	2110665B	■▲ CABINET FRONT
REMOTE	247905	21084940	REMOTE TRANSMITTER CRK10H1
RETAIN R	164699	90542011	RETAINER, WIRE TIE
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	233357	2055914C	▲ WINDOW, IR

INSTURMENT ASSEMBLY

CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
-------	--------	----------	-------------------------------

E13702(M)**INSTRUMENT ASSEMBLY**

ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	257200	2116488A	▲ BACK COVER
BUTTON	233744	2062325B	BUTTON, CLUSTER
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
MASK	MK2525	2116485A	MASK, CABINET FRONT
REMOTE	254621	21164960	TRANSMITTER REMOTE CRK76BB1
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	235444	11097490	SCREW, 3.5MMDX13MM
SPEAKE R	232316	2041186A	SPEAKER, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	233357	2055914D	WINDOW IR
WIRE TIE	139301	67492300	RETAINER, BEAD CHAIN
WIRE TIE	164699	90542011	▲ RETAINER, WIRE TIE

E13710(A)**INSTRUMENT ASSEMBLY**

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2420	21087200	■▲ BACKCOVER
BP01	248816	21024560	▲ CABLE, AC POWER
BUTTON	251340	2108743A	▲ BUTTON, CLUSTER
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
MASK	MK2432	21087260	■▲ MASK
REMOT	247906	21084920	REMOTE TRANSMITTER CRK10J1
RETAIN R	164699	90542011	RETAINER, WIRE TIE
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	233357	2055914D	▲ WINDOW IR

INSTURMENT ASSEMBLY

CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
-------	--------	----------	-------------------------------

E13711(H)**INSTRUMENT ASSEMBLY**

ANTENN A	251276	21120980	DIPOLE ANT/75 OHM ADAPTER
BACK	BK2420	21087200	■▲ BACKCOVER
BP01	248816	21024560	▲ CABLE, AC POWER
BUTTON	251340	2108743A	▲ BUTTON, CLUSTER
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	37SX110Y22	21068360	▲ PIX TUBE/YOKE 37SX110Y22DC08
CRT	A34AGT133 8	20786290	▲ PIX TUBE/YOKE ASY,A34AGT13X38
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	37GDA86TC 2	21026720	▲ PIX TUBE/YOKE HA37GDA86XTC02
MASK	MK2419	2110662B	■▲ CABINET,FRONT
REMOTE	247906	21084920	REMOTE TRANSMITTER CRK10J1
RETAIN R	164699	90542011	RETAINER, WIRE TIE
SCREW	149552	1054050A	SCREW, 5.7MMD X 28.5MM (KINE)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
SCREW	221586	30909799	SCREW, 4.8MMDX15.8MM (CABT)
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	233357	2055914C	▲ WINDOW, IR

INSTURMENT ASSEMBLY

CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
-------	--------	----------	-------------------------------

F19421(S)**INSTRUMENT ASSEMBLY**

BACK	260593	2121865B	■▲ BACK COVER
BRACKE T	260592	21218640	BRACKET, CHASSIS SUPPORT(LEFT)
BRACKE T	260594	21218660	BRACKET, CHASSIS SUPPT(RIGHT)
BUTTON	256962	2114938A	BUTTON CLUSTER
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR
CABLE	260587	2097856C	▲ CABLE, DEFL. YOKE TO CHASSIS
CABLE	251347	21025120	CABLE, CRT GROUND
COIL	247230	21010510	▲ COIL, DEGAUSSING
CRT	A48AGY135 5	20809380	▲ HA48AGY13X55 51
CRT	A48QAD220 9	20734440	▲ PIX TUBE/YOKE ASY,A48QAD220X09
CRT	A48LGS300 3	20972640	▲ CRT/YOKE ASY, HA48LGS30X03
FOOT	236156	20294570	FOOT, RUBBER
LOGO	256960	2115052A	■ LOGO, RCA
MASK	MK2561	2121863D	■ MASK, CABINET FRONT
REMOTE	259274	21257560	TRANSMITTER, REMOTE: RCR100TC1
SCREW	247228	2042132A	■ SCREW, 7MMD X 28MM (KINE MTG)
SCREW	247229	80406922	■ SCREW, 4MMD X 20MM
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SPEAKE R	236014	2041942B	SPKR, 40MM X 70MM
SPRING	260597	5703860A	SPRING, TENSION(KINE GROUND)
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WINDOW	256961	2114983A	WINDOW, IR
WIRE TIE	139301	67492300	RETAINER, BEAD CHAIN

S13800CL(F)**INSTRUMENT ASSEMBLY**

BACK	BK2346	21034570	■ BACK, COVER
BP01	248816	21024560	▲ CABLE, AC POWER
BUTTON	248906	21034580	BUTTON, CLUSTER
CABLE	248936	21019460	▲ CABLE, RF EXTENSION
COIL	232781	20590120	▲ COIL, DEGAUSSING
CRT	4JXV701443	20809640	▲ PIX TUBE/YOKE ASY,A34JXV70X14

REPLACEMENT PARTS (Continued)

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CRT	37GDA86TC 2	21026720	⚠ PIX TUBE/YOKE HA37GDA86XTC02
CRT	37SX110Y22	21068360	⚠ PIX TUBE/YOKE 37SX110Y22DC08
CRT	A34AGT133 8	20786290	⚠ PIX TUBE/YOKE ASY,A34AGT13X38
EARPHO NE	248907	2102117A	EARPHONES, STEREO
MASK	MK2345	2103456A	■ MASK, CABT FRONT
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN
RETAIN R	164699	90542011	⚠ RETAINER, WIRE TIE
SCREW	248937	21032990	■ SCREW, 5MMD X 15.8MM (CABT)
SCREW	248938	21023480	■ SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WASHER	248935	2020212A	WASHER, KINE MTG

S13801CL(G)**INSTRUMENT ASSEMBLY**

ADAPTE R	248939	20313550	ADAPTER, ANTENNA
ANTENN A	220689	1070670B	ANTENNA, UHF/VHF
BACK	BK2346	21034570	■ BACK, COVER
BP01	248816	21024560	⚠ CABLE, AC POWER
BUTTON	248906	21034580	BUTTON, CLUSTER
CABLE	248936	21019460	⚠ CABLE, RF EXTENSION
COIL	232781	20590120	⚠ COIL, DEGAUSSING
CRT	37SX110Y22	21068360	⚠ PIX TUBE/YOKE 37SX110Y22DC08
CRT	37GDA86TC 2	21026720	⚠ PIX TUBE/YOKE HA37GDA86XTC02
CRT	4JXV701443	20809640	⚠ PIX TUBE/YOKE ASY,A34JXV70X14
CRT	A34AGT133 8	20786290	⚠ PIX TUBE/YOKE ASY,A34AGT13X38
EARPHO NE	248907	2102117A	EARPHONES, STEREO
MASK	MK2345	2103456A	■ MASK, CABT FRONT
RETAIN R	139301	67492300	RETAINER, BEAD CHAIN
RETAIN R	164699	90542011	⚠ RETAINER, WIRE TIE
SCREW	248937	21032990	■ SCREW, 5MMD X 15.8MM (CABT)
SCREW	248938	21023480	■ SCREW, 5.7MMD X 28.5MM (KINE)
SCREW	224168	11005556	SCREW, 3.5MMD X 9.5MM
SPEAKE R	232316	2041186A	SPKR, 40MM X 70MM
SPRING	164100	9031330A	SPRING, DEGAUSS MTG
WASHER	248935	2020212A	WASHER, KINE MTG

INSTURMENT ASSEMBLY

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>
CABLE	253191	2027569B	CABLE ASSY, SPKR: W/CONNECTOR