



Service Technical Information

MODEL NO.

TV-F2000 / TV-F2400

SUBJECT

Notes on repairing flat screen TV

Bulletin # 52-00-02

Date: April 14, 2000

<CONTENTS>

Take care when servicing flat screen TV sets. Powering on the set with the degaussing coil disconnected will destroy R848.

When servicing a flat screen TV, always do one of the following:

1. Connect another degaussing coil.
2. Connect a dummy load (6.8Ω , 20W resistor) to the degaussing coil connector.

MODEL	R848	TYPE
TV-F2400	27Ω / 2W	Cement resistor
TV-F2000	56Ω / 2W	Cement resistor

If R848 opens, noises appear in horizontal directions on the screen.