

D-AMP IC Operation & Control

- 1) D-AMP IC (C1AB00000497) was used for this model.
- 2) Three control pins (signal send from micro-processor IC) were used to control the D-AMP IC operation such as muting, standby and normal operation. They are described as below: -

No	Pin no	Signal name	Function
1	4	F_HOP	Frequency Hop control.
2	6	MODE_DA	Digital Amp On/Off control.
3	3	MUTE_F	Digital Amp Muting control

Table 1: Digital AMP Pin Control.

Here is detailed description of the three control pins for the D-AMP IC

A) **MODE_DA** & **MUTE_F** were used to switch the D-AMP IC in the following muting status:

- L(Low/OFF): Standby / OFF
- H (High/ON): Operating or Mute

Below is the logic for the two pins used for the control of the D-AMP IC.

No	MODE_DA	MUTE_F	Digital AMP IC mode status
1	L	X	OFF (0V)
2	H	H	Mute (2.5V)
3	H	L	Operating(5V)

Table 2: Digital AMP IC Mode Status.

Note: Standby/OFF condition of D.AMP IC is available / activated only during the following event: Switching of Frequency Hoping, power off and start up (when the unit is undergoing the transition from standby to normal operation mode)

B) **F_HOP** is used to control the D-AMP operation to avoid interference with AM source by controlling the frequency source used. It will switch from one frequency to the other, depending on the tuned AM frequency.

For 9 KHz Step

AM Band Frequency	F_HOP	Switching Frequency
522 ~ 558	L	301
567 ~ 639	H	350
648 ~ 855	L	301
864 ~ 945	H	350
954 ~ 1152	L	301
1161 ~ 1242	H	350
1251 ~ 1449	L	301
1458 ~ 1539	H	350
1548 ~ 1629	L	301

Table 3: F_HOP Control during 9 kHz Step

For 10 KHz Step

AM Band Frequency	F_HOP	Switching Frequency
520 ~ 560	L	301
570 ~ 640	H	350
650 ~ 860	L	301
870 ~ 950	H	350
960 ~ 1160	L	301