

# 1. Specifications

## 1-1 EUROPE/CIS

Broadcasting System	CW : EURO Multi (PAL,SECAM- B/G,D/K,I,L/L')																																									
Scanning System	100Hz/ Progressive																																									
Tuning Range	VHF : CH2 ~ CH12 UHF : CH21 ~ CH69 Cable : CHS1 ~ CHS40																																									
Antenna Impedence	75 ohm Unbalanced																																									
Intermediate Frequency	<table><tr><td colspan="2">System</td><td colspan="3">Video(MHz)</td><td colspan="2">Sound(MHz)</td></tr><tr><td colspan="2">B/G</td><td colspan="3">38.90</td><td colspan="2">33.40</td></tr><tr><td colspan="2">D/K</td><td colspan="3">38.90</td><td colspan="2">32.40</td></tr><tr><td colspan="2">I</td><td colspan="3">38.90</td><td colspan="2">32.90</td></tr><tr><td colspan="2">L (L')</td><td colspan="3">34.51(41.0)</td><td colspan="2">41.0(34.5)</td></tr></table>							System		Video(MHz)			Sound(MHz)		B/G		38.90			33.40		D/K		38.90			32.40		I		38.90			32.90		L (L')		34.51(41.0)			41.0(34.5)	
	System		Video(MHz)			Sound(MHz)																																				
	B/G		38.90			33.40																																				
	D/K		38.90			32.40																																				
	I		38.90			32.90																																				
	L (L')		34.51(41.0)			41.0(34.5)																																				
Sound Output	STD : 13W MAX : 18 W																																									
Rated Voltage	AC220V / Only																																									
White Balance	<div></div>		High-Light			Low- Light																																				
			x	y	Y	x	y	Y																																		
	42Q2	RF	298	295	9.45	300	301	0.44																																		
		DTV	298	294	9.32	296	285	0.41																																		
	43Q5	RF	298	283	8.0	298	283	0.4																																		
		DTV	298	283	8.3	298	283	0.4																																		
	43T8	RF	298	295	8.5	300	301	0.44																																		
DTV		298	294	9.32	296	295	0.41																																			
High Voltage	29Kv																																									
FUSE	250V 6.3A Code No : 3601- 000300																																									
Power Consumption	210W																																									

## 1-2 MIDDLE-ASIA

Broadcasting System	CS : PAL Multi (PAL,SECAM- B/G,D/K,I,NT4.43,NT3.58)																																		
Scanning System	100Hz / Progressive																																		
Tuning Range	VHF : CH2 ~ CH12 UHF : CH21 ~ CH69 Cable : CHS1 ~ CHS40																																		
Antenna Impedence	75ohm Unbalanced																																		
Intermdiate Frequency	<table><tr><td colspan="2">System</td><td colspan="3">Video(MHz)</td><td colspan="2">Sound(MHz)</td></tr><tr><td colspan="2">B/G</td><td colspan="3">38.90</td><td colspan="2">33.40</td></tr><tr><td colspan="2">D/K</td><td colspan="3">38.90</td><td colspan="2">32.40</td></tr><tr><td colspan="2">I</td><td colspan="3">38.90</td><td colspan="2">32.90</td></tr></table>							System		Video(MHz)			Sound(MHz)		B/G		38.90			33.40		D/K		38.90			32.40		I		38.90			32.90	
	System		Video(MHz)			Sound(MHz)																													
	B/G		38.90			33.40																													
	D/K		38.90			32.40																													
	I		38.90			32.90																													
Sound Output	STD : 13W MAX : 18W																																		
Rated Voltage	AC220V (Turkey) AC100~240V																																		
White Balance			High- Light			Low- Light																													
			x	y	Y	x	y	Y																											
	42Q2	RF	298	295	9.45	300	301	0.44																											
		DTV	298	294	9.32	296	285	0.41																											
	43Q5	RF	298	283	8.0	298	283	0.4																											
		DTV	298	283	8.3	298	283	0.4																											
	43T8	RF	298	295	8.5	300	301	0.44																											
DTV		298	294	9.32	296	295	0.41																												
High Voltage	29Kv																																		
FUSE	250V 6.3A Code No : 3601- 000300																																		
Power Consumption	210W																																		

## 1-3 CHINA

Broadcasting System	C S : PAL Multi (PAL,SECAM- B/G,D/K,I,NT4.43,NT3.58)																																																																	
Scanning System	100Hz / Progressive																																																																	
Tuning Range	VHF: CH 2 ~ CH12 UHF: CH21 ~ CH 69 Cable : CHS1 ~ CHS40																																																																	
Antenna Impedence	75ohm Unbalanced																																																																	
Intermadiate Frequency	<table><tr><td colspan="2">System</td><td colspan="3">Video(MHz)</td><td colspan="2">Sound(MHz)</td></tr><tr><td colspan="2">B/G</td><td colspan="3">38.90</td><td colspan="2">33.40</td></tr><tr><td colspan="2">D/ K</td><td colspan="3">38.90</td><td colspan="2">32.40</td></tr><tr><td colspan="2">I</td><td colspan="3">38.90</td><td colspan="2">32.90</td></tr></table>							System		Video(MHz)			Sound(MHz)		B/G		38.90			33.40		D/ K		38.90			32.40		I		38.90			32.90																																
System		Video(MHz)			Sound(MHz)																																																													
B/G		38.90			33.40																																																													
D/ K		38.90			32.40																																																													
I		38.90			32.90																																																													
Sound Output	STD : 13 W MAX : 18 W																																																																	
Rated Voltage	AC 220V / Only																																																																	
White Balance	<table><tr><td colspan="2" rowspan="2"></td><td colspan="3">H igh- Light</td><td colspan="3">L ow- Light</td></tr><tr><td>x</td><td>y</td><td>Y</td><td>x</td><td>y</td><td>Y</td></tr><tr><td rowspan="2">42Q 2</td><td>RF</td><td>300</td><td>315</td><td>12.5</td><td>271</td><td>263</td><td>0.65</td></tr><tr><td>DTV</td><td>284</td><td>289</td><td>10.5</td><td>260</td><td>251</td><td>0.4</td></tr><tr><td rowspan="2">43Q5</td><td>RF</td><td>298</td><td>283</td><td>8.0</td><td>298</td><td>283</td><td>0.4</td></tr><tr><td>DTV</td><td>298</td><td>283</td><td>8.3</td><td>298</td><td>283</td><td>0.4</td></tr><tr><td rowspan="2">43T8</td><td>RF</td><td>300</td><td>315</td><td>12.0</td><td>273</td><td>263</td><td>0.6</td></tr><tr><td>DTV</td><td>284</td><td>289</td><td>9.6</td><td>266</td><td>251</td><td>0.4</td></tr></table>									H igh- Light			L ow- Light			x	y	Y	x	y	Y	42Q 2	RF	300	315	12.5	271	263	0.65	DTV	284	289	10.5	260	251	0.4	43Q5	RF	298	283	8.0	298	283	0.4	DTV	298	283	8.3	298	283	0.4	43T8	RF	300	315	12.0	273	263	0.6	DTV	284	289	9.6	266	251	0.4
		H igh- Light			L ow- Light																																																													
		x	y	Y	x	y	Y																																																											
42Q 2	RF	300	315	12.5	271	263	0.65																																																											
	DTV	284	289	10.5	260	251	0.4																																																											
43Q5	RF	298	283	8.0	298	283	0.4																																																											
	DTV	298	283	8.3	298	283	0.4																																																											
43T8	RF	300	315	12.0	273	263	0.6																																																											
	DTV	284	289	9.6	266	251	0.4																																																											
High Voltage	29Kv																																																																	
FUSE	250V 6.3A Code No : 3601-000300																																																																	
Power Consumption	210W																																																																	

## 1-4 EAST-ASIA

Broadcasting System	C S : PAL Multi (PAL ,SECAM - B/G ,D/K,I,NT4.43,NT3.58)																																		
Scanning System	100Hz / Progressive																																		
Tuning Range	VHF : CH2 ~ CH12 UHF : CH21 ~ CH69 Cable : CHS1 ~ CHS40																																		
Antenna Impedence	75 ohm Unbalanced																																		
Intermediate Frequency	<table><tr><td colspan="2">System</td><td colspan="3">Video(MHz)</td><td colspan="2">Sound(MHz)</td></tr><tr><td colspan="2">B/G</td><td colspan="3">38.90</td><td colspan="2">33.40</td></tr><tr><td colspan="2">D/K</td><td colspan="3">38.90</td><td colspan="2">32.40</td></tr><tr><td colspan="2">I</td><td colspan="3">38.90</td><td colspan="2">32.90</td></tr></table>							System		Video(MHz)			Sound(MHz)		B/G		38.90			33.40		D/K		38.90			32.40		I		38.90			32.90	
	System		Video(MHz)			Sound(MHz)																													
	B/G		38.90			33.40																													
	D/K		38.90			32.40																													
	I		38.90			32.90																													
Sound Output	STD : 13 W MAX : 18 W																																		
Rated Voltage	AC220V (Singapore,Australia,NewZeland) AC100~240V																																		
White Balance	<div></div>		High- Light			Low- Light																													
			x	y	Y	x	y	Y																											
	42Q2	RF	300	315	12.5	271	263	0.65																											
		DTV	284	289	10.5	260	251	0.4																											
	43Q5	RF	298	283	8.0	298	283	0.4																											
		DTV	298	283	8.3	298	283	0.4																											
	43T8	RF	300	315	12.0	273	263	0.6																											
DTV		284	289	9.6	266	251	0.4																												
High Voltage	29Kv																																		
FUSE	250V 6.3A Code No : 3601- 000300																																		
Power Consumption	210W																																		